

RF Exposure Report

Report No.: SA160205C08C

FCC ID: PY315200317

Test Model: EX7300

Received Date: Feb. 04, 2016

Test Date: Feb. 23 ~ Mar. 17, 2016 (For 2.4GHz and U-NII-1 Band)
May 13 ~ May 31, 2016 (For U-NII-3 Band)

Issued Date: Jun. 03, 2016

Applicant: NETGEAR, INC.

Address: 350 East Plumeria Drive San Jose, CA 95134

Issued By: Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch

Lab Address: No. 47-2, 14th Ling, Chia Pau Vil., Lin Kou Dist., New Taipei City, Taiwan (R.O.C.)

Test Location: No. 19, Hwa Ya 2nd Rd., Wen Hwa Vil., Kwei Shan Dist., Taoyuan City 33383, TAIWAN (R.O.C.)



This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification. The report must not be used by the client to claim product certification, approval, or endorsement by TAF or any government agencies.

Table of Contents

Release Control Record	3
1 Certificate of Conformity	4
2 RF Exposure	5
2.1 Limits for Maximum Permissible Exposure (MPE).....	5
2.2 MPE Calculation Formula	5
2.3 Classification	5
3 Calculation Result of Maximum Conducted Power	6

Release Control Record

Issue No.	Description	Date Issued
SA160205C08C	Original release.	Jun. 03, 2016

1 Certificate of Conformity

Product: Nighthawk X4 AC2200 WiFi Range Extender

Brand: NETGEAR

Test Model: EX7300

Sample Status: Engineering sample

Applicant: NETGEAR, INC.

Test Date: Feb. 23 ~ Mar. 17, 2016 (For 2.4GHz and U-NII-1 Band)
May 13 ~ May 31, 2016 (For U-NII-3 Band)

Standards: FCC Part 2 (Section 2.1091)
KDB 447498 D01 (October 23, 2015)
IEEE C95.1

The above equipment has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

Prepared by : Suntee Liu , **Date:** Jun. 03, 2016
Suntee Liu / Specialist

Approved by : Ken Liu , **Date:** Jun. 03, 2016
Ken Liu / Senior Manager

2 RF Exposure

2.1 Limits for Maximum Permissible Exposure (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)	Average Time (minutes)
Limits For General Population / Uncontrolled Exposure				
300-1500	F/1500	30
1500-100,000	1.0	30

F = Frequency in MHz

2.2 MPE Calculation Formula

$$Pd = (Pout * G) / (4 * \pi * r^2)$$

where

Pd = power density in mW/cm²

Pout = output power to antenna in mW

G = gain of antenna in linear scale

Pi = 3.1416

R = distance between observation point and center of the radiator in cm

2.3 Classification

The antenna of this product, under normal use condition, is at least 29cm away from the body of the user. So, this device is classified as **Mobile Device**.

3 Calculation Result of Maximum Conducted Power

CDD Mode

Band	Modulation type	Frequency (MHz)	Max Power (dBm)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)	
2.4GHz	802.11b	2412	25.56	7.16	29	0.177	1	
		2437	27.25	7.69	29	0.295	1	
		2462	25.53	8.27	29	0.227	1	
	802.11g	2412	22.85	7.16	29	0.095	1	
		2437	27.36	7.69	29	0.303	1	
		2462	24.06	8.27	29	0.162	1	
	802.11n (HT20)	2412	21.71	7.16	29	0.073	1	
		2437	27.50	7.69	29	0.313	1	
		2462	21.95	8.27	29	0.100	1	
	802.11n (HT40)	2422	19.31	7.30	29	0.043	1	
		2437	21.68	7.69	29	0.082	1	
		2452	19.88	8.07	29	0.059	1	
5GHz (U-NII-1)	802.11a	5180	27.13	8.60	29	0.354	1	
		5200	28.04	8.76	29	0.453	1	
		5240	27.39	9.01	29	0.413	1	
	802.11ac (VHT20)	5180	27.11	8.60	29	0.352	1	
		5200	27.90	8.76	29	0.439	1	
		5240	27.20	9.01	29	0.395	1	
	802.11ac (VHT40)	5190	25.66	8.64	29	0.255	1	
		5230	27.46	8.89	29	0.408	1	
	802.11ac (VHT80)	5210	25.76	8.87	29	0.275	1	
	5GHz (U-NII-3)	802.11a	5745	28.77	9.39	29	0.619	1
			5785	28.76	9.56	29	0.643	1
			5825	28.76	9.63	29	0.653	1
802.11ac (VHT20)		5745	28.72	9.39	29	0.612	1	
		5785	28.73	9.56	29	0.638	1	
		5825	28.75	9.63	29	0.652	1	
802.11ac (VHT40)		5755	28.79	9.47	29	0.634	1	
		5795	28.80	9.61	29	0.656	1	
802.11ac (VHT80)		5775	28.71	9.56	29	0.635	1	

Note:

2412: Directional gain = $10 \log[(10^{G_1/20} + 10^{G_2/20} + \dots + 10^{G_N/20})^2/N] = 7.16\text{dBi}$

2437: Directional gain = $10 \log[(10^{G_1/20} + 10^{G_2/20} + \dots + 10^{G_N/20})^2/N] = 7.69\text{dBi}$

2462: Directional gain = $10 \log[(10^{G_1/20} + 10^{G_2/20} + \dots + 10^{G_N/20})^2/N] = 8.27\text{dBi}$

2422: Directional gain = $10 \log[(10^{G_1/20} + 10^{G_2/20} + \dots + 10^{G_N/20})^2/N] = 7.30\text{dBi}$

2452: Directional gain = $10 \log[(10^{G_1/20} + 10^{G_2/20} + \dots + 10^{G_N/20})^2/N] = 8.07\text{dBi}$

5180: Directional gain = $10 \log[(10^{G_1/20} + 10^{G_2/20} + \dots + 10^{G_N/20})^2/N] = 8.60\text{dBi}$

5200: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.76\text{dBi}$
 5240: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.01\text{dBi}$
 5190: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.64\text{dBi}$
 5230: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.89\text{dBi}$
 5210: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.87\text{dBi}$
 5745: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.39\text{dBi}$
 5785: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.56\text{dBi}$
 5825: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.63\text{dBi}$
 5755: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.47\text{dBi}$
 5795: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.61\text{dBi}$
 5775: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.56\text{dBi}$

Beamforming Mode

Band	Modulation type	Frequency (MHz)	Max Power (dBm)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
5GHz (U-NII-1)	802.11ac (VHT20)	5180	26.99	8.60	29	0.343	1
		5200	26.99	8.76	29	0.356	1
		5240	26.89	9.01	29	0.368	1
	802.11ac (VHT40)	5190	25.43	8.64	29	0.242	1
		5230	27.07	8.89	29	0.373	1
		5210	25.26	8.87	29	0.245	1
5GHz (U-NII-3)	802.11ac (VHT20)	5745	26.42	9.39	29	0.361	1
		5785	26.43	9.56	29	0.376	1
		5825	26.34	9.63	29	0.374	1
	802.11ac (VHT40)	5755	26.49	9.47	29	0.373	1
		5795	26.38	9.61	29	0.376	1
		5775	26.41	9.56	29	0.374	1

Note:

5180: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.60\text{dBi}$
 5200: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.76\text{dBi}$
 5240: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.01\text{dBi}$
 5190: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.64\text{dBi}$
 5230: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.89\text{dBi}$
 5210: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.87\text{dBi}$
 5745: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.39\text{dBi}$
 5785: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.56\text{dBi}$
 5825: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.63\text{dBi}$
 5755: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.47\text{dBi}$
 5795: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.61\text{dBi}$
 5775: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.56\text{dBi}$

Conclusion:

The formula of calculated the MPE is:

$CPD1 / LPD1 + CPD2 / LPD2 + \dots \text{etc.} < 1$

CPD = Calculation power density

LPD = Limit of power density

WLAN 2.4GHz + WLAN 5GHz = 0.313 + 0.656 = 0.969

Therefore all the maximum calculations of above situations are less than the "1" limit.

---END---