



A D T

RF Exposure Report

Report No.: SA160205C08A

FCC ID: PY315300322

Test Model: EX6400

Received Date: Feb. 04, 2016

Test Date: Feb. 23 ~ Mar. 17, 2016

Issued Date: Apr. 08, 2016

Applicant: NETGEAR, INC.

Address: 350 East Plumeria Drive San Jose, CA 95134

Issued By: Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch

Lab Address: No. 47-2, 14th Ling, Chia Pau Vil., Lin Kou Dist., New Taipei City, Taiwan (R.O.C.)

Test Location: No.19, Hwa Ya 2nd Rd., Wen Hwa Vil., Kwei Shan Dist., Taoyuan City 33383, TAIWAN (R.O.C.)



This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification. The report must not be used by the client to claim product certification, approval, or endorsement by TAF or any government agencies.



Table of Contents

Release Control Record	3
1 Certificate of Conformity	4
2 RF Exposure	5
2.1 Limits for Maximum Permissible Exposure (MPE)	5
2.2 MPE Calculation Formula	5
2.3 Classification	5
3 Calculation Result of Maximum Conducted Power	6



A D T

Release Control Record

Issue No.	Description	Date Issued
SA160205C08A	Original release.	Apr. 08, 2016



A D T

1 Certificate of Conformity

Product: AC1900 WiFi Range Extender

Brand: NETGEAR

Test Model: EX6400

Sample Status: Engineering sample

Applicant: NETGEAR, INC.

Test Date: Feb. 23 ~ Mar. 17, 2016

Standards: FCC Part 2 (Section 2.1091)
KDB 447498 D01 (October 23, 2015)
IEEE C95.1

The above equipment has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

Prepared by : Suntee Liu, **Date:** Apr. 08, 2016
Suntee Liu / Specialist

Approved by : Ken Liu, **Date:** Apr. 08, 2016
Ken Liu / Senior Manager

2 RF Exposure

2.1 Limits for Maximum Permissible Exposure (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)	Average Time (minutes)
Limits For General Population / Uncontrolled Exposure				
300-1500	F/1500	30
1500-100,000	1.0	30

F = Frequency in MHz

2.2 MPE Calculation Formula

$$P_d = (P_{out} \cdot G) / (4 \cdot \pi \cdot r^2)$$

where

P_d = power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm

2.3 Classification

The antenna of this product, under normal use condition, is at least 26cm away from the body of the user. So, this device is classified as **Mobile Device**.



A D T

3 Calculation Result of Maximum Conducted Power

CDD Mode

Band	Modulation type	Frequency (MHz)	Max Power (dBm)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
2.4GHz	802.11b	2412	23.75	5.02	26	0.089	1
		2437	25.48	5.57	26	0.150	1
		2462	23.75	6.25	26	0.118	1
	802.11g	2412	20.96	5.02	26	0.047	1
		2437	25.58	5.57	26	0.153	1
		2462	22.13	6.25	26	0.081	1
	802.11n (HT20)	2412	19.75	5.02	26	0.035	1
		2437	25.76	5.57	26	0.160	1
		2462	19.95	6.25	26	0.049	1
	802.11n (HT40)	2422	17.45	5.12	26	0.021	1
		2437	19.85	5.57	26	0.041	1
		2452	17.85	5.93	26	0.028	1
5GHz (U-NII-1)	802.11a	5180	27.13	8.60	26	0.440	1
		5200	28.04	8.76	26	0.563	1
		5240	27.39	9.01	26	0.514	1
	802.11ac (VHT20)	5180	27.11	8.60	26	0.438	1
		5200	27.90	8.76	26	0.546	1
		5240	27.20	9.01	26	0.492	1
	802.11ac (VHT40)	5190	25.66	8.64	26	0.317	1
		5230	27.46	8.89	26	0.508	1
	802.11ac (VHT80)	5210	25.76	8.87	26	0.342	1
5GHz (U-NII-3)	802.11a	5745	27.20	9.39	26	0.537	1
		5785	28.76	9.56	26	0.800	1
		5825	27.35	9.63	26	0.587	1
	802.11ac (VHT20)	5745	27.07	9.39	26	0.521	1
		5785	28.73	9.56	26	0.794	1
		5825	27.22	9.63	26	0.570	1
	802.11ac (VHT40)	5755	25.83	9.47	26	0.399	1
		5795	26.33	9.61	26	0.462	1
	802.11ac (VHT80)	5775	25.58	9.56	26	0.384	1

Note:

2412: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 5.02\text{dBi}$

2437: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 5.57\text{dBi}$

2462: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 6.25\text{dBi}$

2422: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 5.12\text{dBi}$

2452: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 5.93\text{dBi}$

5180: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.60\text{dBi}$

5200: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.76\text{dBi}$
5240: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.01\text{dBi}$
5190: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.64\text{dBi}$
5230: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.89\text{dBi}$
5210: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.87\text{dBi}$
5745: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.39\text{dBi}$
5785: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.56\text{dBi}$
5825: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.63\text{dBi}$
5755: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.47\text{dBi}$
5795: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.61\text{dBi}$
5775: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.56\text{dBi}$

Beamforming Mode

Band	Modulation type	Frequency (MHz)	Max Power (dBm)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
5GHz (U-NII-1)	802.11ac (VHT20)	5180	26.99	8.60	26	0.426	1
		5200	26.99	8.76	26	0.442	1
		5240	26.89	9.01	26	0.458	1
	802.11ac (VHT40)	5190	25.43	8.64	26	0.300	1
		5230	27.07	8.89	26	0.464	1
	802.11ac (VHT80)	5210	25.26	8.87	26	0.305	1
5GHz (U-NII-3)	802.11ac (VHT20)	5745	26.31	9.39	26	0.437	1
		5785	26.28	9.56	26	0.452	1
		5825	26.33	9.63	26	0.464	1
	802.11ac (VHT40)	5755	25.57	9.47	26	0.376	1
		5795	26.30	9.61	26	0.459	1
	802.11ac (VHT80)	5775	25.41	9.56	26	0.370	1

Note:

5180: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.60\text{dBi}$
5200: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.76\text{dBi}$
5240: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.01\text{dBi}$
5190: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.64\text{dBi}$
5230: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.89\text{dBi}$
5210: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.87\text{dBi}$
5745: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.39\text{dBi}$
5785: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.56\text{dBi}$
5825: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.63\text{dBi}$
5755: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.47\text{dBi}$
5795: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.61\text{dBi}$
5775: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.56\text{dBi}$

Conclusion:

The formula of calculated the MPE is:

$CPD1 / LPD1 + CPD2 / LPD2 + \dots \text{etc.} < 1$

CPD = Calculation power density

LPD = Limit of power density

WLAN 2.4GHz + WLAN 5GHz = 0.160 + 0.800 = 0.960

Therefore all the maximum calculations of above situations are less than the "1" limit.

---END---