

## RF Exposure Report

**Report No.:** SA160419E08

**FCC ID:** PY326200345

**Test Model:** WAC740

**Received Date:** Apr. 19, 2016

**Test Date:** July 11, 2016

**Issued Date:** July 28, 2016

**Applicant:** NETGEAR, Inc.

**Address:** 350 East Plumeria Drive San Jose, CA 95134

**Issued By:** Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch  
Hsin Chu Laboratory

**Lab Address:** E-2, No.1, Li Hsin 1st Road, Hsinchu Science Park, Hsinchu City 300,  
Taiwan R.O.C.

This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification. The report must not be used by the client to claim product certification, approval, or endorsement by any government agencies.

## Table of Contents

<b>Release Control Record .....</b>	<b>3</b>
<b>1     Certificate of Conformity .....</b>	<b>4</b>
<b>2     RF Exposure .....</b>	<b>5</b>
2.1   Limits For Maximum Permissible Exposure (MPE) .....	5
2.2   MPE Calculation Formula .....	5
2.3   Classification .....	5
2.4   Antenna Gain .....	6
2.5   Directional Gain Table .....	7
2.6   Calculation Result Of Maximum Conducted Power .....	8

### Release Control Record

Issue No.	Description	Date Issued
SA160419E08	Original release.	July 28, 2016

## 1 Certificate of Conformity

**Product:** ProSAFE Dual Band Wireless AC Access Point

**Brand:** NETGEAR

**Test Model:** WAC740

**Sample Status:** ENGINEERING SAMPLE

**Applicant:** NETGEAR, Inc.

**Test Date:** July 11, 2016

**Standards:** FCC Part 2 (Section 2.1091)

KDB 447498 D01 General RF Exposure Guidance v06

IEEE C95.1-1992

The above equipment has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

**Prepared by :** Wendy Wu , **Date:** July 28, 2016  
Wendy Wu / Specialist

**Approved by :** May Chen , **Date:** July 28, 2016  
May Chen / Manager

## 2 RF Exposure

### 2.1 Limits For Maximum Permissible Exposure (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm <sup>2</sup> )	Average Time (minutes)
Limits For General Population / Uncontrolled Exposure				
300-1500	...	...	F/1500	30
1500-100,000	...	...	1.0	30

F = Frequency in MHz

### 2.2 MPE Calculation Formula

$$Pd = (Pout * G) / (4 * \pi * r^2)$$

where

Pd = power density in mW/cm<sup>2</sup>

Pout = output power to antenna in mW

G = gain of antenna in linear scale

Pi = 3.1416

R = distance between observation point and center of the radiator in cm

### 2.3 Classification

The antenna of this product, under normal use condition, is at least 37cm away from the body of the user.

So, this device is classified as **Mobile Device**.

## 2.4 Antenna Gain

External Antenna									
Transmitter Circuit (For 2.4G)	Transmitter Circuit (For 5G)	Brand	Model	Antenna Gain(dBi) <including cable loss>	Frequency range (MHz ~ MHz)	Antenna Type	Connector Type	Cable Loss(db)	Cable Length (mm)
Chain (0)	Chain (3)	Master Wave Tech	98364PRSX004	-0.2	2.4~2.4835	Dipole	R-SMA	1	172
				0	5.15~5.25			1.5	
				0.1	5.25~5.35			1.5	
				-0.8	5.47~5.725			1.5	
				-1	5.725~5.85			1.5	
Chain (1)	Chain (2)	Master Wave Tech	98364PRSX004	0	2.4~2.4835	Dipole	R-SMA	0.8	175
				0.1	5.15~5.25			1.4	
				0.2	5.25~5.35			1.4	
				-0.7	5.47~5.725			1.4	
				-0.9	5.725~5.85			1.4	
Chain (2)	Chain (1)	Master Wave Tech	98364PRSX004	0	2.4~2.4835	Dipole	R-SMA	0.8	145
				0.2	5.15~5.25			1.3	
				0.3	5.25~5.35			1.3	
				-0.6	5.47~5.725			1.3	
				-0.8	5.725~5.85			1.3	
Chain (3)	Chain (0)	Master Wave Tech	98364PRSX004	0	2.4~2.4835	Dipole	R-SMA	0.8	135
				0.1	5.15~5.25			1.4	
				0.2	5.25~5.35			1.4	
				-0.7	5.47~5.725			1.4	
				-0.9	5.725~5.85			1.4	
Internal Antenna									
Transmitter Circuit		Brand	Model	Antenna Gain(dBi)	Frequency range (MHz ~ MHz)	Antenna Type		Connector Type	
Chain (0)	NA	NA	5	2.4~2.4835	PIFA	i-pex(MHF)			
			6	5.15~5.25					
			6	5.25~5.35					
			6	5.47~5.725					
			6	5.725~5.85					
Chain (1)	NA	NA	5	2.4~2.4835	PIFA	i-pex(MHF)			
			6	5.15~5.25					
			6	5.25~5.35					
			6	5.47~5.725					
			6	5.725~5.85					
Chain (2)	NA	NA	5	2.4~2.4835	PIFA	i-pex(MHF)			
			6	5.15~5.25					
			6	5.25~5.35					
			6	5.47~5.725					
			6	5.725~5.85					
Chain (3)	NA	NA	5	2.4~2.4835	PIFA	i-pex(MHF)			
			6	5.15~5.25					
			6	5.25~5.35					
			6	5.47~5.725					
			6	5.725~5.85					

## 2.5 Directional Gain Table

Frequency	Max Gain (dBi)
5180-5240	6.04
5745-5825	5.67

Note:

1. Non-TxBF mode & TxBF mode antenna gain refer to KDB 662911 F 2) f) (ii)

$$DirectionalGain = 10 \cdot \log \left[ \frac{\sum_{j=1}^{N_{SS}} \left\{ \sum_{k=1}^{N_{ANT}} g_{j,k} \right\}^2}{N_{ANT}} \right]$$

where

Each antenna is driven by no more than one spatial stream;

$N_{SS}$  = the number of independent spatial streams of data;

$N_{ANT}$  = the total number of antennas

$g_{j,k} = 10^{G_k / 20}$  if the  $k$ th antenna is being fed by spatial stream  $j$ , or zero if it is not;

$G_k$  is the gain in dBi of the  $k$ th antenna.

## 2.6 Calculation Result Of Maximum Conducted Power

Frequency Band (MHz)	Max Power (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm <sup>2</sup> )	Limit (mW/cm <sup>2</sup> )
2412-2462	970.785	11.02	37	0.71369	1
5180-5240	819.499	6.04	37	0.19140	1
5745-5825	909.707	5.67	37	0.19511	1

NOTE:

2.4GHz: Directional gain = 5dBi + 10log(4) = 11.02dBi

5GHz:

UNII-1: Directional gain = 6.04dBi

UNII-3: Directional gain = 5.67dBi

### Conclusion:

The formula of calculated the MPE is:

$CPD1 / LPD1 + CPD2 / LPD2 + \dots \text{etc.} < 1$

CPD = Calculation power density

LPD = Limit of power density

WLAN 2.4GHz + WLAN 5GHz =  $0.71369 / 1 + 0.19511 / 1 = 0.90880$

**Therefore the maximum calculations of above situations are less than the “1” limit.**

**--- END ---**