



**S** Schweizerischer Kalibrierdienst  
**C** Service suisse d'étalonnage  
**C** Servizio svizzero di taratura  
**S** Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)

The Swiss Accreditation Service is one of the signatories to the EA  
 Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

Client **Intertek**

Certificate No: **DAE4-358\_Sep12**

## CALIBRATION CERTIFICATE

Object **DAE4 - SD 000 D04 BJ - SN: 358**

Calibration procedure(s) **QA CAL-06.v25**  
 Calibration procedure for the data acquisition electronics (DAE)

Calibration date: **September 11, 2012**

This calibration certificate documents the traceability to national standards, which realize the physical units of measurements (SI).  
 The measurements and the uncertainties with confidence probability are given on the following pages and are part of the certificate.

All calibrations have been conducted in the closed laboratory facility: environment temperature ( $22 \pm 3$ )°C and humidity < 70%.

Calibration Equipment used (M&TE critical for calibration)

Primary Standards	ID #	Cal Date (Certificate No.)	Scheduled Calibration
Keithley Multimeter Type 2001	SN: 0810278	28-Sep-11 (No:11450)	Sep-12
Secondary Standards	ID #	Check Date (in house)	Scheduled Check
Calibrator Box V2.1	SE UWS 053 AA 1001	05-Jan-12 (in house check)	In house check: Jan-13

Calibrated by:	Name Dominique Steffen	Function Technician	Signature 
Approved by:	Fin Bomholt	R&D Director	

Issued: September 11, 2012

This calibration certificate shall not be reproduced except in full without written approval of the laboratory.



Accredited by the Swiss Accreditation Service (SAS)

The Swiss Accreditation Service is one of the signatories to the EA  
Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

## Glossary

DAE	data acquisition electronics
Connector angle	information used in DASY system to align probe sensor X to the robot coordinate system.

## Methods Applied and Interpretation of Parameters

- *DC Voltage Measurement:* Calibration Factor assessed for use in DASY system by comparison with a calibrated instrument traceable to national standards. The figure given corresponds to the full scale range of the voltmeter in the respective range.
- *Connector angle:* The angle of the connector is assessed measuring the angle mechanically by a tool inserted. Uncertainty is not required.
- The following parameters as documented in the Appendix contain technical information as a result from the performance test and require no uncertainty.
  - *DC Voltage Measurement Linearity:* Verification of the Linearity at +10% and -10% of the nominal calibration voltage. Influence of offset voltage is included in this measurement.
  - *Common mode sensitivity:* Influence of a positive or negative common mode voltage on the differential measurement.
  - *Channel separation:* Influence of a voltage on the neighbor channels not subject to an input voltage.
  - *AD Converter Values with inputs shorted:* Values on the internal AD converter corresponding to zero input voltage
  - *Input Offset Measurement:* Output voltage and statistical results over a large number of zero voltage measurements.
  - *Input Offset Current:* Typical value for information; Maximum channel input offset current, not considering the input resistance.
  - *Input resistance:* Typical value for information: DAE input resistance at the connector, during internal auto-zeroing and during measurement.
  - *Low Battery Alarm Voltage:* Typical value for information. Below this voltage, a battery alarm signal is generated.
  - *Power consumption:* Typical value for information. Supply currents in various operating modes.

## DC Voltage Measurement

A/D - Converter Resolution nominal

High Range: 1LSB =  $6.1\mu V$ , full range =  $-100...+300\text{ mV}$

Low Range: 1LSB =  $61\text{nV}$ , full range =  $-1.....+3\text{mV}$

DASY measurement parameters: Auto Zero Time: 3 sec; Measuring time: 3 sec

Calibration Factors	X	Y	Z
High Range	$404.152 \pm 0.1\% (\text{k=2})$	$403.803 \pm 0.1\% (\text{k=2})$	$403.662 \pm 0.1\% (\text{k=2})$
Low Range	$3.94011 \pm 0.7\% (\text{k=2})$	$3.96985 \pm 0.7\% (\text{k=2})$	$3.94913 \pm 0.7\% (\text{k=2})$

## Connector Angle

Connector Angle to be used in DASY system	$327^\circ \pm 1^\circ$
---	-------------------------

## Appendix

### 1. DC Voltage Linearity

High Range		Reading ( $\mu$ V)	Difference ( $\mu$ V)	Error (%)
Channel X	+ Input	199993.45	-3.10	-0.00
Channel X	+ Input	20004.21	4.62	0.02
Channel X	- Input	-19995.92	5.87	-0.03
Channel Y	+ Input	199998.64	1.65	0.00
Channel Y	+ Input	20001.30	1.69	0.01
Channel Y	- Input	-20001.55	0.23	-0.00
Channel Z	+ Input	199996.91	0.31	0.00
Channel Z	+ Input	20001.52	1.95	0.01
Channel Z	- Input	-20001.48	0.31	-0.00

Low Range		Reading ( $\mu$ V)	Difference ( $\mu$ V)	Error (%)
Channel X	+ Input	1999.92	0.16	0.01
Channel X	+ Input	201.49	1.19	0.59
Channel X	- Input	-198.68	1.00	-0.50
Channel Y	+ Input	1999.36	-0.41	-0.02
Channel Y	+ Input	199.54	-0.81	-0.41
Channel Y	- Input	-201.27	-1.62	0.81
Channel Z	+ Input	1999.61	-0.03	-0.00
Channel Z	+ Input	200.05	-0.11	-0.05
Channel Z	- Input	-199.80	-0.14	0.07

### 2. Common mode sensitivity

DASY measurement parameters: Auto Zero Time: 3 sec; Measuring time: 3 sec

	Common mode Input Voltage (mV)	High Range Average Reading ( $\mu$ V)	Low Range Average Reading ( $\mu$ V)
Channel X	200	9.33	7.15
	-200	-5.37	-6.83
Channel Y	200	-5.70	-5.54
	-200	2.55	2.71
Channel Z	200	11.89	11.79
	-200	-12.64	-12.89

### 3. Channel separation

DASY measurement parameters: Auto Zero Time: 3 sec; Measuring time: 3 sec

	Input Voltage (mV)	Channel X ( $\mu$ V)	Channel Y ( $\mu$ V)	Channel Z ( $\mu$ V)
Channel X	200	-	-3.39	-2.03
Channel Y	200	7.88	-	-1.01
Channel Z	200	6.68	4.74	-

#### 4. AD-Converter Values with inputs shorted

DASY measurement parameters: Auto Zero Time: 3 sec; Measuring time: 3 sec

	High Range (LSB)	Low Range (LSB)
Channel X	16032	15634
Channel Y	16126	15697
Channel Z	15853	13766

#### 5. Input Offset Measurement

DASY measurement parameters: Auto Zero Time: 3 sec; Measuring time: 3 sec

Input  $10M\Omega$

	Average ( $\mu V$ )	min. Offset ( $\mu V$ )	max. Offset ( $\mu V$ )	Std. Deviation ( $\mu V$ )
Channel X	1.57	-0.26	2.41	0.41
Channel Y	-1.28	-2.12	-0.14	0.37
Channel Z	0.57	-0.25	2.20	0.44

#### 6. Input Offset Current

Nominal Input circuitry offset current on all channels: <25fA

#### 7. Input Resistance (Typical values for information)

	Zeroing (kOhm)	Measuring (MOhm)
Channel X	200	200
Channel Y	200	200
Channel Z	200	200

#### 8. Low Battery Alarm Voltage (Typical values for information)

Typical values	Alarm Level (VDC)
Supply (+ Vcc)	+7.9
Supply (- Vcc)	-7.6

#### 9. Power Consumption (Typical values for information)

Typical values	Switched off (mA)	Stand by (mA)	Transmitting (mA)
Supply (+ Vcc)	+0.01	+6	+14
Supply (- Vcc)	-0.01	-8	-9