

# Installation & Operating Instructions




## Contents of this package include:

1. One Emergency Response Light Model #RSB03
2. One RF transmitter with phone wire Model #TMT03
3. Two pairs of Velcro for mounting



**Batteries are not included** – Requires (4) AAA & (4) AA batteries


## Please read all instructions before installation

**Mount the Emergency Response Light (RSB03) and the transmitter (TMT03) no further than 50 feet apart.**




## Emergency Response Light (RSB03) Installation

1. Insert (4) new AA batteries, per markings, into the back of the Emergency Response Light. 
2. **Select the window in your house that is most visible from the street.**
3. Clean and dry surfaces are required for mounting and proper adhesion of Velcro strip.
4. Adhere Velcro to the front of the Emergency Response Light (where indicated on the RSB03) and to the inside of the window. For best results, allow adhesive to bond for 24 hours. 

5. Attach the Emergency Response Light to the window. Do not place it on the glass where it might interfere with the proper opening and closing of the window. 


**Warning: This product is for indoor use only.** Do not place on any plastic coated window that may cause a fire or smoke hazard.




(continued on bottom left)


## Transmitter (TMT03) Installation



1. Insert (4) new AAA batteries, per markings, into the front of the transmitter.
2. Clean and dry surfaces are required for mounting and proper adhesion of Velcro strip.
3. Determine the best location and the phone line that you choose to monitor. **The transmitter (TMT03) must be located within 50 feet of Emergency Response Light RSB03.** You have (2) options:
  - A. mount over a single or double telephone jack plate, insert excess wire into the cutout back of unit (TMT03) for flush mounting or;
  - B. mount adjacent to the telephone jack plate, snap the telephone wire into groove on back of the transmitter (TMT03) prior to installing the Velcro strip. 

**Warning: Residential homes or businesses with multiple phone lines must mount the transmitter (TMT03) to the phone line that is chosen to monitor outgoing emergency calls. The transmitter (TMT03) will only monitor the phone line that is chosen.**

4. Adhere Velcro to the transmitter (top or bottom where indicated on the TMT03) and the telephone jack plate or wall depending on method of installation that you choose (refer to Transmitter Installation instruction #3.A or B.) 

5. Plug the transmitter into the telephone jack of the line that you want to monitor. 

6. **Optional** – plug phone into top of transmitter 

**Warning: This product is for indoor use only.**

## Operation

**Test unit after installation. Use test codes only. Do not dial 911 for testing purposes.**

1. **Dial #99 to activate** the Emergency Response Light (RSB03) and check to see Emergency Response Light unit flashing.
2. **Dial #11 to deactivate** the Emergency Response Light (RSB03), or simply press the reset button on the transmitter unit (TMT03)

**Caution: Excessive testing can shorten battery life significantly.**

Once your Guide Light 911™ is installed, dialing 911 will automatically turn on the Emergency Response Light making it faster and easier for emergency personnel to find your home's exact location.

**Warning:** Periodically check the low battery light and chirp indicators for both units (TMT03 & RSB03). If either or both of them are on, simply replace the batteries and test the units following the same procedure listed above for testing. It is recommended that you change batteries on both units at least twice per year at daylight savings & standard times. Use only high quality, long lasting batteries.

The user of this equipment is advised that changes or modifications not expressly approved by Emergency Safety Systems, Inc. could void the user's authority to operate the equipment. **NOTE:** This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

## Limited Warranty (applies to Models RSB03 and TMT03)

If Guide Light 911™ fails to operate properly under normal household conditions within one year from date of purchase because of defects in workmanship or material, Emergency Safety Systems, Inc. (the Company) will at our option, repair or replace this product without cost to the purchaser for parts and labor. To obtain repair or replacement within the terms of this warranty, the product is to be delivered with proof of warranty coverage (e.g. dated bill of sale), with postage prepaid to Emergency Safety Systems, Inc. 80 Turnpike Drive, Middlebury, CT 06762. Do not return this product to the store where purchased. Please enclose a check or money order in the amount of \$6.50 to cover postage and handling. Products out of warranty will be repaired at our standard repair charges.

This warranty does not cover batteries nor apply to products or parts thereof which, in the opinion of the Company, has suffered or been damaged through alterations, improper installation, mishandling, misuse, neglect, accident, or by removal or defacement of the factory serial number/bar code label(s). This warranty is not assignable or transferable. ANY IMPLIED WARRANTIES, INCLUDING ANY IMPLIED WARRANTY OF MERCHANTABILITY, SHALL BE LIMITED TO THE DURATION OF THIS WRITTEN WARRANTY. IN NO CASE SHALL THE COMPANY BE LIABLE FOR ANY CONSEQUENTIAL OR INCIDENTAL DAMAGES FOR BREACH OF THIS OR ANY OTHER WARRANTY, EXPRESS OR IMPLIED, WHATSOEVER. No person or representative is authorized to assume for the Company any liability other than expressed herein in connection with the sale of this product. THE EXTENT OF THE COMPANY'S LIABILITY UNDER THIS WARRANTY IS LIMITED TO THE REPAIR OR REPLACEMENT PROVIDED ABOVE AND, IN NO EVENT, SHALL THE COMPANY'S LIABILITY EXCEED THE PURCHASE PRICE PAID BY PURCHASER FOR THE PRODUCT.

Since some states do not allow limitations of the duration of an implied warranty or do not allow the exclusion or limitation of incidental or consequential damage, the above limitations or exclusions may not apply. You may have rights that vary from state to state. Guide Light 911™ is not a substitute for property, fire, life, disability or other insurance of any kind. Appropriate insurance is your responsibility.

Guide Light 911™ does not guarantee saving lives nor does it guarantee reducing the time it takes for emergency personnel to respond to or locate the source of the emergency call.

This is the entirety of the warranty on Guide Light 911™. No other written or express warranty is given.

Guide Light 911™ is distributed by:  
Emergency Safety Systems, Inc.  
80 Turnpike Drive, Middlebury, CT 06762  
1-866-FIND911 (346-3911)



# Instrucciones de Instalar y Funcionar




## Los Contenos de este paquete incluyen:

1. Una "Emergency Response Light" (ERL) modelo #RSB03
2. Un transmisor RF con linea de teléfono modelo #TMT03
3. Dos parejas de velcro para amarrar

**No incluye las baterías** – Requiere (4) baterías de AAA y (4) baterías de AA

## Por favor, lea todas las instrucciones antes de Instalación

**Ponga la Emergency Response Light (ERL) RSB03 y el transmisor (TMT03) no más aparte que cincuenta pies.**



## Instalación de la Luz de Emergencia (RSB03)


1. Ponga (4) baterías nuevas de AA atrás de la ERL.
2. **Seleccione la ventana en su casa más visible de la calle.**
3. Superficies limpias y secos son necesarios para poner y adherir el velcro correctamente.
4. Ponga el velcro al frente de la ERL (donde indicado en el RSB03) y al dentro de la ventana. Para los resultados mejores, no lo toque por 24 horas.



5. Adjunte la ERL a la ventana. No ponga en el vidrio donde pueda meterse con como abirir y cerrar de la ventana en una manera correcta.



**Advertencia: Este producto es para el uso interior solamente.** No ponga en una ventana hecha de plástico porque pueda causar un peligro de fuego o humo.



(continued on bottom left)

## Instalación de Transmisor (TMT03)

1. Ponga (4) baterías nuevas de AAA en el frente de la transmisor.
2. Superficies limpias y secos son necesarios para poner y adherir el velcro correctamente.
3. Escoja el lugar mejor y la linea de teléfono escogida. **El transmisor (TMT03) tiene que estar dentro de cincuenta pies de ERL (RSB03).** Usted tiene dos opciones:
  - A. Ponga sobre de uno o doble plato de teléfono, ponga el hilo exceso en el posterior cortado del unito (TMT03) para montura tendida o;
  - B. Ponga adyacente al plato de teléfono, ponga el hilo de teléfono dentro de la ranura en el posterior de la transmisor (TMT03) antes de instalar el pedazo de velcro.



**AVISO: Casas residenciales o comercios con lineas multiples tienen que poner el transmisor (TMT03) a la linea del teléfono que sea escogida para supervisar llamadas de emergencias. El transmisor (TMT03) solamente supervisar la linea que sea escogida.**

4. Adhiera el velcro al transmisor (arriba o fondo donde es indicado en la TMT03) y el plato del teléfono o pared seguia el método de instalación escogido (**Refiera a las instrucciones de instalación para el transmisor TMT03, #3.A o B).**
5. Enchufe el transmisor en el plato del teléfono de la linea supervisada.
6. **Opcional** – Enchufe el teléfono en la parte superior del transmisor.

**Aviso: Este producto es para el uso interior solamente.**

## Funcionamiento

**Pruebe despues de instalar. Use los codigos de probar solamente. No disque 911 para el uso de probar.**

1. **Disque #99 para activar** el ERL (RSB03) y para ver la llamada de ERL.
2. **Disque #11 para desactivar** el ERL (RSB03) o simplemente pulse el botón reestablecer (reponer) en el unito de la transmisor (TMT03).

**Aviso: Pruebas demasiadas pueden cortar la vida de las baterías significativamente.**

Quando usted ha instalado la Guide Light 911™, la ERL empezará cuando usted llame 911 y será más rápido y más fácil para las personas de emergencia quienes están buscando el posicion exacto de su casa.

**Aviso:** Periódicamente compruebe la luz de batería baja y señalizadores de gorjeos de los unitos (TMT03 y RSB03). Si no hay las luces, entonces reponga las baterías y pruebe los unitos (lea las mismas direcciones que el "Funcionamiento"). Es recomendado de poner baterías nuevas en los dos unitos dos veces cada año, en el otoño y primavera cuando la hora cambia (Daylight Savings Time). Use solamente baterías de calidad buena y durable.

El usuario de este equipo es avisado que cambios y modificaciones no aprobados por Emergency Safety Systems, Inc. Pueden negar el autoridad del usuario operar el equipo.

NOTA: Este equipo ha sido probado y condesce con los limites para un aparato digital de la clase B, en conformidad a parte 15 de las reglas FCC. Estos limites son designados para facilitar protección razonable contra interferencia dañina en una instalación residencial. Este equipo genera usos y puede radiar energia del radio frecuencia y si no instalado y usado con las instrucciones correctamente, pueda causar interferencia dañina a las comunicaciones del radio. Aunque, no hay garantía que la interferencia no ocurrirá en una instalación particular. Si este equipo cause interferencia dañina a recepción del radio o televisor, que puede ser determinado por usar y detener el equipo, el usuario es alentado probar corregir la interferencia con uno o más del siguiente:

- Cambiar o reubicar la antena del recepción
- Aumentar la separación entre el equipo y el receptor
- Conectar el equipo al tomacorriente diferente que el receptor
- Consultar un tecnico experimentado con televisor o radio para ayudarle con el problema

## Garantía Limitada (aplica a los modelos RSB03 y TMT03)

Si Guide Light 911™ falle operar correctamente en condiciones normales de casas dentro de un año de la fecha de comprar o causa de los defectos en habilidad o material, Emergency Safety Systems, Inc. (la compania) reparara o sustuir este producto sin coste al comprador para los partes o trabajo. Para obtener reparación o sustitución con los acuerdos de esta garantía, el producto debe ser entregado con prueba de la cobertura de garantía (la cuenta con la fecha), con franqueo pagado por adelantado a Emergency Safety Systems, Inc. 80 Turnpike Drive, Middlebury, CT 06762. No traiga este producto a la tienda donde fue comprado. Productos con garantías expiradas serán reparados para un precio normal de reparar.

Esta garantía no es para las baterías y también no aplica a los productos y partes que han sido maltratados (en la opinion de la compania) por cambios, instalación impropios, maltratamiento, mal uso, descuido, accidente, or por retiro o cubierta del numero serial de la fábrica / escritura codigo de barra. Esta garantía no es asignable o transferible. LAS GARANTÍAS IMPLÍCITAS, INCLUYENDO GARANTÍA IMPLÍCITA O MERCANTILIDAD, SON LIMITADAS A LA DURACIÓN DE ESTA GARANTÍA ESCRITA. EN NO CASO SERÁ LA COMPANIA RESPONSABLE PARA DAÑOS CONSIGUIENTES O INTRASCENDENTES PARA BRECHA DE ESTA GARANTÍA OR OTRAS GARANTÍAS, EXPRESO O IMPLÍCITO, TOTALMENTE. Ninguna persona o representante es autorizado asumir para la compania la obligación otra de lo que es expresado en esta garantía en conexión con la venta de este producto. LA CANTIDAD DE LA OBLIGACIÓN DE LAS COMPANIA ES LIMITADA A LA REPARACIÓN O SUSTITUCIÓN ESCRITO ARRIBA Y, EN NO ACONTECIMIENTO, LA OBLIGACIÓN DE LA COMPANIA EXCEDERÁ EL PRECIO PAGADO POR EL COMPRADOR PARA ESTE PRODUCTO.

Porque algunos estados no dejan limitaciones de duración de una garantía implícita o no dejan la exclusión o limitación de daño consiguiente, las limitaciones o exclusiones no aplican necesariamente. Usted tenga derechos que varían estado a estado. Guide Light 911™ no es un sustituto para propiedad, fuego, vida, incapacidad o otro seguro. Seguro apropiado es su responsabilidad.

Guide Light 911™ no es una garantía de salvar vidas ni es garantía de reducir el tiempo de personas de emergencia responder o encontrar el origen de una llamada de emergencia.

Este es la integridad de la garantía de Guide Light 911™. No garantía otra escrita o expresa es dado.

Guide Light 911™ es distribuida por:  
Emergency Safety Systems, Inc.  
80 Turnpike Drive, Middlebury, CT 06762  
1-866-FIND911 (346-3911)

