

Operational Description of the equipment

After connecting landline phone with Voiis Dock, Voiis Mini/Phone thus can receive/dial regular phone calls.

The following section will explain how to connect Voiis Dock with Voiis Mini/Phone.

Step 1. Please take the Voiis Dock from the package and plug the telephone line to the Phone jack (Line). Optionally, you may plug the telephone line that comes with Voiis Dock into the Phone jack (Phone) and then cascade to the other phone.

Step 2. Please insert the Power adapter to Power connector of the Voiis Dock and plug the Power adapter to an electrical outlet.

Step 3. Please make sure the Power indicator light of Voiis Dock is on.

Step 4. Please follow the instruction of Voiis Mini/Phone to pair with Voiis Dock. (On the Voiis Mini/Phone, please select **Menu->Settings->Bluetooth->Pairing mode** to enter pairing mode.)

Step 5. Press the **Function button** on Voiis Dock for 3 seconds until the Bluetooth indicator light flashes fastly. Voiis Dock will automatically search the Voiis Mini/Phone around the neighborhood to be paired with.

Step 6. When the pairing procedure completed, Voiis Dock's Power indicator light will be slowly changed to indicate the successful connection.

Step 7. If it failed to complete the connection, the pairing mode will be exited automatically, which will take about 60 seconds. When the pairing mode ends, please repeat Step 4 to 7 to try again.

PRODUCT	Voiis Dock
MODEL NO.	BV-002
POWER ADAPTOR	Input AC100V~240V Output DC5V/1.0A
CRADLE POWER IN	DC 5.0V, 500mA
FREQUENCY BAND	2.402GHz~2.480GHz
CARRIER FREQUENCY	FHSS(Frequency Hopping Spread Spectrum)
NUMBER OF CHANNEL	79
CHANNEL SPACING	1 MHz
RATED RF OUTPUT POWER	+1.9 dBm
MODE OF OPERATION	duplex
MODULATION TYPE	GFSK(1Mbps)
BIT RATE OF TRANSMISSION	Bluetooth V1.2(1Mbps)
ANTENNA TYPE	Mono Pole
ANTENNA GAIN	-1.0dBi(peak gain)
OPERATING TEMPERATURE	0~45°C
CHANNEL BANDWIDTH	1MHz