

RF EXPOSURE EVALUATION

Applicant	: HIMS International Corporation
Applicant Address	: KT Daejeon Satellite Center, 139-9, Gajung- dong, Yuseong-gu, Daejeon, KOREA, 305-350
Kind of Product	: Braille Sense U2 MINI
Equipment model name	: H418B
RF power	: 7.52 dBm Peak Conducted
Antenna type	: Chip antenna
Antenna Gain	: 1.7 dBi
Frequency Range	: 2412 - 2462 MHz



CTK Co., Ltd. 386-1, Ho-dong, Cheoin-gu, Yongin-si, Gyeonggi-do, 449-100, Korea Tel: +82-31-339-9970 Fax: +82-31-339-9855 www.e-ctk.com

**** MPE Calculations ****

The EUT will only be used with a separation of 20 centimeters or greater between the antenna and the body of the user. The MPE calculation for this exposure is shown below.

The peak radiated output power (EIRP) is calculated as follows:

EIRP = P + G EIRP = 7.52 + 1.7 = 9.22 dBm => 8.356 mW	Where, P = Power input to the antenna (mW) G = Power gain of the antenna (dBi)

The numeric gain(G) of the antenna with a gain specified in dB is determined by:

 $G = Log^{-1} (dB \text{ antenna gain / 10})$ $G = Log^{-1} (1.7/10)$ G = 1.48

Power density at the specific separation:

$S = PG/(4R^2\pi)$	Where,
S = $(8.356)/(4 * 20^2 * \pi)$	 S = Maximum power density (mW/cm²) P = Power input to the antenna (mW) G = Numeric power gain of the antenna R = Distance to the center of the radiation of the
S =0.002 mW/cm ²	antenna (20cm = limit for MPE)

The Maximum permissible exposure (MPE) for the general population is $1\ mW/cm^2$. The power density at 20cm does not exceed the $1\ mW/cm^2$ limit.

Estimated safe separation:

$R = \sqrt{(PG / 4\pi)}$	Where,
$R = \sqrt{(8.356 / 4\pi)}$	P = Power input to the antenna (mW) G = Numeric power gain of the antenna R = Distance to the center of the radiation of the
R = 0.82 cm	antenna (20cm = limit for MPE)