



110 Nortech Parkway
San Jose, California, 95134

**Maximum Permissible Exposure Calculation
for the
Airespace VAP 1200 FCC ID: QTZWNAP1200B
Using INTERNAL 2.4 GHz patch antennas**

The Airespace Access Point (AP) is an IEE802.11 B radio. The access point operates on the 2.4 GHz ISM band. The MPE distance is calculated below. This calculation assumes the use of the internal 2.4GHz antennas.

Operating Environment:

The operating environment for the for the radio in all cases is a fixed, uncontrolled environment, however, the devices are classified as being “Mobile”

Fixed, Uncontrolled Environment:

The FCC limit for the power density for uncontrolled exposure to RF devices operation at 2.4GHz and 5GHz is:
1 mW/cm²

Power density is calculated from the following equation:

$$\text{Exposure (mW/cm}^2\text{)} = \text{Pout (mW)} * \text{Duty Cycle} * (\text{Antenna Gain (as a ratio)} / (4 * \text{PI} * \text{Radius}^2(\text{cm})))$$

Solving the above equation for Radius yields:

$$\text{Radius} = \sqrt{\frac{\text{P}_{\text{out}}(\text{mw}) * \text{Duty Cycle} * \text{Antenna Gain}_{(\text{ratio})}}{\text{Exposure (mW/cm}^2\text{)} * 4 * \text{Pi}}}$$

2.4GHz ISM Band MPE distance Calculation

On channels 1 and 11 of this band, the power is reduced to meet other regulatory criteria.

MAX Pout: 15.5 dBm (35.48 mW)
MAX Ant Gain 7.8 dBi (6.02x)
EIRP: 23.3 dBm (213.79 mW EIRP)

Calculating the MPE distance based on this EIRP:

Calculating the radius of the sphere around which the power density is at the FCC limit. This radius is the MPE distance. To calculate the worst case, a 100% duty cycle is also assumed for each band.

$$\text{MPE Distance} = \sqrt{\frac{35.48 * 6.02 * 1}{1 * 4 * \text{Pi}}} \Rightarrow \sqrt{\frac{213.79}{12.56}} \Rightarrow \text{4.125cm}$$

The following RF Exposure statement will appear near the front of the users / installation manual for the VAP 1200

RF Exposure Safety

FCC RF Exposure Requirements

To ensure compliance with FCC RF exposure requirements, this device must be installed in a location such that the antenna of the device that will be greater than 20cm (8 in.) from all persons. Using higher gain antennas and types of antennas not covered under the FCC certification of this product is not allowed.

Installers of the radio and end users of the system must adhere to the installation instructions outlined in this manual.