



Net = Network  
Flashing = Searching  
SA = Sensor Active

R = Relay  
LED "ON" = Relay Active



800534



Contains: FCC ID: QZC-MNIC  
Contains: IC: 4557A-MNIC  
Model MNIC

Relay 1, 5 amps 120 vac  
Relay 2, 5 amps 120 vac  
Relay 3, 30 amps 240 vac  
Relay 4, 30 amps 240 vac  
All relays are dry contact type

**Not all relays or wires may  
be installed in all units**

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) This device must accept any interference received, including interference that may cause undesired operation.

## CN340AC

120 - 240 vac 50/60 Hz  
10 VA Max

Power = Black  
Input = Black

R1 open = Brown  
R1 com = White  
R1 closed = Yellow

R2 open = Violet  
R2 com = Blue  
R2 closed = Orange

R3 open = Blue / Black  
R3 com = Red  
R3 closed = Blue / White

R4 open = Yellow / Black  
R4 com = Orange / Black  
R4 closed = Yellow / White

Made in USA/Fabriqué aux États-Unis

# Honeywell



## WARNING AVERTISSEMENT

Do not tamper, risk of electrical shock, This controller is not a disconnect. Power may be restored any time. One or more disconnects must be opened before servicing this controller or appliance. To reduce the risk of electrical shock do not connect to a circuit operating at greater than 150 Volts to Ground.

Ne pas altérer, risque de choc électrique. Ce contrôleur n'est pas une déconnexion. L'alimentation peut être rétablie à tout moment. Une ou plusieurs déconnexions doivent être ouvertes avant de réparer ce contrôleur ou cet appareil. Pour réduire le risque de choc électrique, ne pas connecter à un circuit fonctionnant à plus de 150 volts à la terre.

Demand Response by EnTek FC340-H-LC-001 Rev 1.2