

# TC3000UHF Part List 1 (Control Board)

| No. | Material No.  | Material Name                    | Qty. | Ref.No. | Address | Remarks |
|-----|---------------|----------------------------------|------|---------|---------|---------|
| 1   | 3101051030020 | Chip capacitor 0402 0.01UF K 25V | 1    | C501    | B1C     |         |
| 2   | 3101051030020 | Chip capacitor 0402 0.01UF K 25V | 1    | C502    | B2B     |         |
| 3   | 3101051030020 | Chip capacitor 0402 0.01UF K 25V | 1    | C503    | B3B     |         |
| 4   | 3101052700000 | Chip capacitor 0402 27PF J 50V   | 1    | C504    | T3C     |         |
| 5   | 3101051030020 | Chip capacitor 0402 0.01UF K 25V | 1    | C505    | T3C     |         |
| 6   | 3101052700000 | Chip capacitor 0402 27PF J 50V   | 1    | C506    | T3C     |         |
| 7   | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C507    | B4B     |         |
| 8   | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C508    | B4B     |         |
| 9   | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C509    | B4B     |         |
| 10  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C510    | B4C     |         |
| 11  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C511    | B4C     |         |
| 12  | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1    | C512    | B4B     |         |
| 13  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C514    | B4B     |         |
| 14  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C515    | B4B     |         |
| 15  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C516    | B4B     |         |
| 16  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C517    | B4C     |         |
| 17  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C518    | B4C     |         |
| 18  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C519    | B4B     |         |
| 19  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C522    | B4B     |         |
| 20  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C523    | B4B     |         |
| 21  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C524    | B4B     |         |
| 22  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C525    | B4B     |         |
| 23  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C526    | B4B     |         |
| 24  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C527    | B4B     |         |
| 25  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C528    | B4B     |         |
| 26  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C530    | B4B     |         |
| 27  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C531    | B4B     |         |
| 28  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C532    | B4B     |         |
| 29  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C533    | B4B     |         |
| 30  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C534    | B4B     |         |
| 31  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C535    | B4B     |         |
| 32  | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1    | C536    | B4B     |         |
| 33  | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1    | C553    | B3C     |         |
| 34  | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1    | C554    | B3C     |         |
| 35  | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1    | C555    | B3C     |         |
| 36  | 3104074750030 | Ta-capacitor 0805 4.7UF M 10V    | 1    | C556    | B3C     |         |
| 37  | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1    | C557    | B3C     |         |
| 38  | 3101051030020 | Chip capacitor 0402 0.01UF K 25V | 1    | C558    | B3B     |         |
| 39  | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1    | C559    | B3B     |         |
| 40  | 3101052730000 | Chip capacitor 0402 0.027UF K    | 1    | C560    | B3B     |         |
| 41  | 3101052730000 | Chip capacitor 0402 0.027UF K    | 1    | C561    | B2C     |         |
| 42  | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1    | C570    | B2C     |         |
| 43  | 3104074750030 | Ta-capacitor 0805 4.7UF M 10V    | 1    | C571    | B2C     |         |
| 44  | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1    | C572    | B2C     |         |
| 45  | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1    | C573    | B2C     |         |
| 46  | 3101051050010 | Chip capacitor 0402 1UF Z 6.3V   | 1    | C601    | B3C     |         |

确认人:

接收时间:

确认时间:

|    |               |                                  |   |      |     |  |
|----|---------------|----------------------------------|---|------|-----|--|
| 47 | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1 | C603 | T2B |  |
| 48 | 3101051040040 | Chip capacitor 0402 0.1UF K 10V  | 1 | C604 | B2C |  |
| 49 | 3101051040040 | Chip capacitor 0402 0.1UF K 10V  | 1 | C605 | B2C |  |
| 50 | 3101051030020 | Chip capacitor 0402 0.01UF K 25V | 1 | C609 | T2B |  |
| 51 | 3104071060010 | Ta-capacitor 0805 10UF M 10V     | 1 | C610 | T2B |  |
| 52 | 3104071560020 | Ta-capacitor 0805 15UF M 6.3V    | 1 | C611 | B2C |  |
| 53 | 3101051040040 | Chip capacitor 0402 0.1UF K 10V  | 1 | C613 | B2C |  |
| 54 | 3101051040040 | Chip capacitor 0402 0.1UF K 10V  | 1 | C614 | B1C |  |
| 55 | 3101051030020 | Chip capacitor 0402 0.01UF K 25V | 1 | C615 | B1D |  |
| 56 | 3104071060010 | Ta-capacitor 0805 10UF M 10V     | 1 | C616 | B1C |  |
| 57 | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1 | C617 | T2B |  |
| 58 | 3104071560020 | Ta-capacitor 0805 15UF M 6.3V    | 1 | C618 | T1B |  |
| 59 | 3101051050010 | Chip capacitor 0402 1UF Z 6.3V   | 1 | C620 | T1B |  |
| 60 | 3104072250010 | Ta-capacitor 0805 2.2UF M 10V    | 1 | C625 | T2B |  |
| 61 | 3104071060010 | Ta-capacitor 0805 10UF M 10V     | 1 | C626 | B1C |  |
| 62 | 3101051050010 | Chip capacitor 0402 1UF Z 6.3V   | 1 | C627 | T2B |  |
| 63 | 3101051040040 | Chip capacitor 0402 0.1UF K 10V  | 1 | C628 | B3C |  |
| 64 | 3104071060010 | Ta-capacitor 0805 10UF M 10V     | 1 | C629 | B1B |  |
| 65 | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1 | C630 | B3C |  |
| 66 | 3101051040040 | Chip capacitor 0402 0.1UF K 10V  | 1 | C632 | B2D |  |
| 67 | 3104072250010 | Ta-capacitor 0805 2.2UF M 10V    | 1 | C633 | B3C |  |
| 68 | 3104071060010 | Ta-capacitor 0805 10UF M 10V     | 1 | C634 | T2B |  |
| 69 | 3101051050010 | Chip capacitor 0402 1UF Z 6.3V   | 1 | C636 | B2D |  |
| 70 | 3101052710000 | Chip capacitor 0402 270PF J 50V  | 1 | C638 | B2D |  |
| 71 | 3101051020010 | Chip capacitor 0402 1000PF K 50V | 1 | C640 | T2A |  |
| 72 | 3101054700010 | Chip capacitor 0402 47PF J 50V   | 1 | C642 | B2D |  |
| 73 | 3101051030020 | Chip capacitor 0402 0.01UF K 25V | 1 | C645 | B2D |  |
| 74 | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1 | C646 | B3C |  |
| 75 | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1 | C647 | B3C |  |
| 76 | 3104074750030 | Ta-capacitor 0805 4.7UF M 10V    | 1 | C648 | B3C |  |
| 77 | 3101051030020 | Chip capacitor 0402 0.01UF K 25V | 1 | C649 | B3C |  |
| 78 | 3101051030020 | Chip capacitor 0402 0.01UF K 25V | 1 | C650 | B3C |  |
| 79 | 3101051040040 | Chip capacitor 0402 0.1UF K 10V  | 1 | C651 | B3C |  |
| 80 | 3101053330000 | Chip capacitor 0402 0.033UF K    | 1 | C652 | B3C |  |
| 81 | 3101053330000 | Chip capacitor 0402 0.033UF K    | 1 | C654 | B3C |  |
| 82 | 3104071060010 | Ta-capacitor 0805 10UF M 10V     | 1 | C655 | T2B |  |
| 83 | 3101053330000 | Chip capacitor 0402 0.033UF K    | 1 | C657 | T2B |  |
| 84 | 3101051030020 | Chip capacitor 0402 0.01UF K 25V | 1 | C658 | B1C |  |
| 85 | 3101051040040 | Chip capacitor 0402 0.1UF K 10V  | 1 | C660 | B1C |  |
| 86 | 3101056830000 | Chip capacitor 0402 0.068UF K    | 1 | C661 | B1C |  |
| 87 | 3101061050060 | Chip capacitor 0603 1UF K 10V    | 1 | C663 | B1C |  |
| 88 | 3101053320010 | Chip capacitor 0402 3300PF K 50V | 1 | C664 | B1C |  |
| 89 | 3101053310020 | Chip capacitor 0402 330PF K 50V  | 1 | C665 | B1C |  |
| 90 | 3101051030020 | Chip capacitor 0402 0.01UF K 25V | 1 | C666 | B1C |  |
| 91 | 3101051050010 | Chip capacitor 0402 1UF Z 6.3V   | 1 | C667 | B3C |  |
| 92 | 3101053320010 | Chip capacitor 0402 3300PF K 50V | 1 | C668 | B3C |  |
| 93 | 3101051020010 | Chip capacitor 0402 1000PF K 50V | 1 | C669 | B3C |  |
| 94 | 3101053330000 | Chip capacitor 0402 0.033UF K    | 1 | C670 | B3C |  |

确认人:

接收时间:

确认时间:

|     |               |                                   |   |       |     |  |
|-----|---------------|-----------------------------------|---|-------|-----|--|
| 95  | 3101055620000 | Chip capacitor 0402 5600PF K 25V  | 1 | C671  | B4C |  |
| 96  | 3104074750030 | Ta-capacitor 0805 4.7UF M 10V     | 1 | C673  | B3C |  |
| 97  | 3101051050010 | Chip capacitor 0402 1UF Z 6.3V    | 1 | C674  | B3D |  |
| 98  | 3101051050010 | Chip capacitor 0402 1UF Z 6.3V    | 1 | C675  | B4D |  |
| 99  | 3101051030020 | Chip capacitor 0402 0.01UF K 25V  | 1 | C676  | B3C |  |
| 100 | 3101051040040 | Chip capacitor 0402 0.1UF K 10V   | 1 | C677  | B4C |  |
| 101 | 3101051020010 | Chip capacitor 0402 1000PF K 50V  | 1 | C678  | B4C |  |
| 102 | 3101056830000 | Chip capacitor 0402 0.068UF K     | 1 | C679  | B4C |  |
| 103 | 3101053330000 | Chip capacitor 0402 0.033UF K     | 1 | C680  | B4D |  |
| 104 | 3101051050010 | Chip capacitor 0402 1UF Z 6.3V    | 1 | C681  | B4D |  |
| 105 | 3101051050010 | Chip capacitor 0402 1UF Z 6.3V    | 1 | C682  | B4D |  |
| 106 | 3101061050060 | Chip capacitor 0603 1UF K 10V     | 1 | C683  | B3D |  |
| 107 | 3104071560020 | Ta-capacitor 0805 15UF M 6.3V     | 1 | C685  | B3C |  |
| 108 | 3104071560020 | Ta-capacitor 0805 15UF M 6.3V     | 1 | C686  | B3D |  |
| 109 | 3101061050060 | Chip capacitor 0603 1UF K 10V     | 1 | C689  | B4C |  |
| 110 | 3101054710010 | Chip capacitor 0402 470PF K 50V   | 1 | C691  | B3D |  |
| 111 | 3104071060010 | Ta-capacitor 0805 10UF M 10V      | 1 | C692  | B2C |  |
| 112 | 3101054730000 | Chip capacitor 0402 0.047UF K     | 1 | C693  | B3C |  |
| 113 | 3101051020010 | Chip capacitor 0402 1000PF K 50V  | 1 | C694  | B3C |  |
| 114 | 3104071060010 | Ta-capacitor 0805 10UF M 10V      | 1 | C702  | T3A |  |
| 115 | 3101051010030 | Chip capacitor 0402 100PF J 50V   | 1 | C733  | T3A |  |
| 116 | 3101051010030 | Chip capacitor 0402 100PF J 50V   | 1 | C734  | T3B |  |
| 117 | 3101051010030 | Chip capacitor 0402 100PF J 50V   | 1 | C735  | B2C |  |
| 118 | 3101051010030 | Chip capacitor 0402 100PF J 50V   | 1 | C736  | T2B |  |
| 119 | 3101051010030 | Chip capacitor 0402 100PF J 50V   | 1 | C737  | B3C |  |
| 120 | 3101051010030 | Chip capacitor 0402 100PF J 50V   | 1 | C738  | T2B |  |
| 121 | 3101051010030 | Chip capacitor 0402 100PF J 50V   | 1 | C739  | T3B |  |
| 122 | 3101051010030 | Chip capacitor 0402 100PF J 50V   | 1 | C740  | B1D |  |
| 123 | 3101051010030 | Chip capacitor 0402 100PF J 50V   | 1 | C741  | B1D |  |
| 124 | 3101051010030 | Chip capacitor 0402 100PF J 50V   | 1 | C742  | B1C |  |
| 125 | 3101051010030 | Chip capacitor 0402 100PF J 50V   | 1 | C743  | B1C |  |
| 126 | 3101051050010 | Chip capacitor 0402 1UF Z 6.3V    | 1 | C744  | B1C |  |
| 127 | 3101051040040 | Chip capacitor 0402 0.1UF K 10V   | 1 | C747  | T3B |  |
| 128 | 3101051040040 | Chip capacitor 0402 0.1UF K 10V   | 1 | C748  | B2D |  |
| 129 | 3101081060020 | Chip capacitor 1206 10UF +80、-20  | 1 | C749  | T2B |  |
| 130 | 3101051020010 | Chip capacitor 0402 1000PF K 50V  | 1 | C750  | B2C |  |
| 131 | 3101081060020 | Chip capacitor 1206 10UF +80、-20  | 1 | C751  | B3C |  |
| 132 | 3101051040040 | Chip capacitor 0402 0.1UF K 10V   | 1 | C752  | T3B |  |
| 133 | 3005054730000 | Array resistor 0402 47K*2 J 1/16W | 1 | CP501 | B2B |  |
| 134 | 3005054730000 | Array resistor 0402 47K*2 J 1/16W | 1 | CP502 | B2B |  |
| 135 | 3005054730000 | Array resistor 0402 47K*2 J 1/16W | 1 | CP504 | B3B |  |
| 136 | 3303020100029 | Switching diode MA2S11100L        | 1 | D501  | B2C |  |
| 137 | 3303020100089 | Switching diode MA2S07700L        | 1 | D601  | B1C |  |
| 138 | 3303020100069 | Switching diode MA3J74200L        | 1 | D611  | T3B |  |
| 139 | 3303020100069 | Switching diode MA3J74200L        | 1 | D612  | T2B |  |
| 140 | 3309030600009 | Noise suppression diode RSA6.1EN  | 1 | D700  | B4C |  |
| 141 | 3302031100009 | Zener diode EDZ6.8(TE61)          | 1 | D719  | B4D |  |
| 142 | 3302031100009 | Zener diode EDZ6.8(TE61)          | 1 | D720  | B4C |  |

确认人:

接收时间:

确认时间:

|     |               |                                              |   |       |     |  |
|-----|---------------|----------------------------------------------|---|-------|-----|--|
| 143 | 3302031100009 | Zener diode EDZ6.8(TE61)                     | 1 | D721  | B4D |  |
| 144 | 3302031100009 | Zener diode EDZ6.8(TE61)                     | 1 | D722  | B4D |  |
| 145 | 3610004002909 | SCM M30622M4A-466GP                          | 1 | IC500 | T2C |  |
| 146 | 3612031004459 | Memory AT29C020-90TI                         | 1 | IC501 | T1C |  |
| 147 | 3612031004449 | Memory AT24C64AN-10SI                        | 1 | IC502 | T3C |  |
| 148 | 3609006003959 | Reset IC R3111N421A                          | 1 | IC503 | T3B |  |
| 149 | 3608015000000 | Power supply managing IC (voltage regulator) | 1 | IC505 | T3B |  |
| 150 | 3609015002269 | IC XC62FP5002PR(5V)                          | 1 | IC506 | T2B |  |
| 151 | 3613005004539 | Audio base band processing IC CMX881E1       | 1 | IC601 | T2B |  |
| 152 | 3609999005269 | IC S1T8507B01                                | 1 | IC603 | T2A |  |
| 153 | 3605002005709 | Operational amplifier TA75S01F               | 1 | IC605 | T2B |  |
| 154 | 3605002005729 | Operational amplifier TC75W51FU              | 1 | IC606 | T3B |  |
| 155 | 3605002005729 | Operational amplifier TC75W51FU              | 1 | IC607 | B1C |  |
| 156 | 3605002005729 | Operational amplifier TC75W51FU              | 1 | IC608 | T3B |  |
| 157 | 3605002005729 | Operational amplifier TC75W51FU              | 1 | IC612 | T3B |  |
| 158 | 3602023005739 | AF amplification IC TDA8547TS                | 1 | IC720 | T3A |  |
| 159 | 5202040100019 | Socket connector XF2M-4015-1L 40p            | 1 | J502  | T4C |  |
| 160 | 5202020100049 | Socket connector XF2M-2015-1L 20p            | 1 | J703  | T4B |  |
| 161 | 3221505121009 | Chip ferrite bead 0402 120Ω                  | 1 | L512  | B3B |  |
| 162 | 3221505121009 | Chip ferrite bead 0402 120Ω                  | 1 | L523  | B1C |  |
| 163 | 3221505121009 | Chip ferrite bead 0402 120Ω                  | 1 | L524  | B1C |  |
| 164 | 3221505121009 | Chip ferrite bead 0402 120Ω                  | 1 | L528  | T3B |  |
| 165 | 3212105101000 | Multilayer inductor 0402 100nH               | 1 | L601  | B2C |  |
| 166 | 3212105101000 | Multilayer inductor 0402 100nH               | 1 | L603  | B2C |  |
| 167 | 3403008000019 | Transistor DTC114EE(TL) NPN                  | 1 | Q501  | B2C |  |
| 168 | 3403002000009 | Transistor 2SB1132L02T100R                   | 1 | Q502  | T1B |  |
| 169 | 3411002000009 | Transistor 2SC5343EG NPN                     | 1 | Q601  | T2B |  |
| 170 | 3411002000009 | Transistor 2SC5343EG NPN                     | 1 | Q602  | B2D |  |
| 171 | 3411002000009 | Transistor 2SC5343EG NPN                     | 1 | Q603  | B2D |  |
| 172 | 3411002000009 | Transistor 2SC5343EG NPN                     | 1 | Q604  | B1C |  |
| 173 | 3411002000009 | Transistor 2SC5343EG NPN                     | 1 | Q605  | B3C |  |
| 174 | 3411002000009 | Transistor 2SC5343EG NPN                     | 1 | Q606  | B3C |  |
| 175 | 3403008000059 | Transistor DTC114YE(TL) NPN                  | 1 | Q609  | B1D |  |
| 176 | 3503010000019 | FET 2SJ243-T1 P-channal                      | 1 | Q700  | B3D |  |
| 177 | 3503040000019 | FET UPA672T N-channal                        | 1 | Q701  | T3A |  |
| 178 | 3403008000059 | Transistor DTC114YE(TL) NPN                  | 1 | Q710  | B3C |  |
| 179 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W                | 1 | Q711  | B3D |  |
| 180 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W                | 1 | R501  | B3B |  |
| 181 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W              | 1 | R504  | T3C |  |
| 182 | 3001051010000 | Chip resistor 0402 100Ω J 1/16W              | 1 | R505  | B2B |  |
| 183 | 3001051010000 | Chip resistor 0402 100Ω J 1/16W              | 1 | R506  | B3B |  |
| 184 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W                | 1 | R507  | B3B |  |
| 185 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W                | 1 | R508  | B3B |  |
| 186 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W              | 1 | R510  | B2B |  |
| 187 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W              | 1 | R511  | B2B |  |
| 188 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W              | 1 | R532  | B2B |  |
| 189 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W                | 1 | R533  | B3B |  |
| 190 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W              | 1 | R536  | T3C |  |

确认人:

接收时间:

确认时间:

|     |               |                                  |   |      |     |  |
|-----|---------------|----------------------------------|---|------|-----|--|
| 191 | 3001051020010 | Chip resistor 0402 1KΩ J 1/16W   | 1 | R537 | T3C |  |
| 192 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W    | 1 | R538 | T3B |  |
| 193 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W  | 1 | R539 | T2C |  |
| 194 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W  | 1 | R540 | T2C |  |
| 195 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W  | 1 | R550 | B3B |  |
| 196 | 3001051040010 | Chip resistor 0402 100KΩ J 1/16W | 1 | R551 | B3C |  |
| 197 | 3001051040010 | Chip resistor 0402 100KΩ J 1/16W | 1 | R556 | B3C |  |
| 198 | 3001051040010 | Chip resistor 0402 100KΩ J 1/16W | 1 | R557 | B3C |  |
| 199 | 3001051040010 | Chip resistor 0402 100KΩ J 1/16W | 1 | R558 | B3C |  |
| 200 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W  | 1 | R560 | T3C |  |
| 201 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W  | 1 | R562 | B3B |  |
| 202 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W  | 1 | R563 | B1C |  |
| 203 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W  | 1 | R564 | B1C |  |
| 204 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W  | 1 | R565 | B2C |  |
| 205 | 3001054720000 | Chip resistor 0402 4.7KΩ J 1/16W | 1 | R567 | B3B |  |
| 206 | 3001054720000 | Chip resistor 0402 4.7KΩ J 1/16W | 1 | R568 | B3B |  |
| 207 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W    | 1 | R570 | T1B |  |
| 208 | 3001053320000 | Chip resistor 0402 3.3KΩ J 1/16W | 1 | R571 | B2C |  |
| 209 | 3001051020010 | Chip resistor 0402 1KΩ J 1/16W   | 1 | R601 | B2C |  |
| 210 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W  | 1 | R602 | B2C |  |
| 211 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W  | 1 | R603 | B3C |  |
| 212 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W  | 1 | R604 | B3C |  |
| 213 | 3001051040010 | Chip resistor 0402 100KΩ J 1/16W | 1 | R605 | B3C |  |
| 214 | 3001051540000 | Chip resistor 0402 150KΩ F 1/16W | 1 | R606 | B3C |  |
| 215 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W  | 1 | R607 | B3C |  |
| 216 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W    | 1 | R608 | B2C |  |
| 217 | 3001051240000 | Chip resistor 0402 120KΩ J 1/16W | 1 | R609 | T1B |  |
| 218 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W  | 1 | R610 | B2D |  |
| 219 | 3001053030010 | Chip resistor 0402 30KΩ J 1/16W  | 1 | R611 | B2C |  |
| 220 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W    | 1 | R612 | B2C |  |
| 221 | 3001051040010 | Chip resistor 0402 100KΩ J 1/16W | 1 | R613 | T2B |  |
| 222 | 3001055630000 | Chip resistor 0402 56KΩ J 1/16W  | 1 | R614 | T2B |  |
| 223 | 3001051540000 | Chip resistor 0402 150KΩ F 1/16W | 1 | R615 | T2B |  |
| 224 | 3001051040010 | Chip resistor 0402 100KΩ J 1/16W | 1 | R616 | T2B |  |
| 225 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W  | 1 | R617 | B1D |  |
| 226 | 3001051540000 | Chip resistor 0402 150KΩ F 1/16W | 1 | R618 | B3C |  |
| 227 | 3001051040010 | Chip resistor 0402 100KΩ J 1/16W | 1 | R619 | B3C |  |
| 228 | 3001051000000 | Chip resistor 0402 10Ω J 1/16W   | 1 | R620 | B1C |  |
| 229 | 3001052730000 | Chip resistor 0402 27KΩ J 1/16W  | 1 | R621 | T1B |  |
| 230 | 3001053930000 | Chip resistor 0402 39KΩ J 1/16W  | 1 | R622 | T1B |  |
| 231 | 3001053030010 | Chip resistor 0402 30KΩ J 1/16W  | 1 | R623 | B1C |  |
| 232 | 3001051520000 | Chip resistor 0402 1.5KΩ J 1/16W | 1 | R624 | B2D |  |
| 233 | 3001053930000 | Chip resistor 0402 39KΩ J 1/16W  | 1 | R626 | B3C |  |
| 234 | 3001051040010 | Chip resistor 0402 100KΩ J 1/16W | 1 | R627 | B3C |  |
| 235 | 3001051840000 | Chip resistor 0402 180KΩ J 1/16W | 1 | R628 | B3C |  |
| 236 | 3001053320000 | Chip resistor 0402 3.3KΩ J 1/16W | 1 | R629 | T2B |  |
| 237 | 3001051020010 | Chip resistor 0402 1KΩ J 1/16W   | 1 | R630 | T3B |  |
| 238 | 3001051020010 | Chip resistor 0402 1KΩ J 1/16W   | 1 | R631 | T3B |  |

确认人:

接收时间:

确认时间:

|     |               |                                  |   |      |     |  |
|-----|---------------|----------------------------------|---|------|-----|--|
| 239 | 3001051020010 | Chip resistor 0402 1KΩ J 1/16W   | 1 | R632 | T3B |  |
| 240 | 3001051020010 | Chip resistor 0402 1KΩ J 1/16W   | 1 | R633 | T3B |  |
| 241 | 3001051020010 | Chip resistor 0402 1KΩ J 1/16W   | 1 | R634 | B1C |  |
| 242 | 3001051040010 | Chip resistor 0402 100KΩ J 1/16W | 1 | R635 | B1C |  |
| 243 | 3001051840000 | Chip resistor 0402 180KΩ J 1/16W | 1 | R637 | T2B |  |
| 244 | 3001051850000 | Chip resistor 0402 1.8MΩ J 1/16W | 1 | R639 | B3C |  |
| 245 | 3001053330010 | Chip resistor 0402 33KΩ J 1/16W  | 1 | R642 | B2C |  |
| 246 | 3001053330010 | Chip resistor 0402 33KΩ J 1/16W  | 1 | R643 | B3C |  |
| 247 | 3001051030000 | Chip resistor 0402 10KΩ J 1/16W  | 1 | R644 | B3C |  |
| 248 | 3001053330010 | Chip resistor 0402 33KΩ J 1/16W  | 1 | R645 | B3C |  |
| 249 | 3001053330010 | Chip resistor 0402 33KΩ J 1/16W  | 1 | R646 | B3C |  |
| 250 | 3001051030000 | Chip resistor 0402 10KΩ J 1/16W  | 1 | R647 | B3C |  |
| 251 | 3001053320000 | Chip resistor 0402 3.3KΩ J 1/16W | 1 | R648 | B3C |  |
| 252 | 3001051850000 | Chip resistor 0402 1.8MΩ J 1/16W | 1 | R649 | B3C |  |
| 253 | 3001051040010 | Chip resistor 0402 100KΩ J 1/16W | 1 | R650 | B2D |  |
| 254 | 3001053920010 | Chip resistor 0402 3.9KΩ J 1/16W | 1 | R651 | B2D |  |
| 255 | 3001051540000 | Chip resistor 0402 150KΩ F 1/16W | 1 | R652 | B2D |  |
| 256 | 3001051540000 | Chip resistor 0402 150KΩ F 1/16W | 1 | R653 | B2D |  |
| 257 | 3001053920010 | Chip resistor 0402 3.9KΩ J 1/16W | 1 | R654 | B2D |  |
| 258 | 3001053320000 | Chip resistor 0402 3.3KΩ J 1/16W | 1 | R655 | B2D |  |
| 259 | 3001051540000 | Chip resistor 0402 150KΩ F 1/16W | 1 | R656 | B2D |  |
| 260 | 3001051540000 | Chip resistor 0402 150KΩ F 1/16W | 1 | R657 | B2D |  |
| 261 | 3001052220000 | Chip resistor 0402 2.2KΩ J 1/16W | 1 | R659 | B2D |  |
| 262 | 3001054720000 | Chip resistor 0402 4.7KΩ J 1/16W | 1 | R660 | B1C |  |
| 263 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W    | 1 | R661 | B1B |  |
| 264 | 3001056820000 | Chip resistor 0402 6.8KΩ J 1/16W | 1 | R662 | T2B |  |
| 265 | 3001052730000 | Chip resistor 0402 27KΩ J 1/16W  | 1 | R663 | B1C |  |
| 266 | 3001054720000 | Chip resistor 0402 4.7KΩ J 1/16W | 1 | R665 | B1C |  |
| 267 | 3001051230000 | Chip resistor 0402 12KΩ J 1/16W  | 1 | R666 | B1C |  |
| 268 | 3001051030000 | Chip resistor 0402 10KΩ J 1/16W  | 1 | R667 | B1C |  |
| 269 | 3001052730000 | Chip resistor 0402 27KΩ J 1/16W  | 1 | R669 | T2B |  |
| 270 | 3001053320000 | Chip resistor 0402 3.3KΩ J 1/16W | 1 | R670 | B2C |  |
| 271 | 3001053940000 | Chip resistor 0402 390KΩ J 1/16W | 1 | R671 | T2B |  |
| 272 | 3001051240000 | Chip resistor 0402 120KΩ J 1/16W | 1 | R672 | T2B |  |
| 273 | 3001051020010 | Chip resistor 0402 1KΩ J 1/16W   | 1 | R673 | B1C |  |
| 274 | 3001051030000 | Chip resistor 0402 10KΩ J 1/16W  | 1 | R674 | B1C |  |
| 275 | 3001051530000 | Chip resistor 0402 15KΩ J 1/16W  | 1 | R675 | B1C |  |
| 276 | 3001051040010 | Chip resistor 0402 100KΩ J 1/16W | 1 | R676 | B3C |  |
| 277 | 3001051840000 | Chip resistor 0402 180KΩ J 1/16W | 1 | R677 | B3C |  |
| 278 | 3001051040010 | Chip resistor 0402 100KΩ J 1/16W | 1 | R678 | T2B |  |
| 279 | 3001051240000 | Chip resistor 0402 120KΩ J 1/16W | 1 | R679 | B3C |  |
| 280 | 3001056820000 | Chip resistor 0402 6.8KΩ J 1/16W | 1 | R680 | B3C |  |
| 281 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W    | 1 | R681 | B3C |  |
| 282 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W    | 1 | R682 | B3C |  |
| 283 | 3001053330010 | Chip resistor 0402 33KΩ J 1/16W  | 1 | R683 | B3C |  |
| 284 | 3001056820000 | Chip resistor 0402 6.8KΩ J 1/16W | 1 | R684 | B3C |  |
| 285 | 3001054730000 | Chip resistor 0402 47KΩ J 1/16W  | 1 | R685 | B3C |  |
| 286 | 3001058230000 | Chip resistor 0402 82KΩ J 1/16W  | 1 | R686 | B2C |  |

确认人:

接收时间:

确认时间:

|     |               |                                       |   |       |     |  |
|-----|---------------|---------------------------------------|---|-------|-----|--|
| 287 | 3001058230000 | Chip resistor 0402 82KΩ J 1/16W       | 1 | R687  | T3B |  |
| 288 | 3001058230000 | Chip resistor 0402 82KΩ J 1/16W       | 1 | R688  | B3C |  |
| 289 | 3001053930000 | Chip resistor 0402 39KΩ J 1/16W       | 1 | R689  | B3C |  |
| 290 | 3001058230000 | Chip resistor 0402 82KΩ J 1/16W       | 1 | R690  | T3B |  |
| 291 | 3001058230000 | Chip resistor 0402 82KΩ J 1/16W       | 1 | R691  | T3B |  |
| 292 | 3001051040010 | Chip resistor 0402 100KΩ J 1/16W      | 1 | R692  | B3C |  |
| 293 | 3001054710000 | Chip resistor 0402 470Ω J 1/16W       | 1 | R702  | B3D |  |
| 294 | 3001054710000 | Chip resistor 0402 470Ω J 1/16W       | 1 | R703  | B3D |  |
| 295 | 3001051820000 | Chip resistor 0402 1.8KΩ J 1/16W      | 1 | R704  | B3D |  |
| 296 | 3001051040010 | Chip resistor 0402 100KΩ J 1/16W      | 1 | R705  | B3D |  |
| 297 | 3001051040010 | Chip resistor 0402 100KΩ J 1/16W      | 1 | R712  | B3D |  |
| 298 | 3001051020010 | Chip resistor 0402 1KΩ J 1/16W        | 1 | R714  | B4D |  |
| 299 | 3001054740000 | Chip resistor 0402 470KΩ J 1/16W      | 1 | R723  | B3D |  |
| 300 | 3001053030010 | Chip resistor 0402 30KΩ J 1/16W       | 1 | R724  | B3C |  |
| 301 | 3001054740000 | Chip resistor 0402 470KΩ J 1/16W      | 1 | R731  | B3C |  |
| 302 | 3001051010000 | Chip resistor 0402 100Ω J 1/16W       | 1 | R738  | B3D |  |
| 303 | 3001051010000 | Chip resistor 0402 100Ω J 1/16W       | 1 | R739  | B3C |  |
| 304 | 3001056800000 | Chip resistor 0402 68Ω J 1/16W        | 1 | R750  | B3C |  |
| 305 | 3001052230010 | Chip resistor 0402 22KΩ J 1/16W       | 1 | R771  | T3B |  |
| 306 | 3001053030010 | Chip resistor 0402 30KΩ J 1/16W       | 1 | R772  | B3D |  |
| 307 | 3001051000000 | Chip resistor 0402 10Ω J 1/16W        | 1 | R773  | B4C |  |
| 308 | 3001051030000 | Chip resistor 0402 10KΩ J 1/16W       | 1 | R798  | B3C |  |
| 309 | 3001051030000 | Chip resistor 0402 10KΩ J 1/16W       | 1 | R799  | B3D |  |
| 310 | 3003990000029 | Thermistor 0603 4.7K ±3% N            | 1 | TH601 | B3C |  |
| 311 | 3002994730009 | Trimmer capacitor 47KΩ                | 1 | VR601 | T3B |  |
| 312 | 3701098340000 | Crystal 9.8304MHz TSS-705             | 1 | X500  | T3C |  |
| 313 | 3701184340000 | Crystal 18.432MHz TSS-705             | 1 | X601  | T2A |  |
| 314 | 6201112100009 | TC3000 Lower shield sheet (CPU) 0.2mm | 1 | B3C   |     |  |
| 315 | 4103000100500 | TC3000U-RE CN PCB FR                  | 1 |       |     |  |

确认人：

接收时间：

确认时间：

| TC3000 UHF Part list 1 (RF Board) |               |                                  |      |        |          |                |
|-----------------------------------|---------------|----------------------------------|------|--------|----------|----------------|
| NO.                               | Material NO.  | Material Name/ description       | Qty. | Ref.NO | Print NO | Remarks        |
| 1                                 | 1             | 1                                | 1    | *C108  | T2C      | U(1)400-430MHz |
|                                   | 3101050700010 | Chip capapcitor 0402 7PF B 50V   | 1    |        |          | U(2)440-470MHz |
|                                   | 3101058290010 | Chip capapcitor 0402 8.2PF 50V   | 1    |        |          | U(3)330-370MHz |
|                                   | 3101050700010 | Chip capapcitor 0402 7PF B 50V   | 1    |        |          | U(4)450-480MHz |
|                                   | 3101058290010 | Chip capapcitor 0402 8.2PF 50V   | 1    |        |          | U(5)350-400MHz |
|                                   | 3101050700010 | Chip capapcitor 0402 7PF B 50V   | 1    |        |          | U(6)480-520MHz |
|                                   | 3101050700010 | Chip capapcitor 0402 7PF B 50V   | 1    |        |          | U(0)400-470MHz |
| 2                                 | 3101050800000 | Chip capapcitor 0402 8PF B 50V   | 1    | *C111  | T2C      | U(1)400-430MHz |
|                                   | 3101050800000 | Chip capapcitor 0402 8PF B 50V   | 1    |        |          | U(2)440-470MHz |
|                                   | 3101053900000 | Chip capapcitor 0402 39PF J 50V  | 1    |        |          | U(3)330-370MHz |
|                                   | 3101050800000 | Chip capapcitor 0402 8PF B 50V   | 1    |        |          | U(4)450-480MHz |
|                                   | 3101053900000 | Chip capapcitor 0402 39PF J 50V  | 1    |        |          | U(5)350-400MHz |
|                                   | 3101050800000 | Chip capapcitor 0402 8PF B 50V   | 1    |        |          | U(6)480-520MHz |
|                                   | 3101050800000 | Chip capapcitor 0402 8PF B 50V   | 1    |        |          | U(0)400-470MHz |
| 3                                 | 3101053900000 | Chip capapcitor 0402 39PF J 50V  | 1    | *C118  | T2C      | U(1)400-430MHz |
|                                   | 3101053300000 | Chip capapcitor 0402 33PF J 50V  | 1    |        |          | U(2)440-470MHz |
|                                   | 3101054700010 | Chip capapcitor 0402 47PF J 50V  | 1    |        |          | U(3)330-370MHz |
|                                   | 3101053300000 | Chip capapcitor 0402 33PF J 50V  | 1    |        |          | U(4)450-480MHz |
|                                   | 3101054700010 | Chip capapcitor 0402 47PF J 50V  | 1    |        |          | U(5)350-400MHz |
|                                   | 3101052700000 | Chip capapcitor 0402 27PF J 50V  | 1    |        |          | U(6)480-520MHz |
|                                   | NC            | NC                               | 1    |        |          | U(0)400-470MHz |
| 4                                 | 3101061500010 | Chip capapcitor 0603 15PF J 50V  | 1    | *C130  | T2D      | U(1)400-430MHz |
|                                   | 3101060900010 | Chip capapcitor 0603 9PF B 50V   | 1    |        |          | U(2)440-470MHz |
|                                   | 3101061100010 | Chip capapcitor 0603 11PF B 50V  | 1    |        |          | U(3)330-370MHz |
|                                   | 3101060900010 | Chip capapcitor 0603 9PF B 50V   | 1    |        |          | U(4)450-480MHz |
|                                   | 3101060800010 | Chip capapcitor 0603 8PF B 50V   | 1    |        |          | U(5)350-400MHz |
|                                   | 3101060700020 | Chip capapcitor 0603 7PF B 50V   | 1    |        |          | U(6)480-520MHz |
|                                   | 3101061000010 | Chip capapcitor 0603 10PF D 50V  | 1    |        |          | U(0)400-470MHz |
| 5                                 | 3101061200000 | Chip capapcitor 0603 12PF J 50V  | 1    | *C130a | T2D      | U(1)400-430MHz |
|                                   | 3101061200000 | Chip capapcitor 0603 12PF J 50V  | 1    |        |          | U(2)440-470MHz |
|                                   | 3101061100010 | Chip capapcitor 0603 11PF B 50V  | 1    |        |          | U(3)330-370MHz |
|                                   | 3101061100010 | Chip capapcitor 0603 11PF B 50V  | 1    |        |          | U(4)450-480MHz |
|                                   | 3101060800010 | Chip capapcitor 0603 8PF B 50V   | 1    |        |          | U(5)350-400MHz |
|                                   | 3101060700020 | Chip capapcitor 0603 7PF B 50V   | 1    |        |          | U(6)480-520MHz |
|                                   | 3101061500010 | Chip capapcitor 0603 15PF J 50V  | 1    |        |          | U(0)400-470MHz |
| 6                                 | 3101060600010 | Chip capapcitor 0603 6PF B 50V   | 1    | *C136  | T1D      | U(1)400-430MHz |
|                                   | 3101060700020 | Chip capapcitor 0603 7PF B 50V   | 1    |        |          | U(2)440-470MHz |
|                                   | 3101061100010 | Chip capapcitor 0603 11PF B 50V  | 1    |        |          | U(3)330-370MHz |
|                                   | 3101060700020 | Chip capapcitor 0603 7PF B 50V   | 1    |        |          | U(4)450-480MHz |
|                                   | 3101060800010 | Chip capapcitor 0603 8PF B 50V   | 1    |        |          | U(5)350-400MHz |
|                                   | 3101060700020 | Chip capapcitor 0603 7PF B 50V   | 1    |        |          | U(6)480-520MHz |
|                                   | 3101060600010 | Chip capapcitor 0603 6PF B 50V   | 1    |        |          | U(0)400-470MHz |
| 7                                 | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1    | *C136a | T1D      | U(1)400-430MHz |
|                                   | 3101060300010 | Chip capapcitor 0603 3PF B 50V   | 1    |        |          | U(2)440-470MHz |
|                                   | 3101060600010 | Chip capapcitor 0603 6PF B 50V   | 1    |        |          | U(3)330-370MHz |
|                                   | 3101060300010 | Chip capapcitor 0603 3PF B 50V   | 1    |        |          | U(4)450-480MHz |
|                                   | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1    |        |          | U(5)350-400MHz |
|                                   | 3101060300010 | Chip capapcitor 0603 3PF B 50V   | 1    |        |          | U(6)480-520MHz |
|                                   | 3101060300010 | Chip capapcitor 0603 3PF B 50V   | 1    |        |          | U(0)400-470MHz |
| 8                                 | 3101064710000 | Chip capapcitor 0603 470PF K 50  | 1    | *C138  | T2D      | U(1)400-430MHz |
|                                   | 3101061010010 | Chip capapcitor 0603 100PF J 50V | 1    |        |          | U(2)440-470MHz |

确认人：

接收时间：

确认时间：

|    |               |                                  |   |       |     |                |
|----|---------------|----------------------------------|---|-------|-----|----------------|
|    | 3101064710000 | Chip capapcitor 0603 470PF K 50  | 1 |       |     | U(3)330-370MHz |
|    | 3101061010010 | Chip capapcitor 0603 100PF J 50V | 1 |       |     | U(4)450-480MHz |
|    | 3101064710000 | Chip capapcitor 0603 470PF K 50V | 1 |       |     | U(5)350-400MHz |
|    | 3101061010010 | Chip capapcitor 0603 100PF J 50V | 1 |       |     | U(6)480-520MHz |
|    | 3101061010010 | Chip capapcitor 0603 100PF J 50V | 1 |       |     | U(0)400-470MHz |
| 9  | 3101060100010 | Chip capapcitor 0603 1PF B 50V   | 1 | *C140 | T1D | U(1)400-430MHz |
|    | 3101060100010 | Chip capapcitor 0603 1PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101061500010 | Chip capapcitor 0603 15PF J 50V  | 1 |       |     | U(3)330-370MHz |
|    | 3101060100010 | Chip capapcitor 0603 1PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101060800010 | Chip capapcitor 0603 8PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101060100010 | Chip capapcitor 0603 1PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101060100010 | Chip capapcitor 0603 1PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 10 | 3101051500020 | Chip capapcitor 0402 15PF J 50V  | 1 | *C142 | T2C | U(1)400-430MHz |
|    | 3101051500020 | Chip capapcitor 0402 15PF J 50V  | 1 |       |     | U(2)440-470MHz |
|    | 3101050900000 | Chip capapcitor 0402 9PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101051500020 | Chip capapcitor 0402 15PF J 50V  | 1 |       |     | U(4)450-480MHz |
|    | 3101050900000 | Chip capapcitor 0402 9PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101051200020 | Chip capapcitor 0402 12PF J 50V  | 1 |       |     | U(6)480-520MHz |
|    | 3101051500020 | Chip capapcitor 0402 15PF J 50V  | 1 |       |     | U(0)400-470MHz |
| 11 | 3101061590010 | Chip capapcitor 0603 1.5PF B 50V | 1 | *C147 | T1E | U(1)400-430MHz |
|    | 3101060100010 | Chip capapcitor 0603 1PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101060100010 | Chip capapcitor 0603 1PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101060100010 | Chip capapcitor 0603 1PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101060300010 | Chip capapcitor 0603 3PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 12 | 3101051500020 | Chip capapcitor 0402 15PF J 50V  | 1 | *C148 | T2C | U(1)400-430MHz |
|    | 3101051500020 | Chip capapcitor 0402 15PF J 50V  | 1 |       |     | U(2)440-470MHz |
|    | NC            | NC                               | 1 |       |     | U(3)330-370MHz |
|    | 3101051500020 | Chip capapcitor 0402 15PF J 50V  | 1 |       |     | U(4)450-480MHz |
|    | NC            | NC                               | 1 |       |     | U(5)350-400MHz |
|    | 3101051200020 | Chip capapcitor 0402 12PF J 50V  | 1 |       |     | U(6)480-520MHz |
|    | 3101051500020 | Chip capapcitor 0402 15PF J 50V  | 1 |       |     | U(0)400-470MHz |
| 13 | 3101060100010 | Chip capapcitor 0603 1PF B 50V   | 1 | *C149 | T2E | U(1)400-430MHz |
|    | 3101061590010 | Chip capapcitor 0603 1.5PF B 50V | 1 |       |     | U(2)440-470MHz |
|    | 3101060200010 | Chip capapcitor 0603 2PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101061590010 | Chip capapcitor 0603 1.5PF B 50V | 1 |       |     | U(4)450-480MHz |
|    | 3101060200010 | Chip capapcitor 0603 2PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101060200010 | Chip capapcitor 0603 2PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101060200010 | Chip capapcitor 0603 2PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 14 | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 | *C150 | T2E | U(1)400-430MHz |
|    | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101060600010 | Chip capapcitor 0603 6PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 15 | 3101060200010 | Chip capapcitor 0603 2PF B 50V   | 1 | *C151 | T2E | U(1)400-430MHz |
|    | 3101060100010 | Chip capapcitor 0603 1PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101062290000 | Chip capapcitor 0603 2.2PF B 50V | 1 |       |     | U(3)330-370MHz |
|    | 3101060100010 | Chip capapcitor 0603 1PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101060200010 | Chip capapcitor 0603 2PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101060100010 | Chip capapcitor 0603 1PF B 50V   | 1 |       |     | U(6)480-520MHz |

确认人：

接收时间：

确认时间：

|    |               |                                  |   |       |     |                |
|----|---------------|----------------------------------|---|-------|-----|----------------|
|    | 3101060300010 | Chip capapcitor 0603 3PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 16 | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 | *C153 | T2E | U(1)400-430MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101060300010 | Chip capapcitor 0603 3PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 17 | 3101060200010 | Chip capapcitor 0603 2PF B 50V   | 1 | *C154 | T2E | U(1)400-430MHz |
|    | 3101061590010 | Chip capapcitor 0603 1.5PF B 50V | 1 |       |     | U(2)440-470MHz |
|    | 3101061590010 | Chip capapcitor 0603 1.5PF B 50V | 1 |       |     | U(3)330-370MHz |
|    | 3101061590010 | Chip capapcitor 0603 1.5PF B 50V | 1 |       |     | U(4)450-480MHz |
|    | 3101060200010 | Chip capapcitor 0603 2PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101061590010 | Chip capapcitor 0603 1.5PF B 50V | 1 |       |     | U(6)480-520MHz |
|    | 3101061590010 | Chip capapcitor 0603 1.5PF B 50V | 1 |       |     | U(0)400-470MHz |
| 18 | 3101056890000 | Chip capapcitor 0402 6.8PF B 50V | 1 | *C201 | T2E | U(1)400-430MHz |
|    | 3101056890000 | Chip capapcitor 0402 6.8PF B 50V | 1 |       |     | U(2)440-470MHz |
|    | 3101055690010 | Chip capapcitor 0402 5.6PF C 25V | 1 |       |     | U(3)330-370MHz |
|    | 3101056890000 | Chip capapcitor 0402 6.8PF B 50V | 1 |       |     | U(4)450-480MHz |
|    | 3101055690010 | Chip capapcitor 0402 5.6PF C 25V | 1 |       |     | U(5)350-400MHz |
|    | 3101056890000 | Chip capapcitor 0402 6.8PF B 50V | 1 |       |     | U(6)480-520MHz |
|    | 3101051800010 | Chip capapcitor 0402 18PF J 50V  | 1 |       |     | U(0)400-470MHz |
| 19 | 3101050400010 | Chip capapcitor 0402 4PF B 50V   | 1 | *C203 | T3E | U(1)400-430MHz |
|    | 3101050400010 | Chip capapcitor 0402 4PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101050500010 | Chip capapcitor 0402 5PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101050400010 | Chip capapcitor 0402 4PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101050500010 | Chip capapcitor 0402 5PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101050400010 | Chip capapcitor 0402 4PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101050400010 | Chip capapcitor 0402 4PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 20 | 3101051000000 | Chip capapcitor 0402 10PF D 50V  | 1 | *C213 | B2C | U(1)400-430MHz |
|    | 3101051000000 | Chip capapcitor 0402 10PF D 50V  | 1 |       |     | U(2)440-470MHz |
|    | 3101050900000 | Chip capapcitor 0402 9PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101051000000 | Chip capapcitor 0402 10PF D 50V  | 1 |       |     | U(4)450-480MHz |
|    | 3101050900000 | Chip capapcitor 0402 9PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101051000000 | Chip capapcitor 0402 10PF D 50V  | 1 |       |     | U(6)480-520MHz |
|    | 3101051000000 | Chip capapcitor 0402 10PF D 50V  | 1 |       |     | U(0)400-470MHz |
| 21 | 3101053690000 | Chip capapcitor 0402 3.6PF B 50V | 1 | *C215 | T2E | U(1)400-430MHz |
|    | 3101050590020 | Chip capapcitor 0402 0.5PF B 50V | 1 |       |     | U(2)440-470MHz |
|    | NC            | NC                               | 1 |       |     | U(3)330-370MHz |
|    | 3101050590020 | Chip capapcitor 0402 0.5PF B 50V | 1 |       |     | U(4)450-480MHz |
|    | NC            | NC                               | 1 |       |     | U(5)350-400MHz |
|    | 3101050590020 | Chip capapcitor 0402 0.5PF B 50V | 1 |       |     | U(6)480-520MHz |
|    | 3101050600010 | Chip capapcitor 0402 6PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 22 | 3101050400010 | Chip capapcitor 0402 4PF B 50V   | 1 | *C216 | B2C | U(1)400-430MHz |
|    | 3101050400010 | Chip capapcitor 0402 4PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101050500010 | Chip capapcitor 0402 5PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101050400010 | Chip capapcitor 0402 4PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101050500010 | Chip capapcitor 0402 5PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101050400010 | Chip capapcitor 0402 4PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101050400010 | Chip capapcitor 0402 4PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 23 | 3101050600010 | Chip capapcitor 0402 6PF B 50V   | 1 | *C281 | T3D | U(1)400-430MHz |
|    | 3101050600010 | Chip capapcitor 0402 6PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101050300000 | Chip capapcitor 0402 3PF B 50V   | 1 |       |     | U(3)330-370MHz |

确认人：

接收时间：

确认时间：

|    |               |                                  |   |       |     |                |
|----|---------------|----------------------------------|---|-------|-----|----------------|
|    | 3101050600010 | Chip capapcitor 0402 6PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101050300000 | Chip capapcitor 0402 3PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101050600010 | Chip capapcitor 0402 6PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101050600010 | Chip capapcitor 0402 6PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 24 | 3101050600010 | Chip capapcitor 0402 6PF B 50V   | 1 | *C315 | T2B | U(1)400-430MHz |
|    | 3101050600010 | Chip capapcitor 0402 6PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101050500010 | Chip capapcitor 0402 5PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101050600010 | Chip capapcitor 0402 6PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101050500010 | Chip capapcitor 0402 5PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101050600010 | Chip capapcitor 0402 6PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101050600010 | Chip capapcitor 0402 6PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 25 | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 | *C347 | T3B | U(1)400-430MHz |
|    | NC            | NC                               | 1 |       |     | U(2)440-470MHz |
|    | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | NC            | NC                               | 1 |       |     | U(4)450-480MHz |
|    | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | NC            | NC                               | 1 |       |     | U(6)480-520MHz |
|    | NC            | NC                               | 1 |       |     | U(0)400-470MHz |
| 26 | 3101062700010 | Chip capapcitor 0603 27PF J 50V  | 1 | *C350 | T3B | U(1)400-430MHz |
|    | 3101061500010 | Chip capapcitor 0603 15PF J 50V  | 1 |       |     | U(2)440-470MHz |
|    | 3101065600000 | Chip capapcitor 0603 56PF J 50V  | 1 |       |     | U(3)330-370MHz |
|    | 3101061500010 | Chip capapcitor 0603 15PF J 50V  | 1 |       |     | U(4)450-480MHz |
|    | 3101063300000 | Chip capapcitor 0603 33PF J 50V  | 1 |       |     | U(5)350-400MHz |
|    | 3101061500010 | Chip capapcitor 0603 15PF J 50V  | 1 |       |     | U(6)480-520MHz |
|    | 3101063900000 | Chip capapcitor 0603 39PF J 50V  | 1 |       |     | U(0)400-470MHz |
| 27 | 3101060700020 | Chip capapcitor 0603 7PF B 50V   | 1 | *C351 | T3B | U(1)400-430MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101060300010 | Chip capapcitor 0603 3PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 28 | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 | *C354 | T3B | U(1)400-430MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101060300010 | Chip capapcitor 0603 3PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101060300010 | Chip capapcitor 0603 3PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101060300010 | Chip capapcitor 0603 3PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 29 | 3101060300010 | Chip capapcitor 0603 3PF B 50V   | 1 | *C355 | T3B | U(1)400-430MHz |
|    | 3101060300010 | Chip capapcitor 0603 3PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101060300010 | Chip capapcitor 0603 3PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101062490000 | Chip capapcitor 0603 2.4PF B 50V | 1 |       |     | U(5)350-400MHz |
|    | 3101060300010 | Chip capapcitor 0603 3PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 30 | 3101060600010 | Chip capapcitor 0603 6PF B 50V   | 1 | *C356 | T3B | U(1)400-430MHz |
|    | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101060800010 | Chip capapcitor 0603 8PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101060800010 | Chip capapcitor 0603 8PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101064790010 | Chip capapcitor 0603 4.7PF B 50V | 1 |       |     | U(5)350-400MHz |
|    | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 |       |     | U(0)400-470MHz |

确认人：

接收时间：

确认时间：

|    |               |                                  |   |       |     |                |
|----|---------------|----------------------------------|---|-------|-----|----------------|
| 31 | 3101063900000 | Chip capapcitor 0603 39PF J 50V  | 1 | *C366 | T3B | U(1)400-430MHz |
|    | 3101063300000 | Chip capapcitor 0603 33PF J 50V  | 1 |       |     | U(2)440-470MHz |
|    | 3101068200000 | Chip capapcitor 0603 82PF J 50V  | 1 |       |     | U(3)330-370MHz |
|    | 3101063300000 | Chip capapcitor 0603 33PF J 50V  | 1 |       |     | U(4)450-480MHz |
|    | 3101062710000 | Chip capapcitor 0603 270PF J 50V | 1 |       |     | U(5)350-400MHz |
|    | 3101063300000 | Chip capapcitor 0603 33PF J 50V  | 1 |       |     | U(6)480-520MHz |
|    | 3101066800000 | Chip capapcitor 0603 68PF J 50V  | 1 |       |     | U(0)400-470MHz |
| 32 | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 | *C367 | T3B | U(1)400-430MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101060300010 | Chip capapcitor 0603 3PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101060900010 | Chip capapcitor 0603 9PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101061590010 | Chip capapcitor 0603 1.5PF B 50V | 1 |       |     | U(0)400-470MHz |
| 33 | 3101060600010 | Chip capapcitor 0603 6PF B 50V   | 1 | *C368 | T3B | U(1)400-430MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101060900010 | Chip capapcitor 0603 9PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101060300010 | Chip capapcitor 0603 3PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101060800010 | Chip capapcitor 0603 8PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 34 | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 | *C369 | T3B | U(1)400-430MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101060400010 | Chip capapcitor 0603 4PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101060500010 | Chip capapcitor 0603 5PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 35 | 3101061000010 | Chip capapcitor 0603 10PF D 50V  | 1 | *C370 | T3B | U(1)400-430MHz |
|    | 3101060600010 | Chip capapcitor 0603 6PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101060600010 | Chip capapcitor 0603 6PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101060600010 | Chip capapcitor 0603 6PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101060600010 | Chip capapcitor 0603 6PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101060600010 | Chip capapcitor 0603 6PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101060600010 | Chip capapcitor 0603 6PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 36 | NC            | NC                               | 1 | *C373 | T3B | U(1)400-430MHz |
|    | 3101060590010 | Chip capapcitor 0603 0.5PF B 50V | 1 |       |     | U(2)440-470MHz |
|    | NC            | NC                               | 1 |       |     | U(3)330-370MHz |
|    | NC            | NC                               | 1 |       |     | U(4)450-480MHz |
|    | NC            | NC                               | 1 |       |     | U(5)350-400MHz |
|    | NC            | NC                               | 1 |       |     | U(6)480-520MHz |
|    | NC            | NC                               | 1 |       |     | U(0)400-470MHz |
| 37 | 3210305180009 | Multilayer inductor 0402 18nH    | 1 | *L101 | T2C | U(1)400-430MHz |
|    | 3210305180009 | Multilayer inductor 0402 18nH    | 1 |       |     | U(2)440-470MHz |
|    | 3210305330009 | Multilayer inductor 0402 33nH    | 1 |       |     | U(3)330-370MHz |
|    | 3210305180009 | Multilayer inductor 0402 18nH    | 1 |       |     | U(4)450-480MHz |
|    | 3210305330009 | Multilayer inductor 0402 33nH    | 1 |       |     | U(5)350-400MHz |
|    | 3210305180009 | Multilayer inductor 0402 18nH    | 1 |       |     | U(6)480-520MHz |
|    | 3210305180009 | Multilayer inductor 0402 18nH    | 1 |       |     | U(0)400-470MHz |
| 38 | 3210305150010 | Multilayer inductor 0402 15nH    | 1 | *L102 | T2C | U(1)400-430MHz |
|    | 3210305150010 | Multilayer inductor 0402 15nH    | 1 |       |     | U(2)440-470MHz |
|    | 3210305829009 | Multilayer inductor 0402 8.2nH   | 1 |       |     | U(3)330-370MHz |
|    | 3210305150010 | Multilayer inductor 0402 15nH    | 1 |       |     | U(4)450-480MHz |

确认人：

接收时间：

确认时间：

|    |               |                                 |   |        |     |                |
|----|---------------|---------------------------------|---|--------|-----|----------------|
|    | 3210305829009 | Multilayer inductor 0402 8.2nH  | 1 |        |     | U(5)350-400MHz |
|    | 3210305150010 | Multilayer inductor 0402 15nH   | 1 |        |     | U(6)480-520MHz |
|    | 3210305150010 | Multilayer inductor 0402 15nH   | 1 |        |     | U(0)400-470MHz |
| 39 | 3231351640009 | Coil E2-0.35*1.6*4TL            | 1 | *L112  | T2E | U(1)400-430MHz |
|    | 3231351630000 | Coil E2-0.35*1.6*3TR            | 1 |        |     | U(2)440-470MHz |
|    | 3231351640009 | Coil E2-0.35*1.6*4TL            | 1 |        |     | U(3)330-370MHz |
|    | 3231351630000 | Coil E2-0.35*1.6*3TR            | 1 |        |     | U(4)450-480MHz |
|    | 3231351640009 | Coil E2-0.35*1.6*4TL            | 1 |        |     | U(5)350-400MHz |
|    | 3231351630000 | Coil E2-0.35*1.6*3TR            | 1 |        |     | U(6)480-520MHz |
|    | 3231351630000 | Coil E2-0.35*1.6*3TR            | 1 |        |     | U(0)400-470MHz |
| 40 | 3231351650000 | Coil E2-0.35*1.6*5TL            | 1 | *L113  | T2E | U(1)400-430MHz |
|    | 3231351640009 | Coil E2-0.35*1.6*4TL            | 1 |        |     | U(2)440-470MHz |
|    | 3231351650000 | Coil E2-0.35*1.6*5TL            | 1 |        |     | U(3)330-370MHz |
|    | 3231351640009 | Coil E2-0.35*1.6*4TL            | 1 |        |     | U(4)450-480MHz |
|    | 3231351650000 | Coil E2-0.35*1.6*5TL            | 1 |        |     | U(5)350-400MHz |
|    | 3231351630000 | Coil E2-0.35*1.6*3TR            | 1 |        |     | U(6)480-520MHz |
|    | 3231351640009 | Coil E2-0.35*1.6*4TL            | 1 |        |     | U(0)400-470MHz |
| 41 | 3231351640009 | Coil E2-0.35*1.6*4TL            | 1 | *L114  | T2E | U(1)400-430MHz |
|    | 3231351630000 | Coil E2-0.35*1.6*3TR            | 1 |        |     | U(2)440-470MHz |
|    | 3231351650000 | Coil E2-0.35*1.6*5TL            | 1 |        |     | U(3)330-370MHz |
|    | 3231351630000 | Coil E2-0.35*1.6*3TR            | 1 |        |     | U(4)450-480MHz |
|    | 3231351650000 | Coil E2-0.35*1.6*5TL            | 1 |        |     | U(5)350-400MHz |
|    | 3231351630000 | Coil E2-0.35*1.6*3TR            | 1 |        |     | U(6)480-520MHz |
|    | 3231351630000 | Coil E2-0.35*1.6*3TR            | 1 |        |     | U(0)400-470MHz |
| 42 | 3212105279000 | Multilayer inductor 0402 2.7nH  | 1 | *L119  | T2C | U(1)400-430MHz |
|    | 3210305229009 | Multilayer inductor 0402 2.2nH  | 1 |        |     | U(2)440-470MHz |
|    | 3210305399009 | Multilayer inductor 0402 3.9nH  | 1 |        |     | U(3)330-370MHz |
|    | 3210305229009 | Multilayer inductor 0402 2.2nH  | 1 |        |     | U(4)450-480MHz |
|    | 3210305399009 | Multilayer inductor 0402 3.9nH  | 1 |        |     | U(5)350-400MHz |
|    | 3210305189000 | Multilayer inductor 0402 1.8nH  | 1 |        |     | U(6)480-520MHz |
|    | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 |        |     | U(0)400-470MHz |
| 43 | 3210305229009 | Multilayer inductor 0402 2.2nH  | 1 | *L120  | T2C | U(1)400-430MHz |
|    | NC            | NC                              | 1 |        |     | U(2)440-470MHz |
|    | 3210305229009 | Multilayer inductor 0402 2.2nH  | 1 |        |     | U(3)330-370MHz |
|    | NC            | NC                              | 1 |        |     | U(4)450-480MHz |
|    | 3210305229009 | Multilayer inductor 0402 2.2nH  | 1 |        |     | U(5)350-400MHz |
|    | NC            | NC                              | 1 |        |     | U(6)480-520MHz |
|    | NC            | NC                              | 1 |        |     | U(0)400-470MHz |
| 44 | 3210305180009 | Multilayer inductor 0402 18nH   | 1 | *L120a | T2C | U(1)400-430MHz |
|    | 3210305180009 | Multilayer inductor 0402 18nH   | 1 |        |     | U(2)440-470MHz |
|    | 3210305270009 | Multilayer inductor 0402 27nH   | 1 |        |     | U(3)330-370MHz |
|    | 3210305180009 | Multilayer inductor 0402 18nH   | 1 |        |     | U(4)450-480MHz |
|    | 3210305270009 | Multilayer inductor 0402 27nH   | 1 |        |     | U(5)350-400MHz |
|    | 3210305150010 | Multilayer inductor 0402 15nH   | 1 |        |     | U(6)480-520MHz |
|    | 3210305180009 | Multilayer inductor 0402 18nH   | 1 |        |     | U(0)400-470MHz |
| 45 | 3210107220000 | Inductor 0805 22nH              | 1 | *L203  | B3B | U(1)400-430MHz |
|    | 3210107220000 | Inductor 0805 22nH              | 1 |        |     | U(2)440-470MHz |
|    | 3214307270019 | Inductor 0805 27nH              | 1 |        |     | U(3)330-370MHz |
|    | 3210107220000 | Inductor 0805 22nH              | 1 |        |     | U(4)450-480MHz |
|    | 3214307270019 | Inductor 0805 27nH              | 1 |        |     | U(5)350-400MHz |
|    | 3210107220000 | Inductor 0805 22nH              | 1 |        |     | U(6)480-520MHz |
|    | 3210107220000 | Inductor 0805 22nH              | 1 |        |     | U(0)400-470MHz |
| 46 | 3210306390009 | Multilayer inductor 0603 39nH   | 1 | *L310  | T3B | U(1)400-430MHz |

确认人：

接收时间：

确认时间：

|    |               |                                |   |       |     |                |
|----|---------------|--------------------------------|---|-------|-----|----------------|
|    | 3210306330009 | Multilayer inductor 0603 33nH  | 1 |       |     | U(2)440-470MHz |
|    | 3210306470009 | Multilayer inductor 0603 47nH  | 1 |       |     | U(3)330-370MHz |
|    | 3210306330009 | Multilayer inductor 0603 33nH  | 1 |       |     | U(4)450-480MHz |
|    | 3210306470009 | Multilayer inductor 0603 47nH  | 1 |       |     | U(5)350-400MHz |
|    | 3210306330009 | Multilayer inductor 0603 33nH  | 1 |       |     | U(6)480-520MHz |
|    | 3210306330009 | Multilayer inductor 0603 33nH  | 1 |       |     | U(0)400-470MHz |
| 47 | 3210107220000 | Framework inductor 0805 22nH   | 1 | *L356 | T2B | U(1)400-430MHz |
|    | 3210107220000 | Framework inductor 0805 22nH   | 1 |       |     | U(2)440-470MHz |
|    | 3210107330009 | Framework inductor 0805 33nH   | 1 |       |     | U(3)330-370MHz |
|    | 3210107220000 | Framework inductor 0805 22nH   | 1 |       |     | U(4)450-480MHz |
|    | 3210107330009 | Framework inductor 0805 33nH   | 1 |       |     | U(5)350-400MHz |
|    | 3210107180000 | Framework inductor 0805 18nH   | 1 |       |     | U(6)480-520MHz |
|    | 3210107220000 | Framework inductor 0805 22nH   | 1 |       |     | U(0)400-470MHz |
| 48 | 3214307270010 | Framework inductor 0805 27nH   | 1 | *L357 | T3B | U(1)400-430MHz |
|    | 3214307270010 | Framework inductor 0805 27nH   | 1 |       |     | U(2)440-470MHz |
|    | 3214307390000 | Framework inductor 0805 39nH   | 1 |       |     | U(3)330-370MHz |
|    | 3214307270010 | Framework inductor 0805 27nH   | 1 |       |     | U(4)450-480MHz |
|    | 3210107330009 | Framework inductor 0805 33nH   | 1 |       |     | U(5)350-400MHz |
|    | 3210107220000 | Framework inductor 0805 22nH   | 1 |       |     | U(6)480-520MHz |
|    | 3214307270010 | Framework inductor 0805 27nH   | 1 |       |     | U(0)400-470MHz |
| 49 | 3001051000000 | Chip resistor 0402 10Ω J 1/16W | 1 | *R115 | T2C | U(1)400-430MHz |
|    | 3001051000000 | Chip resistor 0402 10Ω J 1/16W | 1 |       |     | U(2)440-470MHz |
|    | 3001050000000 | Chip resistor 0402 0Ω J 1/16W  | 1 |       |     | U(3)330-370MHz |
|    | 3001051000000 | Chip resistor 0402 10Ω J 1/16W | 1 |       |     | U(4)450-480MHz |
|    | 3001050000000 | Chip resistor 0402 0Ω J 1/16W  | 1 |       |     | U(5)350-400MHz |
|    | 3001050000000 | Chip resistor 0402 0Ω J 1/16W  | 1 |       |     | U(6)480-520MHz |
|    | 3001051000000 | Chip resistor 0402 10Ω J 1/16W | 1 |       |     | U(0)400-470MHz |
| 50 | 3001053910000 | Chip resistor 0402 390Ω J      | 1 | *R117 | T2C | U(1)400-430MHz |
|    | 3001052230010 | Chip resistor 0402 22KΩ J      | 1 |       |     | U(2)440-470MHz |
|    | 3001056830000 | Chip resistor 0402 68KΩ J      | 1 |       |     | U(3)330-370MHz |
|    | 3001052230010 | Chip resistor 0402 22KΩ J      | 1 |       |     | U(4)450-480MHz |
|    | 3001058220000 | Chip resistor 0402 8.2KΩ J     | 1 |       |     | U(5)350-400MHz |
|    | 3001052230010 | Chip resistor 0402 22KΩ J      | 1 |       |     | U(6)480-520MHz |
|    | 3001051530000 | Chip resistor 0402 15KΩ J      | 1 |       |     | U(0)400-470MHz |
| 51 | 3001054730000 | Chip resistor 0402 47KΩ J      | 1 | *R125 | T2C |                |
| 52 | NC            | NC                             | 1 | *R127 | T2C | U(1)400-430MHz |
|    | 3001050000000 | Chip resistor 0402 0Ω J 1/16W  | 1 |       |     | U(2)440-470MHz |
|    | NC            | NC                             | 1 |       |     | U(3)330-370MHz |
|    | 3001050000000 | Chip resistor 0402 0Ω J 1/16W  | 1 |       |     | U(4)450-480MHz |
|    | NC            | NC                             | 1 |       |     | U(5)350-400MHz |
|    | 3001050000000 | Chip resistor 0402 0Ω J 1/16W  | 1 |       |     | U(6)480-520MHz |
|    | 3212105279000 | Multilayer inductor 0402 2.7nH | 1 |       |     | U(0)400-470MHz |
| 53 | 3001052210000 | Chip resistor 0402 220Ω J      | 1 | *R233 | T3C | U(1)400-430MHz |
|    | 3001054710000 | Chip resistor 0402 470Ω J      | 1 |       |     | U(2)440-470MHz |
|    | 3001052210000 | Chip resistor 0402 220Ω J      | 1 |       |     | U(3)330-370MHz |
|    | 3001054710000 | Chip resistor 0402 470Ω J      | 1 |       |     | U(4)450-480MHz |
|    | 3001052210000 | Chip resistor 0402 220Ω J      | 1 |       |     | U(5)350-400MHz |
|    | 3001054710000 | Chip resistor 0402 470Ω J      | 1 |       |     | U(6)480-520MHz |
|    | 3001054710000 | Chip resistor 0402 470Ω J      | 1 |       |     | U(0)400-470MHz |
| 54 | 3001051040010 | Chip resistor 0402 100KΩ J     | 1 | *R350 | T2B | U(1)400-430MHz |
|    | 3001051040010 | Chip resistor 0402 100KΩ J     | 1 |       |     | U(2)440-470MHz |
|    | 3001058230000 | Chip resistor 0402 82KΩ J      | 1 |       |     | U(3)330-370MHz |
|    | 3001051040010 | Chip resistor 0402 100KΩ J     | 1 |       |     | U(4)450-480MHz |

确认人：

接收时间：

确认时间：

|    |               |                                 |   |       |     |                |
|----|---------------|---------------------------------|---|-------|-----|----------------|
|    | 3001059130000 | Chip resistor 0402 91KΩ F       | 1 |       |     | U(5)350-400MHz |
|    | 3001051040010 | Chip resistor 0402 100KΩ J      | 1 |       |     | U(6)480-520MHz |
|    | 3001051040010 | Chip resistor 0402 100KΩ J      | 1 |       |     | U(0)400-470MHz |
| 55 | 3001053340000 | Chip resistor 0402 330KΩ J      | 1 | *R358 | T3B | U(1)400-430MHz |
|    | 3001052240000 | Chip resistor 0402 220KΩ J      | 1 |       |     | U(2)440-470MHz |
|    | 3001056840000 | Chip resistor 0402 680KΩ J      | 1 |       |     | U(3)330-370MHz |
|    | 3001052240000 | Chip resistor 0402 220KΩ J      | 1 |       |     | U(4)450-480MHz |
|    | 3001053340000 | Chip resistor 0402 330KΩ J      | 1 |       |     | U(5)350-400MHz |
|    | 3001052240000 | Chip resistor 0402 220KΩ J      | 1 |       |     | U(6)480-520MHz |
|    | 3001052240000 | Chip resistor 0402 220KΩ J      | 1 |       |     | U(0)400-470MHz |
| 56 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C1    | B3C |                |
| 57 | 3101051030020 | Chip capacitor 0402 0.01UF K    | 1 | C10   | T3E |                |
| 58 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C106  | T2C |                |
| 59 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C107  | T2C |                |
| 60 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C109  | T2C |                |
| 61 | 3101051030020 | Chip capacitor 0402 0.01UF K    | 1 | C11   | T3F |                |
| 62 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C110  | T2C |                |
| 63 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C112  | B2D |                |
| 64 | 3101051040040 | Chip capacitor 0402 0.1UF K     | 1 | C113  | T2C |                |
| 65 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C114  | T2C |                |
| 66 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C115  | B2D |                |
| 67 | 3101051020010 | Chip capacitor 0402 1000PF K    | 1 | C116  | T2C |                |
| 68 | 3101051020010 | Chip capacitor 0402 1000PF K    | 1 | C119  | T2C |                |
| 69 | 3101051030020 | Chip capacitor 0402 0.01UF K    | 1 | C12   | T3E |                |
| 70 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C120  | T1C |                |
| 71 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C121  | T2C |                |
| 72 | 3101051020010 | Chip capacitor 0402 1000PF K    | 1 | C123  | T2C |                |
| 73 | 3101060300010 | Chip capacitor 0603 3PF B 50V   | 1 | C124  | T2D |                |
| 74 | 3101064710000 | Chip capacitor 0603 470PF K 50  | 1 | C125  | T2D |                |
| 75 | 3101061050060 | Chip capacitor 0603 1UF K 10V   | 1 | C126  | T2D |                |
| 76 | 3104074750030 | Ta-capacitor 0805 4.7UF M 10V   | 1 | C127  | B2D |                |
| 77 | 3101061030010 | Chip capacitor 0603 0.01UF K 2  | 1 | C128  | T2D |                |
| 78 | 3101064710000 | Chip capacitor 0603 470PF K 50  | 1 | C129  | T2D |                |
| 79 | 3101051030020 | Chip capacitor 0402 0.01UF K    | 1 | C13   | T3F |                |
| 80 | 3101061040010 | Chip capacitor 0603 0.1UF K 16  | 1 | C131  | T2D |                |
| 81 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C132  | B1D |                |
| 82 | 3101051010030 | Chip capacitor 0402 100PF J 50V | 1 | C134  | B1D |                |
| 83 | 3101060100010 | Chip capacitor 0603 1PF B 50V   | 1 | C135  | T2D |                |
| 84 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C139  | B1D |                |
| 85 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C14   | B4D |                |
| 86 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C141  | B1D |                |
| 87 | 3101064710000 | Chip capacitor 0603 470PF K 50  | 1 | C143  | B2B |                |
| 88 | 3101064710000 | Chip capacitor 0603 470PF K 50  | 1 | C144  | B2C |                |
| 89 | 3101064710000 | Chip capacitor 0603 470PF K 50  | 1 | C145  | T2E |                |
| 90 | 3101061030010 | Chip capacitor 0603 0.01UF K 2  | 1 | C146  | B2C |                |
| 91 | 3101051040040 | Chip capacitor 0402 0.1UF K     | 1 | C15   | B3D |                |
| 92 | 3101060400010 | Chip capacitor 0603 4PF B 50V   | 1 | C153  | T2E | U(1)400-430MHz |
|    | 3101060400010 | Chip capacitor 0603 4PF B 50V   | 1 |       |     | U(2)440-470MHz |
|    | 3101060500010 | Chip capacitor 0603 5PF B 50V   | 1 |       |     | U(3)330-370MHz |
|    | 3101060400010 | Chip capacitor 0603 4PF B 50V   | 1 |       |     | U(4)450-480MHz |
|    | 3101060400010 | Chip capacitor 0603 4PF B 50V   | 1 |       |     | U(5)350-400MHz |
|    | 3101060300010 | Chip capacitor 0603 3PF B 50V   | 1 |       |     | U(6)480-520MHz |
|    | 3101060400010 | Chip capacitor 0603 4PF B 50V   | 1 |       |     | U(0)400-470MHz |

确认人：

接收时间：

确认时间：

|     |               |                                     |   |       |     |  |
|-----|---------------|-------------------------------------|---|-------|-----|--|
| 93  | 3101054710010 | Chip capacitor 0402 470PF K 50V     | 1 | C154a | T3C |  |
| 94  | 3101051040040 | Chip capacitor 0402 0.1UF K         | 1 | C156  | T2C |  |
| 95  | 3101054710010 | Chip capacitor 0402 470PF K 50V     | 1 | C157  | T2C |  |
| 96  | 3101051030020 | Chip capacitor 0402 0.01UF K        | 1 | C16   | T1D |  |
| 97  | 3101054710010 | Chip capacitor 0402 470PF K 50V     | 1 | C165  | B2D |  |
| 98  | 3101051030020 | Chip capacitor 0402 0.01UF K        | 1 | C17   | T3F |  |
| 99  | 3101051030020 | Chip capacitor 0402 0.01UF K        | 1 | C18   | T1D |  |
| 100 | 3101051030020 | Chip capacitor 0402 0.01UF K        | 1 | C19   | T1C |  |
| 101 | 3101054710010 | Chip capacitor 0402 470PF K 50V     | 1 | C2    | T3E |  |
| 102 | 3101050900000 | Chip capacitor 0402 9PF B 50V       | 1 | C202  | T2E |  |
| 103 | 3101050900000 | Chip capacitor 0402 9PF B 50V       | 1 | C204  | T3E |  |
| 104 | 3101052000000 | Chip capacitor 0402 20PF J 50V      | 1 | C205  | T3E |  |
| 105 | 3101051040040 | Chip capacitor 0402 0.1UF K         | 1 | C207  | T3E |  |
| 106 | 3101051040040 | Chip capacitor 0402 0.1UF K         | 1 | C207a | B3B |  |
| 107 | 3101051040040 | Chip capacitor 0402 0.1UF K         | 1 | C208  | T4E |  |
| 108 | 3104071060010 | Ta-capacitor 0805 10UF M 6.3V       | 1 | C209  | T4D |  |
| 109 | 3101051010030 | Chip capacitor 0402 100PF J 50V     | 1 | C209a | B2B |  |
| 110 | 3101051030020 | Chip capacitor 0402 0.01UF K        | 1 | C210  | T4D |  |
| 111 | 3101051040040 | Chip capacitor 0402 0.1UF K         | 1 | C210a | B2B |  |
| 112 | 3101050700010 | Chip capacitor 0402 7PF B 50V       | 1 | C212  | B2C |  |
| 113 | 3101052210010 | Chip capacitor 0402 220PF J 50      | 1 | C214  | T3D |  |
| 114 | 3101051040040 | Chip capacitor 0402 0.1UF K         | 1 | C214a | B3B |  |
| 115 | 3101051010030 | Chip capacitor 0402 100PF J 50V     | 1 | C215a | B3C |  |
| 116 | 3101050900000 | Chip capacitor 0402 9PF B 50V       | 1 | C217  | B2C |  |
| 117 | 3101057590000 | Chip capacitor 0402 7.5PF $\pm 0.1$ | 1 | C218  | B2C |  |
| 118 | 3101051010030 | Chip capacitor 0402 100PF J 50V     | 1 | C219  | T3E |  |
| 119 | 3101051010030 | Chip capacitor 0402 100PF J 50V     | 1 | C22   | B2F |  |
| 120 | 3101051040040 | Chip capacitor 0402 0.1UF K         | 1 | C220  | T3E |  |
| 121 | 3101051010030 | Chip capacitor 0402 100PF J 50V     | 1 | C221  | B3B |  |
| 122 | 3101058200000 | Chip capacitor 0402 82PF J 50V      | 1 | C222  | T3D |  |
| 123 | 3101052210010 | Chip capacitor 0402 220PF J 50      | 1 | C223  | T3D |  |
| 124 | 3101051030020 | Chip capacitor 0402 0.01UF K        | 1 | C225  | T4C |  |
| 125 | 3101051010030 | Chip capacitor 0402 100PF J 50V     | 1 | C23   | B2F |  |
| 126 | 3101052700000 | Chip capacitor 0402 27PF J 50V      | 1 | C230  | T3D |  |
| 127 | 3101054710010 | Chip capacitor 0402 470PF K 50V     | 1 | C230a | T3D |  |
| 128 | 3101053300000 | Chip capacitor 0402 33PF J 50V      | 1 | C231  | T4D |  |
| 129 | 3101051030020 | Chip capacitor 0402 0.01UF K        | 1 | C232  | T3D |  |
| 130 | 3101058200000 | Chip capacitor 0402 82PF J 50V      | 1 | C233  | T3D |  |
| 131 | 3101051030020 | Chip capacitor 0402 0.01UF K        | 1 | C234  | T3C |  |
| 132 | 3101051030020 | Chip capacitor 0402 0.01UF K        | 1 | C235  | T3C |  |
| 133 | 3101051030020 | Chip capacitor 0402 0.01UF K        | 1 | C236  | T3C |  |
| 134 | 3101051020010 | Chip capacitor 0402 1000PF K        | 1 | C237  | T3C |  |
| 135 | 3101051040040 | Chip capacitor 0402 0.1UF K         | 1 | C238  | T4D |  |
| 136 | 3101051810000 | Chip capacitor 0402 180PF $\pm 5\%$ | 1 | C239  | T3D |  |
| 137 | 3101051010030 | Chip capacitor 0402 100PF J 50V     | 1 | C24   | B2F |  |
| 138 | 3101051030020 | Chip capacitor 0402 0.01UF K        | 1 | C240  | T3C |  |
| 139 | 3101051040040 | Chip capacitor 0402 0.1UF K         | 1 | C241  | T3D |  |
| 140 | 3101051040040 | Chip capacitor 0402 0.1UF K         | 1 | C242  | T3D |  |
| 141 | 3101051040040 | Chip capacitor 0402 0.1UF K         | 1 | C247  | T3D |  |
| 142 | 3101051040040 | Chip capacitor 0402 0.1UF K         | 1 | C248  | T3D |  |
| 143 | 3101051040040 | Chip capacitor 0402 0.1UF K         | 1 | C249  | T3E |  |
| 144 | 3101051010030 | Chip capacitor 0402 100PF J 50V     | 1 | C25   | B2F |  |
| 145 | 3101051030020 | Chip capacitor 0402 0.01UF K        | 1 | C251  | T3E |  |

确认人：

接收时间：

确认时间：

|     |               |                                 |   |       |     |                |
|-----|---------------|---------------------------------|---|-------|-----|----------------|
| 146 | 3101051010030 | Chip capacitor 0402 100PF J 50V | 1 | C26   | B1F |                |
| 147 | 3101050400010 | Chip capacitor 0402 4PF B 50V   | 1 | C261  | T2C |                |
| 148 | 3101051020010 | Chip capacitor 0402 1000PF K    | 1 | C264  | T4E |                |
| 149 | 3101051200020 | Chip capacitor 0402 12PF J 50V  | 1 | C268  | T2C |                |
| 150 | 3101050700010 | Chip capacitor 0402 7PF B 50V   | 1 | C269  | T2C |                |
| 151 | 3101051010030 | Chip capacitor 0402 100PF J 50V | 1 | C27   | B1F |                |
| 152 | 3101052200010 | Chip capacitor 0402 22PF J 50V  | 1 | C271  | T4E |                |
| 153 | 3101052200010 | Chip capacitor 0402 22PF J 50V  | 1 | C273  | T4E |                |
| 154 | 3104071560020 | Ta-capacitor 0805 15UF M 6.3V   | 1 | C277  | T3D |                |
| 155 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C278  | T3C |                |
| 156 | 3101051010030 | Chip capacitor 0402 100PF J 50V | 1 | C28   | B1F |                |
| 157 | 3101051030020 | Chip capacitor 0402 0.01UF K    | 1 | C280  | B3C |                |
| 158 | 3101051010030 | Chip capacitor 0402 100PF J 50V | 1 | C29   | B1F |                |
| 159 | 3104071560020 | Ta-capacitor 0805 15UF M 6.3V   | 1 | C292  | T3D |                |
| 160 | 3101061050060 | Chip capacitor 0603 1UF K 10V   | 1 | C3    | B3D |                |
| 161 | 3101051010030 | Chip capacitor 0402 100PF J 50V | 1 | C30   | B1F |                |
| 162 | 3101051010030 | Chip capacitor 0402 100PF J 50V | 1 | C31   | B1F |                |
| 163 | 3101052200010 | Chip capacitor 0402 22PF J 50V  | 1 | C310  | T3B |                |
| 164 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C311  | T3B |                |
| 165 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C312  | T2B |                |
| 166 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C313  | T3B |                |
| 167 | 3101051040040 | Chip capacitor 0402 0.1UF K     | 1 | C314  | T2B |                |
| 168 | 3101051010030 | Chip capacitor 0402 100PF J 50V | 1 | C32   | B1F |                |
| 169 | 3101051010030 | Chip capacitor 0402 100PF J 50V | 1 | C33   | B1F |                |
| 170 | 3101051010030 | Chip capacitor 0402 100PF J 50V | 1 | C34   | B1F |                |
| 171 | 3104071560020 | Ta-capacitor 0805 15UF M 6.3V   | 1 | C346  | T4B |                |
| 172 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C348  | T3B |                |
| 173 | 3101051010030 | Chip capacitor 0402 100PF J 50V | 1 | C35   | B1F |                |
| 174 | 3101051020010 | Chip capacitor 0402 1000PF K    | 1 | C352  | T4B |                |
| 175 | 3101051020010 | Chip capacitor 0402 1000PF K    | 1 | C352a | T3B |                |
| 176 | 3101060590010 | Chip capacitor 0603 0.5PF B 50  | 1 | C353  | T2B |                |
| 177 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C354a | T4B |                |
| 178 | 3101060600010 | Chip capacitor 0603 6PF B 50V   | 1 | C356  | T3B | U(1)400-430MHz |
|     | 3101060500010 | Chip capacitor 0603 5PF B 50V   | 1 |       |     | U(2)440-470MHz |
|     | 3101060800010 | Chip capacitor 0603 8PF B 50V   | 1 |       |     | U(3)330-370MHz |
|     | 3101060500010 | Chip capacitor 0603 5PF B 50V   | 1 |       |     | U(4)450-480MHz |
|     | 3101064790010 | Chip capacitor 0603 4.7PF B 50V | 1 |       |     | U(5)350-400MHz |
|     | 3101060500010 | Chip capacitor 0603 5PF B 50V   | 1 |       |     | U(6)480-520MHz |
|     | 3101060500010 | Chip capacitor 0603 5PF B 50V   | 1 |       |     | U(0)400-470MHz |
| 179 | 3101051020010 | Chip capacitor 0402 1000PF K    | 1 | C357  | T3B |                |
| 180 | 3101060590010 | Chip capacitor 0603 0.5PF B 50  | 1 | C358  | T3B |                |
| 181 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C359  | T3B |                |
| 182 | 3101051010030 | Chip capacitor 0402 100PF J 50V | 1 | C36   | B2F |                |
| 183 | 3101050600010 | Chip capacitor 0402 6PF B 50V   | 1 | C360  | T3B |                |
| 184 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C363  | T2B |                |
| 185 | 3101051010030 | Chip capacitor 0402 100PF J 50V | 1 | C364  | T3B |                |
| 186 | 3101051020010 | Chip capacitor 0402 1000PF K    | 1 | C365  | T3B |                |
| 187 | 3101051010030 | Chip capacitor 0402 100PF J 50V | 1 | C37   | B2F |                |
| 188 | 3101060590010 | Chip capacitor 0603 0.5PF B 50  | 1 | C371  | T3B |                |
| 189 | 3101051010030 | Chip capacitor 0402 100PF J 50V | 1 | C38   | B2F |                |
| 190 | 3101051010030 | Chip capacitor 0402 100PF J 50V | 1 | C39   | B2F |                |
| 191 | 3101054710010 | Chip capacitor 0402 470PF K 50V | 1 | C4    | B3D |                |
| 192 | 3101051010030 | Chip capacitor 0402 100PF J 50V | 1 | C40   | B2F |                |

确认人：

接收时间：

确认时间：

|     |               |                                  |   |       |     |                |
|-----|---------------|----------------------------------|---|-------|-----|----------------|
| 193 | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1 | C41   | B2F |                |
| 194 | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1 | C42   | B2F |                |
| 195 | 3104074750030 | Ta-capacitor 0805 4.7UF M 10V    | 1 | C426  | T2B | U(1)400-430MHz |
|     | 3104072250010 | Ta-capacitor 0805 2.2UF M 10V    | 1 |       |     | U(2)440-470MHz |
|     | 3104072250010 | Ta-capacitor 0805 2.2UF M 10V    | 1 |       |     | U(3)330-370MHz |
|     | 3104074750030 | Ta-capacitor 0805 4.7UF M 10V    | 1 |       |     | U(4)450-480MHz |
|     | 3104072250010 | Ta-capacitor 0805 2.2UF M 10V    | 1 |       |     | U(5)350-400MHz |
|     | 3104074750030 | Ta-capacitor 0805 4.7UF M 10V    | 1 |       |     | U(6)480-520MHz |
|     | 3104072250010 | Ta-capacitor 0805 2.2UF M 10V    | 1 |       |     | U(0)400-470MHz |
| 196 | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1 | C43   | B2F |                |
| 197 | 3101051020010 | Chip capacitor 0402 1000PF K     | 1 | C430  | T2B |                |
| 198 | 3101050500010 | Chip capacitor 0402 5PF B 50V    | 1 | C433  | T2B |                |
| 199 | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1 | C434  | B2E |                |
| 200 | 3101064740020 | Chip capacitor 0603 0.47UF Z     | 1 | C436  | T2B | U(1)400-430MHz |
|     | 3101061040010 | Chip capacitor 0603 0.1UF K 16V  | 1 |       |     | U(2)440-470MHz |
|     | 3101061040010 | Chip capacitor 0603 0.1UF K 16V  | 1 |       |     | U(3)330-370MHz |
|     | 3101064740020 | Chip capacitor 0603 0.47UF Z     | 1 |       |     | U(4)450-480MHz |
|     | 3101061040010 | Chip capacitor 0603 0.1UF K      | 1 |       |     | U(5)350-400MHz |
|     | 3101064740020 | Chip capacitor 0603 0.47UF Z     | 1 |       |     | U(6)480-520MHz |
|     | 3101061040010 | Chip capacitor 0603 0.1UF K      | 1 |       |     | U(0)400-470MHz |
| 201 | 3101050300000 | Chip capacitor 0402 3PF B 50V    | 1 | C438  | T2B |                |
| 202 | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1 | C44   | B2F |                |
| 203 | 3101050500010 | Chip capacitor 0402 5PF B 50V    | 1 | C440  | T2B |                |
| 204 | 3101051020010 | Chip capacitor 0402 1000PF K     | 1 | C442  | B2E |                |
| 205 | 3101051000000 | Chip capacitor 0402 10PF D 50V   | 1 | C443  | T2B |                |
| 206 | 3101051000000 | Chip capacitor 0402 10PF D 50V   | 1 | C444  | B2E |                |
| 207 | 3101051000000 | Chip capacitor 0402 10PF D 50V   | 1 | C445  | B2E |                |
| 208 | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1 | C449  | T2B |                |
| 209 | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1 | C45   | B2F |                |
| 210 | 3101050500010 | Chip capacitor 0402 5PF B 50V    | 1 | C450  | T2B |                |
| 211 | 3101051020010 | Chip capacitor 0402 1000PF K     | 1 | C453  | T2B |                |
| 212 | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1 | C458  | T2B |                |
| 213 | 3101051010030 | Chip capacitor 0402 100PF J 50V  | 1 | C46   | B2F |                |
| 214 | 3101051040040 | Chip capacitor 0402 0.1UF K      | 1 | C47   | B2F |                |
| 215 | 3104071060010 | Ta-capacitor 0805 10UF M 6.3V    | 1 | C479  | T2B |                |
| 216 | 3101051040040 | Chip capacitor 0402 0.1UF K      | 1 | C481  | T2B |                |
| 217 | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1 | C482  | T2B |                |
| 218 | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1 | C485  | T2B |                |
| 219 | 3101061040010 | Chip capacitor 0603 0.1UF K 16   | 1 | C490  | T2B |                |
| 220 | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1 | C495  | T1B |                |
| 221 | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1 | C496  | T1B |                |
| 222 | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1 | C5    | B3D |                |
| 223 | 3104074750030 | Ta-capacitor 0805 4.7UF M 10V    | 1 | C52   | B4D |                |
| 224 | 3101051040040 | Chip capacitor 0402 0.1UF K      | 1 | C6    | B3E |                |
| 225 | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1 | C60   | B4C |                |
| 226 | 3104071060010 | Ta-capacitor 0805 10UF M 6.3V    | 1 | C7    | B3E |                |
| 227 | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1 | C8    | B3D |                |
| 228 | 3101054710010 | Chip capacitor 0402 470PF K 50V  | 1 | C9    | T3E |                |
| 229 | 3801045530099 | Ceramic filter 455KHz CDBC455    | 1 | CD201 | B3C |                |
| 230 | 3801045530089 | Ceramic filter 455KHz ±7.5K C    | 1 | CF201 | B3C |                |
| 231 | 3801045530009 | Ceramic filter 455KHz ±4.5K C    | 1 | CF202 | B3B |                |
| 232 | 3005051020010 | Resistor array 0402 1K*4 J 1/16W | 1 | CP401 | T2B |                |
| 233 | 3301031200009 | Rectifier diode ISR154-400       | 1 | D1    | B2D |                |

确认人：

接收时间：

确认时间：

|     |               |                                              |   |       |     |                |
|-----|---------------|----------------------------------------------|---|-------|-----|----------------|
| 234 | 3303020100089 | Switching diode MA2S07700L                   | 1 | D100  | T2C |                |
| 235 | 3303020100079 | Switching diode MA2Z07700L SOD               | 1 | D101  | T2D |                |
| 236 | 3303020100089 | Switching diode MA2S07700L                   | 1 | D103  | T2C |                |
| 237 | 3001060000000 | Chip resistor 0603 0Ω J 1/10W                | 1 | D2    | B4E |                |
| 238 | 3303020100089 | Switching diode MA2S07700L                   | 1 | D201  | T2E |                |
| 239 | 3303020100089 | Switching diode MA2S07700L                   | 1 | D202  | T2E |                |
| 240 | 3304060300029 | Varactor HVC350B UFP                         | 1 | D204  | B2C |                |
| 241 | 3304060300029 | Varactor HVC350B UFP                         | 1 | D205  | B2C |                |
| 242 | 3304060300029 | Varactor HVC350B UFP                         | 1 | D206  | T2E |                |
| 243 | 3304060300029 | Varactor HVC350B UFP                         | 1 | D207  | T3E |                |
| 244 | 3303030100019 | Switching diode DAN222(TL) PNP               | 1 | D215  | T3E |                |
| 245 | 3399060700009 | Mixer diode HSM88AS SOT-23                   | 1 | D216  | B3B |                |
| 246 | 3303030100019 | Switching diode DAN222(TL) PNP               | 1 | D217  | T3E |                |
| 247 | 3302031100009 | Zener diode EDZ6.8(TE61)                     | 1 | D3    | T1D |                |
| 248 | 3303020100029 | Switching diode MA2S11100L SS-               | 1 | D306  | T3B |                |
| 249 | 3304060300029 | Varactor HVC350B UFP                         | 1 | D350  | T3B |                |
| 250 | 3304060300029 | Varactor HVC350B UFP                         | 1 | D351  | T4B |                |
| 251 | 3304060300029 | Varactor HVC350B UFP                         | 1 | D352  | T3B |                |
| 252 | 3304060300029 | Varactor HVC350B UFP                         | 1 | D353  | T4B |                |
| 253 | 3304060300029 | Varactor HVC350B UFP                         | 1 | D354  | T3B |                |
| 254 | 3304060300029 | Varactor HVC350B UFP                         | 1 | D355  | T3B |                |
| 255 | 3304060300029 | Varactor HVC350B UFP                         | 1 | D356  | T4B |                |
| 256 | 3304060300029 | Varactor HVC350B UFP                         | 1 | D357  | T4B |                |
| 257 | 3304040200009 | Varactor BB179 SOD523                        | 1 | D358  | T3B |                |
| 258 | 3302031100009 | Zener diode EDZ6.8(TE61)                     | 1 | D4    | T3E |                |
| 259 | 3302031100009 | Zener diode EDZ6.8(TE61)                     | 1 | D5    | T1D |                |
| 260 | 3302031100009 | Zener diode EDZ6.8(TE61)                     | 1 | D6    | T1C |                |
| 261 | 3307110100029 | LED KPT-1608SRC                              | 1 | D7    | T2F |                |
| 262 | 3307110100019 | LED KPT1608-SGC                              | 1 | D8    | T2F |                |
| 263 | 4002000000059 | ★Fuse R429003 3.0A/32                        | 1 | F1    | B3D |                |
| 264 | 3605008005079 | Operational amplifier NJM2904V               | 1 | IC100 | B1D |                |
| 265 | 3603002005419 | IF processing IC TA31136FN                   | 1 | IC204 | T3D |                |
| 266 | 3609030005620 | Exclusive IC HSMS-2827 AGILE                 | 1 | IC218 | B3D |                |
| 267 | 3604025004359 | PLL ADF4111BRU 1.2GH                         | 1 | IC400 | T2B |                |
| 268 | 3608015000000 | Power supply managing IC (voltage regulator) | 1 | IC6   | B4D |                |
| 269 | 3608020005749 | Power supply managing IC TK11250CM 5.0       | 1 | IC9   | B3D |                |
| 270 | 5202040100019 | Socket connector XF2M-4015-1L 40p            | 1 | J1    | T2A |                |
| 271 | 5202003100039 | TC3000 battery electrode piece socket 3pin   | 1 | JP1   | B3D |                |
| 272 | 3221507600000 | Chip ferrite bead 0805 60Ω±25%               | 1 | L1    | B3D |                |
| 273 | 3210305180009 | Multilayer inductor 0402 18nH                | 1 | L101  | T2C | U(1)400-430MHz |
|     | 3210305180009 | Multilayer inductor 0402 18nH                | 1 |       |     | U(2)440-470MHz |
|     | 3210305330009 | Multilayer inductor 0402 33nH                | 1 |       |     | U(3)330-370MHz |
|     | 3210305180009 | Multilayer inductor 0402 18nH                | 1 |       |     | U(4)450-480MHz |
|     | 3210305330009 | Multilayer inductor 0402 33nH                | 1 |       |     | U(5)350-400MHz |
|     | 3210305180009 | Multilayer inductor 0402 18nH                | 1 |       |     | U(6)480-520MHz |
|     | 3210305180009 | Multilayer inductor 0402 18nH                | 1 |       |     | U(0)400-470MHz |
| 274 | 3210305150010 | Multilayer inductor 0402 15nH                | 1 | L102  | T2C | U(1)400-430MHz |
|     | 3210305150010 | Multilayer inductor 0402 15nH                | 1 |       |     | U(2)440-470MHz |
|     | 3210305829009 | Multilayer inductor 0402 8.2nH               | 1 |       |     | U(3)330-370MHz |
|     | 3210305150010 | Multilayer inductor 0402 15nH                | 1 |       |     | U(4)450-480MHz |

确认人：

接收时间：

确认时间：

|     |               |                                |   |       |     |                |
|-----|---------------|--------------------------------|---|-------|-----|----------------|
|     | 3210305829009 | Multilayer inductor 0402 8.2nH | 1 |       |     | U(5)350-400MHz |
|     | 3210305150010 | Multilayer inductor 0402 15nH  | 1 |       |     | U(6)480-520MHz |
|     | 3210305150010 | Multilayer inductor 0402 15nH  | 1 |       |     | U(0)400-470MHz |
| 275 | 3221505121009 | Chip ferrite bead 0402 120Ω    | 1 | L103  | T2C |                |
| 276 | 3213212102009 | Multilayer inductor 1008 1uH   | 1 | L104  | T1C |                |
| 277 | 3221507600000 | Chip ferrite bead 0805 60Ω±25% | 1 | L105  | T2D |                |
| 278 | 3231351680000 | Coil E2-0.35*1.6*8TR           | 1 | L106  | T2D |                |
| 279 | 3221507600000 | Chip ferrite bead 0805 60Ω±25% | 1 | L107  | B2B |                |
| 280 | 3210107221009 | Framework inductor 0805 220nH  | 1 | L109  | B2B |                |
| 281 | 3210209102019 | Framework inductor 1210 1uH    | 1 | L118  | T2E |                |
| 282 | 3231301250000 | Coil E2-0.30*1.2*5TL           | 1 | L201  | T3E |                |
| 283 | 3231301250000 | Coil E2-0.30*1.2*5TL           | 1 | L202  | T4E |                |
| 284 | 3214307220019 | Inductor 0805 22nH             | 1 | L203  | B3B | U(1)400-430MHz |
|     | 3214307220019 | Inductor 0805 22nH             | 1 |       |     | U(2)440-470MHz |
|     | 3214307270019 | Inductor 0805 27nH             | 1 |       |     | U(3)330-370MHz |
|     | 3214307220019 | Inductor 0805 22nH             | 1 |       |     | U(4)450-480MHz |
|     | 3214307270019 | Inductor 0805 27nH             | 1 |       |     | U(5)350-400MHz |
|     | 3214307220019 | Inductor 0805 22nH             | 1 |       |     | U(6)480-520MHz |
|     | 3214307220019 | Inductor 0805 22nH             | 1 |       |     | U(0)400-470MHz |
| 285 | 3212206102000 | Multilayer inductor 0603 1uH   | 1 | L204  | B2B |                |
| 286 | 3214307181009 | Inductor 0805 180nH(Q)         | 1 | L204a | B2C |                |
| 287 | 3214307220019 | Inductor 0805 22nH             | 1 | L205  | B3C |                |
| 288 | 3231301250000 | Coil E2-0.30*1.2*5TL           | 1 | L206  | B3C |                |
| 289 | 3231301250000 | Coil E2-0.30*1.2*5TL           | 1 | L207  | T3D |                |
| 290 | 3214307151009 | Inductor 0805 150nH(Q)         | 1 | L210  | T3C |                |
| 291 | 3214307151009 | Inductor 0805 150nH(Q)         | 1 | L211  | T2E |                |
| 292 | 3231351640009 | Coil E2-0.35*1.6*4TL           | 1 | L213  | T2C |                |
| 293 | 3210305150010 | Multilayer inductor 0402 15nH  | 1 | L215  | T2C |                |
| 294 | 3210305150010 | Multilayer inductor 0402 15nH  | 1 | L217  | T3B |                |
| 295 | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 | L350  | T4B | U(1)400-430MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |       |     | U(2)440-470MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |       |     | U(3)330-370MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |       |     | U(4)450-480MHz |
|     | 3213306472000 | Multilayer inductor 0603 4.7uH | 1 |       |     | U(5)350-400MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |       |     | U(6)480-520MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |       |     | U(0)400-470MHz |
| 296 | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 | L351  | T3B | U(1)400-430MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |       |     | U(2)440-470MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |       |     | U(3)330-370MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |       |     | U(4)450-480MHz |
|     | 3213306472000 | Multilayer inductor 0603 4.7uH | 1 |       |     | U(5)350-400MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |       |     | U(6)480-520MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |       |     | U(0)400-470MHz |
| 297 | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 | L352  | T4B | U(1)400-430MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |       |     | U(2)440-470MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |       |     | U(3)330-370MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |       |     | U(4)450-480MHz |
|     | 3213306472000 | Multilayer inductor 0603 4.7uH | 1 |       |     | U(5)350-400MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |       |     | U(6)480-520MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |       |     | U(0)400-470MHz |
| 298 | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 | L353  | T3B | U(1)400-430MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |       |     | U(2)440-470MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |       |     | U(3)330-370MHz |

确认人：

接收时间：

确认时间：

|     |               |                                |   |      |     |                |
|-----|---------------|--------------------------------|---|------|-----|----------------|
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |      |     | U(4)450-480MHz |
|     | 3213306472000 | Multilayer inductor 0603 4.7uH | 1 |      |     | U(5)350-400MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |      |     | U(6)480-520MHz |
|     | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 |      |     | U(0)400-470MHz |
| 299 | 3214307220019 | Inductor 0805 22nH             | 1 | L356 | T2B | U(1)400-430MHz |
|     | 3214307220019 | Inductor 0805 22nH             | 1 |      |     | U(2)440-470MHz |
|     | 3210107330000 | Inductor 0805 33nH             | 1 |      |     | U(3)330-370MHz |
|     | 3214307220019 | Inductor 0805 22nH             | 1 |      |     | U(4)450-480MHz |
|     | 3210107330000 | Inductor 0805 33nH             | 1 |      |     | U(5)350-400MHz |
|     | 3210107180000 | Inductor 0805 18nH             | 1 |      |     | U(6)480-520MHz |
|     | 3214307220019 | Inductor 0805 22nH             | 1 |      |     | U(0)400-470MHz |
| 300 | 3214307270019 | Inductor 0805 27nH             | 1 | L357 | T3B | U(1)400-430MHz |
|     | 3214307270019 | Inductor 0805 27nH             | 1 |      |     | U(2)440-470MHz |
|     | 3214307390000 | Inductor 0805 39nH             | 1 |      |     | U(3)330-370MHz |
|     | 3214307270019 | Inductor 0805 27nH             | 1 |      |     | U(4)450-480MHz |
|     | 3210107330000 | Inductor 0805 33nH             | 1 |      |     | U(5)350-400MHz |
|     | 3214307220010 | Inductor 0805 22nH             | 1 |      |     | U(6)480-520MHz |
|     | 3214307270019 | Inductor 0805 27nH             | 1 |      |     | U(0)400-470MHz |
| 301 | 3214206101009 | Inductor 0603 100nH(Q)         | 1 | L358 | T3B |                |
| 302 | 3214206101009 | Inductor 0603 100nH(Q)         | 1 | L359 | T3B |                |
| 303 | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 | L360 | T3B |                |
| 304 | 3213306332000 | Multilayer inductor 0603 3.3uH | 1 | L361 | T3B |                |
| 305 | 3221505121009 | Chip ferrite bead 0402 120Ω    | 1 | L362 | T3B |                |
| 306 | 3210306180000 | Multilayer inductor 0603 18nH  | 1 | L363 | B2E |                |
| 307 | 3213306472000 | Multilayer inductor 0603 4.7uH | 1 | L403 | T2B |                |
| 308 | 3221505121009 | Chip ferrite bead 0402 120Ω    | 1 | L405 | T2B |                |
| 309 | 3221505121009 | Chip ferrite bead 0402 120Ω    | 1 | L406 | T2B |                |
| 310 | 3210305120009 | Multilayer inductor 0402 12nH  | 1 | L409 | T2B |                |
| 311 | 3210305390009 | Multilayer inductor 0402 39nH  | 1 | L410 | T2B |                |
| 312 | 3221505121009 | Chip ferrite bead 0402 120Ω    | 1 | L411 | T1E |                |
| 313 | 4399090000000 | Button switch 3000/3600        | 1 | PB1  | T3F |                |
| 314 | 4399090000000 | Button switch 3000/3600        | 1 | PB2  | T1D |                |
| 315 | 4399090000000 | Button switch 3000/3600        | 1 | PB3  | T1C |                |
| 316 | 4399090000000 | Button switch 3000/3600        | 1 | PB4  | B4D |                |
| 317 | 3403008000079 | Transistor DTC144EE(TL) NPN    | 1 | Q1   | T2C |                |
| 318 | 3401002000099 | Transistor 2SC5108-Y(TE85L)    | 1 | Q101 | T2C |                |
| 319 | 3406001000009 | Transistor 2SC4988FRTR NPN     | 1 | Q102 | B2D |                |
| 320 | 3503020000039 | FET 2SK1824-T1                 | 1 | Q103 | B2D |                |
| 321 | 3499000000189 | Transistor UFM717              | 1 | Q104 | T2C |                |
| 322 | 3502010000039 | FET 2SK3475                    | 1 | Q105 | B2D |                |
| 323 | 3503020000039 | FET 2SK1824-T1                 | 1 | Q106 | T2D |                |
| 324 | 3502010000049 | FET 2SK3476                    | 1 | Q107 | B2D |                |
| 325 | 3403008000019 | Transistor DTC114EE(TL) NPN    | 1 | Q108 | B2D |                |
| 326 | 3403007000079 | Transistor DTA144EE PNP        | 1 | Q109 | B2D |                |
| 327 | 3403008000039 | Transistor DTC114TE NPN        | 1 | Q110 | B4D |                |
| 328 | 3503010000019 | FET 2SJ243-T1                  | 1 | Q2   | B2B |                |
| 329 | 3418001000009 | Transistor AT-41511 NPN        | 1 | Q201 | T3E |                |
| 330 | 3403007000079 | Transistor DTA144EE PNP        | 1 | Q206 | T3E |                |
| 331 | 3403008000079 | Transistor DTC144EE(TL) NPN    | 1 | Q207 | T3D |                |
| 332 | 3403008000079 | Transistor DTC144EE(TL) NPN    | 1 | Q209 | T3C |                |
| 333 | 3408002000009 | Transistor 2SC3356-R24 NPN     | 1 | Q216 | T4D |                |
| 334 | 3401002000099 | Transistor 2SC5108-Y(TE85L)    | 1 | Q222 | T3D |                |
| 335 | 3403007000009 | Transistor DTA114EE(TL) PNP    | 1 | Q226 | B3D |                |

确认人：

接收时间：

确认时间：

|     |               |                                 |   |      |     |  |
|-----|---------------|---------------------------------|---|------|-----|--|
| 336 | 3410001000029 | Transistor 2SA1745 PNP          | 1 | Q3   | T3B |  |
| 337 | 3411002000009 | Transistor 2SC5343EG NPN        | 1 | Q308 | T3B |  |
| 338 | 3401002000099 | Transistor 2SC5108-Y(TE85L)     | 1 | Q310 | T3B |  |
| 339 | 3503020000109 | FET 2SK508NV(K52)               | 1 | Q350 | T3B |  |
| 340 | 3503010000019 | FET 2SJ243-T1                   | 1 | Q351 | T3B |  |
| 341 | 3503020000109 | FET 2SK508NV(K52)               | 1 | Q352 | T3B |  |
| 342 | 3499000000159 | (Exclusive) TransistorUMC4N(TR) | 1 | Q353 | T3B |  |
| 343 | 3401002000099 | Transistor 2SC5108-Y(TE85L)     | 1 | Q354 | B3D |  |
| 344 | 3503010000019 | FET 2SJ243-T1                   | 1 | Q4   | T2B |  |
| 345 | 3401002000099 | Transistor 2SC5108-Y(TE85L)     | 1 | Q416 | T4E |  |
| 346 | 3411002000009 | Transistor 2SC5343EG NPN        | 1 | Q5   | T4E |  |
| 347 | 3411002000009 | Transistor 2SC5343EG NPN        | 1 | Q6   | B3D |  |
| 348 | 3001054730000 | Chip resistor 0402 47KΩ J       | 1 | R1   | T2C |  |
| 349 | 3001053320000 | Chip resistor 0402 3.3KΩ J      | 1 | R106 | T2C |  |
| 350 | 3001054730000 | Chip resistor 0402 47KΩ J       | 1 | R107 | T2C |  |
| 351 | 3001053310010 | Chip resistor 0402 330Ω J       | 1 | R108 | T2C |  |
| 352 | 3001052200000 | Chip resistor 0402 22Ω J 1/16W  | 1 | R109 | T2C |  |
| 353 | 3001056810000 | Chip resistor 0402 680Ω J       | 1 | R110 | T2C |  |
| 354 | 3001052200000 | Chip resistor 0402 22Ω J 1/16W  | 1 | R111 | T2C |  |
| 355 | 3001051520000 | Chip resistor 0402 1.5KΩ J      | 1 | R112 | T2C |  |
| 356 | 3001053310010 | Chip resistor 0402 330Ω J       | 1 | R113 | T2C |  |
| 357 | 3001054730000 | Chip resistor 0402 47KΩ J       | 1 | R118 | B2D |  |
| 358 | 3001054720000 | Chip resistor 0402 4.7KΩ J      | 1 | R119 | T2C |  |
| 359 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W   | 1 | R120 | T2C |  |
| 360 | 3001054700000 | Chip resistor 0402 47Ω J 1/16W  | 1 | R121 | B2D |  |
| 361 | 3001051020010 | Chip resistor 0402 1KΩ J 1/16W  | 1 | R122 | T1D |  |
| 362 | 3001060000000 | Chip resistor 0603 0Ω J 1/10W   | 1 | R123 | B2D |  |
| 363 | 3001051020010 | Chip resistor 0402 1KΩ J 1/16W  | 1 | R124 | T2C |  |
| 364 | 3001054730000 | Chip resistor 0402 47KΩ J       | 1 | R125 | T2C |  |
| 365 | 3001054730000 | Chip resistor 0402 47KΩ J       | 1 | R126 | T2C |  |
| 366 | 3001054700000 | Chip resistor 0402 47Ω J 1/16W  | 1 | R128 | B2D |  |
| 367 | 3001080590000 | Chip resistor 1206 0.5Ω J       | 1 | R130 | B2D |  |
| 368 | 3001080590000 | Chip resistor 1206 0.5Ω J       | 1 | R131 | B2D |  |
| 369 | 3001080590000 | Chip resistor 1206 0.5Ω J       | 1 | R132 | B1D |  |
| 370 | 3001051540000 | Chip resistor 0402 150KΩ F      | 1 | R133 | B2D |  |
| 371 | 3001051540000 | Chip resistor 0402 150KΩ F      | 1 | R134 | B1D |  |
| 372 | 3001051540000 | Chip resistor 0402 150KΩ F      | 1 | R135 | B1D |  |
| 373 | 3001051540000 | Chip resistor 0402 150KΩ F      | 1 | R136 | B2D |  |
| 374 | 3001051540000 | Chip resistor 0402 150KΩ F      | 1 | R137 | B2D |  |
| 375 | 3001051540000 | Chip resistor 0402 150KΩ F      | 1 | R138 | B2B |  |
| 376 | 3001062710000 | Chip resistor 0603 270Ω J       | 1 | R139 | B1D |  |
| 377 | 3001051030000 | Chip resistor 0402 10KΩ J       | 1 | R140 | B2D |  |
| 378 | 3001054730000 | Chip resistor 0402 47KΩ J       | 1 | R141 | B1D |  |
| 379 | 3001051050020 | Chip resistor 0402 1MΩ J 1/16W  | 1 | R142 | B2D |  |
| 380 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W   | 1 | R143 | B2D |  |
| 381 | 3001052220000 | Chip resistor 0402 2.2KΩ J      | 1 | R144 | B2D |  |
| 382 | 3001051840000 | Chip resistor 0402 180KΩ J      | 1 | R145 | B2D |  |
| 383 | 3001051040010 | Chip resistor 0402 100KΩ J      | 1 | R146 | B2D |  |
| 384 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W   | 1 | R148 | B1E |  |
| 385 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W   | 1 | R15  | B2D |  |
| 386 | 3001051020010 | Chip resistor 0402 1KΩ J 1/16W  | 1 | R150 | B2D |  |
| 387 | 3001053910000 | Chip resistor 0402 390Ω J       | 1 | R152 | B2D |  |
| 388 | 3001053320000 | Chip resistor 0402 3.3KΩ J      | 1 | R153 | B2B |  |

确认人：

接收时间：

确认时间：

|     |               |                                |   |       |     |  |
|-----|---------------|--------------------------------|---|-------|-----|--|
| 389 | 3001062710000 | Chip resistor 0603 270Ω J      | 1 | R154  | B3D |  |
| 390 | 3001060000000 | Chip resistor 0603 0Ω J 1/10W  | 1 | R16   | T2C |  |
| 391 | 3001051030000 | Chip resistor 0402 10KΩ J      | 1 | R174  | B4D |  |
| 392 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W  | 1 | R2    | T3D |  |
| 393 | 3001051040010 | Chip resistor 0402 100KΩ J     | 1 | R201  | T3E |  |
| 394 | 3001051040010 | Chip resistor 0402 100KΩ J     | 1 | R202  | B2B |  |
| 395 | 3001051020010 | Chip resistor 0402 1KΩ J 1/16W | 1 | R203  | T3E |  |
| 396 | 3001051040010 | Chip resistor 0402 100KΩ J     | 1 | R204  | B3B |  |
| 397 | 3001051230000 | Chip resistor 0402 12KΩ J      | 1 | R204a | B3B |  |
| 398 | 3001055110000 | Chip resistor 0402 510Ω J      | 1 | R205  | T4D |  |
| 399 | 3001052720000 | Chip resistor 0402 2.7KΩ J     | 1 | R206  | B2C |  |
| 400 | 3001051040010 | Chip resistor 0402 100KΩ J     | 1 | R207  | T3D |  |
| 401 | 3001052220000 | Chip resistor 0402 2.2KΩ J     | 1 | R208  | T3D |  |
| 402 | 3001052710010 | Chip resistor 0402 270Ω J      | 1 | R208a | T3C |  |
| 403 | 3001051800000 | Chip resistor 0402 18Ω J 1/16W | 1 | R209  | T3D |  |
| 404 | 3001052710010 | Chip resistor 0402 270Ω J      | 1 | R210  | B2C |  |
| 405 | 3001051040010 | Chip resistor 0402 100KΩ J     | 1 | R220  | B3C |  |
| 406 | 3001051040010 | Chip resistor 0402 100KΩ J     | 1 | R222  | T2C |  |
| 407 | 3001051800000 | Chip resistor 0402 18Ω J 1/16W | 1 | R228  | B2B |  |
| 408 | 3001052790000 | Chip resistor 0402 2.7Ω J      | 1 | R228a | B2C |  |
| 409 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W  | 1 | R229  | T3C |  |
| 410 | 3001054710000 | Chip resistor 0402 470Ω J      | 1 | R230  | T3C |  |
| 411 | 3001056820000 | Chip resistor 0402 6.8KΩ J     | 1 | R232  | T3C |  |
| 412 | 3001051020010 | Chip resistor 0402 1KΩ J 1/16W | 1 | R234  | T3D |  |
| 413 | 3001051020010 | Chip resistor 0402 1KΩ J 1/16W | 1 | R235  | T3C |  |
| 414 | 3001052700000 | Chip resistor 0402 27Ω J 1/16W | 1 | R236  | T3C |  |
| 415 | 3001052220000 | Chip resistor 0402 2.2KΩ J     | 1 | R238  | T3E |  |
| 416 | 3001054720000 | Chip resistor 0402 4.7KΩ J     | 1 | R239  | B3B |  |
| 417 | 3001056820000 | Chip resistor 0402 6.8KΩ J     | 1 | R240  | T3E |  |
| 418 | 3001052230010 | Chip resistor 0402 22KΩ J      | 1 | R242  | T3E |  |
| 419 | 3001052230010 | Chip resistor 0402 22KΩ J      | 1 | R243  | T3E |  |
| 420 | 3001052230010 | Chip resistor 0402 22KΩ J      | 1 | R246  | T3E |  |
| 421 | 3001052230010 | Chip resistor 0402 22KΩ J      | 1 | R247  | T4E |  |
| 422 | 3001054720000 | Chip resistor 0402 4.7KΩ J     | 1 | R256  | T4E |  |
| 423 | 3001051230000 | Chip resistor 0402 12KΩ J      | 1 | R260  | T3D |  |
| 424 | 3001051830000 | Chip resistor 0402 18KΩ J      | 1 | R271  | T3D |  |
| 425 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W  | 1 | R273  | T3E |  |
| 426 | 3001051010000 | Chip resistor 0402 100Ω J      | 1 | R277  | T3D |  |
| 427 | 3001053920010 | Chip resistor 0402 3.9KΩ J     | 1 | R282  | T3D |  |
| 428 | 3001051840000 | Chip resistor 0402 180KΩ J     | 1 | R284  | T3D |  |
| 429 | 3001053320000 | Chip resistor 0402 3.3KΩ J     | 1 | R293  | T4C |  |
| 430 | 3001054710000 | Chip resistor 0402 470Ω J      | 1 | R294  | T3D |  |
| 431 | 3001051830000 | Chip resistor 0402 18KΩ J      | 1 | R297  | T4D |  |
| 432 | 3001056840000 | Chip resistor 0402 680KΩ J     | 1 | R299  | B3D |  |
| 433 | 3001054720000 | Chip resistor 0402 4.7KΩ J     | 1 | R3    | T3B |  |
| 434 | 3001053320000 | Chip resistor 0402 3.3KΩ J     | 1 | R310  | T3B |  |
| 435 | 3001055620000 | Chip resistor 0402 5.6KΩ J     | 1 | R311  | T3B |  |
| 436 | 3001052710010 | Chip resistor 0402 270Ω J      | 1 | R312  | T3B |  |
| 437 | 3001053320000 | Chip resistor 0402 3.3KΩ J     | 1 | R313  | T2B |  |
| 438 | 3001051000000 | Chip resistor 0402 10Ω J 1/16W | 1 | R314  | T2B |  |
| 439 | 3001053320000 | Chip resistor 0402 3.3KΩ J     | 1 | R315  | T3B |  |
| 440 | 3001054720000 | Chip resistor 0402 4.7KΩ J     | 1 | R345  | T2B |  |
| 441 | 3001051030000 | Chip resistor 0402 10KΩ J      | 1 | R351  | T3B |  |

确认人：

接收时间：

确认时间：

|     |               |                                                   |   |       |     |                |
|-----|---------------|---------------------------------------------------|---|-------|-----|----------------|
| 442 | 3001054730000 | Chip resistor 0402 47KΩ J                         | 1 | R352  | T3B |                |
| 443 | 3001051010000 | Chip resistor 0402 100Ω J                         | 1 | R353  | T3B |                |
| 444 | 3001051010000 | Chip resistor 0402 100Ω J                         | 1 | R354  | T3B |                |
| 445 | 3001051040010 | Chip resistor 0402 100KΩ J                        | 1 | R355  | T3B |                |
| 446 | 3001051810010 | Chip resistor 0402 180Ω J                         | 1 | R356  | T3B |                |
| 447 | 3001051510000 | Chip resistor 0402 150Ω J                         | 1 | R357  | T3B |                |
| 448 | 3001051010000 | Chip resistor 0402 100Ω J                         | 1 | R359  | T2F |                |
| 449 | 3001058210000 | Chip resistor 0402 820Ω J                         | 1 | R4    | T2B |                |
| 450 | 3001055600000 | Chip resistor 0402 56Ω J                          | 1 | R401  | B2E |                |
| 451 | 3001056830000 | Chip resistor 0402 68KΩ J                         | 1 | R402  | B2E |                |
| 452 | 3001052730000 | Chip resistor 0402 27KΩ J                         | 1 | R403  | T2B |                |
| 453 | 3001052220000 | Chip resistor 0402 2.2KΩ J                        | 1 | R404  | T2B |                |
| 454 | 3001051020010 | Chip resistor 0402 1KΩ J 1/16W                    | 1 | R419  | T2B |                |
| 455 | 3001051040010 | Chip resistor 0402 100KΩ J                        | 1 | R420  | B2E |                |
| 456 | 3001051010000 | Chip resistor 0402 100Ω J                         | 1 | R438  | T2B |                |
| 457 | 3001054720000 | Chip resistor 0402 4.7KΩ J                        | 1 | R454  | T2B | U(1)400-430MHz |
|     | 3001054720000 | Chip resistor 0402 4.7KΩ J                        | 1 |       |     | U(2)440-470MHz |
|     | 3001052720000 | Chip resistor 0402 2.7KΩ J                        | 1 |       |     | U(3)330-370MHz |
|     | 3001054720000 | Chip resistor 0402 4.7KΩ J                        | 1 |       |     | U(4)450-480MHz |
|     | 3001052720000 | Chip resistor 0402 2.7KΩ J                        | 1 |       |     | U(5)350-400MHz |
|     | 3001054720000 | Chip resistor 0402 4.7KΩ J                        | 1 |       |     | U(6)480-520MHz |
|     | 3001054720000 | Chip resistor 0402 4.7KΩ J                        | 1 |       |     | U(0)400-470MHz |
| 458 | 3001052210000 | Chip resistor 0402 220Ω J                         | 1 | R484  | T2B |                |
| 459 | 3001051020010 | Chip resistor 0402 1KΩ J 1/16W                    | 1 | R496  | T1B |                |
| 460 | 3001050000000 | Chip resistor 0402 0Ω J 1/16W                     | 1 | R497  | T2F |                |
| 461 | 3001053310010 | Chip resistor 0402 330Ω J                         | 1 | R5    | T4E |                |
| 462 | 3001051030000 | Chip resistor 0402 10KΩ J                         | 1 | R6    | B2F |                |
| 463 | 3001051050020 | Chip resistor 0402 1MΩ J 1/16W                    | 1 | R7    | T3C |                |
| 464 | 3244599189009 | Transmitting coil 4BLH(020984189)                 | 1 | T201  | T3C |                |
| 465 | 3244599189009 | Transmitting coil 4BLH(020984189)                 | 1 | T202  | T3B |                |
| 466 | 3102992000049 | Trimmer capacitor 3.2*2.5*1.25mm                  | 1 | TC350 | T3B |                |
| 467 | 3102992000049 | Trimmer capacitor 3.2*2.5*1.25mm                  | 1 | TC351 | T2D |                |
| 468 | 3003994730000 | Thermistor 0603 47KΩ J                            | 1 | TH101 | T3E |                |
| 469 | 3701443940000 | Crystal 44.395MHz NX6035S                         | 1 | X202  | B2E |                |
| 470 | 3703016850019 | Temperature compensate crystal oscillator 16.8MHz | 1 | X401  | T3C |                |
| 471 | 3802388540039 | Crystal filter 44.85MHz ±7.5K                     | 1 | XF201 | T3C |                |
| 472 | 4103000100700 | TC3000U-RE RF PCB FR                              | 1 |       |     |                |
| 473 | 6201114100009 | TC3000 low pass filter (2) lower shield sheet     | 1 |       |     |                |
| 474 | 6201116100009 | TC3000 IF lower shield sheet 0.2mm white          | 1 |       |     |                |
| 475 | 6201118100009 | TC3000 mixer (2) lower shield sheet 0.2           | 1 |       |     |                |
| 476 | 6201120100009 | TC3000 transmitter lower shield sheet 0.2mm white | 1 |       |     |                |
| 477 | 6201122100009 | TC3000 PLL lower shield sheet 0.2mm               | 1 |       |     |                |
| 478 | 6201124100009 | TC3000 VCO lower shield sheet 0.2mm               | 1 |       |     |                |
| 479 | 6201126100009 | TC3000 filter lower shield sheet 0.2mm            | 1 |       |     |                |
| 480 | 6201127100009 | TC3000 low pass filter (1) lower shield sheet 0   | 1 |       |     |                |
| 481 | 6201130100009 | TC3000 mixer (1) lower shield sheet 0.2           | 1 |       |     |                |
| 482 | 7000066000009 | TC3000 cooler 9.60×6.00                           | 1 |       |     |                |

确认人：

接收时间：

确认时间：