

## 1 Your mobile .....

### Keys in idle mode




- OT-E101A by Alcatel
- OT-E201A by Alcatel
- OT-E207A by Alcatel

1

## 2 Getting started.....


### 2.1 Remove the back cover



### 2.2 Insert the SIM Card


Inserting the SIM card in order to use your phone. To insert your SIM card, turn off your phone by holding down the key.

Fit the SIM card with the chip (indicated by the gold connectors) facing downwards. Slide the SIM card into its compartment taking care of the correct orientation with the angled corner. Push the SIM card with your finger to release it.



### 2.3 Insert and remove the battery

To remove the battery, make the same thing in the other direction.



## 3 Menu .....

Select the item you require using the navigation keys (, , , ), then press again the left softkey to confirm.

- Tools:**  
Access the Alarm and Calculator functions.
- Call services:**  
Access functions such as: voicemail number, call memory, call settings, network, forward and call barring.
- Messages:**  
Read, write and send your SMS. View your messages in your inbox, outbox. Adjust the settings and activate/deactivate SMS CB <sup>(1)</sup> message reception.
- Directory:**  
Access/create directory files and make calls from your directory.
- Sounds:**  
Change the mode, volume, ringtones, alerts, power on/off sounds, key beep.
- Display:**  
Change the main screen wallpaper, colours/contrast, power on/off display, screensaver and contrast.
- Settings:**  
Set the time, date, language, security mode, answer mode, etc
- Games:**  
Play the 2 games embedded in your telephone.
- Services <sup>(2)</sup>:**  
Access the Operator services.

<sup>(1)</sup> Contact your network operator to check service availability.  
<sup>(2)</sup> Depending on your operator's network.

2

## 4 Main screen icons.....

- Battery charge level.**
- Vibrate mode <sup>(1)</sup>**
- Silence mode <sup>(2)</sup>**
- Unread message.**
- Message list is full**
- Unanswered call**
- Call forwarding activated:** your calls are forwarded
- Alarm programmed**
- Signal strength indicator.**
- Keypad lock.**
- Roaming.**

<sup>(1)</sup> For E201/E207 only  
<sup>(2)</sup> For E101 also means vibrate mode

3

## 5 Tools .....

### 5.1 Alarm

- + = "snooze": The alarm will ring again after 5 minutes.
- + = "cancel"

When the phone is switched off, the alarm will ring.

### 5.2 Calculator



4

## 6 Calls.....

### 6.1 Making a call

Dial number then press

To hang up, press

If you make a mistake, press . Press and hold the key to delete all the digits.

### Making an emergency call

Dial 112 or any other number and press . Emergency calls can be performed at any time without your SIM card or PIN code. Once the call has been made, the screen will display: "SOS".

### Making an international call

Hold down when "+" is displayed, enter the country and area codes, then complete the number and send the call.

### Calling a number from the directory

Press the key to access the directory. Select the desired phone number and press .

### 6.2 Calling your voicemail <sup>(1)</sup>

Make a long keypress on the key.

### 6.3 Available functions during the call

Access the available options during a call by pressing .

<sup>(1)</sup> Contact your network operator for more information.

5

## 7 Messages.....

Press or press and select .

### 7.1 Create an SMS

→ "create" → Abc →

and choose your action:

**Send:** send the message to a recipient.

**Send to many:** send the message to a group of people you have defined

**Send to email:** send a message to an email address <sup>(1)</sup>.

**Save:** save the message in the unsent box and send it later.

**Templates:** use or modify an existing message.

**Discard:** discard the message.

**Predictive (T9):** select this mode to enter the words more quickly.

**123:** switch to numeric mode

**T9 help:** help menu for the predictive mode

**7.2 Read an SMS**  
In the inbox, read and unread messages are shown with different icon. The outbox included sent and unsent messages.

**7.3 Inbox/Outbox**  
Select the message and press and choose your option: Reply/Delete/Forward message/Archives/Modify/Extract number/Call number.

<sup>(1)</sup> Contact your network operator for service availability.

6

## 8 Directory.....

You may store up to 250 entries in the phone memory.

### 8.1 Directory menu

- View:** access the list contacts (alphabetic order).
- Create:** enter number and name of a new contact.
- Delete:** delete the selected contact.
- Copy:** copy the selected contact from the SIM memory to the phone memory and vice versa.
- Caller group:** group together names by category.
- Select Dir.:** select the SIM directory, Phone directory or both at the same time.
- Memory status:** check the numbers of contacts and the memory space left.
- My number:** enter your own phone numbers for future reference.
- Speed Dial:** set up speed dial for each key from to .

### 8.2 Creating a contact

select "create" and enter number and name of a new contact.

### 8.3 Consulting your directory ("View")

Select "Dir." then "View" to access the list of your contacts

#### Available options in the contact list

Once you have selected a name, press to access the following options: Call number/Send message/Details/Modify/Delete/Copy/Caller group/Search number.

#### Caller group

You can group together names by category and select a special ringtone. For each group, you can select the following options: Modify/Ringtone/SMS alert/Members/Add member/Delete all.

## 9 Sounds.....

From the main screen and select one of the following options in order to customise your telephone.

### 9.1 Mode

- Ringtone:** only the tone is played.
- Vibrate:** only vibrator is set (but the alarms and low battery sound will be played anyway).
- Vibrate & ring:** vibrator and tone at the same time.
- Vibrate then ring:** vibrator then tone.
- Vibrate.Beep.Ring:** vibrator then warning beep, then tone.
- Silence:** no sound no beep (but the alarms and low battery sound will be played anyway).

### 9.2 Volume

The volume can be adjusted to one of the set levels.

## 10 Display .....

### 10.1 Wall paper <sup>(1)</sup>

Select the image you wish to be displayed as the idle screen.

### 10.2 Colours <sup>(1)</sup>/Reverse <sup>(2)</sup>

Choose different colors for the presentation of the screen.

<sup>(1)</sup> OT-E201A, OT-E207A.  
<sup>(2)</sup> OT-E101A.

7

### 10.3 Contrast

Set the contrast of your phone by choosing one of the 5 levels proposed.

### 10.4 Backlight

Select the display backlight duration : 7s, 15s, 20s, 30s.

## 11 Settings .....

### 11.1 Clock

Set time and date, time format, display (show or hide the clock).

### 11.2 Languages

To choose the language in which the messages will be displayed.

### 11.3 Dictionary

Create, modify or delete a word in your personal dictionary. When creating a SMS, the word of this dictionary are automatically called if you choose the Predictive Mode (T9).

### 11.4 Auto keypad lock

To select the timing for the automatic locking of the keypad when the handset is not in use. From this function you may select a timing of 5 to 40 seconds, or to set it "off" if you prefer to lock it manually.

### 11.5 Auto power

### 11.6 Answer mode

### 11.7 Factory reset

<sup>(1)</sup> Contact your network operator for more information.

8

## 12 Call services .....

### 12.1 Call memory

From the main screen, press and your phone display a call list. Each call is displayed with an icon indicating the type of the call.

Select a telephone number in the list and press to redial it or press to access the following options :

- Details:** display the information of the call selected.
- Save number:** store the number in your directory.
- Send message:** create an SMS.
- Call number:** call the selected number.
- Modify:** modify the number, then call it or save it.
- Delete:** delete the number selected.
- Delete all:** delete the entire list.

### 12.2 Call settings <sup>(1)</sup>

Minute alert/Call waiting/Auto redial/Billing/Duration/Amount/Hide my ID.

### 12.3 Call services <sup>(1)</sup>

Network/Call forwarding/Call barring.

<sup>(1)</sup> Contact your network operator for more information.

9

## 13 Games .....

### 13.1 Russia

The aim of this game is to make as many complete lines of bricks as possible.

#### Key functions:



Toggle the upgrade level flag: if the flag is on, the game level will move up when your score increase 300. The level impacts the speed of the bricks : the higher the level, the higher the speed.

### 13.2 Bricks

The aim is to break as many bricks as possible with a bat and ball.

3 lives per game.

Miss a ball = lose a life

Bonus depending on the position in which the ball hits the bricks.

#### Key functions:



Alcatel logo and Alcatel name are trademark of Alcatel-Lucent used under license by T&A Mobile Phones Limited.

All rights reserved © Copyright 2007 T&A Mobile Phones Limited.

T&A Mobile Phones Limited reserves the right to alter material or technical specification without prior notice.

10

11

## Safety and use .....

We recommend that you read this chapter carefully before using your cellphone. The manufacturer disclaims any liability for damage, which may result as a consequence of improper use or use contrary to the instructions contained in this manual.

#### •TRAFFIC SAFETY:

**Given that studies, which show that using a cellphone while driving a vehicle constitutes a real risk, even when the hands-free kit is used (headset...), drivers are requested to refrain from using their cellphone when the vehicle is not parked**

When switched on, your cellphone emits electromagnetic waves that can interfere with the vehicle's electronic systems such as ABS anti-lock brakes or airbags. To ensure that there is no problem:

- do not place your cellphone on top of the dashboard or within an airbag deployment area.
- check with your dealer or car manufacturer to make sure that the car's electronics devices are well shielded.

#### • CONDITIONS OF USE:

Your are advised to switch off your cellphone from time to time to optimise performance.

Switch the cellphone off before boarding.

Switch the cellphone off when you are in health care facilities, except in designated areas. As with many other types of equipment now in regular use, cellphones can interfere with other electrical or electronic devices, or equipment using radio frequency.

Switch the cellphone off when you are near gas or flammable liquids. Strictly obey all signs and instructions posted in a fuel depot, gas station, or chemical plant, or in any potentially explosive atmosphere.

When the cellphone is switched on, it should be kept at least 15 cm from any medical device such as a pacemaker, a hearing aid or insulin pump. VWhen using the cellphone you should hold it against the ear on the opposite side to the device, if any.

To avoid hearing impairment, pick up the call before holding your cellphone to your ear. Also move the handset away from your ear while using the "hands-free" option because the amplified volume might cause hearing damage.

Do not let small children use the cellphone without supervision.

When replacing the cover please note that your cellphone may contain substances that could create an allergic reaction.

Always handle your cellphone with care and keep it in a clean and dust-free place. Do not allow your cellphone to be exposed to unfavourable environmental conditions (moisture, humidity, rain, infiltration of liquids, dust, sea air, etc). The manufacturer's recommended operating temperature range is -20°C to +55°C. Over 55°C the legibility of the cellphone's display may be impaired, though this is temporary and not serious.

Emergency call numbers may not be reachable on all cellular networks. You should never rely only on your cellphone for emergency calls.

Do not open, dismantle or attempt to repair your cellphone yourself.

Do not drop, throw or try to bend your cellphone.

Do not paint it.

Use only Alcatel batteries, battery chargers, and accessories that are compatible with your cellphone model. T&A Mobile Phones Limited or its affiliates disclaim any liability for damage caused by the use of other batteries.

Your cellphone should not be disposed of in a municipal dump. Please check local regulations for disposal of electronic products.

Remember to make back-up copies or keep a written record of all important information stored in your cellphone.

Some people may suffer epileptic seizures or blackouts when exposed to flashing lights, or when playing video games. These seizures or blackouts may occur even if a person never had a previous seizure or blackout. If you have experienced seizures or blackouts, or if you have a family history of such occurrences, please consult your doctor before playing videos games on your cellphone or enabling a flashing-lights feature on your cellphone. Parents should monitor their children's use of video games or other features that incorporate flashing lights on the cellphones. All persons should discontinue use and consult a doctor if any of the following symptoms occur: convulsion, eye or muscle twitching, loss of awareness, involuntary movements, or disorientation. To limit the likelihood of such symptoms, please take the following safety precautions:

- Do not play or use a flashing-lights feature if you are tired or need sleep.
- Take a minimum of a 15- minute break hourly.
- Play in a room in which all lights are on.
- Play at the farthest distance possible from the screen.
- If your hands, wrists, or arms become tired or sore while playing, stop and rest for several hours before playing again.
- If you continue to have sore hands, wrists, or arms during or after playing, stop the game and see a doctor.

When you play games on your cellphone, you may experience occasional discomfort in your hands, arms, shoulders, neck, or other parts of your body. Follow the instructions to avoid problems such as tendinitis, carpal tunnel syndrome, or other musculoskeletal disorders:



This symbol on your telephone, the battery and the accessories means that these products must be taken to collection points at the end of their life:

- Municipal waste disposal centres with specific bins for these items of equipment
  - Collection bins at points of sale.
- They will then be recycled, preventing substances being disposed of in the environment, so that their components can be reused.

#### In European Union countries:

These collection points are accessible free of charge. All products with this sign must be brought to these collection points.

#### In non European Union countries:

Items of equipment with this symbol are not be thrown into ordinary bins if your country or your region has suitable recycling and collection facilities; instead they are to be taken to collection points for them to be recycled.

#### • PRIVACY:

Please note that you must respect the laws and regulations in force in your country regarding taking photographs and recording sounds with your mobile telephone. Pursuant to such laws and regulations, it may be strictly forbidden to take photographs and/or to record the voices of other people or any of their personal attributes, and duplicate or distribute them, as this may be considered to be an invasion of privacy. It is the user's sole responsibility to ensure that prior authorization be obtained, if necessary, in order to record private or confidential conversations or take a photograph of another person; the manufacturer, the seller or vendor of your mobile phone (including the operator) disclaim any liability which may result from the improper use of the mobile phone.

#### • BATTERY:

Before removing the battery from your cellphone, please make sure that the telephone is switched off.

Take precautions with the battery and do not attempt to open the battery (chemical substances may cause burns).

Do not pierce, disassemble nor cause a short-circuit in a battery.


Do not burn or dispose of a used battery in household waste or store it at temperatures above 60 °C.

Batteries must be disposed of in accordance with locally applicable environmental legislation.

Batteries should not be used for any other purpose than the one intended. Never use damaged batteries or not recommended by T&A Mobile Phones Limited and/or its affiliates.


## Troubleshooting .....

Before contacting the aftersales department, you are advised to follow the instructions below:


- You are advised to switch off the telephone from time to time to optimise its performance.
- You are advised to fully charge the battery (  ) for optimal operation.
- Avoid storing large amounts of data in your telephone as this may affect the performance of your telephone.

and carry out the following checks:

#### My mobile phone does not switch on

- Press  until the screen comes on
- Check the battery charge level
- Check the battery contacts, remove and reinstall your battery, then turn your telephone back on

#### My phone does not respond since several minutes

- Press the  key
- Remove the battery and re-insert it, then switch the phone back on

#### My screen is difficult to read

- Clean your screen
- Use your mobile phone in accordance with the recommended conditions of use

#### My mobile phone turns off by itself

- Check that your keypad is locked when you are not using your mobile phone
- Check the battery charge level
- Check that the function **"Auto OFF"** is not activated.

#### • CHARGERS:

Mains powered chargers will operate within the temperature range: 0°C to 40°C. The chargers designed for your cellphone meet with the standard for safety of information technology equipment and office equipment use. They should be used for this purpose only.

**Electrical characteristic of power supply** (depending on the country):

110V charger (used in Mexico):

Input: 100-127 V, 50/60 Hz, 0.30 A

Output: 4.5 V, 350 mA

220V charger:

Input: 220-240 V, 50/60 Hz, 0.30 A

Output: 4.5 V, 350 mA

Battery: Lithium 650 mAh

#### • RADIO WAVES:

THIS CELLPHONE MEETS THE GOVERNMENT'S REQUIREMENTS FOR EXPOSURE TO RADIO WAVES.

Your cellphone is a radio transmitter and receiver. It is designed and manufactured not to exceed the emission limits for exposure to radio-frequency (RF) energy. These limits are part of comprehensive guidelines and establish permitted levels of RF energy for the general population. The guidelines are based on standards that were developed by independent scientific organizations through periodic and thorough evaluation of scientific studies. These guidelines include a substantial safety margin designed to ensure the safety of all persons, regardless of age and health.

The exposure standard for cellphones employs a unit of measurement known as the Specific Absorption Rate, or SAR. The SAR limit set by public authorities such as the Federal Communications Commission of the US Government (FCC) or by Industry Canada, is 1.6 W/kg averaged over 1 gram of body tissue. Tests for SAR are conducted using standard operating positions with the cellphone transmitting at its highest certified power level in all tested frequency bands.

Although the SAR is determined at the highest certified power level, the actual SAR level of the cellphone while operating can be well below the maximum value. This is because the cellphone is designed to operate at multiple power levels so as to use only the power required to reach the network. In general, the closer you are to a wireless base station antenna, the lower the power output of the cellphone. Before a cellphone model is available for sale to the public, compliance with national regulations and standards must be shown.

The highest SAR value for this cellphone when tested is:
OT-E101A: 1.24 W/kg for use at the ear and 0.62 W/kg for use close to the body.
OT-E201A: XXX W/kg for use at the ear and XXX W/kg for use close to the body
OT-E207A: XXX W/kg for use at the ear and XXX W/kg for use close to the body
NOTE: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

While there may be differences between the SAR levels of various cellphones and at various positions, they all meet the government requirement for RF exposure. For body-worn operation, the cellphone meets FCC RF exposure guidelines provided that it is used with a non-metallic accessory with the handset at least 2 cm from the body. Use of other accessories may not ensure compliance with FCC RF exposure guidelines.

The World Health Organization (WHO) considers that present scientific information does not indicate the need for any special precautions for use of cellphones. If individuals are concerned, they might choose to limit their own or their children's RF exposure by limiting the length of calls, or using "hands-free" devices to keep cellphones away from the head and body (fact sheet n°193). Additional WHO information about electromagnetic fields and public health are available on the following website: http://www.who.int/peh-emf. Your telephone is equipped with a built-in antenna. For optimal operation, you should avoid touching it or degrading it.

# General information .....

- **Website:** www.tctmobile.com

- **Hot Line Number:** see the “TCL & Alcatel Mobile Phones Services” leaflet or go to our Internet site.

On our Internet site, you will find our FAQ (Frequently Asked Questions) section. You can also contact us by e-mail to ask any questions you may have.

#### Unable to receive incoming calls

- Make sure your mobile phone is switched on and connected to a network (check for overloaded or unavailable network)
- Check your subscription with your operator (credit, SIM card valid, etc.)
- Make sure you have not forwarded incoming calls
- Make sure that you have not barred certain calls

#### The caller's name does not appear when a call is received

- Check that you have subscribed to this service with your operator
- Your caller has concealed his/her number

#### The sound quality of the calls is not optimal

- You can adjust the volume during a call by means of the  key
- Check the radio reception icon 


#### I am unable to use the features described in the manual

- Check with your operator to make sure that your subscription includes this service
- Check to be sure this feature does not require an Alcatel accessory.

#### When I select a number from my directory, the number is not dialled

- Make sure that you have correctly recorded the number in your file
- Make sure that you have selected the country prefix when calling a foreign country

Your telephone is a transceiver that operates on PCS networks with 850 and 1900 MHz bands.

The  marking indicates that your telephone complies with "1999/5/EC (R&TTE)" directive and that the accessories concerned comply with current EC directives. The entire copy of the Declaration of Conformity for your telephone can be obtained through our website: www.tctmobile.com.

#### Protection against theft <sup>(1)</sup>

**Your telephone is identified by an IMEI (phone serial number) shown on the packaging label and in the product's memory. We recommend that you note the number the first time you use your telephone by entering \* , #, 0, 6, # and keep it in a safe place. It may be requested by the police or your operator if your telephone is stolen. This number allows your mobile telephone to be blocked preventing a third person from using it, even with a different SIM card.**

#### Disclaimer

There may be certain differences between the user manual description and the phone's operation, depending on the software release of your telephone or specific operator services.



T9 Text Input is licensed under one or more of the following: U.S. Pat. Nos. 5,187,480, 5,818,437, 5,945,928, 5,953,541, 6,011,554, 6,286,064, 6,307,548, 6,307,549, and 6,636,162, 6,646,573; European Pat. Nos. 0 842 463 (96927260.8), 1 010 057 (98903671.0), 1 018 069 (98950708.2);

and additional patents are pending worldwide

<sup>[1]</sup> Contact your network operator for service availability.

<sup>[1]</sup> The mandatory period may vary if overriding statutory provisions are applicable in your country.

<sup>[2]</sup> The life of a rechargeable Alcatel telephone battery in terms of conversation time, standby time, and total service life, will depend on the conditions of use and network configuration. Batteries being considered expendable supplies, the specifications state that you should obtain optimal performance for your Alcatel phone during the first six months after purchase and for approximately 200 more recharges.

<sup>[1]</sup> The mandatory period may vary if overriding statutory provisions are applicable in your country.

<sup>[2]</sup> The life of a rechargeable Alcatel telephone battery in terms of conversation time, standby time, and total service life, will depend on the conditions of use and network configuration. Batteries being considered expendable supplies, the specifications state that you should obtain optimal performance for your Alcatel phone during the first six months after purchase and for approximately 200 more recharges.

<sup>[1]</sup> The mandatory period may vary if overriding statutory provisions are applicable in your country.

<sup>[2]</sup> The life of a rechargeable Alcatel telephone battery in terms of conversation time, standby time, and total service life, will depend on the conditions of use and network configuration. Batteries being considered expendable supplies, the specifications state that you should obtain optimal performance for your Alcatel phone during the first six months after purchase and for approximately 200 more recharges.

<sup>[1]</sup> The mandatory period may vary if overriding statutory provisions are applicable in your country.

<sup>[2]</sup> The life of a rechargeable Alcatel telephone battery in terms of conversation time, standby time, and total service life, will depend on the conditions of use and network configuration. Batteries being considered expendable supplies, the specifications state that you should obtain optimal performance for your Alcatel phone during the first six months after purchase and for approximately 200 more recharges.

<sup>[1]</sup> The mandatory period may vary if overriding statutory provisions are applicable in your country.

<sup>[2]</sup> The life of a rechargeable Alcatel telephone battery in terms of conversation time, standby time, and total service life, will depend on the conditions of use and network configuration. Batteries being considered expendable supplies, the specifications state that you should obtain optimal performance for your Alcatel phone during the first six months after purchase and for approximately 200 more recharges.

<sup>[1]</sup> The mandatory period may vary if overriding statutory provisions are applicable in your country.

<sup>[2]</sup> The life of a rechargeable Alcatel telephone battery in terms of conversation time, standby time, and total service life, will depend on the conditions of use and network configuration. Batteries being considered expendable supplies, the specifications state that you should obtain optimal performance for your Alcatel phone during the first six months after purchase and for approximately 200 more recharges.