



RF EXPOSURE REPORT

REPORT NO.: RF920725H03

MODEL NO.: WN6401C

ACCORDING: FCC Guidelines for Human Exposure
IEEE C95.1

APPLICANT: Arcadyan Technology Corporation

ADDRESS: 4F, No. 9, Park Avenue II, Science-based
Industrial Park, Hsinchu 300, Taiwan, R.O.C.

ISSUED BY: Advance Data Technology Corporation

LAB LOCATION: 47 14th Lin, Chiapau Tsun, Linko, Taipei,
Taiwan, R.O.C.



Lab Code: 200376-0



RF Exposure Measurement

1. Introduction

In this document, we try to prove the safety of radiation harmfulness to the human body for our product. The limit for Maximum Permissible Exposure (MPE) specified in FCC 1.1310 is followed. The Gain of the antenna used in this product is measured in a Fully Anechoic Chamber (FAC) calibrated for antenna measurement in ADT, and also the maximum total power input to the antenna is measured. Through the Friis transmission formula and the maximum gain of the antenna, we can calculate the distance, away from the product, where the limit of MPE is reached.

Although the Friis transmission formula is a far field assumption, the calculated result of that is an over-prediction for near field power density. We will take that as the worst case to specify the safety range.

2. RF Exposure Limit

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environmental impact of human exposure to radio-frequency (RF) radiation as specified in 1.1307(b)

LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)	Average Time (minutes)
(A)Limits For Occupational / Control Exposures				
300-1500	F/300	6
1500-100,000	5	6
(B)Limits For General Population / Uncontrolled Exposure				
300-1500	F/1500	6
1500-100,000	1.0	30

F = Frequency in MHz



3. Friis Formula

Friis transmission formula : $P_d = (P_{out} * G) / (4 * \pi * r^2)$

where

P_d = power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm

P_d is the limit of MPE, 1 mW/cm². If we know the maximum Gain of the antenna and the total power input to the antenna, through the calculation, we will know the MPE value at distance 20cm.

Ref. : David K. Cheng, *Field and Wave Electromagnetics*, Second Edition,
Page 640, Eq. (11-133).

4 EUT Operating condition

The software provided by Manufacturer enabled the EUT to transmit and receive data at lowest, middle and highest channel individually.

5. Classification

The antenna of this product, under normal use condition, is at least 20cm away from the body of the user. Warning statement to the user for keeping at least 20cm or more separation distance with the antenna should be included in users manual. So, this device is classified as **Mobile Device**



6 Test Results

6.1 Antenna Gain

Antenna 1:

The maximum Gain measured in Fully Anechoic Chamber are -2.16Bi or 0.608 (numeric). for 5.15-5.35GHz and -0.11dBi or 0.975(numeric) for 2.4GHz.

Antenna 2:

The maximum Gain measured in Fully Anechoic Chamber are -3.34Bi or 0.463 (numeric). for 5.15-5.35GHz and -2.86dBi or 0.518(numeric) for 2.4GHz.

Antenna 3:

The maximum Gain measured in Fully Anechoic Chamber are -0.35Bi or 0.923 (numeric). for 5.15-5.35GHz and -3.73dBi or 0.424(numeric) for 2.4GHz.

Antenna 4:

The maximum Gain measured in Fully Anechoic Chamber are 0.02Bi or 1.005 (numeric). for 5.15-5.35GHz and -3.98dBi or 0.400(numeric) for 2.4GHz.

6.2 Output Power Into Antenna & RF Exposure value at distance 20cm:

Antenna 1: (For Part 802.11b)

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	2412	72.778	0.0088	1.0
6	2437	69.343	0.0084	1.0
11	2462	64.565	0.0078	1.0

Antenna 1: (For Part 802.11g)

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	2412	20.091	0.0024	1.0
6	2437	23.988	0.0029	1.0
11	2462	22.182	0.0027	1.0



Antenna 2: (For Part 802.11b)

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	2412	72.778	0.0067	1.0
6	2437	69.343	0.0064	1.0
11	2462	64.565	0.00595	1.0

Antenna 2: (For Part 802.11g)

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	2412	20.091	0.00185	1.0
6	2437	23.988	0.0022	1.0
11	2462	22.182	0.00205	1.0

Antenna 3: (For Part 802.11b)

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	2412	72.778	0.01334	1.0
6	2437	69.343	0.01273	1.0
11	2462	64.565	0.01185	1.0

Antenna 3: (For Part 802.11g)

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	2412	20.091	0.0037	1.0
6	2437	23.988	0.0044	1.0
11	2462	22.182	0.0041	1.0

**Antenna 4: (For Part 802.11b)**

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	2412	72.778	0.0145	1.0
6	2437	69.343	0.0139	1.0
11	2462	64.565	0.0129	1.0

Antenna 4: (For Part 802.11g)

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	2412	20.091	0.0040	1.0
6	2437	23.988	0.0048	1.0
11	2462	22.182	0.0044	1.0

For 802.11a (5GHz Band):**Antenna 1: Normal Mode :**

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	5180	16.982	0.0033	1.0
4	5240	17.579	0.0034	1.0
5	5260	16.866	0.0033	1.0
8	5320	16.144	0.0031	1.0

Antenna 1: Turbo Mode :

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	5210	17.620	0.0034	1.0
2	5250	18.155	0.0035	1.0
3	5290	17.258	0.0033	1.0



Antenna 2: Normal Mode :

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	5180	16.982	0.0017	1.0
4	5240	17.579	0.0018	1.0
5	5260	16.866	0.0017	1.0
8	5320	16.144	0.0017	1.0

Antenna 2: Turbo Mode :

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	5210	17.620	0.0018	1.0
2	5250	18.155	0.0019	1.0
3	5290	17.258	0.0018	1.0

Antenna 3: Normal Mode :

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	5180	16.982	0.00143	1.0
4	5240	17.579	0.00148	1.0
5	5260	16.866	0.00142	1.0
8	5320	16.144	0.00136	1.0

Antenna 3: Turbo Mode :

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	5210	17.620	0.00148	1.0
2	5250	18.155	0.00153	1.0
3	5290	17.258	0.00145	1.0



Antenna 4: Normal Mode :

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	5180	16.982	0.00135	1.0
4	5240	17.579	0.0014	1.0
5	5260	16.866	0.00134	1.0
8	5320	16.144	0.00128	1.0

Antenna 4: Turbo Mode :

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	5210	17.620	0.00140	1.0
2	5250	18.155	0.00144	1.0
3	5290	17.258	0.00137	1.0

The minimum allowable power density is $(0.0252+0.0478=0.0730)$ which is lower than 1 mW/ cm²