

## **MyOrigo mydevice Z1**

Second Edition

This document is provided "as is" without warranty of any kind, either expressed or implied, including, but not limited to, the implied warranties of merchant ability, fitness for a particular purpose, or non-infringement.

This manual could include technical or other inaccuracies or typographical errors. Changes are periodically added to the information herein; these changes will be incorporated in a new edition of this manual. MyOrigo Oy, Ltd. reserves the right to make improvements and /or changes in the product(s) described in this manual at any time.

©MyOrigo Oy, Ltd. 2003

All rights reserved.

**Issued by:**

**MyOrigo Oy, Ltd.**

**Kasarmintie 28 H25**

**90230 Oulu**

**Finland**

DRAFT

**Publication Number:**

intent is a registered trademark of Tao Group Ltd.

espial

# Introduction

The MyOrigo **mydevice** Z1 is a triple band phone and can be operated on E-GSM 900, GSM 1800 and GSM 1900 networks, which means that you are able to use the device in many regions across the world.

The device has a large colour display that is also a touch screen with feedback when you press the screen. This feedback from the touch screen is referred to as Haptitouch. The device has a built in digital camera which can be used to take photos.

In the device are motion sensors that can be used to control certain movements and functions in the device, like mirroring and zooming the views.

The device supports GPRS (General Packet Radio Services) which means that you can make fast data connections. MMS, E-mail messaging and Internet browsing are supported in the device through GPRS connections.

DRAFT

# Getting Started

## Overview



1. Function Key A

3. Infrared Port

5. Earpiece

7. Microphone

9. Battery Cover Release

11. Headset Connector Port

2. Function Key B

4. LED Indicator

6. Haptitouch Screen

8. Camera Lens

10. Mini USB Data Cable Connector

12. Charger Connector Port

## Inserting the Battery

### *Removing the Battery Cover*

1. With your fingernail, pull the battery cover latch downwards



2. Lift the cover slightly at the battery cover latch end and gently slide upwards to release the battery cover from the upper corner release catches.



### *Replacing the Battery Cover*

Repeat the *Removing the battery Cover* in the opposite order.

### ***Attaching the battery***

1. Place the battery into the back of the phone, with the golden connectors facing down.
2. Push the battery down at the bottom and then slide up so that the battery is locked into position by means of the battery locking pins.



### ***Removing the battery***

1. With your finger nail pull down and lift out the battery.



**NOTE:** Always switch the phone off before removing the battery.

### ***Inserting your SIM Card***

1. If the SIM card is attached to the plastic surround card, then first snap out the card pushing it out at the snap points.



### ***Inserting the SIM card in the device***

1. Insert the SIM card with the golden contacts facing down as shown in the picture.



### ***Removing the SIM card from the device***

1. Press lightly on the card and slide out in the opposite direction from inserting.



### ***Inserting the Multimedia Card***

1. Insert the MultiMedia card with the golden contacts facing down and the cut corner at the bottom right, as shown in the picture.



### Removing the MultiMedia card

1. Press lightly on the card and slide out in the opposite direction from inserting.



### Charging the device

1. Connect the charger to the mains socket.



2. Connect the other end of the charger lead to the bottom of the device.  
When the device is switched off and the charger is connected, *Charging...* is displayed on the screen.

If the device is switched on when the charger is connected, *Charging*  will be briefly displayed.

The battery meter level in the status field shows the charged state of the battery. When charging, this will be animated to show that the battery is being charged.



When the battery level is low, the device will give a warning signal and *Battery Low, Recharge battery*  will be briefly displayed.

**NOTE:** You can use the device whilst the battery is being charged. However, this lengthens the charging time.

Do not connect any chargers to the device other than the charger model that was provided in the sales package.

## LED Indication Lights

Normal blinking is when the LED flashes every 2 seconds. Slow blinking is when the LED flashes three times slower than normal.

### Green LED indications

- **Continuously on** - the device is in the start up procedure.
- **Normal blinking** - when a new message is received, missed call etc. whilst the device is in standby mode.
- **Slow blinking** - when the device is on and in standby mode.

### Red LED indications

- **Continuously on** - the device is in the shut down procedure.
- **Normal blinking** - when the battery is low

## Switching the device On and Off

Before you try to turn on the power, follow the SIM card and Battery insert procedure. See.....

### *Turning on the device*

1. Press and hold the function keys A & B simultaneously for approximately 2 seconds until the display comes to life.



2. Press the icon on the screen to select the mode you wish to use the device in.

## Aeroplane Mode

The aeroplane mode allows you to use the device without any voice calls and data connections.

You may be asked to provide a Device lock code, the factory set device lock code is 0000. To change this code, switch this function off see...

1. Enter your Device lock code and press *OK* .  
Press *Clear*  if you make a mistake whilst entering the code.  
If you enter the code incorrectly *Wrong code, Enter device lock code again* is displayed.



## Phone Mode

The phone mode allows you to use the device normally with all the data connections so that it is possible to make voice calls, data calls, etc.

You may be asked to enter a PIN code, if so this is supplied by the operator with your subscription. To change this code, switch this function off see...

1. Enter your PIN number and press *OK* .  
Press *Clear*  if you make a mistake whilst entering the PIN number.  
If you enter the PIN code incorrectly *Wrong code, Enter PIN code again* is displayed.  
If a PIN code is entered incorrectly 3 times in a row then the SIM card will be blocked and the message *Wrong code, SIM use blocked. Enter PUK code* is displayed. See SIM card locking...



## Tutorial Demo

The tutorial demo will be launched the first time the device is started after the start up mode is selected and the PIN/Device lock codes have been entered. The tutorial demo can be accessed at any time when the device is on from the Main index *Info/Show tutorial*  menu.

The tutorial demo shows how to browse the book, open Fast menus and the mirroring and zooming function.

### *Turning off the device*

1. Press the function keys A & B simultaneously to display the standby menu.
2. Press *Shutdown* 

DRAFT

# Key Functions

## Keys

### Lens Keys

Lens Key	Press once	Long Press
ABC	when keyboard is active it will change the keyboard to the character keyboard	to shortcut to the <i>Notepad</i> Application, opens the keyboard to write a new note
123	when keyboard is active it will change the character keyboard to the number keyboard	to shortcut to the <i>Calendars, View today</i> . This shortcut can be changed in the <i>Settings</i> menu.
@	when keyboard is active it will change the character keyboard to the symbols keyboard	to shortcut to the <i>Contact list of Contacts</i> . This shortcut can be changed in the <i>Settings</i> menu.
C	to go back a level higher in the book	to return to the first main index page and closes/cancels all applications and operations
	when an application/operation is in use, to close application/cancel operation	
Phone	opens the virtual phone application	to shortcut to <i>Dialled calls</i> page of <i>Calls</i> menu
Enter	when the cursor is in view and mirroring mode is on to enter to the selected item.	
	when keyboard is active it will move the cursor to the next line, if more than one line can be typed.	



## Side Keys

Side Key	When	Half Press to:	Full Click to:	Long Full Click to:	Continuous Half Press to:
A	in the book	turn 1 page forward			repeat page turning forwards
	using mirroring	lock mirroring on/off	use the cursor to enter	open a Fast menu start dragging/painting	activate mirroring
	during a call		increase the volume		
B	in the book	turn 1 page backward			repeat page turning backwards
	device is in use		fit to screen / 1:1 scale	free zooming / end zooming	
	during a call		decrease the volume		
A & B	device power is off			switch on the device	
	device power is on		open the standby menu	switch off the device	
	device is locked		open the virtual phone for unlocking		

## Cursors

The cursor will change shape depending on the position and actions on the device.

-  - Pointed Cursor
-  - Link or Active areas
-  - Text fields
-  - On keypads
-  - Browse forward
-  - Browse backward

## Main Index Pages

The mydevice menu structure is set out like a book with chapters, sub chapters and pages. There are 12 application chapters which make up the main index and these are the highest level of the book structure.



It is not possible to change the main index page contents or the order. It is possible to change the background image and colour of the main index.

## Browsing the book

There are several methods you can use to browse the book:

- By a single half press of the A key to move 1 page forward through the chapters and a single half press of the B key to move 1 page backwards through the chapters.
- By sliding you finger across the haptitouch screen from right to left will move 1 page forward and sliding you finger across the haptitouch screen from left to right will move 1 page backwards.
- By a continuous half press of the A key and tilting the device to forwards or backwards to view the book contents pages. Depending upon the degree of angle which you tilt the device will have an effect on the speed of the page browsing.

### *Using mirroring to browse the book pages*

1. With the display in the book main index view, partially press and hold the A key.
2. If you are at the first page of the book the direction for browsing will only be forward.
3. Move the book browser forward cursor  to a menu in the book and then tilt to view the next page in that chapter.

### *Using the cursor in mirroring mode to navigate the menus*

1. Partially press and hold the A key.
2. When the cursor  is tilted across the menu pages of an application the cursor changes to  and the menu section is highlighted as grey.
3. Fully pressing the A key will enter that menu.

## Mirroring

The device has sensors which allow you to control movements by tilting the device. There are several functionalities behind the mirroring effect dependant upon what you are viewing. Mirroring can be activated at any point when the device is switched on.

- Activates the controlling using a cursor
- Activates the cursor

If the page is at 1:1 scale then the cursor will be activated and can be moved around the screen by tilting the device whilst continuously half pressing the A key. Fully pressing the A key once will act as an enter button and depending on where the cursor is positioned will enter the selected function.

Mirroring allows you to view pages that are bigger than the display window. Mirroring is especially useful when browsing pages on the internet. If the 1:1 scale is larger than the device display window, for example a large image or internet page, then the page view will start in the upper left corner. continuously half pressing the A key and tilting the device will navigate through the view of the page.

Picture needed

## Zooming

Zooming a view is only possible when the page or image scale is greater than 1:1 to the device display.

*To use zooming to change display views*

When a internet page or large picture is loaded into the device and displayed on the screen.

- Fully pressing the *A* key once will switch the view between *fit to screen* and *1:1 scale*.

Pictures Needed

### ***To zoom by tilting the device***

When a internet page or large picture is loaded into the device and displayed on the screen.


- Continuously fully pressing the *B* key and;
  - tilting the device inwards will zoom in
  - tilting the device outwards will zoom out.

Pictures Needed

## **Action Fields**

An action field is a field that can contain a specific text format and the play icon  and when pressed it will launch a specific action or an application dependant upon the data in the field.

An action field for a phone number when pressed will open the phone application with the number already inputted and only  needs to be pressed to make a call to that number. See the example of a phone number action field.



Action fields for the following formats may be possible:

- Calls -
- E-mail -

- Web page -
- Object -

## Fast Menus

These are option menus that can be activated in the device applications. These menus are dynamic options, meaning that different options will be available depending on what function or position in the book you are. With a long press on an application chapter a fast menu will appear with icons that will show you options for that specific function or will show you the details viewer  if there are no functions available for that specific menu.

### ***How to use the Fast menus***

In the example we are going to use the fast menus to access the find function in the contacts application.

1. Long press the *Contacts* menu in the main index page 1.
2. A fast menu will appear with icons following icons.
3. Press  to access the *Find* function.

Picture

4. Enter the contacts name or first letter by which to search the stored contacts and press *OK* .

A list of contacts will be displayed corresponding to the search criteria that was entered. Pressing the  shortcut will take you to that specific contact page.

If no contacts are stored on the SIM or in the device then the find page will remain empty.

# Commands and Icons

## Status bar icons

	GPRS connection active		GPRS connection inactive
	Circuit Switched Dialing		Sound on
	Irda connection		Sound off
	USB cable attached		Aeroplane mode
	Headset attached		Missed call
	Call active		Divert call on
	Message received		Message in outbox
	Sending message in outbox		Alarm on
	Playing music		

## Generic commands

	Opens keyboard to type or edit		Find
	Delete		Save
	Reset value		Save to target
	Copy		Sort
	Paste		Select all
	Details Viewer		Set Default
	Send Irda		OK
	Yes		No
	Cancel		Close
	Next		Previous
	Back		

## General icons

	Add to: on		Default
	Add to: off		Link
	Action		Index

	Device Busy Wait		Error
	Fatal error		Warning
	Completed		Battery full
	Battery low		Charging battery
	USB connection		USB disconnected
	Headset		

DRAFT

## Standby menu commands

	Power off		Device is locked
	Sounds on		Device is unlocked
	Mute on		Flight mode

## Contact application commands

	Contact		Save to SIM
	Contact Group		Copy from SIM to device
	Contact Chooser		Move to SIM
	Synchronize contacts		Move from SIM
	Delete contact from device		Delete from SIM

## Contact application icons

	Contact in device		Contact on SIM
---	-------------------	---	----------------

## Calls application commands

	Call		Close call
	Conference call		Close all calls
	On hold		DTMF call
	Private call		Mute microphone
	Divert call		Turn on microphone
	Reset counter		

## Messages application commands

	Create SMS		Reply to SMS
	Send SMS		Forward SMS
	Create MMS		Reply to MMS
	Send MMS		Forward MMS
	Create E-mail		Send E-mail
	Attachment		Reply to E-mail

	Reply E-mail to all		Forward E-mail
	Send and Receive E-mail		

DRAFT

## Messages application icons

	Received SMS		Received SMS on SIM
	Opened SMS		Opened SMS on SIM
	Sent SMS		Received MMS
	Opened MMS		Sent MMS
	Received E-mail		Received E-mail with attachment
	Opened E-mail		Opened E-mail with attachment
	Replied E-mail		Replied E-mail with attachment
	Forwarded E-mail		Forwarded E-mail with attachment
	Sent E-mail		Received delivery report
	Received configuration message		Opened configuration message

## Internet application commands

	Start browser		Forward
	Stop		Back
	Home		Reload
	Favourites		Views
	Add to favourites		Open new view
	History		Close view
	Windows up		Windows down
	Hide		To book
	Fit to width		Restore to width
	Options		Views

## Calendar application commands

	New event		New task
	Select date		Synchronise
	Move left		Move right
	Move up		Move down

## Calendar application icons

	Alarm		Event
	Task		Task done

## Camera application commands

	Take picture		Save picture
	Cancel picture		Picture chooser

## Music application commands

	Fast forward		Fast rewind
	Next		Previous
	Play		Pause
	Record		Stop
	Sound on		Sound off
	Music chooser		

## Music application icons

	Music file
---	------------

## My files application commands

	New note		New folder
	File chooser		Save to memory card

## My files application icons

	Image file		Note file
	Program file		Text file

	Web page file		Folder
	Stored on memory card		

### Settings application commands

	Change security code		Server
	User profile		Remove server
	Reset device		Set time and date
	Synchronize		Profile synchronization
	Calibrate		Find time zone

### Programs application commands

	Calculator		Notepad
---	------------	---	---------

### Info application commands

	Help		Show tutorial
	Next tutorial		Previous tutorial
	Close tutorial		

## Standby Menu

The standby menu can be reached at any time when the phone is switched on by pressing both A & B keys simultaneously.

The standby menu contains the following options;

- Turn on key lock
- Turn on/off silent
- Shut down
- Task manager
- Profiles
- Volume control

## The key lock

The key lock is a feature that helps to prevent accidentally pressing buttons or dialling a number, when for example being carried in your pocket.

The key lock will remain locked unless the following happens:

- you unlock the key lock
- you receive an incoming call
- you receive a message

#### ***To turn on the key lock***

1. Full click the A & B keys simultaneously to access the standby menu.
2. Press *Lock* 

When the device is key locked the virtual phone will be displayed with *Screen locked* displayed.

#### ***To turn off the key lock***

- Press *Unlock*  in the display.

**NOTE:**With the key lock on you can still access the phone to make an emergency number call. See....

## **Silent Mode**

The silent mode disables all audible sound with the exception of the alarm clock signal.

#### ***To turn the device audio signals to silent***

1. Full click the A & B keys simultaneously to access the standby menu.
2. Select *Mute* 

To switch the silent function off repeat step 1 and select *Sound* .

## **Task Manager**

The task manager allows you to view, switch to and stop all tasks and/or applications that are running in the device.

## **Profiles**

See Settings.....

## **Volume in Use**

The volume in use function allows you to adjust the currently playing sound/audio volume in the device. If no sound/audio is playing when you access the standby menu then this volume control will be disabled.

#### ***To adjust the volume in use***

- Full click the A & B keys simultaneously to access the standby menu.  
Slide your finger to move the volume slider  to adjust the volume.

# Character and Number Input

## Character Keyboard

The virtual keyboard is used for entering new text and editing texts in all the applications that require or need text inputs, for example writing a note, an SMS message etc.

The title field notifies the text types. For example this title bar shows the keyboard has been



opened in the Messages application, there is an indication that there is a limit of 160 characters that can be typed to the text field and that the shift button is active, meaning that the first letter typed will be in uppercase followed by lower case letters.

The keyboard consists of 3 main keyboard layouts. The character keyboard is default keyboard.



The keyboard does not rotate to the vertical position

### **To activate the Shift key**

- Whilst you are writing text with the virtual keyboard, press  to activate the shift key.

The Shift key  will be active for one key press and then will return to the  state.

When the shift key is active you can enter a letter in Upper case and also the yellow marks   . *Abc* will appear in the header section of the key pad view.

### **To activate the Caps lock key**

- Whilst you are writing text with the virtual keyboard, press  twice or  once to activate the Caps lock key.

The Caps lock key  will be active until you press  to return to the normal state.

When the Caps lock key is active you can enter all letters in Upper case and also the yellow marks   . *ABC* will appear in the header section of the key pad view.

## Numeric keyboard

If you want to add a numbers or numeric signs to the text you are entering then you can switch the input keyboard from the character keyboard to the numeric keyboard by pressing the lens 123 key. After entering the symbols you can switch back to the character keyboard by pressing the lens ABC key.



### ***Scrolling through the text in the keyboard input area***

When writing with the keyboard there are two lines of text visible in the view. When more than two lines of text have been typed in the keyboard input area, you can scroll through the text by using the     keys which are located in the numeric keyboard. It is also possible to scroll using mirroring.

## Symbolic Keyboard

If you want to add a symbol to the text you are entering then you can switch the input keyboard from the character keyboard to the symbols keyboard by pressing the lens @ key. After entering the symbols you can switch back to the character keyboard by pressing the lens ABC key.



# Call Functions

The phone application can be activated in several ways, from the Phone key on the lens , through the Fast menu or from the *Calls/New call* field. Depending on how you are using the device you can choose the most appropriate way to access the phone application.

The Calls chapter contains call management features for this device, dialled, received and missed calls lists.



## Making Calls

### *To make a call*

1. Press 
2. Enter the phone number with the area code if needed.  
If you enter the incorrect number press *Clear*  to delete it. Pressing and holding *Clear*  will delete the whole number.
3. Press Call   
Press *End*  to end the call.
4. To exit the phone application press *Close*  when in standby mode to return to the previous menu.

### *To create a new contact from the entered number in the phone application*

- Press *Create contact*  to create a new contact with that number.  
See *Creating a contact* page.....

### *To answer a call*

- Press *Answer*  to answer the incoming call.

### *To reject an incoming call*

- Press *Reject*  to reject the incoming call.

### *To mute the audio alert for an incoming call*

- Press *Mute Tone*  to mute the audio for the incoming call.

### *To make international calls*

1. Press and hold  to enter the + sign.  
The + sign replaces the international prefix number.
2. Enter the country code, then the area code (without the first 0) and the phone number and press *Call* 

### *To adjust the earpiece volume during a call*

- Press the *A* key to increase the volume
- Press *B* key to decrease the volume



### ***To make a call to a stored contact from the phone application***

1. When in standby mode of the phone application, press **ABC** . The number buttons will change to letter buttons. To change the buttons back to numbers press **123** .
2. Enter the first letter for the contact you wish to recall.
3. Select the contact from the alphabetical list. The contact name will appear in the phone application.
4. Press **Call** .

## **Speed Dialling**

You can assign contacts numbers to the number buttons in the phone application, which can then be quickly recalled and dialled. *To set a speed dial number for a contact* See page...

### ***To make a call to a speed dial number***

- When the phone application is open either:
  - Press the corresponding speed dialling key for the contact you have assigned that number and press **Call** .
  - Press and hold the number until the call is started.

## **Emergency Calls**

At any time when the phone is switched on you can make an emergency call usually even without a SIM card if there is a GSM network in range. The international emergency numbers that are supported in this device are 112, 911 & 08.

It is also possible to make an emergency call when the device is locked. See *Locking and unlocking the device* page...

### ***To make an emergency call***

1. Press
2. Enter **112**, the GSM international emergency number.
3. Press **Call** .

## **Call Details**

- You can check the details of calls from the device. From the *Details viewer* you can see the following information:
  - Start time

- Call duration
- Number of calls
- Phone Number

#### ***To view the details of a call***

1. Select a single call from the *Calls* menu with a long press to activate the Fast menu.
2. Press *Details* .

## **Call Management**

The call management menu is a dynamic menu which contains the in-call options through the menus. The following in-call options may be available.

- Hold Call
- Activate Call
- Send DTMF
- End all calls
- Mute
- Swap

#### ***To turn off the microphone***

1. Select a call from the *Call Management* menu with a long press to activate the Fast menu.
2. Select *Mute Mic* .

To turn the microphone back on repeat this process and press *Mic On* .

## **Dialled Calls**

The device stores the 12 last dialled calls.

#### ***To view your received calls***

- Select *Calls/Dialled calls*.

#### ***Calling a previously dialled number***

1. Select *Calls/Dialled calls*.
2. Select the number or name that you wish to redial.
3. Press *Call* .

**TIP:** Dialled calls can also be reached by pressing *Dialled*  when in the phone application and no numbers have been entered in the phone.

## **Received Calls**

The device stores the 12 last received calls.

#### ***To view your received calls***

- Select *Calls/Received calls*.

## Missed Calls

The device stores the 12 last missed calls, a message *1 missed call* will appear under the *Calls* chapter in the contents page and also be displayed as  in the status header.

### *To view your missed calls*

- Select *Calls/Missed calls*.

## Call Waiting

See *Settings/Phone Settings* page...

## Diverting Calls

See *Settings/Phone Settings* page...

## DTMF touch tones

Dual Tone Multiple Frequency tones are codes sent as touch tone signals for use when controlling answering machines or accessing telephone banking services.

You can also store touch tone codes together with phone numbers in your contacts so that you can dial automatically into a service.

### *Sending touch tone signals*

During a call:

- pressing 0 -  buttons will send numbers
- pressing and holding 0 will send the pause character *P*.
- pressing and holding # will send the .. character *W*.

**NOTE:** Storing touch tone access codes with a phone number to a telephone service carries some risk if your device is stolen.

## Voicemail

Your voice mailbox is an answering service provided by your network or service provider, which allows callers to leave voice messages for you when you are unable to answer the call.

You can save your voicemail service number in the device so that you are able to quickly access the number through the speed dial number 1 which is reserved for your voicemail. See *Creating a contact* page.....

The voicemail indication....

### *To call your voice mailbox*

- Press and hold 1

## Call Holding

### *To put a call on hold*

1. Press *Manage Call* 
2. Select *Hold call* 

To take the call off hold, repeat steps 1 and 2 and select the call *Activate Call* 

### *To hold a call and make a new call*

1. Press *Manage Call* 
2. Select *Hold Call* 
3. Select *Open Phone* 

Either:

- Enter the new number and press *Call* 
- Press *Main Index*  and select a contact from the contacts list, with a long press on the number to activate the Fast Menu and press *Call* 

## Receiving a second call

If Call waiting is activated....

### *To answer the second call and put the ongoing call on hold*

- Press *Answer*  to answer the second call.  
The current call will now be put on hold.

### *To reject the waiting call and continue with the ongoing call*

- Press *Busy*  to reject the second call

### *To switch between calls*

1. Press *Manage Call*  to move to the *Call management* menu.
2. Select the call indicated as *Activate*   
This call is now switched to *Hold Call* .

### *To end the ongoing call and return to the call on hold*

1. Press *Manage Call*  to move to the *Call management* menu.
2. Long press the  to activate the Fast menu on the call indicated as *Online* 
3. Select *End*   
The previously held call is now active.

### *To end all calls*

1. Press *Manage Call*  to move to the *Call management* menu.
2. Long press the  to activate the Fast menu on the call indicated as *Online* 
3. Select *End All*  to end all calls.

## Receiving a third call

It is not possible to answer a third call without ending one of the other two calls first.

### *To handle a third call*

When the a third call is displayed as *Waiting* the following options are available:

- Press *Release and Answer*  to release the online call and answer the waiting call.
- Press *Busy*  to send a busy tone to the waiting call
- Press *End*  to end the online call

## Conference Calls

The device will allow you up to "x" people to be in a conference call. In order to make a conference call, one call must already be active.

### *To make a conference call*

When two calls are ongoing you can then make a conference call...

1. Press *Manage Call*  to move to the *Call management* menu.
2. Select *Conference Call* .

The two calls are now joined into a conference call.

### *To add a new member to an active conference call*

1. Press *Manage Call*  to move to the *Call management* menu.
2. Select *New call* .

Enter the new number and press *Call* . When answered the new call is active and the conference call is on hold.

3. Press *Manage Call*  to move to the *Call management* menu.
4. Select *Add to Conference* .

### *To remove a member from a conference call*

1. Press *Manage Call*  to move to the *Call management* menu.
2. Select the member *At conference*: in the conference call with a long press to activate the Fast menu.
3. Select *End*  to remove that member.

### *To enable a private conversation with a member of a conference call*

The device allows you to have a private conversation with one of the members in the conference call. This will put the rest of the conference call members on hold.

1. Select the member *At conference*: in the conference call with a long press to activate the Fast menu.
2. Select *Private* .

The conference call is now on hold.

***To rejoin a private conversation member to a conference call***

Follow steps 3 & 4 of *To add a new member to an active conference call*.

***To end the conference call***

1. Press *Manage Call*  to move to the *Call management* menu.
2. Select the conference call with a long press to activate the Fast menu.
3. Press *End All* 

## **Call Account**

The call account menu contains timers which will show you the total time for calls, this means both incoming and outgoing call and outgoing time only. The call timers can be reset at any time.

***To view the total time for all calls***

- Select *Calls/Call Account*.

***To view the total time for outgoing calls***

- Select *Calls/Call Account*.


***To reset the call timers***

1. Select *Calls/Call Account*.
2. Long press to activate the Fast menu on the call timer you wish to reset.
3. Press  to reset that counter.
4. Press  to confirm you wish to reset the counter.

DRAFT

# Contacts

The contacts application allows you to save phone numbers, e-mail addresses and other contact information and manage your contacts.



## Creating a new contact

When creating a new contact you must always give the contact a name or the name will automatically be *New Contact 1* or the next available number. When text has been entered into a new contact field the new contact will then be stored and the message *Contact created!* will be briefly displayed.

If nothing has been entered in the *Create Contact page* then pressing **C** or *Back*  will exit the page and will not create a new contact.

### *To create a new contact*

1. Select *Contacts*
2. Press *Create contact* 
3. Press *Name* to activate the keyboard.
4. Enter the contacts name and press *OK* 

The name will then be displayed also in the header row. The contact is now saved to the contacts list in the device memory. All other contact details can be either filled or left empty.

- To add a phone number to a contact
  - Press *Phone*
  - Press a number type field, e.g. *Mobile*: to enter the contacts telephone number and press *OK* 

The first number that you enter will automatically be the default number for that contact. The default indicator  will be shown besides that number. The default number will also be displayed in the main contact page in the *Phone* field.

- To add a e-mail address to a contact
  - Press *E-mail*
  - Press a number type field, e.g. *Work*: to enter the contacts telephone number and press *OK* 

The first e-mail address that you enter will automatically be the default e-mail address for that contact. The default indicator  will be shown

besides that E-mail address. The default e-mail address will also be displayed in the main contact page in the E-mail field.

- To add a picture to a contact
  - Press 
  - Either take a picture by pressing *Take picture*  or retrieve a picture already stored in your photo album by pressing *Photo album* , the short cut to the images stored in your memory.
  - If you use a picture stored in the memory, press the add check box
  - When the picture is selected press *OK* 
- To add notes for a contact
  - Press *Notes*: to activate the keyboard
  - Enter the desired text and press *OK* 

You can also copy and paste text to the contacts notes. See Fast Menus....

- To add a contact to a group
    - Press *Profile*
    - Select *Groups*:
    - Select *Add Group* 
    - Press the add check box  for the group you wish to add the contact to. The selected group will be displayed with the checked indication
    - Press *OK*  to add the selected contact to the group.
- For more information on creating a contact group see.....

- To assign a ring tone to a contact
  - Press *Profile*
  - Select the *Ring tone*: 
  - Select the ring tone stored in your memory and press *OK* 
- To set a speed dial number for a contact
  - Press *Profile*
  - Select *Speed dial key*:
  - Press the desired speed dial number for the contact

If the speed dial number is already in use for another contact then you will be asked if you wish to replace the speed dial for that number.

- Pressing *Yes*  will reassign the speed dial number and leave the previous contact without a speed dial number
- Pressing *No*  will leave the speed dial number unchanged

The assigned speed dial number can be seen from the *Speed dial key*: field  
For more information See Speed dialling page (call functions)....

### ***To cancel a speed dial number for a contact***

1. Repeat steps 1 & 2 for *To set a speed dial number for a contact*
2. Press *None*   
The assigned speed dial number will be removed from the *Speed dial key:* field  
For more information See Speed dialling page (Call functions)....

### **Editing a contact**

#### ***To edit text for a contact stored in the device memory***

1. Select the contact from the contacts list and open the contact page.
2. With a long press select the information you wish to edit to activate the Fast menu and select keyboard 
3. Edit the text and then press *OK*  to store the updated information.

#### ***To edit text for a contact stored on the SIM card***

1. Select the contact from the contacts list and open the contact page.
2. With a long press select the information you wish to edit to activate the Fast menu and select keyboard 
3. Edit the text and then press *OK*  to store the updated information.  
Your SIM card will only store a name and a single number to your SIM card. If you edited the information other than this then *Add to device?* will be displayed.

- Pressing *Yes*  will copy the SIM contact and store the contact to the device memory with the additional information.
- Pressing *No*  will remove the SIM contact and store the contact to the device memory with the additional information.
- Pressing *Cancel*  will cancel any editing and leave the SIM contact unchanged.

#### ***To delete text stored in the contacts details***

1. Select the contact from the contacts list and open the contact page.
2. With a long press select the information you wish to delete to activate the Fast menu and select *Delete* 
3. Confirm that you wish to delete the selected entry by pressing *Yes* 

#### ***To delete a contact***

1. With a long press select the contact from the contacts list you wish to delete to activate the Fast menu and select *Delete* 
2. Confirm that you wish to delete the selected entry by pressing *Yes* 

#### ***To change a default number or e-mail address for a contact***

In order to change the default you must have more than one number or e-mail entry for that contact stored in the device.

1. Select the contact from the contacts list and open the contact page.
2. Press either *Phone* or *E-mail* to view the contacts numbers or e-mail addresses.
3. With a long press select the number or e-mail you wish to change to the default to activate the Fast menu and select default 🟢

#### ***To view your communications with a contact***

1. Select the contact from the contacts list and open the contact page.
2. Press *Communications*:
  - The following categories of communications will be shown.
    - Last call: 📞
    - Last SMS: 📧
    - Last MMS: 📧
    - Last E-mail: 📧
    - Next Event: 📅
3. Selecting a communication that contains a short cut ➡ will take you to that specific item.

#### ***To send a contact***

1. Select the contact from the contacts list and open the contact page.
2. Press *Communications*:
3. Press *Send Contact*
4. Select one of the methods to send the contact details.
  - Send by infrared 🔴
  - Send by SMS 📧
  - Send vCard 📧
  - Send by MMS 📧
  - Send by E-mail 📧

Pressing *Send by infrared* will automatically activate the infrared and send the contact, providing another device with infrared is within the range.

5. Press *Recipient*:
6. Either enter the number or address of the recipient by pressing the *Recipient* field or press *Add from contacts* 👤, select a contact by pressing the add check box  and press *OK* Ⓞ
7. Press *Send*.

## Contacts List

The contact list is organised in alphabetical order by the given contact name.

A short cut to the contact list is available, excluding when the keypad is open by a long press on the @ key.

When the phone application is open and the phone display is empty a shortcut to the contact list is available by pressing 

### *To view your contacts*

1. Select *Contacts*
2. Press *Contact list*
3. Press the appropriate alphabetic grouping to view a specific contact.

### *To arrange your contacts in the contacts list*

It is possible to change the sort order for the contacts list. You can sort the contacts by the first name or second name.

1. Select *Contacts*
2. Press *Options*
3. Press *Arrange contact list by*
4. Select the desired setting.

The selected setting is the one with the filled button 

### **Fast Menus for a contact from the contacts list**

- Call to contact 
- SMS to contact 
- MMS to contact 
- E-mail to contact 
- Copy contact 
- Edit contact 
- View details for contact 
- Delete contact 
- Copy to SIM 
- Copy to device 

## Storing contacts

When you create a new contact with the device it will automatically be stored in the device memory. Contacts can also be copied to the SIM card.

Your SIM card will only store a name and a single number to your SIM card. Contacts stored on your SIM card will display the SIM indication  with the contact entry.

### ***To copy a single contact from the device memory to SIM card***

1. Select **Contacts**
2. With a long press select the contact from the contacts list you wish to copy to activate the Fast menu and select .
3. The contact will be copied to the SIM card and also be displayed in the contacts list with the stored on SIM  indication.

**NOTE:** Only the name and the default number will be saved to the SIM card.

### ***To copy a single contact from the SIM card to the device memory***

1. Select **Contacts**
2. With a long press select the contact from the contacts list you wish to copy to activate the Fast menu and select .
3. The contact will be copied to the device memory and also be displayed in the contacts list with the stored on device memory  indication.

### ***To delete all contacts from the SIM card***

1. Select **Contacts/Options**
2. Press **Edit contact list**
3. Press **Delete all from SIM** .
4. Confirm that you wish to delete all the contacts stored on your SIM card by pressing **Yes** .

*All contacts deleted from SIM* will be displayed.

### ***To delete all contacts from the device memory***

1. Select **Contacts/Options**
2. Press **Edit contact list**
3. Press **Delete all from device** .
4. Confirm that you wish to delete all the contacts stored in your device memory by pressing **Yes** .

*All contacts deleted from the device* will be displayed.

### ***To move all contacts from the SIM card to the device memory***

1. Select **Contacts/Options**
2. Press **Edit contact list**
3. Press **Move all from SIM to device** .
4. Confirm that you wish to move all the contacts stored on your SIM card to the device memory by pressing **Yes** .

*All contacts moved from SIM to device memory* will be displayed.

### ***To copy all contacts from the device memory to SIM card***

1. Select *Contacts/Options*
2. Press *Edit contact list*
3. Press *Copy all from device to SIM* 
4. Confirm that you wish to copy all the contacts from the device memory to your SIM card by pressing *Yes* 

*All contacts copied from device memory to SIM will be displayed.*

### ***To copy all contacts from the SIM card to the device memory***

1. Select *Contacts*
2. Press *Options*
3. Press *Copy all from SIM to Device* 
4. Confirm that you wish to copy all the contacts from your SIM card to the device memory by pressing *Yes* 

*All contacts copied from SIM to device memory will be displayed.*

## **Groups**

Groups can be created from the contacts that you have saved in your device. Groups consists of user made Contact groups. Group members can be collected from contacts at the chapter. Groups amount is not limited.

### ***To create a contacts group***

1. Select *Contacts*
  2. Press *Groups*
  3. Press *Create group* 
  4. Enter a name for the group and then press *OK* 
- The group name will now be displayed in the header.

### ***To add contacts to a group***

1. Select *Contacts/Groups*
2. Press the named group where you wish to add a contact.
3. Press *Add contact* 
4. From the contacts list, the contacts will be displayed with a contact add check box.
5. Press the add check box  for the contacts you wish to add.  
The selected group will be displayed with the checked indication
6. Press *OK*  to add the selected contacts to the group.

***To assign a ring tone to a contact group.***

1. Select *Contacts/Groups*
2. Press the named group where you wish to assign a ringing tone.
3. Select the *Ring tone:*  field.
4. Select the ring tone stored in your memory by pressing the add check box  and press *OK* 

***To create a sub group***

1. Select *Contacts/Groups*
2. With a long press select the group you wish to add a sub group to activate the Fast menu and select 
3. Then follow the same instructions as in *To create a contact group* and *To add contacts to a group*.

***To find a contact***

The find function in the contacts application searches the contacts list.  
See Find Mode from.....

***To view the amount of contacts stored on the SIM***

1. Select *Contacts/Options*
2. Press *SIM card contacts*
3. Select a contact to view the stored details on the SIM.


The card memory status can be seen from the *SIM card contacts* menu.

**Contacts Synchronization**

Contact Synchronization.... 

# Messages

You can send and receive messages with the device in a number of ways and formats. You can send message using the Short Message Service (SMS), by Multimedia Messaging Service (MMS) or though E-mail.



## SMS Messages

 SMS messages are messages that contain a text message.

In order to send or receive an SMS text message you need to ensure that the number for your SMS service centre is stored on the device. The service centre number is provided by your service provider and may be already stored on the SIM card.

**NOTE:**This service is network / service provider dependent. Please check you subscription features with your network / service provider.

### **Checking the number for your service centre**

- See SMSC number in SMS Settings, page...

### **To send an SMS message**

1. Select Messages/Create SMS 
2. Press the *Message* field to activate the keyboard.
3. Enter the message and press OK   
See Entering Characters and Numbers.....
4. Press *Recipient:* 
5. Either enter the number of the recipient by pressing the *Recipient* field or press *Add from contacts* , select a contact by pressing the add check box  and press OK 
6. Press *Send* 

When *Send*  is pressed:

-  - sending of the message in progress appears in status bar.
- Message Sent - after message has been successfully sent.
- Transmission Failed - if the message has failed to be sent to the desired recipient. The message will be moved to Outbox.

**NOTE:**If you wish to send the message later then exit without sending the message and the message will be saved to the SMS Drafts folder

### **To send an SMS message to multiple recipients**

1. After one recipient has been selected press *Recipient:*  displayed in the *Create SMS* page.
2. Press *Add from contacts* , select a contact by pressing the add check box  and press *OK*  and the contact will be added to the next *Recipient* field.
3. Proceed as in *To send an SMS message*, page...

### **To send an SMS message to a group**

1. Press *Recipient:*  displayed in the *Create SMS* page.
2. Select the group from the *Groups* folder of the contacts list.
3. Proceed as in *To send an SMS message*, page...

### **Receiving an SMS message**

When you receive an SMS message the text *New SMS Read Now?* will appear in the display along with an audible signal and  will appear in the header row.

The settings can be altered for informing messages, see *Settings/ Messages*.....

### **To read a received text message**

- Press *Yes* 
- If you press *No*  then the message will be stored to the *Messages / Received* folder and the message *1 new message* will be shown under the *Messages* chapter.

## **Received SMS options**

- Call 
- Reply 
- Forward 

## **Fast menu options for received SMS messages**

- Copy all 
- Delete all 
- Sort by 
- Find 

## **Saving SMS messages**

The device will store received SMS messages in the *Received* folder. Both received and sent SMS messages can be saved from the *Received* and *Sent* folders to the *Drafts and Saved* folder for permanent storage or until you delete them.

The number of messages shown can be changed from the *SMS Settings* in Settings, see page....

### **Saving an SMS message**

- With a long press select the message you wish to save to activate the Fast menu and select *Save* 

The message will now be saved to the *Drafts and Saved* folder

Read messages stored on the SIM card displayed with the  icon with the message

Read messages stored in the device are displayed with the  icon with the message

**NOTE:**Messages received with the device cannot be saved on the SIM card

## **Voicemail messages**

Your voicemail service allows callers to leave a voice message for you when you cannot be reached or the device is switched off. Your voicemail number will be supplied by the network / service provider with your subscription.

**NOTE:**This service is network/service provider dependent. Please check your subscription features with your network/service provider.

### **To set your voicemail number**

- See Voice mail number in Phone Settings, page...

### **To listen to the received voicemail message**

- With the voice mail SMS message open press *Call*  to call your voicemail number.

Also see *To call your voice mailbox*, page.(Call functions)

## **Delivery Reports**

You can set the device depending on if your network or service provider supports this function, to request delivery reports for the messages that you send. A delivery report is represented also with the  icon with the message. The delivery report will indicate the status either *Delivered* or *Failed*.

### **To switch status reports On or Off**

- See Delivery reports in SMS settings, page...

### **Receiving a delivery report**

When you receive a delivery report the text *Delivery report. Message delivered to (recipients number, or contact name) at (time). Delete Report?* will appear in the display along with an audible signal.

- Press *Yes*  to delete the report information

If you press **No**  then the delivery report will be stored to the *Messages/Received* folder.

## Configuration Messages

Configuration messages contain specific settings that can be saved to the device. For example, you may be able to request the settings to set an MMS account from your network or service provider so that you can send and receive MMS messages. A new configuration message is represented with the  icon with the message.

### **Receiving a configuration message**

When you receive a configuration message the text *Received Configuration message. Read now?* will appear in the display along with an audible signal.

- Press **Yes**  to view the message.

If you press **No**  then the configuration message will be stored to the *Messages/Received* folder.

### **To install a configuration message**

1. With a long press select the configuration message you wish to save to activate the Fast menu and select **Save** .
2. The configuration message will be saved to the *Drafts and Saved* folder and the message *Configuration message. Run now?*
3. Press **Yes**  to install.

## MMS Messages

 MMS messages are messages that can contain text, ring tones, animations, graphics, photo images and audio clips.

If the MMS message is larger than 30kB then it will exceed the maximum interoperability guarantee, but may still be possible to send to a recipient depending upon the device used to receive the message.

In order to send or receive an MMS messages you need to ensure that you have a data connection set in the device and that the service is available from your network/service provider. See *Settings/Messages...*

### **To send an MMS message**

1. Select *Messages/Create MMS* .
2. Press **Message** to activate the keyboard.
3. Enter the message and press **OK** .

See Entering Characters and Numbers.....

4. Press *Recipient*: 
5. Either enter the number of the recipient by pressing the *Recipient* field or press *Add from contacts* , select a contact by pressing the add check box  and press *OK* 
6. Press *Subject* to enter a subject header for the message.
7. Press *Send* 

When you are creating a new MMS message you can add an image to the message.

#### ***Including an image in the MMS message***

1. Press 
2. Either take a picture by pressing *Take picture*  or retrieve a picture already stored in your photo album by pressing *Photo album* , the short cut to the images stored in your memory.
  - If you use a picture stored in the memory, press the add check box
3. When the picture is selected press *OK* 

When you are creating a new MMS message you can add audio to the message.

#### ***Including audio in the MMS message***

1. Press 
2. Either record a new clip or retrieve a clip already stored in the memory from the *Music and Sound* folder.
  - If you use a clip stored in the memory, press the add check box
3. When the clip is selected press *OK* 

#### ***Receiving an MMS message***

When you receive an MMS message the text *New MMS, Read Now?* will appear in the display along with an audible signal.

**NOTE:**If the automatic downloading is not activated for MMS messages (see Settings) then *New MMS, Download Now?* is displayed instead.

#### ***To read the received MMS message***

- Press *Yes* 
- If you press *No*  then the message will stored to the *Messages/Received* folder and the message *1 new* will be shown under the *Received* menu in the Messages chapter.

**NOTE:**This service is network / service provider dependent. Please check you subscription features with your network / service provider.

If you receive more than one new SMS and/or MMS message then the text *Received 2 new messages. Go to Received?*

- Press **Yes**  to go to the received messages folder  
If you press **No**  then the messages will be stored to the *Messages/Received* folder which you can access at a later time.

## E-mail Messages

 E-mail messages can be sent and received through the device

In order to send or receive E-mail messages you need to ensure that you have a data connection set in the device. When you have a data connection ongoing, the  network connection icon will be displayed in the status menu.

See E-mail settings, page...

### *To send an E-mail message*

1. Select *Messages/Create E-mail* 
2. Press *Message* field to activate the keyboard.
3. Enter the message and press **OK**   
See Entering Characters and Numbers.....
4. Press *Subject* to enter a subject header for the message.
5. Press *Recipient* 
6. Either enter the number of the recipient by pressing the *Recipient* field or press *Add from contacts* , select a contact by pressing the add check box  and press **OK** 
7. Press *Send* 

When *Send*  is pressed:

You will be asked if you want to *Connect to Network, Send e-mail now?*

- Pressing **Yes**  will open a data connection and send the e-mail message.
  - **Sending e-mail** - sending of the e-mail message in progress appears in the header row.
  - **E-mail sent** - will be briefly displayed after the message has been successfully sent and the message will be moved from the Outbox to the Sent folder.
  - **Transmission failed** - will be briefly displayed if unable to send and the e-mail and it will be moved to the Outbox folder.
- Pressing **No**  will move the e-mail to the *Outbox* so that it can be sent at a later time.
- Pressing *Cancel*  will return back to the e-mail state before *Send* was pressed.

**NOTE:**Automatic check mail can be set to a specified period from Settings/E-mail settings.

### **To send messages from the Outbox**

1. Select *Messages/Outbox and Sent/Outbox*
2. Press *Send* 

You will be asked if you want to *Connect to Network, Send all messages now?*

- Pressing Yes  will send all messages from the Outbox

### **Including an attachment in the E-mail message**

1. Press *Attachments:* 
2. Press *Add Attachment* 

You may attach more than one file, to add another attachment to the E-mail, follow the same process as above. The number of attachments will be displayed in the brackets.

### **To add a Cc (Carbon Copy) recipient to an E-mail message**

1. Press *Cc:* 
2. Either enter the number of the recipient by pressing the *Recipient* field or press *Add from contacts* , select a contact by pressing the add check box  and press *OK* 

### **To add a Bcc (Blind Carbon Copy) recipient to an E-mail message**

1. Press *Bcc:* 
2. Either enter the number of the recipient by pressing the *Recipient* field or press *Add from contacts* , select a contact by pressing the add check box  and press *OK* 

### **To check your received E-mails**

1. Select *Messages/Received/E-mail*.
2. Press *Check mail* . Connecting to the network will be established.
3. The device will now check your specified e-mail box. (see. Setting e-mail account)

The e-mails will be downloaded to the *Received/E-mail* folder.

During this process you can cancel the downloading by pressing *Stop*  and press *Yes*  to confirm.

### **To reply to a received E-mail**

1. After opening the received e-mail message, press *Reply* 
2. The new message will be sent to the sender of the original mail, to change the recipients that receive your reply press *Recipient* 
3. Add or remove the recipients you wish to reply to (see...Adding, Removing)
4. After creating your e-mail, press *Send* 

### ***To reply to all contacts from a received E-mail***

1. After opening the received e-mail message, press *Reply to all* 
2. The new message will be sent to all the recipients that were in the original mail, to change the recipients that receive your reply press *Recipient* 
3. Add or remove the recipients you wish to reply to (see...Adding, Removing)
4. After creating your e-mail, press *Send* 

### ***To forward a received E-mail***

1. After opening the received e-mail message, press *Forward* 
2. Press *Recipient* 
3. Either enter the number of the recipient by pressing the *Recipient* field or press *Add from contacts* , select a contact by pressing the add check box  and press *OK* 
4. After creating your e-mail, press *Send* 


**NOTE:** This service is network / service provider dependent. Please check you subscription features with your network / service provider.

DRAFT

# Internet

The device allows you to surf the internet through the web browser. In order to browse the web you need to ensure that the data connection settings are correct. See Settings/Connection settings...

Navigation of the web pages is done by using the mirroring and zooming functions See.....



When you open the internet browser to start a web session and there is no data connection already open, you will be asked if you want to *Connect to Network?* Pressing *Yes*  will open a data connection and take you to the desired page, pressing *No*  will return you to the previous menu page.

When you have a data connection ongoing, the  network connection icon will be displayed in the status menu. When the browser is open and a data connection ongoing, the  network connection icon will be displayed at the bottom of the display next to the loading bar.

When exiting the browser you will be asked if you want to *Close network connection?* The following options are available.

- Pressing *Yes*  will exit the browser and close the data connection.
- Pressing *No*  will exit the browser but keep the data connection open.
- Pressing *Cancel*  will not close the browser and not close the data connection.

## Using the Internet browser

*To open the internet browser*

1. Select *Internet/Open browser* 
2. Press the address field to enter a web address
3. Enter a web URL using the keyboard. The address can be typed starting with *http:* but can also be entered just by starting with *www*. Picture needed
4. Press *OK*  to go to that page.


The web page will start loading and the status of the loading can be seen at the bottom of the screen.

If you do not want to enter the address press *Close*  to return to the browser page and *Book*  to return to the *Internet* index.

## Browser keys

- Pressing *Book*  goes back to the Internet index and will request whether to close the connection.
- Pressing *Back*  will return to the previously opened page. If the page is the first opened in the browser then the view goes back to the Internet index and will request whether to close the connection.
- Pressing *Forward*  will forward to the next previously opened page. If the page is the first opened in the browser then forward is disabled.
- Pressing *Stop*  will stop loading the new web page.
- Pressing *Refresh*  will reload the current page in the browser.
- Pressing *Home*  will go to the current homepage. See *Homepage...*
- Pressing *Find*  will open the keyboard in order to enter a word or phrase to search the current web page in the browser.
- Pressing *Favourites*  will open the favourites list. See *Favourites..*
- Pressing *Add*  will add the web page to the favourites list. See *Favourites..*
- Pressing *History*  will open the history list. See *History..*
- Pressing *Save*  will add the web page to the downloaded pages list. See *Downloaded pages..*
- Pressing *Fit to*  will resize the browser width and wraps the page content.
- Pressing *Options*  will open the internet options menu. See *Options..*

## Browser views

The Loading bar  indicates the loading progress of the webpage that has been opened in the browser. When the loading is completed the loading bar will disappear from view.

## Browser windows and frame changing

Some of the web pages require opening many views (windows) to pages. Enabling new windows to open can be switched on or off, See *Options...* The browser in the device supports 3 windows to be open at any time.

### *To switch between opened windows in the browser*

- When the browser is open press View2 

### *To close an open window in the browser*

- When the browser is open press Close 

## Homepage

The homepage field allows you to set one web page as a page that you can always load quickly, a web site that you frequently use, for example a company website or a search engine web site.

### ***To set the homepage***

1. Select *Internet*
2. Press *Homepage*:
3. Enter the web address and press *OK*  to store the homepage.

The homepage URL or name can now be seen in the *Homepage*: field.

**NOTE:** It may be that the homepage is already set to your network/service providers website.

### ***To change the homepage***

1. Select *Internet*
2. With a long press select the *Homepage*: field to activate the Fast menu and select *Edit* 
3. Enter the web address and press *OK*  to store the homepage.

### ***To go to the homepage***

1. Select *Internet*
2. Press *Homepage*:
  - If the browser is open then press *Home* 

## History

The history menu stores links to the previously visited websites in chronological order. The history list will store up to 30 website links, when this limit is reached the device will discard the oldest history link and be replaced with the most recent visited web site. The number of history items is shown under the *History* menu.

### ***To go to a linked website stored in the history list***

1. Select *Internet*
2. Press *History*
3. Press the linked history item to open the page in the browser.
  - If the browser is open then press *History*  to view the history list.

### ***To delete the linked web sites stored in the history list***

1. Select *Internet*
2. With a long press select the *History* menu to activate the Fast menu and select *Delete All* 
3. Press *Yes*  to confirm clearing the visited web page history.

**NOTE:**It is not possible to edit or delete individual history items in the history list.

## Favourites

The favourites menu allows you to store webpage links to your favourite, commonly used web pages. It is possible to create sub groups for your favourites so that you can easily go to those webpage links.

### *To add a webpage to your favourites*

1. Select *Internet*
2. Press *Favourites*
3. Press *Add Favourite:* field.
4. Enter the web address and press *OK* 
5. Enter the web address name and press *OK* 
- If the browser is open and the webpage is loaded then you can add the webpage to your Favourites by pressing *Add* 

### *To go to a linked website stored in the favourites*

1. Select *Internet*
2. Press *Favourites*
3. Press the linked favourite to open the page in the browser.
- If the browser is open then press *Favourites*  to view your favourites and press the linked favourite to load the webpage.

### *To delete a website link stored in the favourites*

1. Select *Internet*
2. Press *Favourites*
3. With a long press select the webpage link to activate the Fast menu and select *Delete* 
4. Press *Yes*  to confirm deleting the webpage from your favourites.

### *To delete all website links stored in the favourites*

1. Select *Internet*
2. With a long press select the *Favourites* menu to activate the Fast menu and select *Delete All* 
3. Press *Yes*  to confirm deleting all favourites.

### *To create a sub group folder for website links stored in the favourites*

1. Select *Internet*
2. With a long press select the *Favourites* menu to activate the Fast menu and select *Add group* 
3. Enter a name for the new favourites group folder and press *OK* 

## Sorting the favourites

It is possible to sort the favourites group and sub groups by name, by size and by date so to ease managing the large amount of web pages that can be sorted in Favourites.

### *To sort a favourites group by name*

1. Select *Internet*
2. With a long press select the *Favourites* menu to activate the Fast menu and select *Sort by Name* 

To sort a sub group, follow step 2 and long press the appropriate group folder.

## Downloaded Pages

The downloaded pages menu allows you to view previously visited web pages so that the pages can then be viewed off-line. When downloaded web pages are opened they will be opened in the browser but no network connection will be established.

Downloaded web pages are saved in the *Files* index and are linked to the *Downloaded pages* menu for easy access when in the Internet index.

### *To download a webpage to save off-line*

- When the webpage you wish to download is open in the browser, press *Save will*  save the page off-line.

### *To open an off-line webpage in downloaded pages*

1. Select *Internet*
2. Press *Downloaded pages*
3. Press the desired off-line webpage to open the page in the browser.

### *To delete an off-line webpage in downloaded pages*

1. Select *Internet*
2. Press *Downloaded pages*
3. With a long press select the off-line webpage to activate the Fast menu and select *Delete* 
4. Press *Yes*  to confirm deleting the webpage from downloaded pages.

## Options

### *To set show images in the browser*

1. Select *Internet/Options*
2. Press *Show images*.

The *Show images* option will be displayed with the checked indication  when switched On.

### ***To set play audio in the browser***

1. Select *Internet/Options*
2. Press *Play audio*.

The *Play audio* option will be displayed with the checked indication  when switched On.

### ***To set request to launch a new window in the browser***

1. Select *Internet/Options*
2. Press *Ask before opening windows*.

The *Ask before opening windows* option will be displayed with the checked indication  when switched On.

### **Cookies**

#### ***To set enable cookies when browsing***

1. Select *Internet/Options/Advanced*
2. Press *Enable cookies*.

The *Ask before opening windows* option will be displayed with the checked indication  when switched On.

#### ***To delete cookies stored from whilst browsing***

1. Select *Internet/Options/Advanced*
2. Press *Delete cookies*.

### **Cache Content**

#### ***To set enable caching when browsing***

1. Select *Internet/Options/Advanced*
2. Press *Enable cache*.

The *Ask before opening windows* option will be displayed with the checked indication  when switched On.

#### ***To empty cache stored from whilst browsing***

1. Select *Internet/Options/Advanced*
2. Press *Empty cache*.

### **Page Draw**

#### ***To set enable page draw when browsing***

1. Select *Internet/Options/Advanced*
2. Press *Enable page draw*.

The *Ask before opening windows* option will be displayed with the checked indication  when switched On.

## Image Draw

*To set enable image draw when browsing*

1. Select *Internet/Options/Advanced*
2. Press *Enable image draw*.

The *Ask before opening windows* option will be displayed with the checked indication  when switched On.


## Downloading objects

DRAFT

DRAFT

# Calendar

The calendar function in **mydevice** allows you to keep track of your appointments and events, tasks that you need. You can also set the various alarms and time functions to remind you.



## Viewing your Calendar

You can view the calendar in a number of ways, by a monthly, weekly or daily view.

### *To view your calendar contents*

1. Select *Calendar*.
2. Select the desired view.

### *To find a day in the calendar*

1. With a long press select the Calendar index page to activate the Fast menu and select *Find* 
2. Enter a date and press *OK*  to open that daily view.

### Daily View

#### *To view the current day from your calendar*

1. Select *Calendar*
2. Press *Today View*.

Any events and tasks for that day will be shown in this section.

### Weekly View

#### *To view the current week from your calendar*

1. Select *Calendar*
2. Press *Weekly View*

Any events and tasks for that week will be shown under the days in this section.

### Monthly View

Days with events have bold numbers and the current selected day is coloured.

#### *To view the month from your calendar*

1. Select *Calendar*
2. Press *Monthly view*
  - To navigate in the monthly view:

- Press  to move to the previous day.
- Press  to move to the next day.
- Press  to move to the same day, previous week.
- Press  to move to the next week.

### *To navigate the months from your calendar*

1. Select *Calendar*
2. Press *Monthly view*
3. Press *Previous:* or *Next:*

## Creating a new event in the calendar

### *To create a new event*

1. Select *Calendar*
2. Press *Create Event* 
3. Enter a subject text for the new event and press *OK* 
4. Enter the information you wish to store for the event.
  - To specify a place:
    - Press the *Place:* field
    - Enter a location for the event and press *OK* 
  - To enter a starting time:
    - Press the *Start Time:* field
    - Enter the date and time for when the event starts and press *OK* 
  - To specify an ending time:
    - Press the *End Time:* field
    - Select a time duration or press *Other* to specify another time. The selected setting is the one with the filled button  .
  - To set a reminder:
    - Press *Reminder.*
    - Select a time duration or press *Other* to specify another time. The selected setting is the one with the filled button  .

### Event reminder message

The event reminder alarm can be set from the *Settings/Sounds and alerts/Alarm tone*, see...

When a reminder is set and the event reminder time is reached then a message will appear stating the event details and asking *Show event details in full?*

- Pressing *Yes*  will open the event in the calendar.
- Pressing *No*  will close the message and stop the alarm.

## Event conflict message

When entering a new calendar event and setting the start and/or the end time for the event, the device checks if this new event conflicts with any events already stored in the calendar. If there is a conflict of events then a message will appear stating the stored event details that the new calendar event conflicts with and *Another event coincides with this one. Continue anyway?*

- Pressing **Yes**  will accept the conflict and the new event will overlap the stored event in the calendar.
- Pressing **No**  will return to the event start and/or the end time to re-enter a different time.

## Advanced

*To add participants from the contacts list to the event*

1. Select *Advanced*
2. Press *Participants* 
3. Press *Add from Contacts* , select a contact by pressing the add check box  and press *OK*  and the contact will be added to the next *Recipient* field.

**NOTE:**Participants need to be stored in the device memory to be recalled as participants for an event. Contacts from the SIM card cannot be added. See *Storing Contacts* page....

*To send a reminder to the participants*

1. Select *Advanced*
2. Press *Remind participants*
3. Select a method to inform the participants

The selected setting is the one with the filled button .

- **Participant reminder by E-mail** - If the participant has an e-mail address stored in the contact details. If there is more than one e-mail address stored for the contact then the default e-mail will automatically be used.
- **Participant reminder by SMS** - If the participant has a mobile phone number stored in the contact details. If there is more than one mobile phone number stored for the contact then the default mobile phone number will automatically be used.
- **Participant reminder by E-mail or SMS** - Will send a reminder either way depending on what details are stored for a contact. E-mail is the primary method used.
- **Participant reminder by E-mail and SMS** - Will send a reminder both ways depending on what details are stored for a contact.

### ***To set a type for an event***

1. Select *Advanced*
2. Press *Event type*
3. Select a type for the event.

The selected setting is the one with the filled button .

### ***To set a recurrence for an event***

1. Select *Advanced*
2. Press *Recurrence*
3. Select a time frame for the recurrence.

The selected setting is the one with the filled button .

4. Either:

- Press *Occurrence(s)*: to specify the amount of events you want the recurrence to last.
- Press *End After*: to specify the time when you want the recurrence to end.

### **Templates**

A template will be made based on the current event being entered. You can store up to 11 event templates.

#### ***To create an event template***

1. Select *Advanced/Templates*
2. Press *Create Template* 
3. Enter a name for the template and press *OK*  to store the new template in the *Templates* folder.

#### ***To use a template to create an event***

1. Select *Calendar*
2. Press *Create Event* 
3. Select *Advanced*
4. Press the event template  you wish to use.

The new event will now contain the same values as the template chosen.

#### ***To set an event to private***

1. Select *Advanced*
2. Press *Private* to switch on.

The setting is on when the box is filled

## Managing calendar events

### *To delete an event from the calendar*

1. With a long press select the event you wish to delete to activate the Fast menu and select *Delete* 
2. Confirm that you wish to delete the selected event by pressing *Yes* 

### *To delete all events from a period of the calendar*

1. With a long press select *Today view/Weekly view/Monthly view* for the period you wish to delete to activate the Fast menu and select *Delete* 
2. Confirm that you wish to delete the selected event by pressing *Yes* 

### *To copy all events from a period of the calendar*

- With a long press select *Today view/Weekly view* for the period you wish to copy the events to activate the Fast menu and select *Copy* 
- The events from that period will be copied to the clipboard so that they can then be pasted elsewhere.

### *To paste all events to a period of the calendar from the clipboard*

- With a long press select *Today view/Weekly view* for the period you wish to paste the events to activate the Fast menu and select *Paste* 
- The pasted events from the clipboard will be copied to the selected period, the values will stay the same except for the date which will change to the dates that the events were pasted to.

## Sorting Events

Events can be sorted by: name, start time, event type.

### *To sort the days events in the calendar*

1. With a long press select *Today view* to activate the Fast menu.
2. Press  to sort the events.

## Creating a new task in the calendar

Ongoing tasks are indicated in the calendar with the  icon.

Finished tasks are indicated in the calendar with the  icon.

### *To create a new task*

1. Select *Calendar/Tasks*
  2. Press *Create Task* 
  3. Enter a subject text for the new task and press *OK* 
  4. Enter the information you wish to store for the event.
- To specify a deadline for the task:
    - Press *Deadline*:
    - Enter a date for the task deadline and press *OK* 

- To add notes to the task:
  - Press *Notes*.
  - Enter additional text for the task and press *OK* 
- To set a reminder for the task:
  - Press *Reminder* to switch on.
  - Enter a date for the task reminder and press *OK* 

The setting is on when the box is filled
- To set a responsibility for the task:
  - Press *Responsible* 
  - Press *Add from Contacts* , select a contact by pressing the add check box  and press *OK*  and the contact will be added to the next *Responsible* field.
- To specify the status of the task:
  - Press *Status*
  - Select a status for the task.

The selected setting is the one with the filled button .
- To specify the priority of the task:
  - Press *Priority*
  - Select a status for the task.

The selected setting is the one with the filled button .

### Task reminder message

When a reminder is set and the task reminder time is reached then a message will appear stating the task details and asking *Show task details in full?*

- Pressing *Yes*  will open the task in the calendar.
- Pressing *No*  will close the message and stop the alarm.

#### **To delete a task from the Calendar**

1. With a long press select the task you wish to delete to activate the Fast menu and select delete 
2. Confirm that you wish to delete the selected event by pressing *Yes* 

#### **To send a task in the calendar to a contact**

1. Select *Calendar/ Tasks*
2. With a long press select the task you wish to send to activate the Fast menu and select *Send* 
3. Proceed as in Sending an SMS...see

### Sorting Tasks

Tasks can be sorted by: subject, deadline, priority, responsible, status.

### **To sort the tasks in the Calendar**

1. Select *Calendar*
2. With a long press select *Tasks* to activate the Fast menu.
3. Press  to sort the tasks.

### **Alarms**

If the alarm has been set it can be seen from the header row as . The alarm tone can be set from *Sounds and alerts* in the *Settings* index, see...

#### **To switch the alarm On or Off**

1. Select *Calendar/Alarm*
2. Press *Alarm On* to set the desired setting.  
The setting is on when the box is filled

#### **To set the alarm time**

1. Select *Calendar/Alarm*
2. Press *Set Alarm*:
3. Enter the time for the alarm and press *OK* .  
The alarm will automatically be set On when you enter a new alarm time.

#### **To set the alarm snooze time**

1. Select *Calendar/Alarm*
2. Press *Snooze interval*
3. Select a time period.  
The selected setting is the one with the filled button .

#### **To set an alarm recurrence**

1. Select *Calendar/Alarm*
2. Press *Recurrent alarm*
3. Select the days for the recurrent alarm.  
The setting is on when the box is filled

### **Alarm clock message**

When the alarm clock is set and the alarm time is reached then a message will appear stating the alarm time with an alarm tone playing. If no action is made then the alarm will play for 1 minute then stop. Pressing anywhere on the screen will bring up the message *Turn off the alarm?*

- Pressing *Yes*  will turn the alarm off.
- Pressing *No*  will activate the snooze time interval if set and then play the alarm tone after the specified snooze time has elapsed.

### **Calendar Synchronisation**

The calendar can be synchronised when connected to another device.


### *To synchronise the calendar*

- With a long press select Calendar index page to activate the Fast menu and select *Synchronise*   
The message *Synchronisation Complete* will appear when the synchronisation is complete. It is then safe to disconnect the devices.

DRAFT

# Camera

Your device has a built in camera, the camera lens is located on the reverse side of the display, see Overview..... You can take pictures to view in the display, store the picture in the devices memory and on a Secure Digital (SD card) or Multimedia card (MMC) and you can send them to others either through Multimedia messaging or by e-mail.



## Using the Device Camera

Before taking a picture using the devices integral camera, ensure that the camera lens is free from any marks or dust, so to ensure that the picture quality remains high. If the camera lens is dirty then gently wipe the lens with a soft cloth.

### *To take a picture using the device camera*

1. Select *Camera*.
2. When opened the real-time view is shown in the display.
3. Press *Take picture*  to capture the image that is displayed on the screen.

The still image will now be shown in the display with the question *Save image?*

4. Select *Yes*  to store in the Image gallery or *No*  to discard the picture.

## Image Gallery

Depending on the amount of memory you have available in the device you can store your pictures in the image gallery. The image gallery is a folder which contains links from the Camera index to the images that are stored in the *Files* index

There are some pre-installed pictures in your device which you can edit and delete.

### *To view the images in the image gallery*

1. Select *Camera*.
2. Press *Image gallery*

### ***To delete images in the Image gallery***

1. Select *Camera*.
2. Press *Image gallery*
3. With a long press select the image you wish to delete from the Image gallery to activate the Fast menu and select *Delete*

## **Options**

This menu contains options that allow you to adjust the camera settings.

### **Saving Images**

It is possible to save the pictures taken by the device camera either in the device memory or on a MMC or SD memory card, if one is inserted into the device.

#### ***To save images to the memory card***

1. Select *Camera/Options*.
2. Press *Save to memory card*

The *Save to memory card* option will be displayed with the checked indication  when switched On.

When the *Save to memory card* option is Off then the picture will be stored to the device memory in the Image gallery.

**NOTE:**When there is no memory card inserted in the device or the memory card is busy the image will be saved to the device memory in the Image gallery even if the *Save to memory card* option is On.

### **Image Size**

The device has three settings for the image size of the pictures you can take from the device.

- Large
- Medium
- Small

#### ***To change the image size setting***

1. Select *Camera/Options*
2. Press *Image size*.
3. Press the required setting to select.

The selected setting is the one with the filled button .

**NOTE:**When you select the image size setting the pictures taken after that selection will be with that image size until you change the setting.

## Image Name

You can set a name for the pictures that you take with the device which will help you to categorize the pictures that you store. If you leave the default name empty when you store a picture, the picture will be stored as 001.bmp/png (file extension name), or the next free number available.

### *To set the image default name*

1. Select *Camera/Options*.
2. Press *Image name*
3. Enter the name and press *OK*  to accept.

## Timer

This will allow you to add a time interval before the picture is taken.

### *To activate the timer mode*

1. Select *Camera/Options*.
2. Press *Timer*
3. Press the required time setting.

The selected setting is the one with the filled button .

**NOTE:**The timer delay setting will be turned off after taking each timer picture or if the camera function is exited.

### *Taking a picture with the Timer activated*

1. With the desired timer delay pre-selected press *Take picture*.
2. A countdown is shown, this is the delayed time before the picture will be taken.
3. After the timer picture has been taken, proceed in the same way as taking a normal picture.

**TIP:**Pressing *Cancel timer*  during the countdown will abort the timer shot.

## Night Shot

This function will optimize the camera for taking pictures in poorly lit environments.

### *To switch the Night shot On or Off*

1. Select *Camera/Options*.
2. Press *Night shot*

The *Night shot* option will be displayed with the checked indication  when switched On.

## Image Format

This function allows you to save the pictures into different file formats. Images can be saved from the camera to the following formats.

- .BMP - Bit-mapped image.
- .PNG - Portable network graphic.
- .JPG - Joint Photographics Expert Group (JPEG)

### ***To change the image format***


1. Select *Camera/Options*.
2. Press *Image format*
3. Press the required setting to select.

The selected setting is the one with the filled button .

DRAFT

# Files

The *Files* chapter in **mydevice** is where all the user files for the various device applications are stored. The files stored in this chapter are linked to various application indexes for ease of use. If the files are deleted from this folder then the linked file in an application index will be deleted and vice-versa.



## Notes

Notes stored in the Files chapter are linked to the Programs chapter where the Notepad application can be accessed. See Programs...

### *To sort the notes in Notes*

1. Select *Files*
2. With a long press select the Notes folder to activate the Fast menu and select *Sort by Subject/Sort by Date* 

### *To view the details of a note*

1. Select *Files/Notes*
2. With a long press select the note to activate the Fast menu and select *Show details* 

## My Documents

Any user files can be stored in My Documents.

## Files

### Downloaded pages

Files from the Internet are saved to the *Downloaded pages* folder. The Downloaded pages stored in *Files* can be viewed from the Internet chapter as the Internet chapter contains the linked folder. See Internet...

### Attachments

Files from mail messages are saved to the *Attachments* folder.

### Image Gallery

Files from the Camera are saved to the *Image Gallery* folder. The Images stored in *Files* can be viewed from the Camera chapter as the Camera chapter contains the linked folder. See Camera...

## Music

Music files are saved to the *Music* folder. The music files stored in *Files* can be viewed from the MP3 player chapter as the MP3 player chapter contains the linked folder. See MP3 player...

## Programs

Installed program application files are saved to the *Programs* folder. The program files stored in *Files* can be viewed and launched from the Programs chapter as the Programs chapter contains the linked folder. See Programs chapter...

## Memory Card

### Memory Card

You can view the content of the memory card. The amount of data stored on the memory card will be displayed under the *Memory card* index in KB (kilobytes). The maximum storage space available is dependent upon the memory card installed. The data storage capability will be displayed on the memory card.

**mydevice** uses SD card /MMC card, formatted....

*To view the contents stored on the memory card*

1. Select *Files*
2. Press *Memory card*

If there is no memory card installed then *Not found* will be displayed.

## Zip Files

### Archiving Files

To reduce the amount of memory used in the device, it is possible and recommended to archive the files that are not in frequent use.

Zipping the files will compress the file size for storage.

*To create an archive*

1. Select *Files/Zip files*
2. Press *Create Archive*
3. Enter a name for the zip archive and press **OK** 

The files from the Add files to archive folder will be stored to the named zip file and moved to the Zip archives folder.

### ***To add files to archive***

1. Select *Files/Zip files*
2. Press *Add files* 
3. Press the add check box  for the files you wish to archive.  
A selected file will be displayed with the checked indication .

### ***To unzip files from the Zip archive***


1. Select *Files/Zip files*
2. Press the desired zip file and the message *Extract?* appears.
3. Press *Yes*  to extract the files to the archiving folder.

DRAFT

DRAFT

# Settings

The Settings chapter in **mydevice** allows you to adjust or change the devices many settings so that you can tailor the device to your individual preferences.



## Sounds and Alerts

### Ring Tone

*To set the tone volume*

1. Select *Settings/Sounds and alerts*.
2. Use your finger to slide the button to adjust the *Volume*: level



The volume is represented as a percentage. When it set to zero percent then the volume is turned off.

*To select a different ring tone*

1. Select *Settings/Sounds and alerts*.
2. Press *Ring tone*  field
3. Press the sound clip you wish to use for the ring tone.

### Message Tone

*To select a different message tone*

1. Select *Settings/Sounds and alerts*.
2. Press *Message tone*  field
3. Press the sound clip you wish to use for the message tone.

### Alarm Tone

*To select a different alarm tone*

1. Select *Settings/Sounds and alerts*.
2. Press *Alarm tone*  field
3. Press the sound clip you wish to use for the alarm tone.

### Increasing Volume

You can set the tone volume to progressively increase from the lowest volume setting through to the highest volume setting.

### ***To switch increasing volume on***

1. Select *Settings/Sounds and alerts*.
2. Press *Increasing volume* to switch On.

The *Increasing volume* option will be displayed with the checked indication  when switched On.

### **Key Sounds**

#### ***To change the key sound***

1. Select *Settings/Sounds and alerts*.
2. Press *Key sounds* and then select the desired setting.

The selected setting is the one with the filled button .

## **Themes**

You can change the appearance of the device pages by selecting different themes. The own theme can be personalised to your own preferences. New user themes can also be downloaded.....See....

#### ***To change the theme***

1. Select *Settings/Themes*
2. Press the desired theme setting.

The selected setting is the one with the filled button .

#### ***To edit the own theme***

1. Select *Settings/Themes*
2. Press *Edit own theme*

## **Phone**

#### ***To change the phone background colour***

1. Select *Settings/Themes/Edit own theme/Phone*.
2. Press *Background colour*.
3. Either press a colour from the colour palette or define a custom colour by moving the RGB colour sliders and press *Set Custom Colour*.

#### ***To change the phone background image***

1. Select *Settings/Themes/Edit own theme/Phone*.
2. Press *Background image* .
3. Press the image you wish to use for the phone background image.

## **Pages**

#### ***To switch page background image on***

1. Select *Settings/Themes/Edit own theme/Pages*.
2. Press *Show background image* to switch On.

The *Show background image* option will be displayed with the checked indication  when switched On.

#### **To change the page background image**

1. Select *Settings/Themes/Edit own theme/Pages*.
2. Press *Background image* .
3. Press the image you wish to use for the page background image.

#### **To switch page background colour on**

1. Select *Settings/Themes/Edit own theme/Pages*.
2. Press *Use background colour* to switch On.

The *Use background colour* option will be displayed with the checked indication  when switched On.

#### **To switch page watermark image on**

1. Select *Settings/Themes/Edit own theme/Pages*.
2. Press *Show watermark* to switch On.

The *Show watermark* option will be displayed with the checked indication  when switched On.

### Font

#### **To change the font size**

1. Select *Settings/Themes/Edit own theme/Font Size*.
2. Select the desired setting.

The selected setting is the one with the filled button .

### Startup Screen

#### **To change the start-up image or animation**

1. Select *Settings/Themes/Edit own theme*.
2. Press *Start-up Screen* .
3. Press the image you wish to use for the start-up screen image.

### Startup Sound

#### **To change the start-up sound**

1. Select *Settings/Themes/Edit own theme*.
2. Press *Start-up Sound* .
3. Press the sound clip you wish to use for the start-up sound.

## Profiles

The device contains a selection of preset profiles which are grouped settings which can be used to suit the environment that you are using the device in. Changing profiles allows you to change or adjust a group of settings quickly.

For example a meeting profile could contain settings that switch off all the audible sounds and divert calls straight to your voicemail. When you leave the meeting you can switch back to a profile that turns on all audible sounds and will accept all calls etc.

**NOTE:**It is not possible to change the profile settings or rename the profile for the Flight and Mute profiles.

#### ***To select a profile***

1. Select *Settings/Profiles*.
2. Press the desired profile.

The selected setting is the one with default symbol 

#### ***To create a new profile***

1. Select *Settings/Profiles*.
2. Press Create Profile.
3. Enter a name for the profile and press **OK**  to store the profile.

The created profile will contain the same settings as the presently selected profile.

#### ***To change a profiles settings***

1. Select *Settings/Profiles*.
2. Press

## **Control Settings**

### **Phone**

#### **Voicemail**

The voicemail service may be available through your network operator / service provider. It enables you to receive messages left by callers when you cannot answer a call. The voicemail number is supplied with your subscription.

Depending on your subscription your voicemail number may be installed on the SIM card already.

#### ***To save your voicemail number in the device***

1. Select *Settings/Control settings/Phone*
2. Press the *Voice Mail Number:* field
3. Enter the number for your voicemail and press **OK** 

Use the fast menu for this field to edit a number already stored in the device.

## Call diversion

Your device allows you to divert incoming calls to another number under preset conditions. This function is network dependant.

The following divert options are available:

- **All calls** - will divert all voice, data and fax calls.
- **If no reply** - will divert the call after a specified time has elapsed.
- **If out of reach** - will divert the call after a specified time has elapsed.
- **If busy** -
- **Fax calls** - will divert fax calls.
- **Data calls** - will divert data calls.

### *To switch a divert option on*

1. Select *Settings/Control settings/Phone*
2. Press *Call diversion*.
3. Press the desired option to switch On.

The option will be displayed with the checked indication  when switched On.

## Call barring

Your device allows you to restrict incoming calls and outgoing calls, domestically and internationally. A call barring PIN code is needed to turn this function on and off and this will be provided with your subscription.

This function is network dependant.

The following call barring options are available:

- **All calls** - will restrict all calls.
- **Outgoing calls** - no outgoing calls will be possible.
- **Incoming calls** - no incoming calls will be received.
- **Outgoing international calls** - no international outgoing calls will be possible.
- **Outgoing international calls except to home country** - no international outgoing calls will be possible except to the subscription home country.
- **Incoming calls when outside home country** - no incoming calls will be received when outside the subscription home country.

**NOTE:**It is still possible to make emergency calls when the call barring options are activated. See...

### ***To switch a call barring option on***

1. Select *Settings/Control settings/Phone*
2. Press *Call barring*.
3. Press the desired option.
4. Enter the Call Barring PIN code and press *OK*  to activate the setting.  
The option will be displayed with the checked indication  when switched On.

### ***To cancel all call barring options***

1. Select *Settings/Control settings/Phone*
2. With a long press select *Call barring* to cancel to activate the Fast menu and select *Cancel All*
3. Enter the Call Barring PIN code and press *OK*  to cancel all.

### **Fixed dialling numbers**

Fixed dialling is a function which limits the calls to only specified numbers stored on the SIM card. This feature requires the SIM to have the functionality to save Fixed dialling numbers. The PIN2 code is needed in order to store and edit Fixed numbers.

**NOTE:**It is still possible to make emergency calls when the fixed dialling option is activated. See...

### ***To activate fixed dialling numbers***

1. Select *Settings/Control settings/Phone/Fixed dialling numbers*
2. Press *Activate*.
3. Enter the PIN2 code and press *OK*  activate the setting.  
The option will be displayed with the checked indication  when switched On.

### ***To add a fixed dialling number***

1. Select *Settings/Control settings/Phone/Fixed dialling numbers*
2. Press *Number:*
3. Enter the number and press *OK* . The number will be added to the fixed dialling number list.

### ***To add a fixed dialling number from the contacts list***

1. Select *Settings/Control settings/Phone/Fixed dialling numbers*
2. Press *Add from Contacts* 
3. Enter the PIN2 code and press *OK* 
4. Select a contact and press *OK* . The contact will be added to the fixed dialling numbers list.

## Summary after call

### *To switch on the duration display after a call*

1. Select *Settings/Control settings/Phone*
2. Press *Summary after call* to switch On.

The *Summary after call* option will be displayed with the checked indication  when switched On.

## Calling Line Identification

You can choose to show or hide your phone number when making a call. This function is Network/Operator dependant.

### *To show your phone number when calling*

1. Select *Settings/Control settings/Phone*
2. Press *Show own number*.

The *Show own number* option will be displayed with the checked indication  when switched On.

## Automatic redial

Automatic redial will redial when you have called a busy number and will continue to redial the number until the call connects or you stop the automatic redial.

### *To switch on Automatic redial*

1. Select *Settings/Control settings/Phone*
2. Press *Automatic redial*.

The *Automatic redial* option will be displayed with the checked indication  when switched On.

## Call Waiting

The call waiting service allows you to receive another call whilst already in a call. See...Call Functions. This function is Network/Operator dependant.

### *To switch on the Call waiting service*

1. Select *Settings/Control settings/Phone*
2. Select *Call waiting*.

The *Call waiting* option will be displayed with the checked indication  when switched On.

*Call Waiting Activated* will be briefly displayed. *Call Waiting Not available* will be displayed if your subscription does not support this feature.

## Messaging

### Number of messages

You can set the amount of messages shown in the messaging index. By specifying an amount you can control more easily the amount of memory used to store messages and ease the management of viewing the messages. When the set amount of messages has been reached a new message will replace the oldest message stored in the device.

If you select Unlimited then the messages will be stored until there is no more memory available in the device. If there are lots of messages stored in the device then this will reduce the amount of memory available for the other applications in the device.

Received messages includes SMS, MMS and delivery reports and Received e-mails.

*Sent messages* includes SMS, MMS and delivery reports.

#### ***To set the number of received messages shown***

1. Select *Settings/Control settings/Messaging/Number of messages*
2. Press *Received messages*.
3. Select the desired amount setting.

The selected setting is the one with the filled button .

#### ***To set the number of received e-mails shown***

1. Select *Settings/Control settings/Messaging/Number of messages*
2. Press *Received e-mails*.
3. Select the desired amount setting.

The selected setting is the one with the filled button .

#### ***To set the number of sent messages shown***

1. Select *Settings/Control settings/Messaging/Number of messages*
2. Press *Sent messages*.
3. Select the desired amount setting.

The selected setting is the one with the filled button .

### SMS Settings

#### SMS Validity period

##### ***To set the SMS validity period***

1. Select *Settings/Control settings/Messaging/SMS settings*
2. Press *Validity period*
3. Select the desired time period.

The selected setting is the one with the filled button .

#### Service centre number

### **To set the short message service centre number**

1. Select *Settings/Control settings/Messaging/SMS settings*
2. Press *SMSC number*
3. Enter the SMS service centre number and press **OK** 

Your Service centre number is supplied by your Network operator/Service provider.

### **Delivery reports**

#### **To switch delivery reports On**

1. Select *Settings/Control settings/Messaging/SMS settings*
2. Press *Delivery reports*

The *Delivery reports* option will be displayed with the checked indication  when switched On.

### **Concatenated SMS**

#### **To switch concatenated SMS On or Off**

1. Select *Settings/Control settings/Messaging/SMS settings*
2. Press *Concatenated SMS*

The *Concatenated SMS* option will be displayed with the checked indication  when switched On.

### **MMS Settings**

#### **Primary connection (See connection settings)**

##### **To select a primary connection**

1. Select *Settings/Control settings/Messaging/MMS settings*
2. Press *Primary Connection*.
3. Select the desired connection profile.

The selected connection profile is the one with the default symbol 

#### **Secondary connection (See connection settings)**

##### **To select a secondary connection**

1. Select *Settings/Control settings/Messaging/MMS settings*
2. Press *Secondary Connection*.
3. Select the desired connection profile.

The selected connection profile is the one with the default symbol 

#### **Allowing Multimedia messages**

##### **To allow MMS messages**

1. Select *Settings/Control settings/Messaging/MMS settings*
2. Press *Allow MMS*
3. Select the desired option.

The selected option is the one with the filled button  .

Retrieving incoming MMS messages

**To change how to retrieve incoming MMS messages**

1. Select *Settings/Control settings/Messaging/MMS settings*
2. Press *Retrieve incoming messages*.
3. Select the desired option.

The selected option is the one with the filled button  .

**To allow receiving anonymous MMS messages**

1. Select *Settings/Control settings/Messaging/MMS settings*
2. Press *Allow anonymous messages*

The *Allow anonymous messages* option will be displayed with the checked indication  when switched On.

**To allow receiving advert MMS messages**

1. Select *Settings/Control settings/Messaging/MMS settings*
2. Press *Allow advert messages*

The *Allow advert messages* option will be displayed with the checked indication  when switched On.

**To request delivery reports for MMS messages**

1. Select *Settings/Control settings/Messaging/MMS settings*
2. Press *Request delivery reports*

The *Request delivery reports* option will be displayed with the checked indication  when switched On.

**To reply to delivery reports for MMS messages**

1. Select *Settings/Control settings/Messaging/MMS settings*
2. Press *Reply to delivery reports*

The *Reply to delivery reports* option will be displayed with the checked indication  when switched On.

MMS validity period

**To set the MMS validity period**

1. Select *Settings/Control settings/Messaging/MMS settings*
2. Press *Validity period*
3. Select the desired time period.

The selected setting is the one with the filled button  .

MMS image size

**To set the displayed MMS image size**

1. Select *Settings/Control settings/Messaging/MMS settings*
2. Press *Image size*
3. Select the desired size.

The selected setting is the one with the filled button .

## E-mail settings

### Incoming mail server

#### **To set a new incoming mail server**

1. Select *Settings/Control settings/Messaging/E-mail settings*
2. Press *Set Incoming Mail Server* 
3. Press *Server Address:* to enter the address and press *OK* 
4. Select the server port type
5. The selected setting is the one with the filled button .
6. Press *Enter User Name* to enter the username and press *OK* 
7. Press *Enter Password* to enter the password and press *OK* 

The created server settings will now be stored to the *Incoming mail servers* folder. The settings for the created mail server can be edited from this folder.

The default mail server is the one with default symbol 

#### **To remove an incoming mail server**

1. Select *Settings/Control settings/Messaging/E-mail settings*
2. Press *Incoming mail servers*.
3. Press the mail server to view the server settings.
4. Press *Remove* 
5. Press *Yes*  to confirm.

### Outgoing mail server

#### **To set a new outgoing mail server**

1. Select *Settings/Control settings/Messaging/E-mail settings*
2. Press *Set Outgoing Mail Server* 
3. Press *Server Address:* to enter the address and press *OK* 
4. Select the server port type
5. The selected setting is the one with the filled button .
6. Press *Enter User Name* to enter the username and press *OK* 
7. Press *Enter Password* to enter the password and press *OK* 
8. Press *Mark as Default Server* to set the server as default.

The created server settings will now be stored to the *Outgoing mail servers* folder. The settings for the created mail server can be edited from this folder.

The default mail server is the one with default symbol 

### **To remove an outgoing mail server**

1. Select *Settings/Control settings/Messaging/E-mail settings*
2. Press *Outgoing mail servers*.
3. Press the mail server to view the server settings.
4. Press *Remove* 
5. Press *Yes*  to confirm.

### **Automatic Mail Check**

#### **To set the device to automatically check for new e-mail**

1. Select *Settings/Control settings/Messaging/E-mail settings*
2. Press *Check mail*.
3. Select the desired option.

The selected option is the one with the filled button  .

#### **To include an e-mail in a reply**

1. Select *Settings/Control settings/Messaging/E-mail settings*
2. Press *Reply with quote*

The *Reply with quote* option will be displayed with the checked indication  when switched On.

## **Connections**

### **GPRS settings**

In order to make a data call and use the functions such as E-mail, MMS, Internet you must first set up a GPRS connection setting profile.

**NOTE:**The settings for creating a GPRS profile can be obtained from the network operator or service provider for the subscription.

#### **To create a GPRS profile**

1. Select *Settings/Control settings/Connections/GPRS settings*
2. Press *Set GPRS Profile*.
3. Press *Enter Profile Name* to enter the profile name and press *OK* 
4. Press *Ask when connecting* to turn On or Off.
5. Press *User Name*: to enter the username and press *OK* 
6. Press *Password*: to enter the password and press *OK* 
7. Press *DNS* and select either *Automatic* or *Manual*.
8. Press *Server IP Address*: to enter the IP address and press *OK* 
9. Press *Idle Timeout*: to enter a number in seconds and press *OK* 
10. Press *Network Access Point*: to enter the network address and press *OK* 
11. Press *Connection String*: to enter the connection string and press *OK* 

After completing the settings for a profile, the device can now be used to make a GPRS data call.

#### **To select a GPRS profile**

1. Select *Settings/Control settings/Connections/GPRS settings*
2. Select the desired GPRS profile.
3. Press **Yes**  when asked to change to the selected GPRS profile.  
The default GPRS profile is the one with default symbol 

#### **To edit a GPRS profile**

1. Select *Settings/Control settings/Connections/GPRS settings*
2. With a long press select the GPRS profile you wish to edit to activate the Fast menu and select **Edit** 

#### **To delete a GPRS profile**

1. Select *Settings/Control settings/Connections/GPRS settings*
2. With a long press select the GPRS profile you wish to delete to activate the Fast menu and select **Delete** 

**NOTE:**If you delete the default GPRS profile and no other GPRS profiles are available then the GPRS connection will be disabled.

### **Synchronisation**

#### **To create a new synchronisation profile**

1. Select *Settings/Control settings/Connections/Synchronisation*
2. Press **Create Profile**
3. Enter a name for the new synchronisation profile and press **OK** 
4. Select **Type** and then select the desired connection type.  
If HTTP is the connection type selected then you will need to set the server address and port.
  - Select Server
  - Enter the Server Address and Server Port
  - Enter your User Name and Password.
5. Select the options you wish to synchronise.
6. Press **Synchronise**  to start the synchronising according to the selected profile.

#### **To set a synchronisation profile as default**

1. Select *Settings/Control settings/Connections/Synchronisation*
2. With a long press select the Synchronisation profile you wish to set as default to activate the Fast menu and select **Set Default** 

#### **Synchronization log**

The log shows information including date of synchronisation, the synchronisation server used and the items transferred of the last synchronised profile.

**To view the synchronisation log**

1. Settings/Control settings/Connections/Synchronisation
2. Press *Log*.

## Device Control

### Backlight delay

**To change the backlight delay**

1. Select *Settings/Control settings/Device control*
2. Press *Backlight Delay*.
3. Select the desired option.

The selected option is the one with the filled button  .

**To change the function set to the long press of the 123 lens key**

1. Select *Settings/Control settings/Device control*
2. Press *Long press of 123*.
3. Select the desired function.

The selected option is the one with the filled button  .

**To change the function set to the long press of the @ lens key**

1. Select *Settings/Control settings/Device control*
2. Press *Long press of @*.
3. Select the desired function.

The selected option is the one with the filled button  .

### Touch Screen

**To calibrate the device Haptitouch screen**

1. Select *Settings/Control settings/Device control/Touch screen*
2. Press *Calibrate* 
3. Press the points as directed in the display to calibrate the device touch screen.

**NOTE:**The calibration should be carried out when the device display is in the horizontal view.

**To set the use calibration On**

1. Select *Settings/Control settings/Device control/Touch screen*
2. Press *Use calibration*.

The *Use calibration* option will be displayed with the checked indication  when switched On.

### ***To set the Haptitouch lens feedback On***

1. Select *Settings/Control settings/Device control/Touch screen*
2. Press *Touch feedback*.

The *Touch feedback* option will be displayed with the checked indication  when switched On.

### **Motion Control**

#### ***To change the devices mirroring views***

1. Select *Settings/Control settings/Device control/Motion control*
2. Select the desired display view.

The selected option is the one with the filled button .

#### ***To adjust the devices tilting sensitivity***

1. Select *Settings/Control settings/Device control/Motion control*
2. Press *Tilt speed*.
3. Select the desired tilt speed.

The selected option is the one with the filled button .

### **Software Files**

DRAFT

### **Regional Settings**

#### ***To set the time and date***

1. Select *Settings/Regional settings*
2. Press *Set time and date* 
3. Enter the date and time and press *OK*  to change.

#### ***To change the time format***

1. Select *Settings/Regional settings/Time format*.
2. Select *24 hours* or *a.m./p.m.* setting.

The selected setting is the one with the filled button .

#### ***To change the date format***

1. Select *Settings/Regional settings/Date format*.
2. Select the desired date format setting.

The selected setting is the one with the filled button .

### **Time Zone**

You are able to adjust the time setting in the device to a different time zone, for example when travelling and then upon return select your home time zone to switch back the time setting quickly and easily. You can also use the *Find time zone* function to check the time differences around the world.

### ***To find a time zone***

1. Select *Settings/Regional settings/Time zone*
2. Press *Find Time Zone* 
3. Enter the name of either a country or major city and press *OK*  to search.
4. Press the desired time zone selection if you wish to change the time zone. The time zone function displays the five most recently used time zone settings.

### ***To change the time zone***

1. Select *Settings/Regional settings/Time zone*
2. Either press a desired time zone selection displayed in this menu or press *Find Time Zone*  to find a new time zone setting.

## **Menu Language**

When you insert your SIM card the menu language in most SIM cards will set the language to the language used for the country where the subscription was taken. This is the *Automatic* mode. If the SIM card does not support the *Automatic* SIM language, then English will be the set language.

### ***To change the menu language***

1. Select *Settings/Regional settings/Language*
2. Select the desired language setting.  
The selected setting is the one with the filled button .

## **Keyboard Language**

### ***To change the keyboard input language***

1. Select *Settings/Regional settings/Keyboard language*
2. Select the desired keyboard language character setting.  
The selected setting is the one with the filled button .

## **System and Security**

### **SIM card locking**

Personal Identity Number... Personal Unblocking Code

### ***To turn the SIM card lock On or Off***

1. Select *Settings/System and security/PIN codes*
2. Press *PIN query*
3. Enter the PIN code and press *OK*   
The message *PIN Query ON* will be displayed briefly in the header row.

The setting check box in the *PIN query* field will now be checked, indicating the setting is on .

If you enter the PIN code incorrectly, you will be notified with an audible sound and the message *Wrong code, Enter PIN code again*.

#### **To unblock the SIM card**

If the PIN code has been entered incorrectly 3 times in a row the message *Wrong code, SIM card blocked. Enter PUK code* will be briefly displayed.

1. Enter the PUK code and press *OK* 
2. Enter a new PIN code and press *OK* 
3. Re-enter the new PIN code and press *OK* 

**NOTE:** If you enter the PUK (Personal Unblocking Code) incorrectly 10 times in a row then the SIM card will be permanently blocked and you must then contact your network operator or service provider for assistance.

#### **To change the PIN code**

1. Select *Settings/System and security/PIN codes*
2. Press *Change PIN* 
3. Enter the current PIN code and press *OK* 
4. Enter a new PIN code and press *OK* 
5. Re-enter the new PIN code and press *OK* 

The message *Code changed* will be displayed briefly in the header row.

#### **To change the PIN2 code**

1. Select *Settings/System and security/PIN codes*
2. Press *Change PIN2* 
3. Enter the current PIN2 code and press *OK* 
4. Enter a new PIN2 code and press *OK* 
5. Re-enter the new PIN2 code and press *OK* 

The message *Code changed* will be displayed briefly in the header row.

#### **To change the call barring code**

1. Select *Settings/System and security/PIN codes*
2. Press *Change Call Barring Code* 
3. Enter the current call barring code and press *OK* 
4. Enter a new call barring code and press *OK* 
5. Re-enter the new call barring code and press *OK* 

The message *Call barring code changed* will be displayed briefly in the header row.

## Device Lock

The device lock can be used to protect the device against unauthorised use. The factory set device lock code is XXXX. The device lock can be changed from the factory set code to a code comprising of X-X digits.

### **To use the device lock code**

1. Select *Settings/System and security/Device lock*
2. Press *Device lock query*.
3. Enter the Device lock code and press *OK* 

The message *Device Lock Query ON* will be displayed briefly in the header row.

The setting check box in the *Device lock query* field will now be checked, indicating the setting is on .

To switch the device lock code off repeat steps 1-3 for *To use the device lock code*.

### **To change the device lock code**

1. Select *Settings/System and security/Device lock*
2. Press *Change Device Lock Code* 
3. Enter the current device lock code and press *OK* 
4. Enter a new device lock code and press *OK* 
5. Re-enter the new device lock code and press *OK* 

The message *Code changed* will be displayed briefly in the header row.

**NOTE:** If you change the factory device lock code to a code of your choice and then forget the code, you will need to take the device to your local retailer/service centre along with the receipt so that the device lock code can be reset.

### **To lock the device to the SIM card**

1. Select *Settings/System and security/Device lock*
2. Press *Lock to this SIM card*.
3. Enter the device lock code and press *OK* 

The message *Device Locked to This SIM* will be displayed briefly in the header row.

The setting check box in the *Lock to this SIM card* field will now be checked, indicating the setting is on .

## Auto Keylock

Auto key lock will activate the keylock automatically when the device is not being used. You can also adjust the activation time for the auto key lock from the last device activity.

### ***To set the auto keylock On or Off***

1. Select *Settings/System and security/Automatic keylock*
2. Select the desired setting.

The selected setting is the one with the filled button  .

### **Restoring Factory Settings**

#### ***To reset the device to the factory settings***

1. Select *Settings/System and security*
2. Press *Restore Factory Settings* 

The warning text *Reset all settings to default factory settings?* will be displayed.

3. Press *Yes*  to open the phone application for entering the device lock code.
4. Enter the device lock code and press *OK* . See *Device lock code* page.....


The text *Factory Settings Restored* will be displayed briefly in the header row.

DRAFT

DRAFT

# MP3 Player

Your **mydevice** has a MP3 player which allows you to play MP3's stored in the device memory. The sales package contains a stereo headset so that the music can be played discreetly in public places. The player allows you to make playlist from the music files stored in the device so that custom personal music albums can be made.



## MP3 Player

### *To open the player*

1. Select MP3 Player
2. Press *Start player* 

### MP3 player keys

- Pressing  if there is no music clip already open in the player, the player will play the first clip from the playlist.
- Pressing  when a music clip is playing will pause the clip.
- Pressing  when a music clip is paused will play the clip.
- Pressing  when a music clip is playing will stop the clip.
- Pressing  to skip to the next music clip in the playlist.
- Pressing  to skip to the previous music clip in the playlist.
- Pressing  will fast forward through the music clip that is playing.
- Pressing  will rewind through the music clip that is playing.

### *To adjust the MP3 player volume*

1. Select MP3 Player
2. Press *Start player*
3. Slide your finger to move the volume slider  to adjust the volume.

## Playlists

You can create playlists to compile your own music albums to suit your personal music tastes and moods.

### ***To create a playlist for the MP3 player***

1. Select *MP3 player*
2. Press *Playlist*
3. Press *Add clip* 
4. Press the add check box  for the music file you wish to add to the playlist.
5. A selected music file  will be displayed with the checked indication
6. Press *OK*  to add the selected music files to the playlist.

### ***To delete music clips from the playlist***

1. Select *MP3 player*
2. Press *Playlist*
3. With a long press select the music clip you wish to delete from the playlist to activate the Fast menu and select *Delete* 

### ***To play music clips from the playlist***

1. Select *MP3 player*
2. Press *Playlist*
3. Press the music clip from the playlist you wish to play.  
The music player will open and play all the music clips from the playlist from this position.

### ***To repeat or shuffle playlists***

When only one music clip is in the playlist or being directly played from the *Music* folder then the *Shuffle* option is not possible.

1. Select *MP3 player*
2. Press *Start player*
3. Press the check box  for the play option you wish to make to the playlist.  
A selected play option will be displayed with the checked indication .

## **Music folder**

The music folder is a folder which contains links so that it is easier to locate the files for playing in the MP3 player

Sound clips and music clips that are stored in the *Files* index will be displayed in the music folder as links.

### ***To play music clips or sound clips from the music folder***

1. Select *MP3 player*
2. Press *Music*
3. When pressing the music or sound clip, it will launch the player and will only play that specific music or sound clip.

*To play music clips or sound clips from the memory card*

1. Select *MP3 player*
2. Press *Music*
3. Press *Memory card*
4. When pressing the music or sound clip, it will launch the player and will only play that specific music or sound clip.


**NOTE:**The memory card folder will be disabled if there is no MMC card inserted into the device.

DRAFT

DRAFT

# Programs

The Programs chapter contains downloaded programs, the calculator, games, accessories and notepad.



## Calculator

The calculator in the device allows basic calculating, with square root and memory recall.

**To open the calculator in the device**

1. Select *Programs*
2. Press *Calculator* 

To close the calculator press *Close* 

## Notepad

The note pad allows you to type notes and are stored as a text file in the *Files/Notes* index. The text in the notes can be copied and pasted and the note can be sent as an SMS, MMS or E-mail message or as an attachment in E-mail.

**To create a note**

1. Select *Programs*
2. Press *Create Note* 
3. Enter the text for the note and press to save.

The note is now saved to the *Notes* index in the *Files* Chapter and a short-cut is made to the *Notes* folder in the *Programs* index, see *Notes...*

If *Close*  or *C* is pressed in the keyboard before typing anything then the note will not be created.

## Notes

The notes folder contains links to the notes stored in the *Files* index. A note is indicated by the note icon 

**To edit a note**

1. Select *Programs/Notes*
2. Press the note to open the note
3. With a long press select the text to edit to activate the Fast menu and select *Edit* 

### ***To delete a note***

1. Select *Programs/Notes*
2. With a long press select the note to delete to activate the Fast menu and select *Delete* 

## **Downloads**

The downloads folder contains links to the *Programs* folder stored in the *Files* index. A program is indicated by the program icon .

### ***To launch a program in downloads***

1. Select *Programs*
2. Press *Downloads*
3. Press the desired downloaded program field to launch the application.

## **Games**

Your **mydevice** contains? device games and it is possible to play Java games from the Internet.

## **Accessories**

DRAFT

# Info

The Info chapter contains information on using **mydevice**, including the user guide help function, a tutorial on how to use some of the innovative features of the device and the device system properties.



## Help

The help function will allow you to access the user guide for the device so that you can check the functionality of the devices features and applications.

**To open the user guide in the device**

1. Select *Info*
2. Press *Help* 

The user guide will open in the browser as HTML pages.

## Tutorial

The tutorial function will guide you through a short demonstration of how to use the devices innovative features.

**To view the tutorial in the device**

1. Select *Info*
2. Press *Show Tutorial* 
  - To move forward through the tutorial press *Next* 
  - To move forward through the tutorial press *Back* 
  - To exit the tutorial press *Close* 

## About System

Information stored in this chapter is read only information and the only functions that are available are to copy the information stored here using the *Copy*  function from the Fast menu.

## Product Version

The information contains the product version number and the date of when the device software was last updated.

## **Applications**

The information contains the list of applications in the device with the version numbers and the date of when the device software was last updated.

## **Installed Applications**

The information contains a list of all user installed applications in the device with the version numbers and the date of when the device software was last updated.

## **Memory**

The information contains total memory, free space, memory management and memory distribution, for example, how much memory is being used to store images in the device.

## **System**

The information contains the system description only.

## **Links**

This section contains webpage links to the manufacturer of the device and its operating platform.

DRAFT

# Safety Precautions and Care

Your MyOrigo Z1 is a highly sophisticated electronic device. To get the most out of the product, please read this text about product care, and the safety precautions before using the product.

## Product Care

- Do not expose your product to liquid or moisture or humidity.
- Do not expose your product to extreme high or low temperatures.
- Do not expose your product to open flames etc.
- Do not drop, throw or try to bend the product as rough treatment could damage it.
- Do not apply extreme forces to the product
- Do not paint your product as the paint could obstruct the earphone, microphone or any moveable parts and prevent normal use.
- Do not attempt to disassemble your product. The product does not contain consumer serviceable components. Only Certified Service Centres should perform service.
- Do not use any accessories other than originals. Use of other accessories may result in loss of performance, damage to the product, fire, electric shock or injury. The warranty does not cover product failures which have been caused by use of non original accessories.
- Treat your product with care, keep it in a clean and dust free place.

## Internal Antenna

The device has an internal antenna. In no way or form should this antenna be modified and should only be replaced by an authorized repair centre. Modifying the antenna in any way or form may cause damage to the device and reduce the radio frequency performance and may violate regulations concerning SAR levels.

When using the device, hold the device in a way as to avoid covering the internal antenna (located in the top rear of the device) as this may affect the quality of voice and data calls and may require the device to operate at a higher power level, which may reduce the operating times between recharging.

## Infrared Port

When an infrared data connection is activated, never direct the infrared ray towards a person's eyes and ensure that it does not disturb any other infrared units.

## Radio Frequency Energy

Your device is a low-power radio transmitter and receiver. When it is turned on, it intermittently receives and transmits radio frequency (RF) energy (radio waves). The system that handles the call controls the power level at which the phone transmits.

## Exposure to Radio Frequency Energy

MyOrigo Z1 products are designed to not exceed the limits for exposure to RF energy set by national authorities and international health agencies.\* These limits establish permitted levels of radio wave exposure for the general population. The guidelines were developed by international scientific organizations like ICNIRP (International Commission on Non-Ionising Radiation Protection) through periodic and thorough evaluation of scientific studies. The limits include a safety margin designed to assure the safety of all persons, regardless of age and health.

\*Examples of radio-frequency exposure guidelines and standards that the MyOrigo Z1 device is designed to conform to:

- ICNIRP, "Guidelines for limiting exposure to time-varying electric, magnetic, and electromagnetic fields (up to 300 GHz)", International Commission on Non-Ionizing Radiation Protection (ICNIRP), Health Physics, vol.74, pp494-522, April 1998.
- 99/519/EC, "Council Recommendation of 12 July 1999 on the limitation of exposure of the general public to electromagnetic fields (0 Hz to 300 GHz)", Official Journal of the European Communities, 1999.
- IEEE C95.1-1991, "Safety levels with respect to human exposure to radio frequency electromagnetic fields, 3 kHz to 300 GHz", The Institute of Electrical and Electronics Engineers Inc. (IEEE).
- FCC Report and Order, ET Docket 93-62, FCC 96-326, Federal Communications Commission (FCC), August 1996.
- Radio communications (Electromagnetic Radiation Human Exposure) Standard 1999, Australian Communications Authority (ACA), May 1999.

## SAR (Specific Absorption Rate)

Specific Absorption Rate (SAR) is the unit of measurement for the amount of radio frequency energy absorbed by the body when using a mobile

phone. The SAR value is determined at the highest certified level in laboratory conditions, but the actual SAR level of the mobile phone while operating can be well below this value. This is because the mobile phone is designed to use the minimum power required to reach the network. Therefore, the closer you are to a base station, the more likely it is that the actual SAR level will decrease.

Before a phone model is available for sale to the public, it must be tested and certified to the FCC that it does not exceed the limit established by the government-adopted requirement for safe exposure. The tests are performed in positions and locations (that is, at the ear and worn on the body) as required by the FCC for each model. For body worn operation, MyOrigo Z1 has been tested and meets FCC RF exposure guidelines when MyOrigo Z1 is positioned a minimum of 15 mm from the body without metal parts between the phone and the body. Use of other accessories may not ensure compliance with FCC RF exposure guidelines.

The highest SAR value for this model phone when tested for head held use is 0.334 W/kg, for body worn operations 0.376 W/kg.

## Driving

Driving a vehicle while using the device can be dangerous and is illegal in many countries. It is highly recommended to safely pull off the road and park the vehicle before making or answering a call with the device. It may be possible to use the device with a headset while driving.

RF energy may affect some electronic systems in motor vehicles such as car stereo, safety equipment etc. In addition, some vehicle manufacturers do not allow use of mobile phones in their vehicles, unless a hands free kit with an external antenna supports the installation. Check with your vehicle manufacturer's representative to be sure that your mobile phone will not affect the electronic systems in your vehicle.

## Vehicles Equipped with an Air Bag

An air bag inflates with great force. Do not place objects, including either installed or portable wireless equipment, in the area over the air bag or in the air bag deployment area. If in-vehicle wireless equipment is improperly installed and the air bag inflates, serious injury could result.

## Electronic Devices

Most modern electronic equipment is shielded from RF signals. However, certain electronic equipment may not be shielded against the RF signals from your mobile phone, therefore:

- Do not use your mobile phone near medical equipment without requesting permission.
- Mobile phones may affect the operation of some implanted cardiac pacemakers and other medically implanted equipment. Pacemaker patients should be aware that the use of a mobile phone very close to a pacemaker might cause the device to malfunction. Avoid placing the phone over the pacemaker, i.e. in your breast pocket. When using the phone, place it at your ear opposite the pacemaker. If a minimum distance of 20 cm (9" inches) is kept between the mobile phone and the pacemaker, the risk of interference is limited. If you have any reason to suspect that interference is taking place, immediately turn off your phone. Contact your cardiologist for more information.
- Some hearing aids might be disturbed by mobile phones.
- If you use other medical devices, consult the manufacturer of your device to determine if it is adequately shielded from external RF energy.
- Turn your mobile phone off in any facility where posted notices so require.

## Aircraft

- Turn off your mobile phone before boarding any aircraft.
- To prevent interference with communication systems, you must not use your mobile phone while the plane is in the air.
- Do not use it on the ground without permission from the crew.

## Blasting Areas

Turn off your mobile phone when in a blasting area or in areas posted "turn off two-way radio" to avoid interfering with blasting operations. Construction crews often use remote control RF devices to set off explosives.

## Explosive Atmospheres

Turn off your mobile phone when in any area with a potentially explosive atmosphere. It is rare, but your mobile phone or its accessories could generate sparks. Sparks in such areas could cause an explosion or fire resulting in bodily injury or even death.

Areas with a potentially explosive atmosphere are often, but not always, clearly marked. They include fuelling areas, such as petrol stations, below deck on boats, fuel or chemical transfer or storage facilities, and areas where the air contains chemicals or particles, such as grain, dust, or metal powders.

Do not transport or store flammable gas, liquid, or explosives in the compartment of your vehicle, that contains your mobile phone and accessories.

## Power Supply

- Connect the AC power adapter only to designated power sources as marked on the product.
- To reduce risk of damage to the electric cord, remove it from the outlet by holding onto the AC adapter rather than the cord.
- Make sure the cord is positioned so that it will not be stepped on, tripped over or otherwise subjected to damage or stress.
- To reduce risk of electric shock, unplug the unit from any power source before attempting to clean it.
- The AC power adapter must not be used outdoors or in damp areas.
- DANGER - Never alter the AC cord or plug. If the plug will not fit into the outlet, have a proper outlet installed by a qualified electrician. Improper connection can result in risk of electric shock.

## Children

DO NOT ALLOW CHILDREN TO PLAY WITH YOUR MOBILE PHONE OR ITS ACCESSORIES. THEY COULD HURT THEMSELVES OR OTHERS, OR COULD ACCIDENTALLY DAMAGE THE MOBILE PHONE OR ACCESSORY. YOUR MOBILE PHONE OR ITS ACCESSORY MAY CONTAIN SMALL PARTS THAT COULD BE DETACHED AND CREATE A CHOKING HAZARD.

## Disposing of the Product

The product should never be placed in general waste. Please check local regulations for disposal of electronic products.

## Emergency Calls

### IMPORTANT!

This mobile phone, like any other mobile phone, operates using radio signals, cellular and land line networks as well as user-programmed functions, which cannot guarantee connection under all conditions. Therefore you should never rely solely upon any mobile phone for essential communications (e.g. medical emergencies).

Remember, in order to make or receive calls the mobile phone must be switched on and in a service area with adequate cellular signal strength. Emergency calls may not be possible on all cellular phone networks or

when certain network services and/or mobile phone features are in use. Check with your local service provider.

## Battery Information

### Charging the Battery

The battery delivered with your phone is not fully charged. We recommend that you charge the battery for 4 hours before you use the phone for the first time.

If you are charging a new battery, or a battery that has run out completely, it may take a while (up to 30 minutes) before you get any indication (the battery meter appears in the display) that the battery is being charged.

### Battery Use and Care

A rechargeable battery has a long service life if treated properly. A new battery, or one that has not been used for a long time could have reduced capacity the first few times it is used.

- The talk and standby times depend on the actual transmission conditions when using the phone. If the phone is used near a base station less power is required and talk and standby times are prolonged.
- Use only MyOrigo original batteries and chargers. Using other batteries and chargers could be dangerous.

**NOTE:**The warranty does not cover product failures which have been caused by use of other batteries and chargers.

- Do not expose the battery to extreme temperatures, never above +60°C (+140°F). For maximum battery capacity use the battery in room temperature. If the battery is used in low temperatures the battery capacity will be reduced.
- Turn off your device before removing the battery.
- Use the battery for the intended purpose only.
- Do not attempt to take the battery apart.
- Do not let the metal contacts on the battery touch another metal object. This could short-circuit and damage the battery.
- Do not expose the battery to open flames. This could cause the battery to explode.
- Do not expose the battery to liquid.
- Do not allow the battery to be placed into the mouth. Battery electrolytes may be toxic if swallowed.

## **Battery disposal**

The battery should not be placed in general waste. Take care to dispose of the battery in accordance with local regulations and laws. If you are unsure as to how to dispose of the battery correctly, then please consult your retailer for further advice.

DRAFT

DRAFT

# Limited Warranty

Thank you for purchasing this MyOrigo Z1 Product. To get maximum advantage of your new Product, we recommend that you follow a few simple steps:

- Read the instructions for use carefully.
- Read all the terms and conditions of your MyOrigo Z1 Warranty.
- Save your original receipt that is needed for warranty repair claims. Should your MyOrigo Z1 Product need warranty service, please contact to an authorized service point.

## Our Warranty

MyOrigo warrants this Product to be free from defects in material and workmanship for one (1) year of date of purchase.

Any MyOrigo Z1 accessory is covered by a warranty period of one (1) year from the date of purchase by a consumer in accordance with the applicable terms and conditions stipulated herein.

## Warranty covers

If, during the warranty period, this Product fails to operate under normal use and service, due to improper materials or workmanship, the device will be either repaired or replaced the Product in accordance with the terms and conditions stipulated herein.

## Conditions

1. The warranty is valid only if the original receipt issued to the original purchaser by the dealer, specifying the date of purchase and serial number, is presented with the Product to be repaired or replaced.
2. If MyOrigo repairs or replaces the Product, the repaired or replaced Product shall be warranted for the remaining time of the original warranty period or for ninety (90) days from the date of repair, whichever is longer. Repair or replacement may involve the use of functionally equivalent reconditioned units. Replaced faulty parts or components will become the property of MyOrigo.
3. This warranty does not cover any failure of the Product due to misuse, including but not limited to use in other than the normal and customary manner, in accordance with MyOrigo Z1 instructions for use and maintenance of the Product. Nor does this warranty cover any failure of the Product due to accident, modification or adjustment, improper ventilation or damages resulting from liquid or excess heat.
4. This warranty does not cover Product failures due to improper repair installations, modifications or service performed by a non-MyOrigo Service

Point or Certified Service Centre or opening of the Product by non-MyOrigo certified persons.

5. The warranty does not cover Product failures which have been caused by use of non-MyOrigo original accessories or by use of MyOrigo original accessories not compatible with the Product as specified in the Users guide.
6. Broken seals on the Product will void the warranty.
7. All the user information will be erased from the unit before the maintenance. MyOrigo will not distribute, store or use any of the user data.
8. This warranty does not cover failures or communication breakdowns to this device or to the other GSM/GPRS users and devices caused by third party or user manipulated or misused software installed to the device.
9. This warranty does not cover failures or communication breakdowns to the connected PC and it's peripherals caused by third party or user manipulated or misused software installed to the device.
10. The warranty does not cover the battery and other wearing parts.
11. **NOTE! The MyOrigo Z1 is equipped with very expensive and fragile colour display unit. Pay attention not to misuse the device, do not bend, drop or smite it. The warranty does not cover the broken display caused by rough handling.**
12. **IN NO EVENT SHALL MyOrigo BE LIABLE FOR ANY INCIDENTAL, SPECIAL, INDIRECT OR CONSEQUENTIAL DAMAGES, WHETHER RESULTING FROM THE USE, MISUSE OR INABILITY TO USE THIS PRODUCT OR FROM DEFECTS IN THE PRODUCT, INCLUDING BUT NOT LIMITED TO LOST PROFITS OR COMMERCIAL LOSS, TO THE FULL EXTENT THOSE DAMAGES CAN BE DISCLAIMED BY LAW.**
13. These warranty terms are applicable when using the device in Finland, Lithuania, Estonia and Latvia.

# Technical Data

General	
Product Name	MyOrigo
Type Number	Z1

Dimensions	
Size	123 mm x 58 mm x 23 mm
Weight (including standard battery)	171 g
Li-ion Battery	1310 mAh

Operation	
E-GSM Class	4 (2 watt)
Frequency	900 MHz
GSM Class	1 (1 watt)
Frequency	1800 MHz
GSM Class	1 (1 watt)
Frequency	1900 MHz
SIM card	3 V
GPRS Class	8 (4 downlink + 1 uplink slots)
Operating temperature	Min. -10 C Max. +55 C
Standby time	130 hrs.
Talk time	220 - 600 mins.

**NOTE:**Standby time and talk time are subject to the network conditions

Data Connectivity	
GSM Data Rate	14.4 kb/s
GPRS Data Rate	85.6 kb/s
Infrared Coverage	1 m
Infrared Data Transmission Rate	115 kb/s (SIR) 4 Mb/s (FIR)

<b>Data Connectivity</b>	
Cable Type	
USB Cable Data Transmission Rate	
Memory Card Type	SD card

DRAFT

# Declaration of Conformity

We,

**MyOrigo Oy, Limited**

of

**Kasarmintie 28 H 25**

**90230 Oulu**

**FINLAND**

declare under our sole responsibility that the product

**MyOrigo Z1**

**E-GSM900/GSM1800/GSM1900**

to which this declaration relates is in conformity with all the essential requirements of R&TTE European Directive 1999/05/EC.

We hereby declare that all the essential radio test suites have been carried out and that the above named product is in conformity to all the essential requirements of Directive 1995/5/EC.

The technical documentation relevant to the above equipment will be held at:

**MyOrigo Oy, Ltd.**

**Kasarmintie 28 H 25**

**90230 Oulu**

**FINLAND**

## FCC Statement

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

DRAFT