

# 折页线

330.0 mm

160.0 mm

**QCY T8**  
TWS智能耳机

使用前, 请先下载安装QCY手机APP客户端  
以获得更便捷的耳机操控体验

### 认识耳机

入耳检测位置 | 触控面板

触控面板 | 泄压孔 | 充电触点 | 麦克风 | LED指示灯 | 充电盒按钮 | TYPE-C USB充电

### 双耳机配对

**首次配对方法:**  
打开充电盒, 耳机自动开机, 开机后双耳自动组队成功, 耳机进入配对状态, 手机搜索连接 "QCY-T8" 即可完成双耳与手机的连接。

**切换设备配对方法:**

- 关闭A手机蓝牙, 耳机自动断开进入配对模式
- 刷新B手机蓝牙设备列表, 点击配对QCY-T8, 完成配对
- \*不支持同时连接两台手机, 下次开机默认回上次配对的手机

### 恢复出厂设置

**方法一: 清除配对记录 (此方法用于无法正常连接时)**

- 已有连接过手机, 在手机蓝牙设备列表中, 找到QCY-T8, 点击进入设置, 选择忽略或取消配对。
- 取出两只耳机, 同时长按触控面板5秒, 直至红灯长亮2秒后熄灭, 表示进入关机状态。
- 关机后再次同时长按双耳触控面板约10秒, 直至双耳红灯交替闪烁3次, 表示重置成功, 之后双耳会自动开机重新组队。

\*恢复出厂后需用首次配对的方法连接即可正常使用

**方法二: 打开充电盒盖子, 长按充电盒按钮10秒至充电盒指示灯显示红灯交替闪烁3下后, 关闭盖子完成重置**

### 佩戴耳机

- 将耳帽斜向下轻轻塞入耳道, 以减轻头部耳机不动为宜。
- 通话时, 将耳机麦克风朝向嘴部可使通话更清晰。
- 请正确佩戴左右耳机, 入耳后使其稳固贴合耳廓及出音嘴对准耳道
- 可在APP内选择开/关入耳检测功能

**一键进入配对模式**

- 耳机已经与手机配对。
- 耳机放入充电盒, 打开充电盒盖子, 长按充电盒按钮3秒至充电盒绿灯闪3下, 耳机断开与手机的连接, 进入配对模式。

### 单耳机使用模式

- 双耳有配对历史, 且在关机状态下, 长按任一耳机触控面板约2秒开机, 等5秒后耳机进入配对状态 (蓝灯闪烁)
- 打开手机蓝牙搜索配对名, 选择 QCY-T8 点击连接。
- 连接完成

**给耳机充电**  
耳机放入充电盒, 盖上盖子, 耳机会自动关机, 进入充电状态。

**给充电盒充电**  
未充满电, 充电盒红灯长亮; 充满电, 充电盒绿灯长亮。

**产品参数**

型号: XXXXXX 配对名: QCY-T8  
蓝牙版本: V5.0 待机时间: 约60小时  
充电时间: 约2小时 音乐时间: 约3.5小时  
通话时间: 约3小时 通话距离: 10米 (无障碍环境下)  
电池类型: 聚合物锂离子电池  
耳机电池容量: 3.7V 35mAh  
充电盒电池容量: 3.7V 380mAh  
充电盒输入参数: 5V = 400mA  
支持协议: HSP/HFP/A2DP/AVRCP

### 功能介绍

使用场景	状态	操作	LED	语音提示
开机	耳机不在充电盒内, 呈关机状态	轻按触控面板约2秒	蓝灯闪烁	TONE音
	耳机在充电盒内 (充电盒有电, 关盖状态)	开盖, 耳机开机 (有霍尔开关功能)		
关机	开机状态下, 充电盒有电	放入充电盒, 关盖 (有霍尔开关功能)	充电时红灯长亮	\
	耳机在开机状态下	长按触控面板5秒, 灯灭	红灯长亮2秒	TONE音
接听电话/结束电话	来电响铃中/通话中	轻按触控面板两次接听/结束通话	\	TONE音
拒接来电	来电响铃中	轻按触控面板1秒释放	\	TONE音
唤醒语音助手	在连接状态下	轻按触控面板三次	\	TONE音
音乐暂停/播放	音乐状态下	1. 双击; 2. 取下任意耳机音乐暂停, 15秒内戴上耳机, 音乐继续播放 (取下15秒后回到初始状态, 需先手动轻按触控面板两次或点击手机播放)	\	\
切换下一曲	音乐状态下	轻按左/右触控面板2秒, 切换下一曲	\	\

更多操作方法请关注二维码

### QCY蓝牙耳机售后服务

QCY蓝牙耳机售后服务承诺: 严格按照《中华人民共和国消费者权益保护法》、《中华人民共和国产品质量法》实行售后三包服务, 服务内容如下:

1. 在三包有效期内, 您购买的产品因非人为因素造成性能故障、损坏、更换、退货的权利。

1. 自您购买之日起12个月内, 本产品出现故障, 经由QCY售后服务中心确定为产品质量问题, 可享受修理、更换、退货的服务。

2. 自您购买之日起15日内, 本产品出现故障, 经由QCY售后服务中心确定为产品质量问题, 可享受退货或换货的服务。

3. 自您购买之日起12个月内, 本产品出现故障, 经由QCY售后服务中心确定为产品质量问题, 可享受修理的服务。

售后服务支持保障:

自您购买之日起12个月 (请妥善保管购买凭证)

免费保修:

在产品保修期内, 凡属产品本身质量问题引起的故障, 请用户凭购买凭证与经授权取得联系, 可享受售后服务。

如有在产品保修期外, 非因质量问题引起故障, 不在保修范围内, 有下列情况者不予保修 (费用自理):

- 因火灾、地震、雷击、异常电压、环境因素而发生之故障或毁损的;
- 自行或委托他人对产品进行了拆卸、更改、改装或更换非原厂零件;
- 未按使用手册操作或人为使用不当而造成损坏, 如: 产品浸水、腐蚀、摔落、挤压或置于异常温度环境等。

**三包凭证**

产品信息: \_\_\_\_\_  
产品型号: \_\_\_\_\_  
日期编号: \_\_\_\_\_  
用户信息: \_\_\_\_\_  
用户姓名: \_\_\_\_\_  
联系电话: \_\_\_\_\_  
用户地址: \_\_\_\_\_  
退换货原因: \_\_\_\_\_  
购买信息: \_\_\_\_\_  
销售单位: \_\_\_\_\_

### How to Connect

**First time connectivity:**  
Open the case and earbuds will auto power-on, pair with each other and turn connectable. On phone, search for QCY-T8 and tap to connect both earbuds to phone.

**Switch connected device:**

- Turn off phone's Bluetooth faculty and earbuds will auto disconnect and turn connectable.
- On phoneB, search for QCY-T8 and tap to connect.

\* Multi-point connection is not available and earbuds will auto reconnect to phoneB upon powering up again.

### Factory Setting

(Please refer the following methods to fix connectivity errors)

**Method 1:**

- Delete connectivity record on phone, if any.
- Take out both earbuds from case and keep touching both of the panels for 5s or until LED glows red for 2s to power off them.
- Once again keep touching both of the panels for 10s or until LED blinks red and blue 3 times to reset them to factory. Earbuds will then auto power on and re-pair with each other.

\* Refer How to Connect to build connection after Factory Setting.

**Method 2:** Open the lid and hold charging case button for 10s or until LED of the case blinks red and blue 3 times. Close the lid to reset earbuds to factory.

### How to Wear

- Rotate earbud and pop it into your ear then shake head to check wearing stability.
- Please adjust Mic towards your mouth to gain better calling experience.
- Please wear earbuds properly, making sure they fit in firmly and sound holes are inside ear channels
- You may turn on/off In-ear Detection in APP

**One Press to Enter Pairing Mode**

- Earbuds have been connected with phone.
- Pop earbuds into case. Open lid and hold charging case button for 3s or until LED on case blinks green 3 times. Earbuds will then disconnect to phone and enter pairing mode.

### Mono Mode

- Earbuds were paired before. Keep touching panel on either earbud for 2s to power on them. They will auto turn connectable in 5s(LED will blink blue).
- On phone, search for QCY-T8 and tap to connect the earbud to phone.

**Charge the Earbuds**  
Push earbuds into the case and close the lid. Earbuds will auto turn off and to be charged.

**Charge the Case**  
LED of the case will glow solid red when charging and turn green once topped up.

**Parameters**

Model: TWS Smart Earbuds Pairing name: h2004A  
Bluetooth version: V5.0 Standby time: approx. 60hr  
Charging time: approx. 2hr Music time: approx. 3.5hr  
Talk time: approx. 3hr  
Operation range: 10m(with no obstacle)  
Battery type: Li-Ion  
Battery capacity(earbud): 3.7V 35mAh  
Battery capacity(case): 3.7V 380mAh  
Input parameter(case): 5V = 400mA  
Bluetooth profiles: HSP/HFP/A2DP/AVRCP

### Functions

Functions	Current status	Operation	LED	Prompt
Power-on	Earbuds are not in the case	Keep touching the panel for 2s	LED blinks blue	TONE
	Earbuds are in the case with its lid closed (the case is within power)	Open the lid		
Power-off	Case is within power	Push earbuds into case and close the lid	LED glows solid red when charging	\
	/	Keep touching the panel for 5s	LED glows red for 2s	TONE
Answer/end call	Incoming call/ calling	Double tap the panel to answer/end the call	\	TONE
Ignore call	Incoming call	Keep touching the panel for 1s	\	TONE
Voice assistant	Connected	Triple tap the panel	\	TONE
Music pause/ resume playing	Playing	1. Double tap 2. Put off either earbud to pause and put it on in 1s to resume playing	\	\
Skip track forward	Playing	Keep touching either panel for 2s to skip track forward	\	\

### Warranty Card

Warranty Period  
12 months after you purchase this item.(or you may inquire your local shopper for more details.)  
Free Service:  
Supposing any defects caused by quality issues occur within the warranty period, please take this warranty card and purchase receipts to your distributor for free exchange service.

Model Number: \_\_\_\_\_  
Date of Purchasing: \_\_\_\_\_  
User's Name: \_\_\_\_\_  
User's Address: \_\_\_\_\_  
Shop's Name: \_\_\_\_\_  
Shop's Address: \_\_\_\_\_  
Comments: \_\_\_\_\_

Free exchange service will not be accessed under following circumstances:  
1. Damages caused unauthorized disassembly.  
2. Defects or physical damages caused by leaking or dropping off.  
3. Damages by act of God. Supposing your item is within any damages or defects except the above circumstances, please return to us or your distributor for free repairing.

### FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:  
-- Reorient or relocate the receiving antenna.  
-- Increase the separation between the equipment and receiver.  
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.  
-- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:  
(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

### Hazardous substances and their contents in the item

Part Name	Hazardous Substances									
	Pb	Hg	Cd	Cu	PBB	PSDE	DEHP	DEHP	DEHP	BBP
Main body	X	O	O	O	O	O	O	O	O	O
Battery	O	O	O	O	O	O	O	O	O	O
Ear tips	O	O	O	O	O	O	O	O	O	O
Accessories	O	O	O	O	O	O	O	O	O	O
Charging cable	X	O	O	O	O	O	O	O	O	O

This form is made by SJ/T 11364 regulation.  
O: means that hazardous substance content in the homogeneous materials of this part is within the limits of (EU) 2015/863 regulation.  
X: means that hazardous substance content in at least one certain homogeneous material of this part is beyond the limits of (EU) 2015/863 regulation, but there is no mature alternative in the industry at present, it still conforms to the EU RoHS Directive in the scope of exemption.

Notes: Please arrange using time properly as your hearing may be damaged by using the device for a long time.  
Manufacturer: Dongguan Hele Electronics Co., Ltd.  
Address: Daojiao Town, Dongguan City, Guangdong, China

### Overview

In-ear sensor | Touch panel

Touch panel | Tuning hole | LED | Pressure relief hole | Pogo pins | Mic | LED | Charging case button | TYPE-C USB charging port

### How to Connect

**First time connectivity:**  
Open the case and earbuds will auto power-on, pair with each other and turn connectable. On phone, search for QCY-T8 and tap to connect both earbuds to phone.

**Switch connected device:**

- Turn off phone's Bluetooth faculty and earbuds will auto disconnect and turn connectable.
- On phoneB, search for QCY-T8 and tap to connect.

\* Multi-point connection is not available and earbuds will auto reconnect to phoneB upon powering up again.

### How to Wear

- Rotate earbud and pop it into your ear then shake head to check wearing stability.
- Please adjust Mic towards your mouth to gain better calling experience.
- Please wear earbuds properly, making sure they fit in firmly and sound holes are inside ear channels
- You may turn on/off In-ear Detection in APP

**One Press to Enter Pairing Mode**

- Earbuds have been connected with phone.
- Pop earbuds into case. Open lid and hold charging case button for 3s or until LED on case blinks green 3 times. Earbuds will then disconnect to phone and enter pairing mode.

### Mono Mode

- Earbuds were paired before. Keep touching panel on either earbud for 2s to power on them. They will auto turn connectable in 5s(LED will blink blue).
- On phone, search for QCY-T8 and tap to connect the earbud to phone.

**Charge the Earbuds**  
Push earbuds into the case and close the lid. Earbuds will auto turn off and to be charged.

**Charge the Case**  
LED of the case will glow solid red when charging and turn green once topped up.

**Parameters**

Model: TWS Smart Earbuds Pairing name: h2004A  
Bluetooth version: V5.0 Standby time: approx. 60hr  
Charging time: approx. 2hr Music time: approx. 3.5hr  
Talk time: approx. 3hr  
Operation range: 10m(with no obstacle)  
Battery type: Li-Ion  
Battery capacity(earbud): 3.7V 35mAh  
Battery capacity(case): 3.7V 380mAh  
Input parameter(case): 5V = 400mA  
Bluetooth profiles: HSP/HFP/A2DP/AVRCP

### Functions

Functions	Current status	Operation	LED	Prompt
Power-on	Earbuds are not in the case	Keep touching the panel for 2s	LED blinks blue	TONE
	Earbuds are in the case with its lid closed (the case is within power)	Open the lid		
Power-off	Case is within power	Push earbuds into case and close the lid	LED glows solid red when charging	\
	/	Keep touching the panel for 5s	LED glows red for 2s	TONE
Answer/end call	Incoming call/ calling	Double tap the panel to answer/end the call	\	TONE
Ignore call	Incoming call	Keep touching the panel for 1s	\	TONE
Voice assistant	Connected	Triple tap the panel	\	TONE
Music pause/ resume playing	Playing	1. Double tap 2. Put off either earbud to pause and put it on in 1s to resume playing	\	\
Skip track forward	Playing	Keep touching either panel for 2s to skip track forward	\	\

### Warranty Card

Warranty Period  
12 months after you purchase this item.(or you may inquire your local shopper for more details.)  
Free Service:  
Supposing any defects caused by quality issues occur within the warranty period, please take this warranty card and purchase receipts to your distributor for free exchange service.

Model Number: \_\_\_\_\_  
Date of Purchasing: \_\_\_\_\_  
User's Name: \_\_\_\_\_  
User's Address: \_\_\_\_\_  
Shop's Name: \_\_\_\_\_  
Shop's Address: \_\_\_\_\_  
Comments: \_\_\_\_\_

Free exchange service will not be accessed under following circumstances:  
1. Damages caused unauthorized disassembly.  
2. Defects or physical damages caused by leaking or dropping off.  
3. Damages by act of God. Supposing your item is within any damages or defects except the above circumstances, please return to us or your distributor for free repairing.

### FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:  
-- Reorient or relocate the receiving antenna.  
-- Increase the separation between the equipment and receiver.  
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.  
-- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:  
(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

### Hazardous substances and their contents in the item

Part Name	Hazardous Substances									
	Pb	Hg	Cd	Cu	PBB	PSDE	DEHP	DEHP	DEHP	BBP
Main body	X	O	O	O	O	O	O	O	O	O
Battery	O	O	O	O	O	O	O	O	O	O
Ear tips	O	O	O	O	O	O	O	O	O	O
Accessories	O	O	O	O	O	O	O	O	O	O
Charging cable	X	O	O	O	O	O	O	O	O	O

This form is made by SJ/T 11364 regulation.  
O: means that hazardous substance content in the homogeneous materials of this part is within the limits of (EU) 2015/863 regulation.  
X: means that hazardous substance content in at least one certain homogeneous material of this part is beyond the limits of (EU) 2015/863 regulation, but there is no mature alternative in the industry at present, it still conforms to the EU RoHS Directive in the scope of exemption.

Notes: Please arrange using time properly as your hearing may be damaged by using the device for a long time.  
Manufacturer: Dongguan Hele Electronics Co., Ltd.  
Address: Daojiao Town, Dongguan City, Guangdong, China

### How to Wear

- Rotate earbud and pop it into your ear then shake head to check wearing stability.
- Please adjust Mic towards your mouth to gain better calling experience.
- Please wear earbuds properly, making sure they fit in firmly and sound holes are inside ear channels
- You may turn on/off In-ear Detection in APP

**One Press to Enter Pairing Mode**

- Earbuds have been connected with phone.
- Pop earbuds into case. Open lid and hold charging case button for 3s or until LED on case blinks green 3 times. Earbuds will then disconnect to phone and enter pairing mode.

### Mono Mode

- Earbuds were paired before. Keep touching panel on either earbud for 2s to power on them. They will auto turn connectable in 5s(LED will blink blue).
- On phone, search for QCY-T8 and tap to connect the earbud to phone.

**Charge the Earbuds**  
Push earbuds into the case and close the lid. Earbuds will auto turn off and to be charged.

**Charge the Case**  
LED of the case will glow solid red when charging and turn green once topped up.

**Parameters**

Model: TWS Smart Earbuds Pairing name: h2004A  
Bluetooth version: V5.0 Standby time: approx. 60hr  
Charging time: approx. 2hr Music time: approx. 3.5hr  
Talk time: approx. 3hr  
Operation range: 10m(with no obstacle)  
Battery type: Li-Ion  
Battery capacity(earbud): 3.7V 35mAh  
Battery capacity(case): 3.7V 380mAh  
Input parameter(case): 5V = 400mA  
Bluetooth profiles: HSP/HFP/A2DP/AVRCP

### Functions

Functions	Current status	Operation	LED	Prompt
Power-on	Earbuds are not in the case	Keep touching the panel for 2s	LED blinks blue	TONE
	Earbuds are in the case with its lid closed (the case is within power)	Open the lid		
Power-off	Case is within power	Push earbuds into case and close the lid	LED glows solid red when charging	\
	/	Keep touching the panel for 5s	LED glows red for 2s	TONE
Answer/end call	Incoming call/ calling	Double tap the panel to answer/end the call	\	TONE
Ignore call	Incoming call	Keep touching the panel for 1s	\	TONE
Voice assistant	Connected	Triple tap the panel	\	TONE
Music pause/ resume playing	Playing	1. Double tap 2. Put off either earbud to pause and put it on in 1s to resume playing	\	\
Skip track forward	Playing	Keep touching either panel for 2s to skip track forward	\	\

### Warranty Card

Warranty Period  
12 months after you purchase this item.(or you may inquire your local shopper for more details.)  
Free Service:  
Supposing any defects caused by quality issues occur within the warranty period, please take this warranty card and purchase receipts to your distributor for free exchange service.

Model Number: \_\_\_\_\_  
Date of Purchasing: \_\_\_\_\_  
User's Name: \_\_\_\_\_  
User's Address: \_\_\_\_\_  
Shop's Name: \_\_\_\_\_  
Shop's Address: \_\_\_\_\_  
Comments: \_\_\_\_\_

Free exchange service will not be accessed under following circumstances:  
1. Damages caused unauthorized disassembly.  
2. Defects or physical damages caused by leaking or dropping off.  
3. Damages by act of God. Supposing your item is within any damages or defects except the above circumstances, please return to us or your distributor for free repairing.

### FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:  
-- Reorient or relocate the receiving antenna.  
-- Increase the separation between the equipment and receiver.  
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.  
-- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:  
(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

### Hazardous substances and their contents in the item

Part Name	Hazardous Substances									
	Pb	Hg	Cd	Cu	PBB	PSDE	DEHP	DEHP	DEHP	BBP
Main body	X	O	O	O	O	O	O	O	O	O
Battery	O	O	O	O	O	O	O	O	O	O
Ear tips	O	O	O	O	O	O	O	O	O	O
Accessories	O	O	O	O	O	O	O	O	O	O
Charging cable	X	O	O	O	O	O	O	O	O	O

This form is made by SJ/T 11364 regulation.  
O: means that hazardous substance content in the homogeneous materials of this part is within the limits of (EU) 2015/863 regulation.  
X: means that hazardous substance content in at least one certain homogeneous material of this part is beyond the limits of (EU) 2015/863 regulation, but there is no mature alternative in the industry at present, it still conforms to the EU RoHS Directive in the scope of exemption.

Notes: Please arrange using time properly as your hearing may be damaged by using the device for a long time.  
Manufacturer: Dongguan Hele Electronics Co., Ltd.  
Address: Daojiao Town, Dongguan City, Guangdong, China

### How to Wear

- Rotate earbud and pop it into your ear then shake head to check wearing stability.
- Please adjust Mic towards your mouth to gain better calling experience.
- Please wear earbuds properly, making sure they fit in firmly and sound holes are inside ear channels
- You may turn on/off In-ear Detection in APP

**One Press to Enter Pairing Mode**

- Earbuds have been connected with phone.
- Pop earbuds into case. Open lid and hold charging case button for 3s or until LED on case blinks green 3 times. Earbuds will then disconnect to phone and enter pairing mode.

### Mono Mode

- Earbuds were paired before. Keep touching panel on either earbud for 2s to power on them. They will auto turn connectable in 5s(LED will blink blue).
- On phone, search for QCY-T8 and tap to connect the earbud to phone.

**Charge the Earbuds**  
Push earbuds into the case and close the lid. Earbuds will auto turn off and to be charged.

**Charge the Case**  
LED of the case will glow solid red when charging and turn green once topped up.

**Parameters**

Model: TWS Smart Earbuds Pairing name: h2004A  
Bluetooth version: V5.0 Standby time: approx. 60hr  
Charging time: approx. 2hr Music time: approx. 3.5hr  
Talk time: approx. 3hr  
Operation range: 10m(with no obstacle)  
Battery type: Li-Ion  
Battery capacity(earbud): 3.7V 35mAh  
Battery capacity(case): 3.7V 380mAh  
Input parameter(case): 5V = 400mA  
Bluetooth profiles: HSP/HFP/A2DP/AVRCP

### Functions

Functions	Current status	Operation	LED	Prompt
Power-on	Earbuds are not in the case	Keep touching the panel for 2s	LED blinks blue	TONE
	Earbuds are in the case with its lid closed (the case is within power)	Open the lid		
Power-off	Case is within power	Push earbuds into case and close the lid	LED glows solid red when charging	\
	/	Keep touching the panel for 5s	LED glows red for 2s	TONE
Answer/end call	Incoming call/ calling	Double tap the panel to answer/end the call	\	TONE
Ignore call	Incoming call	Keep touching the panel for 1s	\	TONE
Voice assistant	Connected	Triple tap the panel	\	TONE
Music pause/ resume playing	Playing	1. Double tap 2. Put off either earbud to pause and put it on in 1s to resume playing	\	\
Skip track forward	Playing	Keep touching either panel for 2s to skip track forward	\	\

### Warranty Card

Warranty Period  
12 months after you purchase this item.(or you may inquire your local shopper for more details.)  
Free Service:  
Supposing any defects caused by quality issues occur within the warranty period, please take this warranty card and purchase receipts to your distributor for free exchange service.

Model Number: \_\_\_\_\_  
Date of Purchasing: \_\_\_\_\_  
User's Name: \_\_\_\_\_  
User's Address: \_\_\_\_\_  
Shop's Name: \_\_\_\_\_  
Shop's Address: \_\_\_\_\_  
Comments: \_\_\_\_\_