

Product Overview

1. Multi-function Button
2. Microphone
3. Micro USB Charging Port
4. Speaker
5. LED Indicator

Product Information

- ✧ Bluetooth V3.0
- ✧ Support HSP&HFP and Dual connection.
- ✧ Micro USB connector of the headset allows charging via USB charging cable connecting with computer USB port.
- ✧ Perfect sound quality, humanized design and innovative conception.
- ✧ Mini, compact and fashionable shape.
- ✧ When the battery capacity of cell phone or Bluetooth Headset is low, the signal weakens. The red light will flicker and warning tones will sound every 20 seconds. Please charge it immediately.

Care for your Bluetooth Headset

- ✧ Please protect it from all liquids and do not expose the Bluetooth Headset to extreme temperatures or rapid changes of hot to cold or vice versa.
- ✧ Please do not drop the Bluetooth Headset. The warranty does not cover damage due to breakage or mis-handling.
- ✧ Please do not open up the Bluetooth Headset. There are no user serviceable parts inside and the warranty becomes invalid.

Charge

- ✧ Connect the USB charging cable with the Micro USB charging port of the headset.
- ✧ The red indicator light on indicating the headset is being charged.
- ✧ The charging will take 2-3hrs; after charging, the blue light is on, indicates the charging is completed.
- ✧ Before the first use, the battery must be fully charged.
- ✧ Helpful hints: Extend battery life, it is recommended to charge the headset at least once a month.

Power-on

- ✧ When the Bluetooth Headset is used for the first time, press & hold the multi-function button until blue and red light flicker alternately, then entering into pairing mode .
- ✧ If the Bluetooth headset is reused, press & hold the multi-function button until blue light flickers, then please release the button, it will enter into reconnection mode, the headset will automatically search the latest connected mobile phone.

Pair with the Mobile Phone

- ✧ The pairing distance between mobile phone & the headset should be within 1m.
- ✧ Power on the Bluetooth headset until the blue and red lights flicker alternately and then come into the pairing mode for the first time. From then on, it will come to an automatic pairing with the latest connected mobile phone only with the flickers of the blue light.
- ✧ Switch to the Bluetooth function of the mobile phone and activate searching until the mobile phone finds the Bluetooth headset's pairing name for connection; if necessary, input the password "0000".

Receive a Call

When there is a call, press the multi-function button of the headset once to receive it.

Microphone Mute

- ✧ In call, double click (twice quickly) the multi-function button to actuate the microphone mute.
- ✧ In the Mute Mode, double click (twice quickly) the multi-function button to cancel microphone mute and to actuate the call.

End a Call

After the call is over, press the multi-function button once to end it.

Refuse a Call

When there is a call, press & hold the multi-function button for 1S to refuse it.

Voice Dialing

In the standby mode, press the multi-function button of the Bluetooth Headset once to activate the voice dialing function.

Redial

In the standby mode, redial the last call and double click (twice quickly) the multi-function button to achieve the redialing function.

Default Settings

Charge it and press & hold the multi-function button, the blue and red lights flicker 3 times alternately, then the Bluetooth headset complete Default Settings.

Power off

Press & hold the multi-function button until seeing the red light, then the headset is powered off

Indicator Lamp Status

- ✧ Power-on: Blue light flickering .
- ✧ Power-off: Red light flickering
- ✧ Pairing mode: Blue and red alternative.
- ✧ Standby mode: Blue light flickering
- ✧ Battery Capacity Low: Red light flickering and you hear alert sound
- ✧ Charging: Red light on.
- ✧ Charging over: Blue light on.

Information to Users

According to the FCC Part 15.19, 15.21, and 15.105 rules, for this EUT, the instructions or operation manual furnished the user shall include the following or similar statement, placed in a prominent location in the text of the manual:

FCC Warning

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

NOTE 2: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.