



# RF EXPOSURE REPORT

**REPORT NO.:** RF920910H03

**MODEL NO.:** A300-2

**ACCORDING:** FCC Guidelines for Human Exposure  
IEEE C95.1

**APPLICANT:** Extreme Networks

**ADDRESS:** 3585 Monroe Street Santa Clara CA 05051

**ISSUED BY:** Advance Data Technology Corporation

**LAB LOCATION:** 47 14th Lin, Chiapau Tsun, Linko, Taipei,  
Taiwan, R.O.C.



Lab Code: 200376-0



## RF Exposure Measurement

### 1. Introduction

In this document, we try to prove the safety of radiation harmfulness to the human body for our product. The limit for Maximum Permissible Exposure (MPE) specified in FCC 1.1310 is followed. The Gain of the antenna used in this product is measured in a Fully Anechoic Chamber (FAC) calibrated for antenna measurement in ADT, and also the maximum total power input to the antenna is measured. Through the Friis transmission formula and the maximum gain of the antenna, we can calculate the distance, away from the product, where the limit of MPE is reached.

Although the Friis transmission formula is a far field assumption, the calculated result of that is an over-prediction for near field power density. We will take that as the worst case to specify the safety range.

### 2. RF Exposure Limit

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environmental impact of human exposure to radio-frequency (RF) radiation as specified in 1.1307(b)

#### LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm <sup>2</sup> )	Average Time (minutes)
<b>(A)Limits For Occupational / Control Exposures</b>				
300-1500	...	...	F/300	6
1500-100,000	...	...	5	6
<b>(B)Limits For General Population / Uncontrolled Exposure</b>				
300-1500	...	...	F/1500	6
1500-100,000	...	...	1.0	30

F = Frequency in MHz



### 3. Friis Formula

Friis transmission formula :  $P_d = (P_{out} * G) / (4 * \pi * r^2)$

where

$P_d$  = power density in mW/cm<sup>2</sup>

$P_{out}$  = output power to antenna in mW

$G$  = gain of antenna in linear scale

$\pi$  = 3.1416

$R$  = distance between observation point and center of the radiator in cm

$P_d$  is the limit of MPE, 1 mW/cm<sup>2</sup>. If we know the maximum Gain of the antenna and the total power input to the antenna, through the calculation, we will know the MPE value at distance 20cm.

Ref. : David K. Cheng, *Field and Wave Electromagnetics*, Second Edition,  
Page 640, Eq. (11-133).

### 4 EUT Operating condition

The software provided by Manufacturer enabled the EUT to transmit and receive data at lowest, middle and highest channel individually.

### 5. Classification

This device is not fixed inside the host equipment, it is connected with host through wire. So it is easy to be re-located in the place where at least 20 cm far away from the body of the user. Warning statement to the user for keeping at least 20cm or more separation distance with the antenna should be included in users manual. So, this device is classified as **Mobile Device**.



**6 Test Results**

**6.1 Antenna Gain**

For Antenna 1:

The maximum Gain measured in Fully Anechoic Chamber are 1.5dBi or 1.41(numeric) 2.4GHz and 4.5dBi or 2.82(numeric) for 5GHz.

For Antenna 2:

The maximum Gain measured in Fully Anechoic Chamber are 6dBi or 3.98(numeric).

**6.2 Output Power Into Antenna & RF Exposure value at distance 20cm:**

For Antenna 1:

For Part 802.11b:

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
1	2412	36.56	0.011	1.0
6	2437	67.61	0.019	1.0
11	2462	33.81	0.010	1.0

For Part 802.11g:

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
1	2412	41.98	0.012	1.0
6	2437	66.07	0.019	1.0
11	2462	39.90	0.011	1.0



### FOR FREQUENCY 5.15~5.35GHz

#### Normal Mode :

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
1	5180	32.58	0.018	1.0
4	5240	34.43	0.019	1.0
5	5260	97.72	0.055	1.0
8	5320	32.66	0.018	1.0

#### Turbo Mode :

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
1	5210	32.58	0.018	1.0
2	5250	35.73	0.020	1.0
3	5290	36.06	0.020	1.0

### FOR FREQUENCY 5.725~5.850GHz

#### Normal Mode :

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
9	5745	120.23	0.067	1.0
11	5785	109.65	0.061	1.0
13	5825	125.89	0.071	1.0

#### Turbo Mode :

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
4	5760	107.15	0.060	1.0
5	5800	102.33	0.057	1.0



**For Antenna 2:  
For Part 802.11b:**

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
1	2412	31.38	0.017	1.0
6	2437	23.44	0.019	1.0
11	2462	20.32	0.016	1.0

**For Part 802.11g:**

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
1	2412	21.88	0.017	1.0
6	2437	38.02	0.030	1.0
11	2462	20.84	0.017	1.0



### FOR FREQUENCY 5.15~5.35GHz

#### Normal Mode :

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
5	5260	41.02	0.032	1.0
8	5320	59.16	0.047	1.0

#### Turbo Mode :

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
3	5290	19.68	0.016	1.0

### FOR FREQUENCY 5.725~5.850GHz

#### Normal Mode :

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
9	5745	120.23	0.095	1.0
11	5785	109.65	0.087	1.0
13	5825	125.89	0.010	1.0

#### Turbo Mode :

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
4	5760	107.15	0.085	1.0
5	5800	102.33	0.081	1.0