



## Chuango Security Technology Corporation

Application  
For  
Certification

**FCC ID: RJYWK8000**

**Wireless Keypad**

**Model: WK8000**

Report No.: 160607010SZN-001

We hereby certify that the sample of the above item is considered to comply with the requirements of FCC Part 15, Subpart C for Intentional Radiator, mention 47 CFR [10-1-15]

Prepared and Checked by:

Approved by:

Sign on file

Leo Lai  
Senior Project Engineer

---

Kidd Yang  
Senior Project Engineer  
Date: June 30, 2016

- The test results reported in this test report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report is for the exclusive use of Intertek's Client and is provided pursuant to the agreement between Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this report. Only the Client is authorized to copy or distribute this report. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek. The observations and test results referenced from this report are relevant only to the sample tested. This report by itself does not imply that the material, product, or service is or has ever been under an Intertek certification program.
- For Terms And Conditions of the services, it can be provided upon request.
- The evaluation data of the report will be kept for 3 years from the date of issuance.

TRF No.: FCC 15C\_TX\_b

**Intertek Testing Services Shenzhen Ltd. Kejiyuan Branch**

6F, D Block, Huahan Building, Langshan Road, Nanshan District, Shenzhen, P. R. China

Tel: (86 755) 8601 6288 Fax: (86 755) 8601 6751 Website: [www.china.intertek-etlsemko.com](http://www.china.intertek-etlsemko.com)

---

## INTERTEK TESTING SERVICES

---

### LIST OF EXHIBITS

#### *INTRODUCTION*

<i>EXHIBIT 1:</i>	General Description
<i>EXHIBIT 2:</i>	System Test Configuration
<i>EXHIBIT 3:</i>	Emission Results
<i>EXHIBIT 4:</i>	Equipment Photographs
<i>EXHIBIT 5:</i>	Product Labelling
<i>EXHIBIT 6:</i>	Technical Specifications
<i>EXHIBIT 7:</i>	Instruction Manual
<i>EXHIBIT 8:</i>	Miscellaneous Information
<i>EXHIBIT 9:</i>	Confidentiality Request
<i>EXHIBIT 10:</i>	Test Equipment List

---

---

# INTERTEK TESTING SERVICES

---

---

## MEASUREMENT/TECHNICAL REPORT

### Chuango Security Technology Corporation

Model: WK8000

Wireless Keypad

FCC ID: RJYWK8000

This report concerns (check one)      Original Grant       Class II Change

Equipment Type: DXX - Part 15 Low Power Communication Device Transmitter

---

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)?      Yes       No

If yes, defer until: \_\_\_\_\_  
date

Company Name agrees to notify the Commission by: \_\_\_\_\_  
date

of the intended date of announcement of the product so that the grant can be issued on that date.

---

Transition Rules Request per 15.37?      Yes       No

If no, assumed Part 15, Subpart C for intentional radiator – the new 47 CFR [10-1-15 Edition] provision.

---

Report prepared by:

Leo Lai  
Intertek Testing Services Shenzhen Ltd.  
Kejiyuan Branch  
6F, Block D, Huahan Building, Langshan Road,  
Nanshan District, Shenzhen, P. R. China  
Phone: (86 755) 8601 6288  
Fax: (86 755) 8601 6751

---

---

TRF No.: FCC 15C\_TX\_b  
FCC ID: RJYWK8000  
Report: 160607010SZN-001

---

---

# INTERTEK TESTING SERVICES

---

---

## Table of Contents

<b>1.0 General Description</b> .....	2
1.1 Product Description .....	2
1.2 Related Submittal(s) Grants .....	2
1.3 Test Methodology .....	2
1.4 Test Facility .....	2
<b>2.0 System Test Configuration</b> .....	4
2.1 Justification .....	4
2.2 EUT Exercising Software .....	4
2.3 Special Accessories .....	4
2.4 Equipment Modification .....	4
2.5 Measurement Uncertainty .....	5
2.6 Support Equipment List and Description .....	5
<b>3.0 Emission Results</b> .....	7
3.1 Radiated Test Results .....	8
3.1.1 Field Strength Calculation .....	8
3.1.2 Radiated Emission Configuration Photograph .....	9
3.1.3 Radiated Emissions .....	9
3.1.4 Transmitter Spurious Emissions .....	11
<b>4.0 Equipment Photographs</b> .....	14
<b>5.0 Product Labelling</b> .....	16
<b>6.0 Technical Specifications</b> .....	18
<b>7.0 Instruction Manual</b> .....	20
<b>8.0 Miscellaneous Information</b> .....	22
8.1 Bandedge Plot .....	23
8.2 Discussion of Pulse Desensitization .....	24
8.3 Calculation of Average Factor .....	26
8.4 Emissions Test Procedures .....	26
<b>9.0 Confidentiality Request</b> .....	29
<b>10.0 Test Equipment List</b> .....	31

---

## INTERTEK TESTING SERVICES

---

List of attached file

Exhibit type	File Description	Filename
Test Report	Test Report	report.pdf
Test Setup Photo	Radiated Emission	radiated photos.pdf
Test Report	20dB BW Plot	bw.pdf
Test Report	Timing Plot	af.pdf
External Photo	External Photo	external photos.pdf
Internal Photo	Internal Photo	internal photos.pdf
Block Diagram	Block Diagram	block.pdf
Schematics	Circuit Diagram	circuit.pdf
Operation Description	Technical Description	descri.pdf
ID Label/Location	Label Artwork and Location	label.pdf
User Manual	User Manual	manual.pdf
Cover Letter	Confidentiality Letter	request.pdf
Cover Letter	Letter of Agency	agency.pdf

**EXHIBIT 1**  
**GENERAL DESCRIPTION**

# INTERTEK TESTING SERVICES

---

## 1.0 General Description

### 1.1 Product Description

The equipment under test (EUT) is a Wireless Keypad. The EUT was powered by DC 3.0V (2\*1.5V AAA batteries) and operating at 915MHz. For more detail information pls. refer to the user manual.

Antenna Type: Integral antenna

Modulation Type: ASK

For electronic filing, the brief circuit description is saved with filename: descri.pdf.

### 1.2 Related Submittal(s) Grants

This is an application of certification for the Wireless Keypad operating at 915MHz, and for the wireless keypad operating at 125kHz in which all emissions are at least 40 dB below the limits in § 15.209 was tested and demonstrated in report 160607010SZN-002.

### 1.3 Test Methodology

Radiated emission measurements were performed according to the procedures in ANSI C63.10 (2013). Radiated emission measurement was performed in Semi-anechoic chamber. For radiated emission measurement, preliminary scans were performed in the semi-anechoic chamber only to determine the worst case modes. All radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the "**Justification Section**" of this Application. All other measurements were made in accordance with the procedures in part 2 of CFR 47.

### 1.4 Test Facility

The Semi-anechoic chamber used to collect the radiated data is **Intertek Testing Services Shenzhen Ltd. Kejiyuan Branch** and located at 6F, D Block, Huahan Building, Langshan Road, Nanshan District, Shenzhen, P. R. China. This test facility and site measurement data have been fully placed on file with the FCC(Registration Number: 242492).

**EXHIBIT 2**  
**SYSTEM TEST CONFIGURATION**



## **INTERTEK TESTING SERVICES**

---

---

### **2.0 System Test Configuration**

#### **2.1 Justification**

The system was configured for testing in a typical fashion (as a customer would normally use it), and in the confines as outlined in ANSI C63.10 (2013).

The EUT was powered by new 2 x 1.5V “AAA” batteries during the test. Only the worst case data was reported.

For maximizing emissions, the EUT was rotated through 360°, the antenna height was varied from 1 meter to 4 meters above the ground plane, and the antenna polarization was changed. This step by step procedure for maximizing emissions led to the data reported in Exhibit 3.

The unit was operated standalone and placed in the centre of the turntable.

The equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). The EUT was placed on a turn table, which enabled the engineer to maximize emissions through its placement in the three orthogonal axes.

#### **2.2 EUT Exercising Software**

The EUT exercise program (provided by client) used during testing was designed to exercise the various system components in a manner similar to a typical use.

#### **2.3 Special Accessories**

No special accessories used.

#### **2.4 Equipment Modification**

Any modifications installed previous to testing by Chuango Security Technology Corporation will be incorporated in each production model sold / leased in the United States.

No modifications were installed by Intertek Testing Services Shenzhen Ltd Kejiyuan Branch.

## INTERTEK TESTING SERVICES

---

### 2.5 Measurement Uncertainty

When determining the test conclusion, the Measurement Uncertainty of test has been considered.

### 2.6 Support Equipment List and Description

Description	Manufacturer	Model No.
N/A	N/A	N/A

**EXHIBIT 3**  
**EMISSION RESULTS**

## INTERTEK TESTING SERVICES

---

### 3.0 Emission Results

Data is included worst-case configuration (the configuration which resulted in the highest emission levels).

## INTERTEK TESTING SERVICES

---

### 3.1 Radiated Test Results

A sample calculation, configuration photographs and data tables of the emissions are included.

#### 3.1.1 Field Strength Calculation

The field strength is calculated by adding the reading on the Spectrum Analyzer to the factors associated with preamplifiers (if any), antennas, cables, pulse desensitization and average factors (when specified limit is in average and measurements are made with peak detectors). A sample calculation is included below.

$$FS = RA + AF + CF - AG$$

Where            FS = Field Strength in dB $\mu$ V/m  
                    RA = Receiver Amplitude (including preamplifier) in dB $\mu$ V  
                    CF = Cable Attenuation Factor in dB  
                    AF = Antenna Factor in dB  
                    AG = Amplifier Gain in dB

In the radiated emission table which follows, the reading shown on the data table may reflect the preamplifier gain. An example of the calculations, where the reading does not reflect the preamplifier gain, follows:

$$FS = RA + AF + CF - AG$$

Assume a receiver reading of 62.0 dB $\mu$ V is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted. The net field strength for comparison to the appropriate emission limit is 42 dB $\mu$ V/m. This value in dB $\mu$ V/m was converted to its corresponding level in  $\mu$ V/m.

RA = 62.0 dB $\mu$ V  
AF = 7.4 dB  
CF = 1.6 dB  
AG = 29.0 dB

$$FS = 62 + 7.4 + 1.6 - 29 + 0 = 42 \text{ dB}\mu\text{V/m}$$

$$\text{Level in } \mu\text{V/m} = \text{Common Antilogarithm} [(42 \text{ dB}\mu\text{V/m})/20] = 125.9 \mu\text{V/m}$$

## INTERTEK TESTING SERVICES

---

### 3.1.2 Radiated Emission Configuration Photograph

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: radiated photos. pdf.

### 3.1.3 Radiated Emissions

The data on the following page lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit. Simultaneous transmitting was considered during the testing.

Worst Case Radiated Emission  
at  
915.000 MHz

Judgement: Passed by 0.7 dB

#### **TEST PERSONNEL:**

*Sign on file*

Leo Lai                      Engineer  
*Typed/Printed Name*

June 14, 2016  
*Date*

---

---

## INTERTEK TESTING SERVICES

---

---

Applicant: Chuango Security Technology Corporation  
Date of Test: June 14, 2016  
Model: WK8000  
Sample: 1/1  
Worst Case Operating Mode: Transmitting

Table 1

### Radiated Emissions

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Net at 3m (dB $\mu$ V/m)	Limit at 3m (dB $\mu$ V/m)	Margin (dB)
Horizontal	38.245	24.3	20.0	18.1	22.4	40.0	-17.6
Horizontal	45.035	31.1	20.0	8.8	19.9	40.0	-20.1
Horizontal	79.470	32.7	20.0	11.6	24.3	40.0	-15.7
Horizontal	97.900	21.2	20.0	13.8	15.0	43.5	-28.5
Horizontal	110.995	25.1	20.0	8.9	14.0	43.5	-29.5
Horizontal	915.000	103.8	20.0	9.5	93.3	94.0	-0.7

- NOTES: 1. Quasi-Peak detector is used except for others stated.
2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distances were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
3. Negative value in the margin column shows emission below limit.
4. All emissions are below the QP limit.

## INTERTEK TESTING SERVICES

---

### 3.1.4 Transmitter Spurious Emissions (Radiated)

Worst Case Radiated Emission  
at  
1830.000 MHz

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: radiated photos. pdf.

The data on the following page lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit.

Judgement: Passed by 7.5 dB

#### **TEST PERSONNEL:**

*Sign on file*

Leo Lai            Engineer  
*Typed/Printed Name*

June 14, 2016  
*Date*



## INTERTEK TESTING SERVICES

---

Applicant: Chuango Security Technology Corporation  
 Date of Test: June 14, 2016  
 Model: WK8000  
 Sample: 1/1  
 Mode: Transmitting

Table 2  
**Radiated Emissions**

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Net at 3m (dB $\mu$ V/m)	Peak Limit at 3m (dB $\mu$ V/m)	Margin (dB)
Horizontal	1830.000	61.6	37.2	30.9	55.3	74.0	-18.7
Horizontal	2745.000	51.8	37.2	32.6	47.2	74.0	-26.8
Horizontal	3660.000	55.8	37.1	32.5	51.2	74.0	-22.8

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Average Factor (-dB)	Net at 3m (dB $\mu$ V/m)	AV Limit at 3m (dB $\mu$ V/m)	Margin (dB)
Horizontal	1830.000	61.6	37.2	30.9	8.8	46.5	54.0	-7.5
Horizontal	2745.000	51.8	37.2	32.6	8.8	38.4	54.0	-15.6
Horizontal	3660.000	55.8	37.1	32.5	8.8	42.4	54.0	-11.6

- Notes:
1. Peak detector is used except for others stated.
  2. All measurements were made at 3 meters. Radiated emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other radiated emissions than those reported were detected at a test distance of 0.3-meter.
  3. Negative value in the margin column shows emission below limit.
  4. Horn antenna used for the emission over 1000MHz.

Test Engineer: Leo Lai

**EXHIBIT 4**  
**EQUIPMENT PHOTOGRAPHS**

## INTERTEK TESTING SERVICES

---

### 4.0 Equipment Photographs

For electronic filing, the photographs of the tested EUT are saved with filename: external photos.pdf & internal photos.pdf.

# INTERTEK TESTING SERVICES

---

## EXHIBIT 5 PRODUCT LABELLING

## INTERTEK TESTING SERVICES

---

### 5.0 **Product Labelling**

For electronic filing, the FCC ID label artwork and the label location are saved with filename: label.pdf.

# **INTERTEK TESTING SERVICES**

---

## **EXHIBIT 6**

### **TECHNICAL SPECIFICATIONS**

## INTERTEK TESTING SERVICES

---

### 6.0 Technical Specifications

For electronic filing, the block diagram and schematics of the tested EUT are saved with filename: block.pdf and circuit.pdf respectively.

# **INTERTEK TESTING SERVICES**

---

## **EXHIBIT 7**

### **INSTRUCTION MANUAL**

---

TRF No.: FCC 15C\_TX\_b  
FCC ID: RJYWK8000  
Report: 160607010SZN-001



## INTERTEK TESTING SERVICES

---

### 7.0 Instruction Manual

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf.

This manual will be provided to the end-user with each unit sold/leased in the United States.

**INTERTEK TESTING SERVICES**

---

**EXHIBIT 8**

**MISCELLANEOUS INFORMATION**

---

TRF No.: FCC 15C\_TX\_b  
FCC ID: RJYWK8000  
Report: 160607010SZN-001

## INTERTEK TESTING SERVICES

---

### 8.0 **Miscellaneous Information**

This miscellaneous information includes details of the measured bandedge, the test procedure and calculation of factor such as pulse desensitization.

## INTERTEK TESTING SERVICES

---

### 8.1 Bandedge Plot

Pursuant to FCC part 15 Section 15.215(c), the 20dB bandwidth of the emission was contained within the frequency band designated (mentioned as above) which the EUT operated. The effects, if any, from frequency sweeping, frequency hopping, other modulation techniques and frequency stability over excepted variations in temperature and supply voltage were considered.

Figure 8.1 Bandwidth

## INTERTEK TESTING SERVICES

---

### 8.2 Discussion of Pulse Desensitization

Pulse desensitivity is not applicable for this device. With a resolution bandwidth (3 dB) of 100kHz, the pulse desensitivity factor was 0 dB.

---

## INTERTEK TESTING SERVICES

---

### 8.3 Calculation of Average Factor

Averaging factor in dB =  $20 \log$  (duty cycle)

The specification for output field strengths in accordance with the FCC rules specify measurements with an average detector. During testing, a spectrum analyzer incorporating a peak detector was used. Therefore, a reduction factor can be applied to the resultant peak signal level and compared to the limit for measurement instrumentation incorporating an average detector.

The time period over which the duty cycle is measured is 100 milliseconds, or the repetition cycle, whichever is a shorter time frame. The worst case (highest percentage on) duty cycle is used for the calculation. The duty cycle is measured by placing the spectrum analyzer in zero scan (receiver mode) and linear mode at maximum bandwidth (3 MHz at 3 dB down) and viewing the resulting time domain signal output from the analyzer on a Tektronix oscilloscope. The oscilloscope is used because of its superior time base and triggering facilities.

A plot of the worst-case duty cycle as detected in this manner are saved with filename: af.pdf

The duty cycle is simply the on-time divided by the period:

The duration of one cycle = 72.174 ms

Effective period of the cycle =  $1.739 \text{ ms} \times 9 + 0.652 \text{ ms} \times 16 = 26.083 \text{ ms}$

DC =  $26.083 \text{ ms} / 72.174 \text{ ms} = 0.361$  or 36.1%

Therefore, the averaging factor is found by  $20 \log_{10} 0.361 = -8.8 \text{ dB}$

## **INTERTEK TESTING SERVICES**

---

### **8.4 Emissions Test Procedures**

The following is a description of the test procedure used by Intertek Testing Services in the measurements of transmitters operating under Part 15, Subpart C rules.

The test set-up and procedures described below are designed to meet the requirements of ANSI C63.10 - 2013.

The transmitting equipment under test (EUT) is placed on a polyethylene turntable which is four feet in diameter above the ground plane and approximately 0.8 meter in height for emission up to 1GHz and 1.5 meter above 1GHz. During the radiated emissions test, the turntable is rotated and any cables leaving the EUT are manipulated to find the configuration resulting in maximum emissions. The EUT is adjust through all three orthogonal axes to obtain maximum emission levels. The antenna height and polarization are varied during the testing to search for maximum signal levels.

Detector function for radiated emissions above 1GHz is in peak mode and Quasi-Peak mode is used below 1GHz. Average readings, when required, are taken by measuring the duty cycle of the equipment under test and subtracting the corresponding amount in dB from the measured peak readings.

The frequency range scanned is from the lowest radio frequency signal generated in the device which is greater than 9 kHz to the tenth harmonic of the highest fundamental frequency or 40 GHz, whichever is lower.

## INTERTEK TESTING SERVICES

---

### 8.4 Emissions Test Procedures (cont'd)

The EUT is warmed up for 15 minutes prior to the test.

AC power to the unit is varied from 85% to 115% nominal and variation in the fundamental emission field strength is recorded. If battery powered, a new, fully charged battery is used.

Conducted measurements are made as described in ANSI C63.10 - 2013.

The IF bandwidth used for measurement of radiated signal strength was 10 kHz for emission below 30 MHz and 120 kHz for emission from 30 MHz to 1000 MHz. Where pulsed transmissions of short enough pulse duration warrant, a greater bandwidth is selected according to the recommendations of Hewlett Packard Application Note 150-2. Above 1000 MHz, a resolution bandwidth of 1 MHz is used.

Transmitter measurements are normally conducted at a measurement distance of three meters. However, to assure low enough noise floor in the restricted bands and above 1 GHz, signals are acquired at a distance of one meter or less. All measurements are extrapolated to three meters using inverse scaling, but those measurements taken at a closer distance are so marked.



**INTERTEK TESTING SERVICES**

---

**EXHIBIT 9**

**CONFIDENTIALITY REQUEST**

## INTERTEK TESTING SERVICES

---

### 9.0 Confidentiality Request

For electronic filing, the confidentiality request of the tested EUT is saved with filename: request.pdf.

**INTERTEK TESTING SERVICES**

---

**EXHIBIT10  
TEST EQUIPMENT LIST**

---

TRF No.: FCC 15C\_TX\_b  
FCC ID: RJYWK8000  
Report: 160607010SZN-001

## INTERTEK TESTING SERVICES

---

### 10.0 Test Equipment List

Equipment No.	Equipment	Manufacturer	Model No.	Serial No.	Cal. Date	Due Date
SZ061-12	BiConiLog Antenna	ETS	3142E	00166158	15-Sep-15	15-Sep-16
SZ061-07	Pyramidal Horn Antenna	ETS	3160-09	00083067	29-Mar-16	29-Mar-17
SZ061-08	Horn Antenna	ETS	3115	00092346	17-Oct-15	17-Oct-16
SZ061-06	Active Loop Antenna	Electro-Metrics	EM-6876	217	11-May-16	11-May-17
SZ056-06	Signal Analyzer	R&S	FSV40	Oct-76	8-Jul-15	8-Jul-16
SZ181-04	Preamplifier	Agilent	8449B	3008A02474	23-Jan-16	23-Jan-17
SZ188-01	Anechoic Chamber	ETS	RFD-F/A-100	4102	16-Apr-16	16-Apr-18
SZ062-02	RF Cable	RADIALL	RG 213U	Jan-00	30-Dec-15	30-Jun-16
SZ062-05	RF Cable	RADIALL	0.04-26.5GHz	0833254	6-Apr-16	6-Oct-16
SZ062-12	RF Cable	RADIALL	0.04-26.5GHz	083387	6-Apr-16	6-Oct-16
SZ067-11	Highpass Filter	Wainwright	WHKX1.0/15G-10SS	16	15-Jun-15	15-Jun-16

-----END-----