

## SPECIFICATION AND USER MANUAL

Model NO.	MX803	TYPE	wireless mouse
MP DATE		DATE	2019-11-05



	Item	Specification	Item	Specification
The basic specifications	mouse type	wireless mouse	KEY amount	3D 3key
	Battery Type	1 AA battery	Mouse size (length * width * height)	111.7*60.8*37mm
	Working mode	Photoelectricity (red light)	Mouse net weight (bare)	72.8±5g
	DPI	1000	DONGLE size (length * width * height)	13.2*14.6*6.5mm
			DONGLE Net weight (bare)	2±0.5g
			sensor	KA8
			Key life	More than 1 million times
			Working Distance	8-10m
			Working Distance	Windows98/ME/2000/XP/Vista/Win7/Win8/MAC/LINUX
electric	IC mouse model	PAN207	DONGLE IC model	846+006F

Main parameter	Mouse operating voltage	DC1.5V	DONGLE Working voltage	USB 4.5V to 5.25VDC
	Mouse operating current	14mA	DONGLE operating current	≤50mA
	Mouse sleep current	≤0.1mA	DONGLE sleep current	≤3mA
	Working frequency	2.404-2.478GHZ	Battery life	180 days
Other parameters	Operation Temperature	0~45°C	Storage Temperature	-20~+60°C
	Operating humidity	20~90%	Storage Temperature	≤93% (40°C)
Feature selling point of complete machine	1	Powered by 1 AA battery, the service life is up to 180 days.		
	2	Ergonomic design		
	3	Effective working distance up to 10 meters, strong anti-interference ability.		
	4	Code free, the mouse power, plug into the receiver, not only can automatically code, when the mouse and the receiver successfully connected, if not recharged, will not be connected to other receivers or the mouse.		
	5			

Instructions:

1. Unpack the product package, open the battery cover, take out the receiver inside and plug it into the USB port of the computer;
2. Take the battery, press the positive and negative polarity into the mouse battery slot, close the battery cover;
3. When using this mouse for the first time, the system may need to install USB driver, then the computer will automatically search and install the mouse driver;

After the completion of the driver installation, the mouse can be used for normal work;

FCC Caution

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

---

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

AIKUN COMPANY LTD.