


[TestMode: TX highest channel]; [Polarity: Vertical]



Site	Polarization: <i>Vertical</i>	Temperature: (C)
Limit: FCC Part15 (PK)	Power:	Humidity: %RH
EUT: Loudbox		
M/N: Artist		
Mode: TX-H		
Note:		

No.	Mk.	Freq.	Reading Level	Correct Factor	Measure- ment	Limit	Over					
							MHz	dBuV	dB/m	dBuV/m	dB	Detector
1	*	2483.500	43.61	-3.96	39.65	74.00	-34.35	peak				
2		2500.000	43.08	-4.00	39.08	74.00	-34.92	peak				

Test Result: Pass

19 ANTENNA REQUIREMENT

Test Standard	47 CFR Part 15, Subpart C 15.247
Test Method	N/A


19.1 CONCLUSION

Standard Requirement:

An intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device. The use of a antenna that uses a unique coupling to the intentional radiator, the manufacturer may design the unit permanently attached antenna or of an so that a broken antenna can be replaced by the user, but the use of a standard antenna jack or electrical connector is prohibited.

EUT Antenna:

The antenna is integrated on the main PCB and no consideration of replacement. The best case gain of the antenna is 2dBi.




20 CONDUCTED SPURIOUS EMISSIONS

Test Standard	47 CFR Part 15, Subpart C 15.247
Test Method	ANSI C63.10 (2013) Section 7.8.6 & Section 11.11
Test Mode (Pre-Scan)	TX
Test Mode (Final Test)	TX
Tester	Charlie
Temperature	25 °C
Humidity	60%

20.1 LIMITS

Limit:	In any 100 kHz bandwidth outside the frequency band in which the spread spectrum or digitally modulated intentional radiator is operating, the radio frequency power that is produced by the intentional radiator shall be at least 20 dB below that in the 100 kHz bandwidth within the band that contains the highest level of the desired power, based on either an RF conducted or a radiated measurement, provided the transmitter demonstrates compliance with the peak conducted power limits. If the transmitter complies with the conducted power limits based on the use of RMS averaging over a time interval, as permitted under paragraph (b)(3) of this section, the attenuation required under this paragraph shall be 30 dB instead of 20 dB. Attenuation below the general limits specified in §15.209(a) is not required. In addition, radiated emissions which fall in the restricted bands, as defined in §15.205(a), must also comply with the radiated emission limits specified in §15.209(a) (see §15.205(c)).
---------------	--

20.2 BLOCK DIAGRAM OF TEST SETUP



20.3 TEST DATA

Pass: Please Refer To Appendix: Appendix1 For Details

BlueAsia


21 CONDUCTED BAND EDGES MEASUREMENT

Test Standard	47 CFR Part 15, Subpart C 15.247
Test Method	ANSI C63.10 (2013) Section 7.8.8 & Section 11.13.3.2
Test Mode (Pre-Scan)	TX
Test Mode (Final Test)	TX
Tester	Charlie
Temperature	25 °C
Humidity	60%

21.1 LIMITS

Limit:	In any 100 kHz bandwidth outside the frequency band in which the spread spectrum or digitally modulated intentional radiator is operating, the radio frequency power that is produced by the intentional radiator shall be at least 20 dB below that in the 100 kHz bandwidth within the band that contains the highest level of the desired power, based on either an RF conducted or a radiated measurement, provided the transmitter demonstrates compliance with the peak conducted power limits. If the transmitter complies with the conducted power limits based on the use of RMS averaging over a time interval, as permitted under paragraph (b)(3) of this section, the attenuation required under this paragraph shall be 30 dB instead of 20 dB. Attenuation below the general limits specified in §15.209(a) is not required. In addition, radiated emissions which fall in the restricted bands, as defined in §15.205(a), must also comply with the radiated emission limits specified in §15.209(a) (see §15.205(c)).
---------------	--

21.2 BLOCK DIAGRAM OF TEST SETUP



21.3 TEST DATA

Pass: Please Refer To Appendix: Appendix1 For Details

BlueAsia


22 APPENDIX

Appendix1

22.1 MAXIMUM CONDUCTED OUTPUT POWER

Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Limit (dBm)	Verdict
NVNT	1-DH1	2402	Ant1	0.14	21	Pass
NVNT	1-DH1	2441	Ant1	-0.328	21	Pass
NVNT	1-DH1	2480	Ant1	-0.856	21	Pass
NVNT	2-DH1	2402	Ant1	2.192	21	Pass
NVNT	2-DH1	2441	Ant1	1.765	21	Pass
NVNT	2-DH1	2480	Ant1	1.303	21	Pass
NVNT	3-DH1	2402	Ant1	2.652	21	Pass
NVNT	3-DH1	2441	Ant1	2.252	21	Pass
NVNT	3-DH1	2480	Ant1	1.799	21	Pass


Power NVNT 1-DH1 2402MHz Ant1




Power NVNT 1-DH1 2441MHz Ant1




Power NVNT 1-DH1 2480MHz Ant1




Power NVNT 2-DH1 2402MHz Ant1




Power NVNT 2-DH1 2441MHz Ant1




Power NVNT 2-DH1 2480MHz Ant1




Power NVNT 3-DH1 2402MHz Ant1



Power NVNT 3-DH1 2441MHz Ant1




Power NVNT 3-DH1 2480MHz Ant1




22.2 -20DB BANDWIDTH

Condition	Mode	Frequency (MHz)	Antenna	-20 dB Bandwidth (MHz)	Limit -20 dB Bandwidth (MHz)	Verdict
NVNT	1-DH1	2402	Ant1	0.94	0	Pass
NVNT	1-DH1	2441	Ant1	0.887	0	Pass
NVNT	1-DH1	2480	Ant1	0.873	0	Pass
NVNT	2-DH1	2402	Ant1	1.3	0	Pass
NVNT	2-DH1	2441	Ant1	1.318	0	Pass
NVNT	2-DH1	2480	Ant1	1.295	0	Pass
NVNT	3-DH1	2402	Ant1	1.257	0	Pass
NVNT	3-DH1	2441	Ant1	1.259	0	Pass
NVNT	3-DH1	2480	Ant1	1.259	0	Pass


-20dB Bandwidth NVNT 1-DH1 2402MHz Ant1




-20dB Bandwidth NVNT 1-DH1 2441MHz Ant1




-20dB Bandwidth NVNT 1-DH1 2480MHz Ant1




-20dB Bandwidth NVNT 2-DH1 2402MHz Ant1




-20dB Bandwidth NVNT 2-DH1 2441MHz Ant1




-20dB Bandwidth NVNT 2-DH1 2480MHz Ant1




-20dB Bandwidth NVNT 3-DH1 2402MHz Ant1



-20dB Bandwidth NVNT 3-DH1 2441MHz Ant1




-20dB Bandwidth NVNT 3-DH1 2480MHz Ant1



22.3 OCCUPIED CHANNEL BANDWIDTH

Condition	Mode	Frequency (MHz)	Antenna	99% OBW (MHz)
NVNT	1-DH1	2402	Ant1	0.85421
NVNT	1-DH1	2441	Ant1	0.84046
NVNT	1-DH1	2480	Ant1	0.84723
NVNT	2-DH1	2402	Ant1	1.18608
NVNT	2-DH1	2441	Ant1	1.16924
NVNT	2-DH1	2480	Ant1	1.17115
NVNT	3-DH1	2402	Ant1	1.16870
NVNT	3-DH1	2441	Ant1	1.17014
NVNT	3-DH1	2480	Ant1	1.17214


OBW NVNT 1-DH1 2402MHz Ant1




OBW NVNT 1-DH1 2441MHz Ant1




OBW NVNT 1-DH1 2480MHz Ant1




OBW NVNT 2-DH1 2402MHz Ant1




OBW NVNT 2-DH1 2441MHz Ant1



OBW NVNT 2-DH1 2480MHz Ant1



OBW NVNT 3-DH1 2402MHz Ant1



OBW NVNT 3-DH1 2441MHz Ant1