

## 23. MPE Calculations

### **The MPE calculations are based on 0 dBi declared antenna gain.**

*Note: Empirically determined gain for the PCB trace antenna used in this product is approximately – 5.5 dBi*

#### Prediction of MPE limit at a given distance

Equation from page 18 of OET Bulletin 65, Edition 97-01

$$S = \frac{PG}{4\pi R^2}$$

where: S = power density

P = power input to the antenna

G = power gain of the antenna in the direction of interest relative to an isotropic radiator

R = distance to the center of radiation of the antenna

Maximum peak output power at antenna input terminal: 14.60 (dBm)

Maximum peak output power at antenna input terminal: 28.840 (mW)

Antenna gain(typical): 0 (dBi)

Maximum antenna gain: 1.000 (numeric)

Prediction distance: 20 (cm)

Prediction frequency: 2400 (MHz)

MPE limit for uncontrolled exposure at prediction frequency: 1 (mW/cm<sup>2</sup>)

Power density at prediction frequency: 0.005738 (mW/cm<sup>2</sup>)

Maximum allowable antenna gain: 22.4 (dBi)

Margin of Compliance at 20 cm = 22.4 dB