

# BT-201 (Flash) 藍芽無線耳機

BT-201(Flash)Operation Manual  
簡易操作手冊



 Bluetooth

 Bluetooth

## ■ Introduction

The BT-201 is a portable Bluetooth headset solution based on Bluetooth wireless technology which propels you into a new dimension in connectivity. The technology offers fast and reliable transmission of voice and data information between compatible devices.

## ■ The package

- 1-Bluetooth headset
- 2-The charger
- 3-Operation manual

## ■ Headset Overview

- 1-Charging connector
- 2-Call handling button
- 3-Indicator light
- 4-Volume up
- 5-Volume down
- 6-Ear hook
- 7-Speaker
- 8-Microphone



-1-

## ■ Switching ears

- To accommodate your custom usage, the headset is directional adjustable and can be worn either to your right ear or left ear.
- Gently remove the ear hook.
- Remount the ear hook to a direction desired.



## ■ Getting started

Before use your headset, you must first:

1. Charge the headset battery with our charger.
2. Pair the headset with your mobile phone.



-2-

## ● Charging the battery

The headset comes with a built-in rechargeable battery. When the battery is low, the indicator light flashes red slowly. During the charging, the indicator light shows a steady red light. When the battery is fully charged, the indicator is off.

Please note: The headset is in non-working status while being charged.

## ● To charge the battery

1. Connect the charger to the headset and to the mains.
2. It takes about 3 hours to fully recharge the battery.
3. Disconnect the charger from the headset and the mains when the charging is completed.

## ● Using the headset

Once the headset has been paired with your phone, you can make and receive calls using the headset as long as it is turned on and within the range of the phone – up to 10m (30ft) outdoors or up to 5m (15ft) indoors with no solid objects in between.

## ● Pairing

1. Prepare your phone according to the phone's user documentation on bluetooth pairing.
2. When the headset is off, press the call handling button for up to 10 seconds until the indicator light on the headset flashes green and red. The headset is now ready for pairing.
3. Continue according to the phone's user documentation. The passkey for our headset is 1234.

## ● To turn the headset on

Press and hold the call-handling button until you see the indicator light flashes green.

## ● To turn the headset off

When the headset is on, press and hold the call-handling button until the indicator light is off. The indicator light flashes red for 5 time before being off.

## ● Making and answering phone calls

Phone functionality is still available when the headset is connected. You can make and answer the calls using the buttons on the headset. If you use the keys on the phone to answer the calls, you will have to take this call from the phone rather than the headset.

## ● Adjust the volume

You can adjust the headset speaker volume during a call.

To increase the volume, press +.

To decrease the volume, press -.

## ● Using voice commands

You will be able to use this function through the headset only if your mobile phone supports voice dialling. Press and hold the call handling button for 2 seconds in standby mode, and your mobile phone will be ready for your voice commands.

## ■ The specification

Standard	Bluetooth 1.1 specification
Range (free space)	10 meters
Frequency Band	2.4GHz~2.4835GHz ISM Band
Connection	Point-to-point
Weight	<25g (including battery)
Speaker	85 ±3dB
Talk time	Up to 4 hr
Standby time	Up to 120 hr
Output Power	0 dBm (classII)
Power Consumption	30mA(working) ; <1mA(standby)
Battery	Rechargeable Li-ion polymer 150mA h
Charging	5V DC , 100~240V AC adapter
Charging time	2h~3h
Operating Temperature	-10°C ~ 55°C
Storage Temperature	-20°C ~ 60°C
Humidity	10% ~ 90%
Certification Approval	CE , FCC , BQB

### PLEASE NOTE:

The warranty will be invalid, if fail to follow the operation manual.

### Federal Communications Commission (FCC) Statement:

15.21

You are cautioned that changes or modifications not expressly approved by the part responsible for compliance could void the user's authority to operate the equipment.

15.105(b)

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

You are cautioned that changes or modifications not expressly approved by the party responsible for compliance could void your authority to operate the equipment.

### FCC RF Radiation Exposure Statement:

This Transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.