



# RF EXPOSURE REPORT

**REPORT NO.:** SA120323E02

**MODEL NO.:** G2F

**FCC ID:** RRK-G2F

**RECEIVED:** Mar. 21, 2012

**TESTED:** Apr. 05, 2012

**ISSUED:** Apr. 23, 2012

**APPLICANT:** Alpha Networks Inc.

**ADDRESS:** No.8 Li-shing 7th Rd., Science-based  
Industrial Park, Hsinchu, Taiwan, R.O.C.

**ISSUED BY:** Bureau Veritas Consumer Products Services  
(H.K.) Ltd., Taoyuan Branch Hsin Chu Laboratory

**LAB ADDRESS:** No. 81-1, Lu Liao Keng, 9th Ling, Wu Lung Tsuen,  
Chiung Lin Hsiang, Hsin Chu Hsien 307, Taiwan,  
R.O.C.

This test report consists of 9 pages in total. It may be duplicated completely for legal use with the approval of the applicant. It should not be reproduced, except in full, without the written approval of our laboratory. The client should not use it to claim product certification, approval or endorsement by any government agency. The test results in the report only apply to the tested sample.



## TABLE OF CONTENTS

RELEASE CONTROL RECORD .....	3
1. CERTIFICATION .....	4
2. RF EXPOSURE LIMIT .....	5
3. MPE CALCULATION FORMULA .....	5
4. CLASSIFICATION .....	5
5. ANTENNA GAIN .....	6
6. CALCULATION RESULT OF MAXIMUM CONDUCTED POWER .....	7



## RELEASE CONTROL RECORD

ISSUE NO.	REASON FOR CHANGE	DATE ISSUED
SA120323E02	Original release	Apr. 23, 2012



## 1. CERTIFICATION

**PRODUCT:** MY NET N900 CENTRAL  
**BRAND NAME:** WD  
**MODEL NO.:** G2F  
**TEST SAMPLE:** ENGINEERING SAMPLE  
**APPLICANT:** Alpha Networks Inc.  
**TESTED:** Apr. 05, 2012  
**STANDARDS:** FCC Part 2 (Section 2.1091)  
FCC OET Bulletin 65, Supplement C (01-01)  
IEEE C95.1

The above equipment (Model: G2F) has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

**PREPARED BY :** *Lori Chung* , **DATE:** Apr. 23, 2012  
( Lori Chung, Specialist )

**APPROVED BY :** *May Chen* , **DATE:** Apr. 23, 2012  
( May Chen, Deputy Manager )

## 2. RF EXPOSURE LIMIT

### LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

FREQUENCY RANGE (MHz)	ELECTRIC FIELD STRENGTH (V/m)	MAGNETIC FIELD STRENGTH (A/m)	POWER DENSITY (mW/cm <sup>2</sup> )	AVERAGE TIME (minutes)
<b>LIMITS FOR GENERAL POPULATION / UNCONTROLLED EXPOSURE</b>				
300-1500	...	...	F/1500	30
1500-100,000	...	...	1.0	30

F = Frequency in MHz

### 3. MPE CALCULATION FORMULA

$$P_d = (P_{out} * G) / (4 * \pi * r^2)$$

where

$P_d$  = power density in mW/cm<sup>2</sup>

$P_{out}$  = output power to antenna in mW

G = gain of antenna in linear scale

$\pi$  = 3.1416

R = distance between observation point and center of the radiator in cm

### 4. CLASSIFICATION

The antenna of this product, under normal use condition, is at least 20cm away from the body of the user. So, this device is classified as **Mobile Device**.

## 5. ANTENNA GAIN

The antennas provided to the EUT, please refer to the following table:

For 2.4GHz									
Transmitter Circuit	Brand	Model	Gain (dBi) (Exclu de cable loss )	Cable Loss (dB)	Net Gain (dBi) (Include cable loss)	Cable Length (mm)	Antenna Type	Freq. range (MHz to MHz)	Connector Type
Chain (0)	WHA-YU	C037-511173-A	2.9	0.11	2.79	15	PCB	2400 to 2500	MHF
Chain (1)	WHA-YU	C037-511159-A	3.5	0.13	3.37	40			
Chain (2)	WHA-YU	C037-511160-A	3.3	0.93	2.37	320			
For 5GHz									
Transmitter Circuit	Brand	Model	Gain (dBi) (Exclu de cable loss )	Cable Loss (dB)	Net Gain (dBi) (Include cable loss)	Cable Length (mm)	Antenna Type	Freq. range (MHz to MHz)	Connector Type
Chain (0)	WHA-YU	C037-511161-A	5.2	0.5	4.7	140	PCB	4900 to 5850	MHF
Chain (1)	WHA-YU	C037-511162-A	5.3	0.55	4.75	155			
Chain (2)	WHA-YU	C037-511163-A	4.6	0.8	3.8	225			

## 6. CALCULATION RESULT OF MAXIMUM CONDUCTED POWER

For 15.247(2.4GHz):

802.11b:

FREQUENCY BAND (MHz)	MAX POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2412-2462	347.860	7.62	20	0.400	1.00

Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^3 / 3]$

Effective Legacy Gain (dBi) = 7.62

The effective legacy gain is 7.62 dBi, therefore the limit needs to reduce.

802.11g:

FREQUENCY BAND (MHz)	MAX POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2412-2462	383.543	7.62	20	0.441	1.00

Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^3 / 3]$

Effective Legacy Gain (dBi) = 7.62

The effective legacy gain is 7.62 dBi, therefore the limit needs to reduce.

802.11n(20MHz):

FREQUENCY BAND (MHz)	MAX POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2412-2462	521.340	3.37	20	0.225	1.00

802.11n(40MHz):

FREQUENCY BAND (MHz)	MAX POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2422-2452	450.782	3.37	20	0.195	1.00

**For 15.247(5GHz):**

**802.11a:**

FREQUENCY BAND (MHz)	MAX POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5745 ~ 5825	266.788	9.20	20	0.441	1.00

$$\text{Directional gain} = 10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^3 / 3]$$

Effective Legacy Gain (dBi) = 9.2

The effective legacy gain is 9.2 dBi, therefore the limit needs to reduce.

**802.11n(20MHz):**

FREQUENCY BAND (MHz)	MAX POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5745 ~ 5825	718.798	4.75	20	0.427	1.00

**802.11n(40MHz):**

FREQUENCY BAND (MHz)	MAX POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5755 ~ 5795	700.834	4.75	20	0.416	1.00



**For 15.407(5GHz):  
802.11a:**

FREQUENCY BAND (MHz)	MAX POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5180 ~ 5240	13.958	9.20	20	0.023	1.00

Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^3 / 3]$

Effective Legacy Gain (dBi) = 9.2

The effective legacy gain is 9.2 dBi, therefore the limit needs to reduce.

**802.11n(20MHz):**

FREQUENCY BAND (MHz)	MAX POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5180 ~ 5240	31.073	4.75	20	0.018	1.00

**802.11n(40MHz):**

FREQUENCY BAND (MHz)	MAX POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5190 ~ 5230	49.286	4.75	20	0.029	1.00

**CONCLUSION:**

Both of the 2.4GHz and 5GHz can transmit simultaneously, the formula of calculated the MPE is:

$$CPD_1 / LPD_1 + CPD_2 / LPD_2 + \dots \text{etc.} < 1$$

**CPD = Calculation power density**

**LPD = Limit of power density**

Therefore, the worst-case situation is  $0.441 / 1 + 0.441 / 1 = 0.882$ , which is less than "1". This confirmed that the device comply with FCC 1.1310 MPE limit.

--- END ---