



## Wireless/Internet SDIO WLAN card



SDIO WLAN Card  
**User's Manual**  
ver. 1.24



## ■ Installation Procedure

< First, connect PDA to your computer with a USB wire.




< Main menu window will pop up when you insert the WLAN-11b Installation CD by autorun:









< Choose the desired **Language**, then click **OK**.



< The Installation menu will automatically appear on the screen.





< Click **Next**






< Enter user information, then click **Next**.




< Chose **Setup type**, then click **Next**








< The driver will be installed automatically.



< Click **Yes** to proceed with installation. Click **OK** to finish installation.



< Click **Finish** to complete the driver installation process.





## ■ Inserting the SDIO WLAN Card into a PDA

< Check the direction of the card.  
Insert the card with the label side facing the front of the PDA until it clicks.

# Different PDAs may have different drives. Make sure the direction is correct to avoid damaging the PDA's SD drive.


\* Please do not keep inserting & removing the card, different PDAs needs an interval of 5 to 7 seconds to process.



## ■ How to take a SDIO WLAN card out of a PDA


< When removing the SDIO WLAN card from a PDA, simply press down on the card until it clicks. The card will rise up for easy removal. DO NOT PULL by force, or the slot may be damaged.


< This card is designed to be locked into the slot. Forcefully pulling the card out will not only damage this auto pop-out function, but also the slot and the wireless card.








## How to Connect

- < After install the software, start path as **Start\Programs**.
- < After inserting the card into the PDA, click **Start**. Click **Programs** on the pull-down menu, then select . (Only built-in 11b card for PCC2003)





In "Radio" page of WLAN Utility, you may check **S/W Radio Off/on** for **Enable/Disable** Wi-Fi card, or you can also find a shortcut icon  at the lower right hand corner of the screen.




< Click , shortcut icon to switch **on/off** Wi-Fi radio






## How to Connect Ad-hoc



PS: Channe 12 is the channel in America

1. In **WLAN Utility**, select **Ad-Hoc Channel** (must be channel1).
2. Click **OK** to exit **WLAN Utility**.
3. Remove the card from PDA, then re-insert the card.
4. Go to PDA system: **Settings\Connections\ Network Cards**.
5. Click **Add New**.
6. Type in the name (ex. aa).
7. Check the "This is a device-to-device (ad-hoc) connection" box.
8. Click **OK**. The input name (ex. aa) will be added to the **Network Address**.



\*Ad-hoc channel is a "Point-to-point" network segment. It provides you with a temporary LAN environment.

## How to Remove Settings

In **Settings**, select the network name that you would like to remove. Wait 2 seconds for the '**Remove Settings**' pop-up window to appear.

