

**\*\* MPE Calculations \*\***

The MPE calculation for this exposure is shown below.

The peak radiated output power (EIRP) is calculated as follows:

EIRP = P + G EIRP = 14.21 dBm + 5.37 dBi EIRP = 19.58 dBm	Where, P = Power input to the antenna (mW) G = Power gain of the antenna (dBi)
---	--

**Power density at the specific separation:**

$S = PG / (4R^2 \pi)$ $S = (26.36 * 3.44) / (4 * 20^2 * \pi)$ $S = 0.0181 \text{ mW/cm}^2$	Where, S = Maximum power density (mW/cm <sup>2</sup> ) P = Power input to the antenna (mW) G = Numeric power gain of the antenna R = Distance to the center of the radiation of the antenna (20cm = limit for MPE)
--	---

The Maximum permissible exposure (MPE) for the general population is 1 mW/cm<sup>2</sup> .

The power density does not exceed the 1 mW/cm<sup>2</sup> limit.

Therefore, the exposure condition is compliant with FCC rules.

**Estimated safe separation:**

$R = \sqrt{PG / 4 \pi}$ $R = \sqrt{26.36 * 3.44 / 4 \pi}$ $R = 2.69 \text{ Cm}$	Where, P = Power input to the antenna (mW) G = Numeric power gain of the antenna R = Distance to the center of the radiation of the antenna (20cm = limit for MPE)
---	--

The numeric gain(G) of the antenna with a gain specified in dB is determined by:

$$G = \text{Log}^{-1} (\text{dB antenna gain} / 10)$$

$$G = \text{Log}^{-1} (5.37 / 10)$$

$$G = 3.44$$