



TEST REPORT

Report Number. : 14516849-E8V4

Applicant : SONOS INC.
614 CHAPALA ST.
SANTA BARBARA, CA, 93101, U.S.A.

Model : S44

Brand : SONOS

FCC ID : SBVRM044

IC : 5373A-RM044

EUT Description : 802.11 a/b/g/n/ac/ax 2x2 Client Device with BT and BLE

Test Standard(s) : FCC 47 CFR PART 15 SUBPART E
ISED RSS-248 ISSUE 2
ISED RSS-GEN ISSUE 5 + A1 +A2

Date Of Issue:

2023-05-25

Prepared by:

UL Verification Services Inc.
47173 Benicia Street
Fremont, CA 94538 U.S.A.
TEL: (510) 319-4000
FAX: (510) 661-0888



REPORT REVISION HISTORY

Rev.	Issue Date	Revisions	Revised By
V1	2023-04-18	Initial Issue	---
V2	2023-05-05	Updated Cover page, Section 1, 3, 6.7, 10 and 10.2	Kiya Kedida
V3	2023-05-17	Updated Section 6.7	Kiya Kedida
V4	2023-05-25	Section 6.7 updated the setup diagram and the description of test setup cable #3	Glenn Escano

TABLE OF CONTENTS

REPORT REVISION HISTORY	2
TABLE OF CONTENTS	3
1. ATTESTATION OF TEST RESULTS.....	12
2. TEST RESULT SUMMARY.....	14
3. TEST METHODOLOGY	15
4. FACILITIES AND ACCREDITATION.....	16
5. DECISION RULES AND MEASUREMENT UNCERTAINTY.....	17
5.1. <i>METROLOGICAL TRACEABILITY</i>	<i>17</i>
5.2. <i>DECISION RULES</i>	<i>17</i>
5.3. <i>MEASUREMENT UNCERTAINTY</i>	<i>17</i>
6. EQUIPMENT UNDER TEST	19
6.1. <i>EUT DESCRIPTION.....</i>	<i>19</i>
6.2. <i>EUT DEVICE CLASS</i>	<i>19</i>
6.3. <i>MAXIMUM OUTPUT POWER.....</i>	<i>19</i>
UNII-5 BAND 802.11 ax MODE 2TX.....	19
UNII-6 BAND 802.11 ax MODE 2TX.....	20
UNII-7 BAND 802.11 ax MODE 2TX.....	20
UNII-8 BAND 802.11 ax MODE 2TX.....	21
6.4. <i>DESCRIPTION OF AVAILABLE ANTENNAS</i>	<i>22</i>
6.5. <i>SOFTWARE AND FIRMWARE.....</i>	<i>22</i>
6.6. <i>WORST-CASE CONFIGURATION AND MODE.....</i>	<i>23</i>
6.7. <i>DESCRIPTION OF TEST SETUP.....</i>	<i>24</i>
TEST SETUP.....	25
SETUP DIAGRAM	25
7. MEASUREMENT METHOD	26
8. TEST AND MEASUREMENT EQUIPMENT	27
9. ANTENNA PORT TEST RESULTS	28
9.1. <i>ON TIME AND DUTY CYCLE</i>	<i>28</i>
9.2. <i>26 dB BANDWIDTH</i>	<i>31</i>
9.2.1. 802.11ax HE20 MODE 2TX IN THE UNII-5 BAND	32
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61	32

9.2.2. 802.11ax HE40 MODE 2TX IN THE UNII-5 BAND 34
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65 34

9.2.3. 802.11ax HE80 MODE 2TX IN THE UNII-5 BAND 36
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67 36

9.2.4. 802.11ax HE20 MODE 2TX IN THE UNII-6 BAND 38
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61 38

9.2.5. 802.11ax HE40 MODE 2TX IN THE UNII-6 BAND 40
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65 40

9.2.6. 802.11ax HE80 MODE 2TX IN THE UNII-6 BAND 42
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67 42

9.2.7. 802.11ax HE20 MODE 2TX IN THE UNII-7 BAND 43
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61 43

9.2.8. 802.11ax HE40 MODE 2TX IN THE UNII-7 BAND 45
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65 45

9.2.9. 802.11ax HE80 MODE 2TX IN THE UNII-7 BAND 47
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67 47

9.2.10. 802.11ax HE20 MODE 2TX IN THE UNII-8 BAND 49
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61 49

9.2.11. 802.11ax HE40 MODE 2TX IN THE UNII-8 BAND 51
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65 51

9.2.12. 802.11ax HE80 MODE 2TX IN THE UNII-8 BAND 53
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67 53

9.3. 99% BANDWIDTH..... 54

9.3.1. 802.11ax HE20 MODE 2TX IN THE UNII-5 BAND 55
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61 55

9.3.2. 802.11ax HE40 MODE 2TX IN THE UNII-5 BAND 57
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65 57

9.3.3. 802.11ax HE80 MODE 2TX IN THE UNII-5 BAND 59
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67 59

9.3.4. 802.11ax HE20 MODE 2TX IN THE UNII-6 BAND 61
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61 61

9.3.5. 802.11ax HE40 MODE 2TX IN THE UNII-6 BAND 63
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65 63

9.3.6. 802.11ax HE80 MODE 2TX IN THE UNII-6 BAND 65
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67 65

9.3.7. 802.11ax HE20 MODE 2TX IN THE UNII-7 BAND 66
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61 66

9.3.8. 802.11ax HE40 MODE 2TX IN THE UNII-7 BAND 68
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65 68

9.3.9. 802.11ax HE80 MODE 2TX IN THE UNII-7 BAND 70

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67 70

9.3.10. 802.11ax HE20 MODE 2TX IN THE UNII-8 BAND 72
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61 72

9.3.11. 802.11ax HE40 MODE 2TX IN THE UNII-8 BAND 74
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65 74

9.3.12. 802.11ax HE80 MODE 2TX IN THE UNII-8 BAND 76
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67 76

9.4. OUTPUT POWER AND PSD 77

9.4.1. 802.11ax HE20 MODE 2TX IN THE UNII-5 BAND 78
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 78
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 4 79
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 8 80
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61 81
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: SU, Single User 83

9.4.2. 802.11ax HE40 MODE 2TX IN THE UNII-5 BAND 84
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 84
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 8 85
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 17 86
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65 87
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: SU, Single User 89

9.4.3. 802.11ax HE80 MODE 2TX IN THE UNII-5 BAND 90
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 90
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 18 91
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 36 92
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67 93
2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: SU, Single User 95

9.4.4. 802.11ax HE20 MODE 2TX IN THE UNII-6 BAND 96
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 96
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 4 97
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 8 98
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61 99
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: SU, Single User 101

9.4.5. 802.11ax HE40 MODE 2TX IN THE UNII-6 BAND 102
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 102
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 17 103
2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65 104

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: SU, Single User 106

9.4.6. 802.11ax HE80 MODE 2TX IN THE UNII-6 BAND 107

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 107

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 18 108

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 36 109

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67 110

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: SU, Single User 111

9.4.7. 802.11ax HE20 MODE 2TX IN THE UNII-7 BAND 112

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 112

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 4 113

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 8 114

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61 115

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: SU, Single User 117

9.4.8. 802.11ax HE40 MODE 2TX IN THE UNII-7 BAND 118

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 118

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 8 119

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 17 120

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65 121

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: SU, Single User 123

9.4.9. 802.11ax HE80 MODE 2TX IN THE UNII-7 BAND 124

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 124

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 18 125

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 36 126

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67 127

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: SU, Single User 129

9.4.10. 802.11ax HE20 MODE 2TX IN THE UNII-8 BAND 130

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 130

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 4 131

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 8 132

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61 133

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: SU, Single User 135

9.4.11. 802.11ax HE40 MODE 2TX IN THE UNII-8 BAND 136

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 136

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 8 137

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 17 138

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65 139

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: SU, Single User 141

9.4.12. 802.11ax HE80 MODE 2TX IN THE UNII-8 BAND 142

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 142

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 18 143

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 36 144

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67 145

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: SU, Single User 146

9.5. SPURIOUS EMISSIONS IN-BAND – EMISSION MASK 147

9.5.1. 802.11ax HE20 MODE 2TX IN THE UNII-5 BAND 148

2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 148

2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 4 148

2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 8 149

2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61 149

9.5.2. 802.11ax HE40 MODE 2TX IN THE UNII-5 BAND 151

2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 151

2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 8 151

2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 17 152

2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65 152

9.5.3. 802.11ax HE80 MODE 2TX IN THE UNII-5 BAND 154

2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 154

2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 18 154

2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 36 155

2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67 155

9.5.4. 802.11ax HE20 MODE 2TX IN THE UNII-6 BAND 157

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 157

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 4 157

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 8 158

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61 158

9.5.5. 802.11ax HE40 MODE 2TX IN THE UNII-6 BAND 160

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 160

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 17 160

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65 161

9.5.6. 802.11ax HE80 MODE 2TX IN THE UNII-6 BAND 163

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 163

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 18 163

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 36 164

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67 165

9.5.7. 802.11ax HE20 MODE 2TX IN THE UNII-7 BAND 166

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 166

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 4 166

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 8 167

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61 168

9.5.8. 802.11ax HE40 MODE 2TX IN THE UNII-7 BAND 170

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 170

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 8 170

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 17 171

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65 172

9.5.9. 802.11ax HE80 MODE 2TX IN THE UNII-7 BAND 174

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 174

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 18 174

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 36 175

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67 176

9.5.10. 802.11ax HE20 MODE 2TX IN THE UNII-8 BAND 178

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 178

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 4 178

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 8 179

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61 179

9.5.11. 802.11ax HE40 MODE 2TX IN THE UNII-8 BAND 181

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 181

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 8 181

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 17 182

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65 182

9.5.12. 802.11ax HE80 MODE 2TX IN THE UNII-8 BAND 184

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 0 184

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 18 184

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 26-Tones, RU Index 36 185

2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67 186

10. RADIATED TEST RESULTS 187

10.1. TRANSMITTER OUTSIDE 5.925-7.125 GHz , 1- 18GHz..... 189

10.1.1. TX ABOVE 1 GHz 802.11ax HE20 MODE IN THE UNII-5 BAND..... 189

2TX Antenna 1 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 0 189

2TX Antenna 1 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 4 193

2TX Antenna 1 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 8 195

2TX Antenna 1 + Antenna 4 OFDMA MODE: 242-Tones, RU Index 61 197

10.1.2. TX ABOVE 1 GHz 802.11ax HE40 MODE IN THE UNII-5 BAND.....205

2TX Antenna 1 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 0 205

2TX Antenna 1 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 8 209

2TX Antenna 1 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 17 211

2TX Antenna 1 + Antenna 4 OFDMA MODE: 484-Tones, RU Index 65 213

10.1.3. TX ABOVE 1 GHz 802.11ax HE80 MODE IN THE UNII-5 BAND.....221

2TX Antenna 1 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 0 221

2TX Antenna 1 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 18 225

2TX Antenna 1 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 36 227

2TX Antenna 1 + Antenna 4 OFDMA MODE: 996-Tones, RU Index 67 229

10.1.4. TX ABOVE 1 GHz 802.11ax HE20 MODE IN THE UNII-6 BAND.....237

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 0 237

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 4 239

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 8 241

2TX Antenna 3 + Antenna 4 OFDMA MODE: 242-Tones, RU Index 61 243

10.1.5. TX ABOVE 1 GHz 802.11ax HE40 MODE IN THE UNII-6 BAND.....249

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 0 249

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 17 251

2TX Antenna 3 + Antenna 4 OFDMA MODE: 484-Tones, RU Index 65 255

10.1.6. TX ABOVE 1 GHz 802.11ax HE80 MODE IN THE UNII-6 BAND.....261

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 0 261

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 18 263

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 36 265

2TX Antenna 3 + Antenna 4 OFDMA MODE: 996-Tones, RU Index 67 267

10.1.7. TX ABOVE 1 GHz 802.11ax HE20 MODE IN THE UNII-7 BAND.....271

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 0 271

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 4 273

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 8 275

2TX Antenna 3 + Antenna 4 OFDMA MODE: 242-Tones, RU Index 61 279

10.1.8. TX ABOVE 1 GHz 802.11ax HE40 MODE IN THE UNII-7 BAND.....287

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 0 287

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 8 289

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 17 291

2TX Antenna 3 + Antenna 4 OFDMA MODE: 484-Tones, RU Index 65 295

10.1.9. TX ABOVE 1 GHz 802.11ax HE80 MODE IN THE UNII-7 BAND..... 303

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 0 303

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 18 305

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 36 307

2TX Antenna 3 + Antenna 4 OFDMA MODE: 996-Tones, RU Index 67 311

10.1.10. TX ABOVE 1 GHz 802.11ax HE20 MODE IN THE UNII-8 BAND..... 319

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 0 319

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 4 321

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 8 323

2TX Antenna 3 + Antenna 4 OFDMA MODE: 242-Tones, RU Index 61 327

10.1.11. TX ABOVE 1 GHz 802.11ax HE40 MODE IN THE UNII-8 BAND..... 335

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 0 335

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 8 337

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 17 339

2TX Antenna 3 + Antenna 4 OFDMA MODE: 484-Tones, RU Index 65 343

10.1.12. TX ABOVE 1 GHz 802.11ax HE80 MODE IN THE UNII-8 BAND..... 351

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 0 351

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 18 353

2TX Antenna 3 + Antenna 4 OFDMA MODE: 26-Tones, RU Index 36 355

2TX Antenna 3 + Antenna 4 OFDMA MODE: 996-Tones, RU Index 67 359

10.2. *WORST CASE BELOW 30MHz* 365

SPURIOUS EMISSIONS BELOW 30 MHz (WORST-CASE CONFIGURATION) 365

10.3. *WORST CASE BELOW 1 GHz*..... 367

10.4. *WORST CASE 18-26 GHz* 369

10.5. *WORST CASE 26-40 GHz* 371

11. AC POWER LINE CONDUCTED EMISSIONS 373

LIMITS..... 373

TEST PROCEDURE 373

RESULTS..... 373

12. SETUP PHOTOS..... 376

ANTENNA PORT AND AC LINE CONDUCTED SETUP 376
RADIATED RF MEASUREMENT SETUP 377

1. ATTESTATION OF TEST RESULTS

COMPANY NAME: SONOS INC.
614 Chapala St.
Santa Barbara, CA, 93101, U.S.A.

EUT DESCRIPTION: 802.11 a/b/g/n/ac/ax 2x2 Client Device with BT and BLE

MODEL: S44

BRAND: SONOS

SERIAL NUMBER: Radiated Sample: A100 2301WC C4-38-75-00-0F-40-9 and
A100 2301WC C4-38-75-00-0E-E0-F
Conducted Sample: A100 2301WC C4-38-75-00-0E-7C-0

SAMPLE RECEIPT DATE: 2023-02-20

DATE TESTED: 2023-02-28 to 2023-04-05

APPLICABLE STANDARDS	
STANDARD	TEST RESULTS
FCC 47 CFR Part 15 Subpart E	Complies
ISED RSS-248 Issue 2	Complies
ISED RSS-GEN Issue 5 + A1 + A2	Complies

UL Verification Services Inc. tested the above equipment in accordance with the requirements set forth in the above standards. The test results show that the equipment tested is capable of demonstrating compliance with the requirements as documented in this report.

The results documented in this report apply only to the tested sample, under the conditions and modes of operation as described herein. It is the manufacturer's responsibility to assure that additional production units of this model are manufactured with identical electrical and mechanical components. All samples tested were in good operating condition throughout the entire test program. Measurement Uncertainties are published for informational purposes only and were not taken into account unless noted otherwise.

This document may not be altered or revised in any way unless done so by UL Verification Services Inc. and all revisions are duly noted in the revisions section. Any alteration of this document not carried out by UL Verification Services Inc. will constitute fraud and shall nullify the document. This report must not be used by the client to claim product certification, approval, or endorsement by A2LA, NIST, any agency of the Federal Government, or any agency of the U.S. government.

Approved & Released For
UL Verification Services Inc. By:



Francisco de Anda
Staff Engineer
Consumer Technology Division
UL Verification Services Inc.

Prepared By:



Glenn Escano
Senior Test Engineer
Consumer Technology Division
UL Verification Services Inc.

1st Reviewed By:



Vien Tran
Senior Laboratory Engineer
Consumer Technology Division
UL Verification Services Inc.

2nd Reviewed By:



Kiya Kedida
Senior Project Engineer
Consumer Technology Division
UL Verification Services Inc.

2. TEST RESULT SUMMARY

This report contains data provided by the customer which can impact the validity of results. UL Verification Services Inc. is only responsible for the validity of results after the integration of the data provided by the customer.

FCC Clause	ISED Clause	Requirement	Result	Comment
See Comment		Duty Cycle	Reporting purposes only	ANSI C63.10 Section 12.2 ...
See Comment	RSS-GEN 6.7	99% BW	Reporting purposes only	ANSI C63.10 Section 6.9.3
§15.407 (a) (10)	---	26dB BW	Compliant	None.
§15.407 (a) (8)	RSS-248 4.6.3	Output Power e.i.r.p.	Compliant	Indoor Client.
§15.407 (a) (8)	RSS-248 4.6.3	PSD e.i.r.p	Compliant	Indoor Client.
§15.407 (b) (6)	RSS-248 4.7.2(a)	Emissions outside 5.925-7.125 GHz band	Compliant	None
§15.407 (b) (7)	RSS-248 4.7.2(b)	Emissions within 5.925-7.125 GHz Band(Emissions Mask)	Compliant	None
§15.205	RSS-GEN 8.10	Unwanted emissions in restricted bands	Compliant	None
§15.209	RSS-GEN 8.9	Radiated Spurious Emissions	Compliant	None
§15.207	RSS-GEN 8.8	AC Mains Conducted Emissions	Compliant	None

3. TEST METHODOLOGY

The tests documented in this report were performed in accordance with:

- FCC 47 CFR Part 2
- FCC 47 CFR Part 15
- FCC KDB 662911 D01 v02r01
- FCC KDB 789033 D01 v01r03
- FCC KDB 789033 D02 v02r01
- FCC KDB 987594 D01 General Requirements v01r03
- FCC KDB 987594 D02 EMC Measurement v01r01
- ANSI C63.10-2013
- RSS-GEN Issue 5 + A1 + A2
- RSS-248 Issue 2

4. FACILITIES AND ACCREDITATION

UL Verification Services Inc. is accredited by A2LA, Certificate Number #0751.05, for all testing performed within the scope of this report. Testing was performed at the locations noted below.

	Address	ISED CABID	ISED Company Number	FCC Registration
<input checked="" type="checkbox"/>	Building 1: 47173 Benicia Street Fremont, CA 94538, U.S.A	US0104	2324A	550739
<input type="checkbox"/>	Building 2: 47266 Benicia Street Fremont, CA 94538, U.S.A	US0104	22541	550739
<input checked="" type="checkbox"/>	Building 4: 47658 Kato Rd Fremont, CA 94538, U.S.A	US0104	2324B	550739

5. DECISION RULES AND MEASUREMENT UNCERTAINTY

5.1. METROLOGICAL TRACEABILITY

All test and measuring equipment utilized to perform the tests documented in this report are calibrated on a regular basis, with a maximum time between calibrations of one year or the manufacturers' recommendation, whichever is less, and where applicable is traceable to recognized national standards.

5.2. DECISION RULES

The Decision Rule is based on Simple Acceptance in accordance with ISO Guide 98-4:2012 Clause 8.2. (Measurement uncertainty is not taken into account when stating conformity with a specified requirement.)

5.3. MEASUREMENT UNCERTAINTY

Where relevant, the following measurement uncertainty levels have been estimated for tests performed on the apparatus:

PARAMETER	U _{Lab}
Radio Frequency (Spectrum Analyzer)	141.16 Hz
Worst Case Conducted Disturbance, 9KHz to 0.15 MHz	1.22%
Power Spectral Density	2.47 dB
RF Power Measurement Direct Method Using Power Meter	1.3 dB (PK) / 0.45 dB (AV)
Unwanted Emissions, Conducted	1.94dB
Worst Case Conducted Disturbance, 9KHz to 0.15 MHz	3.78 dB
Worst Case Conducted Disturbance, 0.15 to 30 MHz	3.40 dB
Worst Case Radiated Disturbance, 9KHz to 30 MHz	2.87 dB
Worst Case Radiated Disturbance, 30 to 1000 MHz	6.01 dB
Worst Case Radiated Disturbance, 1000 to 18000 MHz	4.73 dB
Worst Case Radiated Disturbance, 18000 to 26000 MHz	4.51 dB
Worst Case Radiated Disturbance, 26000 to 40000 MHz	5.29 dB
Time Domain Measurements	3.39%
Temperature	0.57
Humidity	3.39%
DC Supply Voltages	0.57%

Uncertainty figures are valid to a confidence level of 95%.

RADIATED EMISSIONS

Where relevant, the following sample calculation is provided:

$$\begin{aligned} \text{Field Strength (dBuV/m)} &= \text{Measured Voltage (dBuV)} + \text{Antenna Factor (dB/m)} + \text{Cable} \\ &\text{Loss (dB)} - \text{Preamp Gain (dB)} \\ 36.5 \text{ dBuV} + 18.7 \text{ dB/m} + 0.6 \text{ dB} - 26.9 \text{ dB} &= 28.9 \text{ dBuV/m} \end{aligned}$$

MAINS CONDUCTED EMISSIONS

Where relevant, the following sample calculation is provided:

$$\begin{aligned} \text{Final Voltage (dBuV)} &= \text{Measured Voltage (dBuV)} + \text{Cable Loss (dB)} + \text{Limiter Factor (dB)} + \\ &\text{LISN Insertion Loss.} \\ 36.5 \text{ dBuV} + 0 \text{ dB} + 10.1 \text{ dB} + 0 \text{ dB} &= 46.6 \text{ dBuV} \end{aligned}$$

6. EQUIPMENT UNDER TEST

6.1. EUT DESCRIPTION

The EUT is an 802.11 a/b/g/n/ac/ax 2x2 Client Device with BT and BLE.

This report covers ax 6E Wifi radio.

6.2. EUT DEVICE CLASS

EUT is of the following device class:

	U-NII Bands of Operation			
	5	6	7	8
Indoor Client (6XD)	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>

6.3. MAXIMUM OUTPUT POWER

The transmitter has a maximum average e.i.r.p. output power as follows:

UNII-5 BAND 802.11 ax MODE 2TX

Frequency Range (MHz)	Mode	e.i.r.p. Power (dBm)	Output Power (mW)
2TX CDD -UNII-5 band			
5955-6415	802.11ax HE20 SU	11.04	12.71
	802.11ax HE20 OFDMA, 242-Tones	12.88	19.41
	802.11ax HE20 OFDMA, 26-Tones	4.24	2.65
5965-6405	802.11ax HE40 SU	13.46	22.18
	802.11ax HE40 OFDMA, 484-Tones	14.01	25.18
	802.11ax HE40 OFDMA, 26-Tones	3.85	2.43
5985-6385	802.11ax HE80 SU	16.02	39.99
	802.11ax HE80 OFDMA, 996-Tones	17.59	57.41
	802.11ax HE80 OFDMA, 26-Tones	4.72	2.96

UNII-6 BAND 802.11 ax MODE 2TX

Frequency Range (MHz)	Mode	e.i.r.p. Power (dBm)	Output Power (mW)
2TX CDD -UNII-6 band			
6435-6515	802.11ax HE20 SU	9.19	8.30
	802.11ax HE20 OFDMA, 242-Tones	10.95	12.45
	802.11ax HE20 OFDMA, 26-Tones	4.24	2.65
6445-6485	802.11ax HE40 SU	13.47	22.23
	802.11ax HE40 OFDMA, 484-Tones	13.91	24.60
	802.11ax HE40 OFDMA, 26-Tones	5.40	3.47
6525 (Straddle)	802.11ax HE40 SU	12.66	18.45
	802.11ax HE40 OFDMA, 484-Tones	12.92	19.59
	802.11ax HE40 OFDMA, 26-Tones	5.44	3.50
6465	802.11ax HE80 SU	16.72	46.99
	802.11ax HE80 OFDMA, 996-Tones	18.15	65.31
	802.11ax HE80 OFDMA, 26-Tones	4.52	2.83
6545 (Straddle)	802.11ax HE80 SU	16.19	41.59
	802.11ax HE80 OFDMA, 996-Tones	17.05	50.70
	802.11ax HE80 OFDMA, 26-Tones	5.45	3.51

UNII-7 BAND 802.11 ax MODE 2TX

Frequency Range (MHz)	Mode	e.i.r.p. Power (dBm)	Output Power (mW)
2TX CDD -UNII-7 Band			
6535-6855	802.11ax HE20 SU	9.61	9.14
	802.11ax HE20 OFDMA, 242-Tones	11.92	15.56
	802.11ax HE20 OFDMA, 26-Tones	4.22	2.64
6875 (Straddle)	802.11ax HE20 SU	8.13	6.50
	802.11ax HE20 OFDMA, 242-Tones	10.29	10.69
	802.11ax HE20 OFDMA, 26-Tones	3.73	2.36
6525-6845	802.11ax HE40 SU	12.63	18.32
	802.11ax HE40 OFDMA, 484-Tones	13.76	23.77
	802.11ax HE40 OFDMA, 26-Tones	3.07	2.03
6885(Straddle)	802.11ax HE40 SU	10.90	12.30
	802.11ax HE40 OFDMA, 484-Tones	12.12	16.29
	802.11ax HE40 OFDMA, 26-Tones	2.24	1.67
6545-6785	802.11ax HE80 SU	15.23	33.34
	802.11ax HE80 OFDMA, 996-Tones	15.57	36.06
	802.11ax HE80 OFDMA, 26-Tones	3.70	2.34
6865 (Straddle)	802.11ax HE80 SU	14.88	30.76
	802.11ax HE80 OFDMA, 996-Tones	15.98	39.63
	802.11ax HE80 OFDMA, 26-Tones	2.10	1.62

UNII-8 BAND 802.11 ax MODE 2TX

Frequency Range (MHz)	Mode	e.i.r.p. Power (dBm)	Output Power (mW)
2TX CDD -UNII-8 Band			
6895-7115	802.11ax HE20 SU	9.00	7.94
	802.11ax HE20 OFDMA, 242-Tones	10.75	11.89
	802.11ax HE20 OFDMA, 26-Tones	4.23	2.65
6925-7085	802.11ax HE40 SU	11.56	14.32
	802.11ax HE40 OFDMA, 484-Tones	12.64	18.37
	802.11ax HE40 OFDMA, 26-Tones	4.00	2.51
6945-7025	802.11ax HE80 SU	15.19	33.04
	802.11ax HE80 OFDMA, 996-Tones	15.82	38.19
	802.11ax HE80 OFDMA, 26-Tones	2.99	1.99

6.4. DESCRIPTION OF AVAILABLE ANTENNAS

The radio utilizes a Monopole antenna, with a maximum gain as follows.

Frequency Range (MHz)	Peak Antenna Gain (dBi)			
	CHAIN 0		CHAIN 1	
	ANT1 (dBi)	ANT3 (dBi)	ANT2 (dBi)	ANT4 (dBi)
5925 – 6425	4.6	3.9	3.3	4.1
6425 – 6525	3.3	4.2	2.4	3.5
6525 – 6875	3.5	5.5	2.4	3.8
6875 – 7125	3.9	5.3	1.8	3.2

6.5. SOFTWARE AND FIRMWARE

The EUT firmware installed during testing was 74.0-39150-1-41.
The test utility software installed during testing was PrimaComplianceGUIInstaller_TESTBUILD3_17Nov22.

6.6. WORST-CASE CONFIGURATION AND MODE

Radiated emissions below 1GHz, above 18GHz, and power line conducted emission were performed with the EUT set to transmit at the channel with highest output power as worst-case scenario.

The EUT can only be setup in desktop orientation; therefore, all radiated testing was performed with the EUT in desktop orientation.

The fundamental of the EUT was investigated in the antenna combinations, it was determined that:

ANT1 and ANT4 was the worst case in the UNII-5 bands.

ANT3 and ANT4 was the worst case in the UNII-6, UNII-7, and UNII-8 band.

Therefore, all final testing was performed with ANT1 and ANT4 and ANT3 and ANT4 as stated above.

Worst-case data rates as provided by the manufacturer were:

802.11ax HE20mode: MCS0

802.11ax HE40mode: MCS0

802.11ax HE80mode: MCS0

Preliminary Investigation were performed for 802.11ax modes were determined by the following:

- Testing was performed on 802.11ax HE20 26T (Lowest Tones) and 242T (Full Tone) to cover HE20 52T,106T.
- Testing was performed on 802.11ax HE40 26T (Lowest Tones) and 484T (Full Tone) to cover HE40 52T,106T and 242T.
- Testing was performed on 802.11ax HE80 26T (Lowest Tones) and 996T (Full Tone) to cover HE80 52T, 106T, 242T and 484T.

According to Preliminary Investigation, conducted power was performed to compare Full RU Tone modes and SU (Single User) Tone modes. It was determined that Full RU Tone modes were worst case over Single User modes in every instance. Therefore, only full tone modes were tested, and they represent SU modes as the worst-case scenario


6.7. DESCRIPTION OF TEST SETUP

SUPPORT TEST EQUIPMENT						
Description	Manufacturer	Model	Serial Number	FCC ID/ DoC		
Laptop	Lenovo	T460s	PC0JMBF8	Doc		
Laptop AC/DC Adapter	Lenovo	ADLX90NLC2A	11S45N0247Z1ZSHH448JEY	Doc		
AC Power	Sonos	CPS045180250U	N/A	Doc		
Power Supply	Sonos	EC2Y5EB	N/A	Doc		
USB-A to Ethernet Adapter	Plugable	USB2-E100	8CAE4CE46AFA	Doc		
USB-C to USB-A Female Adapter	Amazon Basics	L6LUC160-CS-R	N/A	Doc		
I/O CABLES (CONDUCTED TEST)						
Cable No.	Port	# of Identical Ports	Connector Type	Cable Type	Cable Length (m)	Remarks
1	AC	3	AC	Un-shielded	1.25	AC Mains to Spectrum Analyzer/AC/DC Adapter
2	DC	1	DC	Un-shielded	1.0	AC/DC Adapter to Laptop
3	USB-C	1	USB-C	Un-shielded	1.5	EUT to AC Power
4	Ethernet	1	RJ45	Un-shielded	1.5	Laptop to USB Ethernet Adapter
5	USB-A	1	USB-A	Shielded	0.05	USB Ethernet Adapter to USB
6	USB-C	1	USB-C	Shielded	0.05	EUT to USB-C/USB-A Female Adapter
7	SMA Cable	1	SMA	Un-Shielded	1.0	EUT to Spectrum Analyzer
I/O CABLES (RADIATED TEST)						
Cable No.	Port	# Of Identical Ports	Connector Type	Cable Type	Cable Length (m)	Remarks
1	AC	3	AC	Un-shielded	1.25	AC Mains to Spectrum Analyzer/AC/DC Adapter
2	DC	1	DC	Un-shielded	1.0	AC/DC Adapter to Laptop
3	USB-C	1	USB-C	Un-shielded	1.5	EUT to AC Power
4	Ethernet	1	RJ45	Un-shielded	10	Laptop to USB Ethernet Adapter
5	USB-A	1	USB-A	Shielded	0.05	USB Ethernet Adapter to USB
6	USB-C	1	USB-C	Shielded	0.05	EUT to USB-C/USB-A Female Adapter
7	SMA Cable	1	SMA	Un-Shielded	10	EUT to Horn Antenna

TEST SETUP

The EUT is a stand-alone unit, and the radio is exercised remotely by Sonos Compliance GUI test utility software via ethernet.

SETUP DIAGRAM



7. MEASUREMENT METHOD

On Time and Duty Cycle: KDB 789033 D02 v02r01, Section B.

26 dB Emission BW: KDB 789033 D02 v02r01, Section C.1

Conducted Output Power: KDB 789033 D02 v02r01, Section II E.2.d (Method SA-2).

Conducted Output Power: KDB 789033 D02 v02r01, Section II E.2.d (Method SA-2).
(Output Power (e.i.r.p): Radiated EIRP + DCCF = EIRP)
Radiated method made in lieu of conducted measurements

Power Spectral Density(PSD): KDB 789033 D02 v02r01, Section F
Radiated method made in lieu of conducted measurements

Spurious emissions within 5.925-7.125 GHz Band(Emissions Mask): KDB 987594 D02 EMC
Measurement Section II-J

Unwanted emissions in restricted bands: KDB 789033 D02 v02r01, Sections G.3, G.4, G.5, and G.6.

Unwanted emissions in non-restricted bands: KDB 789033 D02 v02r01, Sections G.3, G.4, and G.5.

AC Power Line Conducted Emissions: ANSI C63.10-2013, Section 6.2.

Radiated Spurious Emissions Below 30MHz: ANSI C63.10-2013 Section 6.4

8. TEST AND MEASUREMENT EQUIPMENT

The following test and measurement equipment was utilized for the tests documented in this report:

TEST EQUIPMENT LIST					
Description	Manufacturer	Model	ID Num	Cal Due	Last Cal
Antenna, Broadband Hybrid, 30MHz to 2GHz	Sunol Sciences Corp.	JB1	80293	2023-09-08	2022-09-08
Amplifier, 10KHz to 1GHz, 32dB	SONOMA INSTRUMENT	310N	29654	2023-04-24	2022-04-24
Antenna, Horn 1-18GHz	ETS-Lindgren (Cedar Park, Texas)	3117	223083	2023-10-25	2022-10-25
RF Filter Box, 1-18GHz	UL-FR1 (CTECH)	SAC 8 port rf box 1	197920	2023-04-19	2022-04-19
EMI TEST RECEIVER, with B8 option	Rohde & Schwarz	ESW44	191429	2024-02-29	2023-02-15
EMI TEST RECEIVER	Rohde & Schwarz	ESW44	225688	2024-02-29	2023-02-14
Antenna, Horn 18 to 26.5GHz	ARA	MWH-1826/B	199659	2023-06-12	2022-06-12
Amplifier 18-26.5GHz, +5Vdc, -54dBm P1dB	AMPLICAL	AMP18G26.5-60	234683	2024-03-29	2023-03-18
Antenna, Horn 26 to 40GHz	ARA	MWH-2640/B	199661	2023-06-12	2022-06-12
Amplifier 26-40GHz +5Vdc, -62dBm P1dB	AMPLICAL	AMP26G40-65	234684	2024-03-29	2023-03-18
Antenna, Passive Loop 30Hz - 1MHz	ELECTRO METRICS	EM-6871	170014	2023-07-19	2022-07-19
Antenna, Passive Loop 100KHz - 30MHz	ELECTRO METRICS	EM-6872	170016	2023-07-19	2022-07-19
Spectrum Analyzer, PXA, 3Hz to 44GHz	Agilent Technologies	N9030A	80396	2024-01-31	2023-01-27
Power Meter, P-series single channel	Keysight Technologies Inc	N1911A	90719	2024-01-31	2023-01-26
Power Sensor, P - series, 50MHz to 18GHz, Wideband	Keysight Technologies Inc	N1921A	81319	2024-01-31	2023-01-25
10dB Fixed Attenuator	Pasternack Enterprises	PE7087-10	N/A	Verified	Verified
AC Line Conducted					
LISN	Fischer Custom Communications, Inc	FCC-LISN-50/250-25-2-01-480V	175765	2024-01-31	2023-01-27
EMI TEST RECEIVER	Rohde & Schwarz	ESR	175765	2024-02-29	2023-02-20
Transient Limiter	Com-Power	LIT-930	207996	2023-07-15	2022-07-15
UL TEST SOFTWARE LIST					
Radiated Software	UL	UL EMC	Ver 2023-01-18, 2016-08-23		
Antenna Port Software	UL	UL RF	Ver 2022-08-16		
AC Line Conducted Software	UL	UL EMC	Rev 9.5, 2022-02-17		

9. ANTENNA PORT TEST RESULTS

9.1. ON TIME AND DUTY CYCLE

LIMITS

None; for reporting purposes only.

TEST PROCEDURE

KDB 789033 Zero-Span Spectrum Analyzer Method.

Test Engineer:	JB45256 and JM28199
Test Date:	2023-02-28 to 2023-03-09

RESULTS

Mode	ON Time B (msec)	Period (msec)	Duty Cycle x (linear)	Duty Cycle (%)	Duty Cycle Correction Factor (dB)	1/B Minimum VBW (kHz)
802.11ax HE20 OFDMA, SU	1.073	1.713	0.626	62.64%	2.03	0.932
802.11ax HE20 OFDMA, RU size 242T	0.375	0.980	0.383	38.27%	4.17	2.667
802.11ax HE20 OFDMA, RU size 26T	0.580	1.193	0.486	48.64%	3.13	1.724
802.11ax HE40 OFDMA, SU	0.565	1.197	0.472	47.20%	3.26	1.770
802.11ax HE40 OFDMA, RU size 484T	0.368	0.978	0.376	37.63%	4.24	2.717
802.11ax HE40 OFDMA, RU size 26T	0.580	1.182	0.491	49.07%	3.09	1.724
802.11ax HE80 OFDMA, SU	0.304	0.924	0.329	32.90%	4.83	3.289
802.11ax HE80 OFDMA, RU size 996T	0.343	0.973	0.352	35.22%	4.53	2.920
802.11ax HE80 OFDMA, RU size 26T	0.582	1.194	0.487	48.74%	3.12	1.718

DUTY CYCLE PLOTS



802.11ax HE20 OFDMA, SU



802.11ax HE20 OFDMA, RU size 242T MODE




802.11ax HE20 OFDMA, RU size 26T MODE




802.11ax HE40 OFDMA, SU




802.11ax HE40 OFDMA, RU size 484T MODE




802.11ax HE40 OFDMA, RU size 26T MODE



802.11ax HE80 OFDMA, SU



802.11ax HE80 OFDMA, RU size 996T MODE



802.11ax HE80 OFDMA, RU size 26T MODE

9.2. 26 dB BANDWIDTH

LIMITS

§15.407 (a) (10)

The maximum transmitter channel bandwidth for U-NII devices in the 5.925-7.125 GHz band is 320 megahertz.


RESULTS

9.2.1. 802.11ax HE20 MODE 2TX IN THE UNII-5 BAND



2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61

Channel	Frequency (MHz)	26 dB Bandwidth Antenna 1 (MHz)	26 dB Bandwidth Antenna 4 (MHz)
Low	5955	22.64	22.28
Mid	6175	22.40	22.40
High	6415	22.64	22.44



LOW CHANNEL



MID CHANNEL



HIGH CHANNEL




9.2.2. 802.11ax HE40 MODE 2TX IN THE UNII-5 BAND



2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65

Channel	Frequency (MHz)	26 dB Bandwidth Antenna 1 (MHz)	26 dB Bandwidth Antenna 4 (MHz)
Low	5965	40.16	40.16
Mid	6165	40.08	40.24
High	6405	40.08	40.00



LOW CHANNEL



MID CHANNEL



HIGH CHANNEL




9.2.3. 802.11ax HE80 MODE 2TX IN THE UNII-5 BAND



2TX Antenna 1 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67

Channel	Frequency (MHz)	26 dB Bandwidth Antenna 1 (MHz)	26 dB Bandwidth Antenna 4 (MHz)
Low	5985	81.60	81.28
Mid	6145	81.60	81.44
High	6385	81.60	81.12



LOW CHANNEL



MID CHANNEL



HIGH CHANNEL




9.2.4. 802.11ax HE20 MODE 2TX IN THE UNII-6 BAND



2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61

Channel	Frequency (MHz)	26 dB Bandwidth Antenna 3 (MHz)	26 dB Bandwidth Antenna 4 (MHz)
Low	6435	22.68	22.36
Mid	6475	22.64	22.48
High	6515	22.40	22.56



LOW CHANNEL



MID CHANNEL



HIGH CHANNEL





9.2.5. 802.11ax HE40 MODE 2TX IN THE UNII-6 BAND



2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65

Channel	Frequency (MHz)	26 dB Bandwidth Antenna 3 (MHz)	26 dB Bandwidth Antenna 4 (MHz)
Low	6445	40.16	40.08
High	6485	40.08	40.16
Straddle	6525	40.08	40.08


LOW CHANNEL



HIGH CHANNEL



STRADDLE CHANNEL





9.2.6. 802.11ax HE80 MODE 2TX IN THE UNII-6 BAND



2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67

Channel	Frequency (MHz)	26 dB Bandwidth Antenna 3 (MHz)	26 dB Bandwidth Antenna 4 (MHz)
Mid	6465	81.76	81.60
Straddle	6545	81.60	81.60

MID CHANNEL



STRADDLE CHANNEL





9.2.7. 802.11ax HE20 MODE 2TX IN THE UNII-7 BAND



2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61

Channel	Frequency (MHz)	26 dB Bandwidth Antenna 3 (MHz)	26 dB Bandwidth Antenna 4 (MHz)
Low	6535	22.44	22.08
Mid	6715	22.64	22.20
High	6855	22.92	22.96
Straddle	6875	23.80	23.32



LOW CHANNEL





MID CHANNEL



HIGH CHANNEL



STRADDLE CHANNEL





9.2.8. 802.11ax HE40 MODE 2TX IN THE UNII-7 BAND



2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65

Channel	Frequency (MHz)	26 dB Bandwidth Antenna 3 (MHz)	26 dB Bandwidth Antenna 4 (MHz)
Low	6565	40.08	40.08
Mid	6685	40.08	40.00
High	6845	40.16	40.16
Straddle	6885	40.08	40.00


LOW CHANNEL




MID CHANNEL



HIGH CHANNEL




HIGH CHANNEL Antenna 3




HIGH CHANNEL Antenna 4

STRADDLE CHANNEL



STRADDLE CHANNEL Antenna 3





STRADDLE CHANNEL Antenna 4

9.2.9. 802.11ax HE80 MODE 2TX IN THE UNII-7 BAND



2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 996-Tones, RU Index 67

Channel	Frequency (MHz)	26 dB Bandwidth Antenna 3 (MHz)	26 dB Bandwidth Antenna 4 (MHz)
Low	6625	81.60	81.44
Mid	6705	81.44	81.60
High	6785	81.60	81.60
Straddle	6865	81.60	81.76



LOW CHANNEL





MID CHANNEL



HIGH CHANNEL



STRADDLE CHANNEL




9.2.10. 802.11ax HE20 MODE 2TX IN THE UNII-8 BAND



2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 242-Tones, RU Index 61

Channel	Frequency (MHz)	26 dB Bandwidth Antenna 3 (MHz)	26 dB Bandwidth Antenna 4 (MHz)
Low	6895	23.52	23.76
Mid	6995	23.92	22.80
High	7115	23.76	23.00



LOW CHANNEL



MID CHANNEL



HIGH CHANNEL





9.2.11. 802.11ax HE40 MODE 2TX IN THE UNII-8 BAND



2TX Antenna 3 + Antenna 4 CDD OFDMA MODE: 484-Tones, RU Index 65

Channel	Frequency (MHz)	26 dB Bandwidth Antenna 3 (MHz)	26 dB Bandwidth Antenna 4 (MHz)
Low	6925	39.92	40.08
Mid	6965	40.16	40.16
High	7085	40.16	40.08

LOW CHANNEL



MID CHANNEL



HIGH CHANNEL

