

## APPENDIX A – TEST DATA OF CONDUCTED EMISSION

### Duty Cycle

Test Mode	Frequency (MHz)	Duty Cycle (%)	Correction Factor(dB)
802.11a	5180	83.68%	0.77
802.11n HT20	5180	83.82%	0.77
802.11ac VHT20	5180	84.23%	0.75
802.11n HT40	5190	78.94%	1.03
802.11ac VHT40	5190	80.07%	0.97
802.11ac VHT80	5210	76.80%	1.15

Note: Correction Factor=10\*log (1/Duty Cycle)

### Output Power

Mode	Tones/ RUIndex	Freq (MHz)	Antenna	Conducted average power output(dBm)	EIRP (dBm)
802.11a	NA	5180	Chain0	14.45	16.35
802.11a	NA	5220	Chain0	14.26	16.16
802.11a	NA	5240	Chain0	14.10	16.00
802.11n HT20	NA	5180	Chain0	14.19	16.09
802.11n HT20	NA	5220	Chain0	14.19	16.09
802.11n HT20	NA	5240	Chain0	13.95	15.85
802.11ac VHT20	NA	5180	Chain0	13.65	15.55
802.11ac VHT20	NA	5220	Chain0	13.79	15.69
802.11ac VHT20	NA	5240	Chain0	14.03	15.93
802.11n HT40	NA	5190	Chain0	13.92	15.82
802.11n HT40	NA	5230	Chain0	13.77	15.67
802.11ac VHT40	NA	5190	Chain0	13.53	15.43
802.11ac VHT40	NA	5230	Chain0	13.66	15.56
802.11ac VHT80	NA	5210	Chain0	13.31	15.21

### Emission Bandwidth



Offset 11.16dB = Attenuator + Temporary antenna connector loss + Cable loss

Test Mode	Antenna	26dB Bandwidth (MHz)		
		Channel No.554	Channel No.562	Channel No.566
		5180MHz	5220MHz	5240MHz
802.11a	Chain0	19.99	21.88	24.67
802.11n HT20	Chain0	19.84	24.83	24.45
802.11ac VHT20	Chain0	22.60	24.78	24.96

Test Mode	Antenna	26dB Bandwidth (MHz)		
		Channel No.556	---	Channel No.564
		5190MHz	---	5230MHz
802.11n HT40	Chain0	45.33	---	39.26
802.11ac VHT40	Chain0	47.15	---	44.36


Test Mode	Antenna	26dB Bandwidth (MHz)		
		Channel No.560	---	---
		5210MHz	---	---
802.11ac VHT80	Chain0	84.29	---	---

Test Mode: 802.11a




Test Mode:802.11a 5180MHz Chain0

Test Mode:802.11a 5220MHz Chain0




Test Mode:802.11a 5240MHz Chain0


Test Mode: 802.11n HT20



Test Mode:802.11n HT20 5180MHz Chain0




Test Mode:802.11n HT20 5220MHz Chain0




Test Mode:802.11n HT20 5240MHz Chain0


Test Mode: 802.11ac VHT20



Test Mode:802.11ac VHT20 5180MHz Chain0





Test Mode:802.11ac VHT20 5220MHz Chain0



Test Mode:802.11ac VHT20 5240MHz Chain0



Test Mode: 802.11n HT40



Test Mode:802.11n HT40 5190MHz Chain0

Test Mode:802.11n HT40 5230MHz Chain0


Test Mode: 802.11ac VHT40



Test Mode:802.11ac VHT40 5190MHz Chain0

Test Mode:802.11ac VHT40 5230MHz Chain0

Test Mode: 802.11ac VHT80



Test Mode:802.11ac VHT80 5210MHz Chain0

### Occupied Bandwidth


Offset 11.16dB = Attenuator + Temporary antenna connector loss + Cable loss

Test Mode	Antenna	Occupied Bandwidth (MHz)		
		Channel No.554	Channel No.562	Channel No.566
		5180MHz	5220MHz	5240MHz
802.11a	Chain0	16.763	16.595	16.775
802.11n HT20	Chain0	17.802	17.741	17.732
802.11ac VHT20	Chain0	17.702	17.751	17.709


Test Mode	Antenna	Occupied Bandwidth (MHz)		
		Channel No.556	---	Channel No.564
		5190MHz	---	5230MHz
802.11n HT40	Chain0	36.524	---	36.339
802.11ac VHT40	Chain0	36.419	---	36.386

Test Mode	Antenna	Occupied Bandwidth (MHz)		
		Channel No.560	---	---
		5210MHz	---	---
802.11ac VHT80	Chain0	76.312	---	---


Test Mode: 802.11a



Test Mode:802.11a 5180MHz Chain0





Test Mode:802.11a 5220MHz Chain0




Test Mode:802.11a 5240MHz Chain0

Test Mode: 802.11n HT20




Test Mode:802.11n HT20 5180MHz Chain0

Test Mode:802.11n HT20 5220MHz Chain0




Test Mode:802.11n HT20 5240MHz Chain0


Test Mode: 802.11ac VHT20



Test Mode:802.11ac VHT20 5180MHz Chain0




Test Mode:802.11ac VHT20 5220MHz Chain0




Test Mode:802.11ac VHT20 5240MHz Chain0

Test Mode: 802.11n HT40




Test Mode:802.11n HT40 5190MHz Chain0




Test Mode:802.11n HT40 5230MHz Chain0

Test Mode: 802.11ac VHT40




Test Mode:802.11ac VHT40 5190MHz Chain0



Test Mode:802.11ac VHT40 5230MHz Chain0

Test Mode: 802.11ac VHT80



Transmitter Power Spectral Density

Offset 11.16dB = Attenuator + Temporary antenna connector loss + Cable loss


Test Mode	Antenna	5180MHz		5220MHz		5240MHz	
		Correction Factor(dB)	Power Density (dBm/MHz)	Correction Factor(dB)	Power Density (dBm/MHz)	Correction Factor(dB)	Power Density (dBm/MHz)
802.11a	Chain0	0.77	2.587	0.77	2.403	0.77	1.694
802.11n HT20	Chain0	0.77	2.745	0.77	2.582	0.77	1.541
802.11ac VHT20	Chain0	0.75	2.747	0.75	2.859	0.75	1.974

Test Mode	Antenna	5190MHz		---		5230MHz	
		Correction Factor(dB)	Power Density (dBm/MHz)	Correction Factor(dB)	Power Density (dBm/MHz)	Correction Factor(dB)	Power Density (dBm/MHz)
802.11n HT40	Chain0	1.03	-1.311	---	---	1.03	-1.490
802.11ac VHT40	Chain0	0.97	-1.201	---	---	0.97	-1.562


Test Mode	Antenna	5210MHz		---		---	
		Correction Factor(dB)	Power Density (dBm/MHz)	Correction Factor(dB)	Power Density (dBm/MHz)	Correction Factor(dB)	Power Density (dBm/MHz)
802.11ac VHT80	Chain0	1.15	-4.358	---	---	---	---




Test Mode: 802.11a



Test Mode:802.11a 5180MHz Chain0




Test Mode:802.11a 5220MHz Chain0




Test Mode:802.11a 5240MHz Chain0


Test Mode: 802.11n HT20



Test Mode:802.11n HT20 5180MHz Chain0




Test Mode:802.11n HT20 5220MHz Chain0




Test Mode:802.11n HT20 5240MHz Chain0


Test Mode: 802.11ac VHT20



Test Mode:802.11ac VHT20 5180MHz Chain0




Test Mode:802.11ac VHT20 5220MHz Chain0




Test Mode:802.11ac VHT20 5240MHz Chain0

Test Mode: 802.11n HT40




Test Mode:802.11n HT40 5190MHz Chain0




Test Mode:802.11n HT40 5230MHz Chain0

Test Mode: 802.11ac VHT40




Test Mode:802.11ac VHT40 5190MHz Chain0



Test Mode:802.11ac VHT40 5230MHz Chain0

Test Mode: 802.11ac VHT80



Test Mode:802.11ac VHT80 5210MHz Chain0