

UniFi SmartPower 6-Port Power Strip

The UniFi SmartPower Strip is a Wi-Fi connector power strip installed between an AC outlet and the power plugs of your internet connectivity hardware (modems, router, etc). The UniFi Network Controller continuously monitors availability of an internet connection. If the connection drops, the UniFi SmartPower Plug automatically restarts the connected devices by disconnecting power for a short period of time*.

The UniFi SmartPower Strip offers six power control outlets for 125VAC devices (up to 1250W total). Four USB Type A ports can charge smartphones, reading lights, and other devices (up to 1A per port).



* Requires UniFi Dream Machine



Mechanical

Dimensions 229.5 x 111.5 x 37.8 mm (9 x 4.4 x 1.5")

Weight 845 g (1.86 lb)

Enclosure Characteristics Fire Retardant Plastic, SABIC Lexan 945 Polycarbonate

Hardware

Processor Specs ESP8266, 32-bit Tensilica LX106 Core, 160 MHz

Memory Information 4 MB Flash

Management Interface 2.4 GHz Wi-Fi

Networking Interface 802.11 b/g/n Wi-Fi

Buttons (1) Multifunction Button

LEDs (1) Power, Blue/White
Flashing White: Bootup in Progress
Flashing Blue: Firmware Upgrading
Steady White: Factory Defaults, Awaiting Adoption
Steady Blue: Device is Adopted

Max. Power Consumption 1250W for 125VAC

Power Method AC Input

Power Supply AC/DC Embedded

Supported Power Voltage AC Input/Output: 125v~10A Max, 60 Hz

Operating Frequency 2.4 GHz

Antennas Single-Band Antenna

MIMO 1x1, 2x1

ESD/EMP Protection Air/Contact: ± 24 kV

Operating Temperature 0 to 40° C (32 to 104° F)

Operating Humidity 10 - 90% Noncondensing

Certifications FCC, IC

Software

Wi-Fi Standards 802.11 b/g/n

Power Save Yes

Wireless Security WPA2-PSK AES/TKIP

Supported Data Rates (Mbps)

802.11b 1, 2, 5.5, 11 Mbps

802.11g 6, 9, 12, 18, 24, 36, 48, 54 Mbps

802.11n

6.5 - 72.2 Mbps (MCS0 - MCS7, HT 20)



Specifications are subject to change. Ubiquiti products are sold with a limited warranty described at: www.ui.com/support/warranty ©2020 Ubiquiti Inc. All rights reserved. Ubiquiti, Ubiquiti Networks, the Ubiquiti U logo, the Ubiquiti beam logo, UniFi, and UniFi Network are trademarks or registered trademarks of Ubiquiti Inc. in the United States and in other countries. All other trademarks are the property of their respective owners.

FCC

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions.

1. This device may not cause harmful interference, and
2. This device must accept any interference received, including interference that may cause undesired operation.

The following apply to Class B products

This equipment has been tested and found to comply with the limits for a Class B digital device. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

ISED Canada

CAN ICES-3(B)/NMB-3(B)

This device complies with ISED Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions:

1. This device may not cause interference, and
2. This device must accept any interference, including interference that may cause undesired operation of the device.

CAN ICES-3(B)/NMB-3(B)

Le présent appareil est conforme aux CNR d'ISDE Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :

1. l'appareil ne doit pas produire de brouillage;
2. l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

RF Exposure Warning

The antennas used for this transmitter must be installed to provide a separation distance of at least 20 cm from all persons and must not be located or operating in conjunction with any other antenna or transmitter.

Les antennes utilisées pour ce transmetteur doivent être installées en considérant une distance de séparation de toute personnes d'au moins 20 cm et ne doivent pas être localisées ou utilisées en conflit avec tout autre antenne ou transmetteur.