

## SIDE A

### USER GUIDE START HERE

Download the Feit Electric App

For 24/7 customer support, visit [feit.com/help](http://feit.com/help)

**System Requirements**  
Minimum: iOS 9.3, Android 4.4 KitKat or higher  
- Dedicated 2.4GHz Wi-Fi Network -

YOUR SCREEN IMAGES MAY DIFFER FROM THIS USER GUIDE.

1. Go to your Wi-Fi settings and connect your phone to your 2.4GHz Wi-Fi network.  
**NOTE: Only works with 2.4GHz Wi-Fi networks**

2. Enter E-Mail address, then tap **Continue**. (A verification code will be sent to your email)

3. Create a Password then tap **Done**.

4. Launch the App and tap **Register** for new accounts or **Login** for existing accounts.

### Permissions & Location Access

5. Allow Notifications (Highly Recommended).

6. You must allow Feit Electric App to access your location to connect to your device.

7. Allow "Feit Electric" to access your location?

8. Enter your location name. Check where your device is located. Tap **Done**.

### Adding Device

**NOTE: Only works with 2.4GHz Wi-Fi networks**

9. Install and power On bulbs, then tap **Add Device** or the plus (+) sign on upper right corner.

### Simple Pairing Mode

10. Make sure you are connected to a 2.4GHz Wi-Fi Network. The device name(s) will pop up for Simple Pairing enabled devices. Tap on **Go to add**.

11. Make sure the bulb is blinking. Then select one from the list. Tap on **+ sign**.

**NOTE: If the bulb is not blinking, turn bulb Off-On-Off-On-Off-On**

12. Select your 2.4GHz Wi-Fi network, tap **Confirm**.

13. The status window will appear and show progress toward set-up.

**NOTE: If unsuccessful, the "Failed to Add" screen will appear. Quit the app and repeat the previous steps.**

14. To rename the device, tap the Pen icon, enter the new name and tap **Done**. The smart bulb is now ready to be controlled with the Feit Electric App.

**NOTE: Constant power to the bulbs is required at all times**

### Alternative Set-up Method (EZ-Mode)

15. Install and power On lighting then tap **Add Device** or the plus (+) sign on upper right corner.

**NOTE: Use this pairing mode to connect multiple devices at a time or if there are issues with Simple Pairing Mode.**

16. Make sure you are connected to a 2.4GHz Wi-Fi Network, then tap **Lighting** and then tap **Lighting Device**.

17. Tap upper right corner and make sure you have **EZ Mode** selected. Follow steps 11-13 to complete setup.

### Features

#### Individual Bulb On/Off

18. Tap the bulb icon to turn the bulb On/Off.

#### Individual Bulb Setting

19. Press and hold the icon for 2 seconds for bulb settings.

### Dimming

20. Slide the dimming bar up or down to set the brightness level.

21. Take below dimmer bar allow you to quick select preset color temperatures and the best color used.

### Tunable White

22. Use the round slider to adjust color temperatures from Warm (2700K) to Cool (6500K).

### Color Changing

23. Tap on any part of the color wheel to select a desired color. Preset colors can be selected below the wheel.

24. Use the slide bar to adjust the color saturation.

### Effects

25. Tap on **Effects**.

26. Choose an Effect

**Solid Fade:** Smooth fade in and out of 1 color.  
**Strobe Effect:** Flash transition between colors. (Up to 6 Colors)  
**Solid Strobe:** Flash on and off of 1 color.  
**Fade Effect:** Smooth transition between colors. (Up to 6 Colors)

### Schedule

27. Tap on **Schedule**.

28. Tap **Add Schedule**.

29. Choose a Start Time (On) and End Time (Off). To repeat on certain days of the week, tap **Repeat** otherwise the schedule will only occur once.

30. Tap on the day(s) of the week you would like the schedule to repeat, then tap back "**<**" then **Save**.

### Additional Features

31. Additional features are available in the bulb settings content menu, including renaming and removing devices. Tap the context menu in the upper right corner (•••).

### Groups

32. Tap the **Groups** icon at the bottom of the App.

**NOTE: To create groups you will need at least 2 bulbs.**

33. Tap on **Create Group**.

34. Tap on **Lighting devices**.

35. Select the bulbs that you want to group.

36. Tap the group name and enter the name of the group.

37. Once the group is named and the bulbs are selected tap **Save**.

**NOTE: Bulbs with different functionalities can be grouped, however the app will only be able to control the bulb's intended capabilities.**

### Manage Groups

38. Tap the **Groups** icon.

39. Tap the context menu in the upper right corner (•••).

40. Tap **Manage Group**.

41. Select the group to edit.

42. Once selected, tap **Manage Group** in the upper right hand corner.

43. Rename the group or remove a bulb from the group. Once complete, tap **Save** in the upper right corner.

44. Tap the **Groups** icon.

45. Tap the context menu in the upper right corner (•••).

46. Tap **Delete Group**.

### Delete Groups

47. Select the group to delete. Once selected, tap **Delete Group** in the upper right corner.

48. Tap **CONFIRM**.

49. Tap **CONFIRM**.

### Share Control of a Device (Two Methods)

50. Tap **Add** at the bottom.

51. Select the device that you wish to share. Tap **Sharing** in the upper right corner.

52. Enter the account name of the person you want to share with. This is typically their email address. Then tap **Done** when prompted.

**NOTE: New members must set up an account before sharing is possible.**

53. Enter **Home Settings**, then tap **Add members**.

54. Tap on **Create Group**.

55. Select the bulbs that you want to group.

56. Tap the group name and enter the name of the group.

57. Once the group is named and the bulbs are selected tap **Save**.

**NOTE: Bulbs with different functionalities can be grouped, however the app will only be able to control the bulb's intended capabilities.**

58. Tap the **Groups** icon.

59. Tap the context menu in the upper right corner (•••).

60. Tap **Manage Group**.

## SIDE B

61. Enter the new member's email address then tap **Add**.

**NOTE: New members must set up an account before sharing is possible.**

### Room Management

62. Tap the settings icon (⚙️) from the home menu, then tap **Add a Room**.

63. Tap on a preset room name or create your own.

64. Add individual lamps by tapping on the **+** icon next to each bulb's name.

65. When finished, tap on **Save**.

66. Remove individual lamps by tapping on the **-** icon next to each bulb's name.

### Home Management

67. Tap **Home** from the main menu, then tap **Home Management**.

68. Tap **Add Location** to indicate where the smart devices are located.

### Smart Scenes

69. Open the Feit Electric App and tap **Smart Scenes** located at the bottom of the screen.

70. In the Scene Tab screen, tap **Add Scenario** or **+ icon**.

71. Enter the scene name by tapping on the **Pen icon**. Then, tap **Confirm**.

72. Next to "Execute the following actions" tap the **+ icon** or tap the **Add Action** box.

73. On the **Select Action** screen, tap on a Device or Group to execute an action.

74. On the **Select Function** screen, tap on the action you want the device to perform. Different feature bulbs may have different actions available. Refer to the designations (A,B,C) below.

75. On the **Switch** screen, tap **On** or **Off**.

### Automation

76. Set up actions that occur automatically. Automations can be triggered by other smart devices, sunrise/sunset etc. From the Home Page tap **Smart Scenes**.

77. Tap **Automation** at the top of the screen, and then tap **+**.

78. To set up an Automation give it a name, select conditions, pick an action that will happen and choose a valid time period. After all the settings are done, click **Save**.

### ENABLE SIRI SHORTCUTS (for use with iPhone)

79. To enable Siri to recognize the scenario you've created, open the Feit Electric App and tap **Smart Scenes** located at the bottom of the screen.

80. In the Scene Tab, tap **add to Siri** located at the bottom of the screen.

81. In the **Siri Shortcut** screen, tap on the scenario you would like to add to Siri.

82. Once on the **Add to Siri** screen, tap on **Add to Siri** at the bottom of the screen.

83. On the **White light** screen, set **Color temperature** and **Brightness** level.

84. On the **Color light** screen, select **Color (RGB)**, **Saturation** and **Brightness** level.

85. Once you have configured your action(s), tap **Save**.

86. See your Scenario in **Smart Scenes** under the **Scene** tab.

87. It will also appear on the top of your **My Home** screen.

88. Tap on Scenario to execute your action.

89. Now you can use the "Hey Siri" command to control this action from your iOS device. "Hey Siri" "Switch On Floor Lamp"

### CONNECTING TO ALEXA

90. Tap on **Profile** at bottom right. Tap on **Use Alexa and Google Assistant**.

91. Tap on **Amazon Alexa**.

92. Tap on **Sign In With Amazon**. If you do not have an account with Amazon, please create one.

93. Tap on **Link**. You will be linked automatically to your Amazon Alexa app.

**Note: Additional devices will be added automatically when added to the Feit Electric App.**

### CONNECTING TO GOOGLE ASSISTANT

94. Tap on **Profile** at bottom right. Tap on **Use Alexa and Google Assistant**.

95. Tap on **Google Assistant**.

96. Tap on **Re-Login**. If you do not have an account with Google, please create one.

97. Tap on **Agree and Link**. You will be linked automatically to your Google Assistant app.

**Note: Additional devices will be added automatically when added to the Feit Electric App.**

### Need Help?

24/7 HELP

For 24/7 customer support, visit [feit.com/help](http://feit.com/help)

[www.feit.com/smart-energy-consumption/](http://www.feit.com/smart-energy-consumption/)

## **RF exposure statement**

This equipment complies with the FCC RF radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with a minimum distance of 20cm between the radiator and any part of your body.

This equipment meets the exemption from the routine evaluation limits in section 2.5 of RSS-102. It should be installed and operated with a minimum distance of 20cm between the radiator and any part of your body.

Cet équipement est conforme à l'exemption des limites d'évaluation habituelle de la section 2.5 de la norme RSS-102. Il doit être installé et utilisé à une distance minimale de 20 cm entre le radiateur et toute partie de votre corps.

## **FCC Warning**

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

NOTE 2: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

## **IC WARNING**

This device contains licence-exempt transmitter(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:

- (1) This device may not cause interference.
- (2) This device must accept any interference, including interference that may cause undesired operation of the device.

L'émetteur/récepteur exempt de licence contenu dans le présent appareil est conforme aux CNR d'Innovation, Sciences et Développement économique Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes:

1. L'appareil ne doit pas produire de brouillage;
2. L'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Note: Bluetooth function will be turned off in the actual product. Bluetooth will be turned off when the product is working and will not be used