



March 30, 2009

Shenzhen Zowee Technology Co., Ltd.
Block 5, Science & Technology Industrial Park of Privately Owned Enterprises,
Pingshan, Xili, Nanshan District,
Shenzhen, China.

Dear Xinmin Chen:

Enclosed you will find your file copy of a Part 15 report (FCC ID: T5Q010901).

For your reference, TCB will normally take another 15-20 days for reviewing the report.
Approval will then be granted when no query is sorted.

Please contact me if you have any questions regarding the enclosed material.

Sincerely,

A handwritten signature in black ink, appearing to read "Shawn Xing", with a stylized flourish extending to the right.

Shawn Xing
Assistant Manager

Enclosure


Intertek Testing Services Shenzhen Ltd. Kejiyuan Branch

6F, D Block, Huahan Building, Langshan Road, Nanshan District, Shenzhen, P. R. China
Tel: (86 755) 8601 6288 Fax: (86 755) 8601 6751 Website: www.china.intertek-etlsemko.com

Shenzhen Zowee Technology Co.,Ltd.

Application
For
Certification
(FCC ID: T5Q010901)

Weather Band Receiver
and
315MHz Receiver



SZ09030027-1

Louisa Lu

March 30, 2009

- The test results reported in this test report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report is for the exclusive use of Intertek's Client and is provided pursuant to the agreement between Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this report. Only the Client is authorized to copy or distribute this report. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek. The observations and test results referenced from this report are relevant only to the sample tested. This report by itself does not imply that the material, product, or service is or has ever been under an Intertek certification program.
- For Terms And Conditions of the services, it can be provided upon request.
- The evaluation data of the report will be kept for 3 years from the date of issuance.

TRF no.: FCC 15B_RX-SHa

Intertek Testing Services Shenzhen Ltd. Kejiyuan Branch

6F, D Block, Huahan Building, Langshan Road, Nanshan District, Shenzhen, P. R. China
Tel: (86 755) 8601 6288 Fax: (86 755) 8601 6751 Website: www.china.intertek-etlsemko.com

INTERTEK TESTING SERVICES

LIST OF EXHIBITS

INTRODUCTION

<i>EXHIBIT 1:</i>	General Description
<i>EXHIBIT 2:</i>	System Test Configuration
<i>EXHIBIT 3:</i>	Emission Results
<i>EXHIBIT 4:</i>	Equipment Photographs
<i>EXHIBIT 5:</i>	Product Labeling
<i>EXHIBIT 6:</i>	Technical Specifications
<i>EXHIBIT 7:</i>	Instruction Manual
<i>EXHIBIT 8:</i>	Miscellaneous Information

INTERTEK TESTING SERVICES

MEASUREMENT / TECHNICAL REPORT

Shenzhen Zowee Technology Co.,Ltd. – MODEL: NS-CLW01
ADDITIONAL MODEL: P109 / P109A / P109B / P109C / P109D

FCC ID: T5Q010901

March 30, 2009

This report concerns (check one:) Original Grant ☒ Class II Change ☐

Equipment Type: CXX-Communications Rcvr for use w/licensed Tx and CBs
CYY-Communications Receiver used w/Pt15 Transmitter

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)? Yes ☐ No ☒

If yes, defer until: _____
date


Company Name agrees to notify the Commission by: _____
date

of the intended date of announcement of the product so that the grant can be issued on that date.

Transition Rules Request per 15.37? Yes ☐ No ☒

If no, assumed Part 15, Subpart C for intentional radiator – the new 47 CFR [09-20-07 Edition] provision.

Report prepared by:



Shawn Xing
Intertek Testing Services Shenzhen Ltd.
Kejiyuan Branch
6F, Block D, Huahan Building, Langshan Road,
Nanshan District, Shenzhen, P. R. China
Phone: (86 755) 8601 6288
Fax: (86 755) 8601 6751

INTERTEK TESTING SERVICES

Table of Contents

1.0	<u>General Description</u>	2
1.1	Product Description	2
1.2	Related Submittal(s) Grants	2
1.3	Test Methodology	3
1.4	Test Facility	3
2.0	<u>System Test Configuration</u>	5
2.1	Justification	5
2.2	EUT Exercising Software	5
2.3	Special Accessories	5
2.4	Equipment Modification	5
2.5	Measurement Uncertainty	6
2.6	Support Equipment List and Description	6
3.0	<u>Emission Results</u>	8
3.1	Field Strength Calculation	9
3.2	Radiated Emission Configuration Photograph	10
3.3	Radiated Emission Data	11
3.4	Conducted Emission Configuration Photograph	14
3.5	Conducted Emission Data	15
4.0	<u>Equipment Photographs</u>	19
5.0	<u>Product Labelling</u>	21
6.0	<u>Technical Specifications</u>	23
7.0	<u>Instruction Manual</u>	25
8.0	<u>Miscellaneous Information</u>	27
8.1	Discussion of Pulse Desensitization	28
8.2	Calculation of Average Factor	29
8.3	Emissions Test Procedures	30

INTERTEK TESTING SERVICES

List of attached file

Exhibit Type	File Description	Filename
Test Report	Test Report	report.pdf
Test Setup Photo	Radiated Emission	radiated photos.pdf
Test Setup Photo	Conducted Emission	conducted photos.pdf
External Photo	External Photo	external photos.pdf
Internal Photo	Internal Photo	internal photos.pdf
Schematics	Circuit Diagram	circuit.pdf
Operation Description	Technical Description	descri.pdf
Block Diagram	Block Diagram	block.pdf
ID Label / Location	Label Artwork and Location	label.pdf
User Manual	User Manual	manual.pdf
Cover Letter	Letter of agency	agency.pdf

INTERTEK TESTING SERVICES

EXHIBIT 1

GENERAL DESCRIPTION

INTERTEK TESTING SERVICES

1.0 **General Description**

1.1 Product Description

The Equipment Under Test (EUT) is a Clock Radio with AM, FM, Weather Band function, It's also has a temperature sensor to measure the indoor temperature and receive the temperature signal which it's send by the outdoor 315MHz transmitter and display the relative outdoor temperature reading as OUTDOOR TEMP. The EUT is powered by 120V AC, 60Hz or by 6Vdc (4× 1.5Vdc "AA" batteries).

The Model: P109 / P109A / P109B / P109C / P109D are the same as the tested Model: NS-CLW01 in hardware and software aspect. The only differences are the packing accessories and model no. for trading purpose.

Antenna Type: Integral

For electronic filing, the brief circuit description is saved with filename: descri.pdf.

1.2 Related Submittal(s) Grants

This is an application for Certification of a receiver. The transmitter, associated with this receiver, has FCC ID: T5Q010902 and has been filled at the same time.

INTERTEK TESTING SERVICES

1.3 Test Methodology

Both AC mains line-conducted and radiated emission measurements were performed according to the procedures in ANSI C63.4 (2003). Radiated emission measurement was performed in semi-anechoic chamber and conducted emission measurement was performed in shield room. For radiated emission measurement, preliminary scans were performed in the semi-anechoic chamber only to determine the worst case modes. All radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the "**Justification Section**" of this Application.

1.4 Test Facility

The Semi-Anechoic chamber and shield room used to collect the radiated data and conducted data is **Interterk Testing Services Shenzhen Ltd. Kejiyuan Branch** and located at 6F, Block D, Huahan Building, Langshan Road, Nanshan District, Shenzhen, P. R. China. This test facility and site measurement data have been fully placed on file with the FCC.

INTERTEK TESTING SERVICES

EXHIBIT 2

SYSTEM TEST CONFIGURATION

INTERTEK TESTING SERVICES

2.0 **System Test Configuration**

2.1 Justification

The system was configured for testing in a typical fashion (as a customer would normally use it), and in the confines as outlined in ANSI C63.4 (2003).

The EUT was powered by 120V AC / 60Hz or 6Vdc (4×1.5Vdc “AA” batteries). during test.

For maximizing emissions, the EUT was rotated through 360°, the antenna height was varied from 1 meter to 4 meters above the ground plane, and the antenna polarization was changed. The step by step procedure for maximizing emissions led to the data reported in Exhibit 3.0.

The rear of unit shall be flushed with the rear of the table.

The equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). The EUT was placed on turntable, which enabled the engineer to maximize emissions through its placement in the three orthogonal axes.

The frequency range from 30MHz to 2GHz was searched for spurious emissions from the device. Only those emissions reported were detected. All other emissions were at least 20 dB below the applicable limits.

2.2 EUT Exercising Software

There was no special software to exercise the device.

2.3 Special Accessories

There are no special accessories necessary for compliance of this product.

2.4 Equipment Modification

Any modifications installed previous to testing by Shenzhen Zowee Technology Co.,Ltd. will be incorporated in each production model sold / leased in the United States.

No modifications were installed by Intertek Testing Services.

INTERTEK TESTING SERVICES

2.5 Measurement Uncertainty

When determining the test conclusion, the Measurement Uncertainty of test has been considered.

2.6 Support Equipment List and Description

This product was tested in the following configuration:


Refer List:

Description	Manufacturer	Model No.
Signal Generator	R&S	SML03

All the items listed under section 2.0 of this report are

Confirmed by:

Shawn Xing
Assistant Manager
Intertek Testing Services Shenzhen Ltd.
Kejiyuan Branch
Agent for Shenzhen Zowee Technology Co.,Ltd.



Signature

March 30, 2009 *Date*

INTERTEK TESTING SERVICES

EXHIBIT 3

EMISSION RESULTS

INTERTEK TESTING SERVICES

3.0 **Emission Results**

Data is included worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

INTERTEK TESTING SERVICES

3.1 Field Strength Calculation

The field strength is calculated by adding the Antenna Factor and Cable Factor, and subtracting the Amplifier Gain (if any) from the measured reading. The basic equation with a sample calculation is as follows:

$$FS = RA + AF + CF - AG$$

where FS = Field Strength in dB μ V/m
 RA = Receiver Amplitude (including preamplifier) in dB μ V
 CF = Cable Attenuation Factor in dB
 AF = Antenna Factor in dB
 AG = Amplifier Gain in dB

In the following table(s), the reading shown on the data table reflects the preamplifier gain. An example for the calculations in the following table is as follows:

$$FS = RR + LF$$

where FS = Field Strength in dB μ V/m
 $RR = RA - AG$ in dB μ V
 $LF = CF + AF$ in dB

Assume a receiver reading of 52.0 dB μ V is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB are added. The amplifier gain of 29 dB is subtracted, giving a field strength of 32 dB μ V/m. This value in dB μ V/m was converted to its corresponding level in μ V/m.

$RA = 52.0$ dB μ V/m	
$AF = 7.4$ dB	$RR = 23.0$ dB μ V
$CF = 1.6$ dB	$LF = 9.0$ dB
$AG = 29.0$ dB	
$FS = RR + LF$	
$FS = 23 + 9 = 32$ dB μ V/m	

Level in μ V/m = Common Antilogarithm $[(32 \text{ dB}\mu\text{V/m})/20] = 39.8 \mu\text{V/m}$

INTERTEK TESTING SERVICES

3.2 Radiated Emission Configuration Photograph

Worst Case Radiated Emission
At
1581.574MHz

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: radiated photos.pdf.

INTERTEK TESTING SERVICES

3.3 Radiated Emission Data

The data on the following page lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit.

Judgement: Passed by 6.4dB margin

TEST PERSONNEL:



Signature

Louisa Lu, Engineer
Typed / Printed Name

March 30, 2009
Date

INTERTEK TESTING SERVICES

Company: Shenzhen Zowee Technology Co.,Ltd.

Date of Test: March 30, 2009

Model: NS-CLW01

Operating Mode: weather band (162.475MHz)

Table 1

FCC Class B Radiated Emissions

Polarization	Frequency (MHz)	Reading (dBμV)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Net at 3m (dBμV/m)	Limit at 3m (dBμV/m)	Margin (dB)
Horizontal	41.640	27.8	20.0	12.5	20.3	40.0	-19.7
Horizontal	162.475	25.0	20.0	9.6	14.6	43.5	-28.9
Vertical	162.475	25.0	20.0	9.6	14.6	43.5	-28.9
Horizontal	316.305	33.7	20.0	14.6	28.3	46.0	-17.7
Vertical	316.309	39.5	20.0	14.6	34.1	46.0	-11.9
Horizontal	324.950	25.9	20.0	14.8	20.7	46.0	-25.3
Vertical	324.950	26.0	20.0	14.8	20.8	46.0	-25.2

- NOTES: 1. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distances were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
2. Negative value in the margin column shows emission below limit.
3. Horn antenna used for the emission over 1000MHz.
4. All emissions below 1000MHz are below the QP limit and all emissions above 1000MHz are below the AV limit.

Test Engineer: Louisa Lu

INTERTEK TESTING SERVICES

Company: Shenzhen Zowee Technology Co.,Ltd.

Date of Test: March 30, 2009

Model: NS-CLW01

Operating Mode: Recieve

Table 2

FCC Class B Radiated Emissions

Polarization	Frequency (MHz)	Reading (dBμV)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Net at 3m (dBμV/m)	Limit at 3m (dBμV/m)	Margin (dB)
Horizontal	316.315	39.6	20.0	14.6	34.2	46.0	-11.8
Vertical	316.315	37.3	20.0	14.6	31.9	46.0	-14.1
Horizontal	632.624	32.7	20.0	20.4	33.1	46.0	-12.9
Vertical	632.624	30.8	20.0	20.4	31.2	46.0	-14.8
Horizontal	948.945	34.6	20.0	23.7	38.3	46.0	-7.7
Vertical	948.945	32.9	20.0	23.7	36.6	46.0	-9.4
Vertical	1581.574	57.2	36.9	27.3	47.6	54.0	-6.4

- NOTES: 1. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distances were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
2. Negative value in the margin column shows emission below limit.
3. Horn antenna used for the emission over 1000MHz.
4. All emissions below 1000MHz are below the QP limit and all emissions above 1000MHz are below the AV limit.

Test Engineer: Louisa Lu

INTERTEK TESTING SERVICES

3.4 Conducted Emission Configuration Photograph

Worst Case Line-Conducted Configuration
at
2.787 MHz


For electronic filing, the worst case conducted emission configuration photograph is saved with filename: conducted photos.pdf.

INTERTEK TESTING SERVICES

3.5 Conducted Emission Data

Judgement: Passed by 38.5 dB margin

TEST PERSONNEL:



Signature

Louisa Lu, Engineer
Typed/Printed Name

March 30, 2009
Date

INTERTEK TESTING SERVICES

Company: Shenzhen Zowee Technology Co.,Ltd.

Date of Test: March 6, 2009

Model: NS-CLW01

Worst Case Operating Mode: weather band (162.475MHz)

Table 3

Conducted Emissions

Live Line Data

Frequency (MHz)	Quasi-Peak		Average	
	Disturbance level dB(μ V)	Permitted limit dB(μ V)	Disturbance level dB(μ V)	Permitted limit dB(μ V)
0.230	9.0	62.4	5.9	52.4
0.366	8.2	58.6	5.4	48.6
0.758	7.8	56.0	5.0	46.0
1.746	7.7	56.0	5.1	46.0
2.818	12.4	56.0	6.9	46.0
6.391	10.5	60.0	5.8	50.0

Neutral Line Data

Frequency (MHz)	Quasi-Peak		Average	
	Disturbance level dB(μ V)	Permitted limit dB(μ V)	Disturbance level dB(μ V)	Permitted limit dB(μ V)
0.174	10.0	64.8	6.8	54.8
2.787	12.0	56.0	7.5	46.0
16.017	8.9	60.0	4.4	50.0
17.042	10.3	60.0	5.8	50.0
23.430	11.8	60.0	7.1	50.0
25.558	11.7	60.0	6.9	50.0

Test Engineer: Louisa Lu

TRF no.: FCC 15B_RX-SHa

FCC ID: T5Q010901

INTERTEK TESTING SERVICES

Company: Shenzhen Zowee Technology Co.,Ltd.

Date of Test: March 27, 2009

Model: NS-CLW01

Worst Case Operating Mode: Receive

Table 4

Conducted Emissions

Live Line Data

Frequency (MHz)	Quasi-Peak		Average	
	Disturbance level dB(μV)	Permitted limit dB(μV)	Disturbance level dB(μV)	Permitted limit dB(μV)
0.173	12.3	64.8	9.0	54.8
0.519	8.4	56.0	5.3	46.0
1.122	7.9	56.0	5.1	46.0
1.950	7.8	56.0	5.0	46.0
2.773	8.7	56.0	4.3	46.0
10.000	8.4	60.0	4.0	50.0

Neutral Line Data

Frequency (MHz)	Quasi-Peak		Average	
	Disturbance level dB(μV)	Permitted limit dB(μV)	Disturbance level dB(μV)	Permitted limit dB(μV)
0.173	12.2	64.8	8.8	54.8
0.834	7.7	56.0	5.1	46.0
1.599	7.6	56.0	5.0	46.0
2.652	8.9	56.0	4.3	46.0
8.943	8.6	60.0	4.2	50.0
20.800	8.6	60.0	4.3	50.0

Test Engineer: Louisa Lu

TRF no.: FCC 15B_RX-SHa

FCC ID: T5Q010901

INTERTEK TESTING SERVICES

EXHIBIT 4

EQUIPMENT PHOTOGRAPHS

INTERTEK TESTING SERVICES

4.0 **Equipment Photographs**

For electronic filing, photographs of the tested EUT are saved with filename: external photos.pdf and internal photos.pdf.

INTERTEK TESTING SERVICES

EXHIBIT 5

PRODUCT LABELLING

INTERTEK TESTING SERVICES

5.0 **Product Labelling**

For electronics filing, the FCC ID label artwork and the label location are saved with filename: label.pdf.

INTERTEK TESTING SERVICES

EXHIBIT 6

TECHNICAL SPECIFICATIONS

INTERTEK TESTING SERVICES

6.0 **Technical Specifications**

For electronic filing, the block diagram of the tested EUT is saved with filename: block.pdf.

INTERTEK TESTING SERVICES

EXHIBIT 7

INSTRUCTION MANUAL

INTERTEK TESTING SERVICES

7.0 **Instruction Manual**

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf.

This manual will be provided to the end-user with each unit sold / leased in the United States.

INTERTEK TESTING SERVICES

EXHIBIT 8

MISCELLANEOUS INFORMATION

INTERTEK TESTING SERVICES

8.0 **Miscellaneous Information**

This miscellaneous information includes the test procedure and calculation of factors such as pulse desensitization and averaging factor.

INTERTEK TESTING SERVICES

8.1 Discussion of Pulse Desensitization

The determination of pulse desensitivity was made in accordance with Hewlett Packard Application Note 150-2, *Spectrum Analysis ... Pulsed RF*.

This device is a superheterodyne receiver. The stabilized signals are continuous, and no desensitization of the measurement equipment occurs.

INTERTEK TESTING SERVICES

8.2 Calculation of Average Factor

The emission limits are specified using spectrum analyzers or receivers which incorporate quasi-peak detectors. Typical measurements are made using peak detectors, however, emissions which approach the respective emission limit are measured using a quasi-peak detector.

For measurements above 1 GHz, spectrum analyzers or receivers using average detectors are employed, or the appropriate average factor can be applied.

Measurements using spectrum analyzers with filters other than peak detectors are recorded in the data table section of this report.

This device is a superheterodyne receiver.

It is not necessary to apply average factor to the measurement results.

INTERTEK TESTING SERVICES

8.3 Emissions Test Procedures

The following is a description of the test procedure used by Intertek Testing Services Shenzhen Ltd. Kejiyuan Branch in the measurements of superheterodyne receivers operating under the Part 15, Subpart B rules.

The test set-up and procedures described below are designed to meet the requirements of ANSI C63.4 - 2003. A typical or an unmodulated CW signal at the operating frequency of the EUT has been supplied to the EUT for all measurements. Such a signal is supplied by a signal generator and an antenna in close proximity to the EUT. The signal level is sufficient to stabilize the local oscillator of the EUT.

The equipment under test (EUT) is placed on a wooden turntable which is four feet in diameter and approximately one meter in height above the groundplane. During the radiated emissions test, the turntable is rotated and any cables leaving the EUT are manipulated to find the configuration resulting in maximum emissions. The EUT is adjusted through all three orthogonal axis to obtain maximum emission levels. The antenna height and polarization are also varied during the testing to search for maximum signal levels. The height of the antenna is varied from one to four meters.

Detector function for radiated emissions is in peak mode. Average readings, when required, are taken by measuring the duty cycle of the equipment under test and subtracting the corresponding amount in dB from the measured peak readings.

The frequency range from 30MHz to 2GHz was searched for spurious emissions from the device. For line conducted emissions, the range scanned is 150 kHz to 30 MHz.

INTERTEK TESTING SERVICES

8.3 Emissions Test Procedures (cont'd)

The EUT is warmed up for 15 minutes prior to the test.

AC power to the unit is varied from 85% to 115% nominal and variation in the fundamental emission field strength is recorded. If battery powered, a new, fully charged battery is used.

Conducted measurements were made as described in ANSI C63.4 - 2003.

The IF bandwidth used for measurement of radiated signal strength was 100 kHz or greater when frequency is below 1000 MHz. Where pulsed transmissions of short enough pulse duration warrant, a greater bandwidth is selected according to the recommendations of Hewlett Packard Application Note 150-2. A discussion of whether pulse desensitivity is applicable to this unit is included in this report. Above 1000 MHz, a resolution bandwidth of 1 MHz is used.

Measurements are normally conducted at a measurement distance of three meters. All measurements are extrapolated to three meters using inverse scaling, unless otherwise reported. Measurements taken at a closer distance are so marked.