



# RF EXPOSURE REPORT

**REPORT NO.:** SA131205E01  
**MODEL NO.:** RTL8812AEBT  
**FCC ID:** TX2RTL8812AEBT  
**RECEIVED:** Dec. 04, 2013  
**TESTED:** Jan. 14 to 17, 2014  
**ISSUED:** Feb. 10, 2014

**APPLICANT:** Realtek Semiconductor Corp.

**ADDRESS:** No. 2, Innovation Road II, Hsinchu Science Park, Hsinchu 300, Taiwan

**ISSUED BY:** Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch Hsin Chu Laboratory

**LAB ADDRESS:** No. 81-1, Lu Liao Keng, 9th Ling, Wu Lung Tsuen, Chiung Lin Hsiang, Hsin Chu Hsien 307, Taiwan, R.O.C.

This report should not be used by the client to claim product certification, approval, or endorsement by any government agencies.

This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification



## TABLE OF CONTENTS

RELEASE CONTROL RECORD .....	3
1. CERTIFICATION .....	4
2. RF EXPOSURE LIMIT .....	5
3. MPE CALCULATION FORMULA .....	5
4. CLASSIFICATION .....	5
5. ANTENNA GAIN .....	6
7. CALCULATION RESULT OF MAXIMUM CONDUCTED POWER .....	8



## RELEASE CONTROL RECORD

ISSUE NO.	REASON FOR CHANGE	DATE ISSUED
SA131205E01	Original release	Feb. 10, 2014

## 1. CERTIFICATION

**PRODUCT:** 802.11a/b/g/n/ac RTL8812AE Combo module  
**BRAND NAME:** Realtek  
**MODEL NO.:** RTL8812AEBT  
**TEST SAMPLE:** ENGINEERING SAMPLE  
**APPLICANT:** Realtek Semiconductor Corp.  
**TESTED DATE:** Jan. 14 to 17, 2014  
**STANDARDS:** FCC Part 2 (Section 2.1091)  
FCC OET Bulletin 65, Supplement C (01-01)  
IEEE C95.1

The above equipment (Model: RTL8812AEBT) has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

**PREPARED BY :** Midoli Peng , **DATE:** Feb. 10, 2014  
( Midoli Peng, Specialist )

**APPROVED BY :** May Chen , **DATE:** Feb. 10, 2014  
( May Chen, Manager )

## 2. RF EXPOSURE LIMIT

### LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

FREQUENCY RANGE (MHz)	ELECTRIC FIELD STRENGTH (V/m)	MAGNETIC FIELD STRENGTH (A/m)	POWER DENSITY (mW/cm <sup>2</sup> )	AVERAGE TIME (minutes)
<b>LIMITS FOR GENERAL POPULATION / UNCONTROLLED EXPOSURE</b>				
300-1500	...	...	F/1500	30
1500-100,000	...	...	1.0	30

F = Frequency in MHz

### 3. MPE CALCULATION FORMULA

$$P_d = (P_{out} * G) / (4 * \pi * r^2)$$

where

$P_d$  = power density in mW/cm<sup>2</sup>

$P_{out}$  = output power to antenna in mW

G = gain of antenna in linear scale

$\pi$  = 3.1416

r = distance between observation point and center of the radiator in cm

### 4. CLASSIFICATION

The antenna of this product, under normal use condition, is at least 20cm away from the body of the user. So, this device is classified as **Mobile Device**.

## 5. ANTENNA GAIN

The antennas provided to the EUT, please refer to the following table:

No.	Brand	Model	Antenna Type	Peak gain with cable loss (dBi) (2.4GHz)	Peak gain with cable loss(dBi) (5GHz)	Cable Loss (dB) (2.4GHz)	Cable Loss (dB) (5GHz)	Connector Type
1	LYNwave	ALA110-222050-300010 (Main) ALA110-222050-300010 (Aux)	PIFA	3.5 3.5	5 5	NA	NA	IPEX
2	JOYMAX	TWF-614XMPXX-500 (Main) TWF-614XMPXX-500 (Aux)	Dipole	3 3	5 5	NA	NA	IPEX
3	WGT	SKA91WMPB02+A (Tx1) SKA91WMPB01+A (Tx2)	PIFA	0.82 -2.23	0.94 2.18	-1.32 -0.75	-2.04 -1.17	IPEX
4	JEM	1510-0122-0027 (Tx1) 1510-0122-0027 (Tx2)	PIFA	3.23 2.31	4.89 1.89	NA	NA	RF
5	FVC	K05007014501(6-23-7W25H-010) (Tx1) K05007014501(6-23-7W25H-010) (Tx2)	PIFA	2.85 1.59	2.46 2.91	NA	NA	IPEX
6	JEM	1510-0122-0022(IA-120073) (Tx1) 1510-0122-0022(IA-120073) (Tx2)	PIFA	2.23 2.21	1.69 1.84	NA	NA	RF
7	WGT	SK81WMPB01+A (Tx1) SK81WMPB02+A (Tx2)	PIFA	1.79 0.66	1.49 -0.40	-1.88 -2.95	-3.17 -4.96	IPEX
8	WGT	SKW2UWMPB01+A (Tx1) SKW2UWMPB01+A (Tx2)	PIFA	1.36 2.88	1.92 3.16	NA	NA	IPEX
9	WGT	SKW25WMPB01+A (Tx1) SKW25WMPB01+A (Tx2)	PIFA	0.72 0.49	-0.72 -0.71	-1.41 -1.39	-2.18 -2.15	IPEX
10	WGT	SK549WMPB01+A (Tx1) SK549WMPB02+A (Tx2)	PIFA	-0.17 -2.24	-0.13 0.03	-1.04 -0.88	-1.94 -1.64	IPEX
11	WGT	SK110WMPB01+A (Tx1) SK110WMPB02+A (Tx2)	PIFA	1.05 -0.41	1.08 2.32	-0.98 -0.99	-1.52 -1.54	IPEX
12	WGT	SKW31WMPB01+A (Tx1) SKW31WMPB01+A (Tx2)	PIFA	1.85 3.14	1.74 2.10	NA	NA	IPEX
13	FVC	6-23-7B51M-031 (Tx1) 6-23-7B51M-031 (Tx2)	PIFA	1.58 1.75	2.54 2.24	NA	NA	IPEX
14	FVC	6-23-7E51Q-011 (Tx1) 6-23-7E51Q-011 (Tx2)	PIFA	2.70 2.19	1.57 2.94	NA	NA	IPEX
15	FVC	6-23-7B710-022 (WM1) 6-23-7B710-022 (WM2)	PIFA	1.51 2.04	2.99 3.02	NA	NA	IPEX
16	WGT	SKM11WMPB03+A (Tx1) SKM11WMPB02+D (Tx2)	PIFA	-1.84 -2.93	0.44 1.35	1.17 0.89	2.02 1.54	IPEX
17	WGT	SKW23WMPB01+A (Tx1) SKW23WMPB02+A (Tx2)	PIFA	-1.61 -2.84	-0.14 -0.96	-2.10 -2.07	-3.25 -3.20	IPEX
18	WGT	SKW24WMPB01+B (WM1) SKW24WMPB01+B (WM2)	PIFA	1.25 3.17	1.95 2.42	NA	NA	IPEX

No.	Brand	Model	Antenna Type	Peak gain with cable loss (dBi) (2.4GHz)	Peak gain with cable loss(dBi) (5GHz)	Cable Loss (dB) (2.4GHz)	Cable Loss (dB) (5GHz)	Connector Type
19	FVC	K05007015501(6-23-7W244-020-1) (Tx1) K05007015501(6-23-7W244-020-1) (Tx2)	PIFA	2.53 2.28	2.86 2.97	NA	NA	IPEX
20	FVC	K05007014201(6-23-7W25P-020) (Tx1) K05007014201(6-23-7W25P-020) (Tx2)	PIFA	3.00 1.52	2.82 2.21	NA	NA	IPEX
21	WGT	SKW10WMPB01+A (Tx1) SKW10WMPB02+A (Tx2)	PIFA	0.85 0.44	0.75 1.24	-1.56 -1.53	-2.42 -2.36	IPEX
22	WGT	SKCZTWMPB01+A (Tx1) SKCZTWMPB02+A (Tx2)	PIFA	0.46 -0.79	2.80 1.03	-1.56 -1.53	-2.42 -2.36	IPEX
23	JEM	IA-120266 (Tx1) IA-120267 (Tx2)	PIFA	2.60 0.53	2.61 2.60	2.12 1.76	3.48 2.87	IPEX
24	WGT	SK547WMPB01+A (Tx1) SK549WMPB02+A (Tx2)	PIFA	-0.66 0.78	-0.19 2.06	-1.42 -1.43	-2.20 -2.21	IPEX
25	WGT	SK555WMPB01+B (Tx1) SK555WMPB02+B (Tx2)	PIFA	0.76 0.09	1.97 0.56	-1.83 -1.80	-2.83 -2.78	IPEX
26	WGT	SK65EWMPB01+A (Tx1) SK650WMPB02+A (Tx2)	PIFA	0.42 -0.13	0.11 1.27	-1.56 -0.61	-2.41 -0.94	IPEX
27	WGT	SK670WMPB01+A (Tx1) SK670WMPB02+A (Tx2)	PIFA	1.48 1.15	-0.44 0.42	-2.47 -1.93	-3.82 -2.99	IPEX
28	WGT	SK740WMPB01+A (Tx1) SK740WMPB02+A (Tx2)	PIFA	-0.93 0.20	0.96 0.86	-1.39 -1.26	-2.16 -1.95	IPEX
29	WGT	SK840WMPB01+B_SN (Tx1) SK840WMPB01+B_SN (Tx2)	PIFA	3.03 0.55	4.16 0.90	-1.12 -1.20	-1.74 -1.86	IPEX
30	WGT	SK94SWMPB01+B (TX1) SK94SWMPB01+B (TX2)	PIFA	0.76 0.46	1.12 1.44	-0.32 -0.44	-0.50 -0.68	IPEX
31	WGT	SK94TWMPB01+B (TX1) SK94TWMPB01+B (TX2)	PIFA	1.32 1.86	2.59 1.57	-0.59 -0.71	-0.91 -1.10	IPEX
32	WGT	SK50SWMPB01+A (TX1) SK50SWMPB02+A (TX2)	PIFA	-0.03 -0.13	1.25 2.13	-0.86 -0.72	-1.32 -1.12	IPEX
33	WGT	SK94TWMPB01+D (TX1) SK94TWMPB01+D (TX2)	PIFA	1.32 1.86	2.59 1.57	-0.59 -0.71	-0.91 -1.10	IPEX
34	WGT	SKC45WMPB03+B (WM1) SKC45WMPB03+B (WM2)	PIFA	2.46 2.91	2.90 2.67	NA	NA	IPEX
35	FVC	K05007015801 (WM1) K05007015901 (WM2)	PIFA	3.12 1.01	3.51 1.93	NA	NA	RF
36	WGT	SK345WMPB01+A (WM1) SK345WMPB02+A (WM2)	PIFA	0.86 2.51	2.94 3.25	NA	NA	IPEX
37	FVC	K05007014901 (WM1) K05007015001 (WM2)	PIFA	1.85 1.94	1.35 1.99	NA	NA	IPEX
38	WGT	SKX51WMPB01+C (WM1) SKX51WMPB02+C (WM2)	PIFA	3.2 2.76	2.28 2.51	NA	NA	IPEX

Antenna 1 & 2 were chosen for final test.

## 6. CALCULATION RESULT OF MAXIMUM CONDUCTED POWER

For WLAN: 15.247(2.4GHz)

802.11b, 1Tx

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2412 - 2462	123.310	3.5	20	0.05492	1.00

802.11g, 1Tx

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2412 - 2462	358.922	3.5	20	0.15986	1.00



### 802.11g, 2Tx

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2412 - 2462	572.434	6.51	20	0.50986	1.00

Directional gain = 3.5dBi + 10log(2) = 6.51dBi

### 802.11n(HT20), 2Tx

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2412 - 2462	514.717	6.51	20	0.45846	1.00

Directional gain = 3.5dBi + 10log(2) = 6.51dBi

### 802.11n(HT40), 2Tx

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2422 - 2452	393.088	6.51	20	0.35012	1.00

Directional gain = 3.5dBi + 10log(2) = 6.51dBi

### BT-LE(GFSK)

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2402 - 2480	2.415	3.5	20	0.00108	1.00

**For WLAN: 15.247(5GHz)**
**802.11a, 1Tx**

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5745 - 5825	306.902	5	20	0.19308	1.00

**802.11a, 2Tx**

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5745 - 5825	676.106	8.01	20	0.85064	1.00

Directional gain = 5dBi + 10log(2) = 8.01dBi

**802.11ac(VHT20)**

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5745 - 5825	579.327	8.01	20	0.72887	1.00

Directional gain = 5dBi + 10log(2) = 8.01dBi

**802.11ac(VHT40)**

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5755 - 5795	592.004	8.01	20	0.74482	1.00

Directional gain = 5dBi + 10log(2) = 8.01dBi

**802.11ac(VHT80)**

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5775	548.990	8.01	20	0.69071	1.00

Directional gain = 5dBi + 10log(2) = 8.01dBi

**For WLAN: 15.407(5GHz)**  
**802.11a, 1Tx**

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5180 -5240, 5260 - 5320, 5500 - 5580 & 5660 - 5700	77.090	5	20	0.04850	1.00

**802.11ac(VHT20), 1Tx**

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5180 -5240	45.290	5	20	0.02849	1.00

**802.11ac(VHT40), 1Tx**

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5190 -5230	48.084	5	20	0.03025	1.00

**802.11ac(VHT80), 1Tx**

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5210	12.190	5	20	0.00767	1.00

### 802.11a, 2Tx

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5180 -5240, 5260 - 5320, 5500 - 5580 & 5660 - 5700	147.582	8.01	20	0.18568	1.00

Directional gain = 5dBi + 10log(2) = 8.01dBi

### 802.11ac(VHT20), 2Tx

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5180 -5240, 5260 - 5320, 5500 - 5580 & 5660 - 5700	137.730	8.01	20	0.17328	1.00

Directional gain = 5dBi + 10log(2) = 8.01dBi

### 802.11ac(VHT40), 2Tx

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5190 -5230, 5270 - 5310, 5510 - 5550 & 5670	139.680	8.01	20	0.17574	1.00

Directional gain = 5dBi + 10log(2) = 8.01dBi

### 802.11ac(VHT80), 2Tx

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5210, 5290, 5530	27.530	8.01	20	0.3464	1.00

Directional gain = 5dBi + 10log(2) = 8.01dBi

**For Bluetooth:  
GFSK**

FREQUENCY BAND (MHz)	MAX POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2402-2480	1.982	3.5	20	0.00088	1.00

**8DPSK**

FREQUENCY BAND (MHz)	MAX POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2402-2480	2.723	3.5	20	0.00121	1.00

**CONCLUSION:**

Both of the Bluetooth and WLAN can transmit simultaneously, the formula of calculated the MPE is:

$$CPD_1 / LPD_1 + CPD_2 / LPD_2 + \dots \text{etc.} < 1$$

**CPD = Calculation power density**

**LPD = Limit of power density**

Therefore, the worst-case situation is  $0.85064 / 1 + 0.00121 / 1 = 0.852$ , which is less than "1". This confirmed that the device comply with FCC 1.1310 MPE limit.

**--- END ---**