

# User Manual

- **Product Name: WiFi 6 ax3000 2x2 dual concurrent mPCIe Module**
- **Model Name: PCE2311M**
- **FCC ID: U2M-PCE2311M**

## 1. Hardware Design Specification

PCE2311M is a WiFi 6 dual concurrent mPCIe module to engine 2.4GHz HE40 and 5GHz HE160 interface to carry high performance WiFi 6 traffic and be backward compatible with ancient 802.11a/b/g/n/ac standard. The advanced MTK chipset had been built in this module to operate service connections via Gateway and SASE appliances under a pervasive environment.

### 1.1 Major Components

SKUs		PCE2311M
Main Chip	Radio	MT7916AN
	2.4GHz Transceiver +iPA	MT7976DN
	5GHz Transceiver +iPA	MT7976DN
	Zero Wait DFS	Support
RF components	2.4GHz FEM	N/A
	5GHz FEM	N/A
	WIPS FEMs	N/A
	2.4GHz Filter	TA2621A x 2
	5GHz Filter	BF1608-N5R5NANT/LF x 3
	Diplexer (2.4GHz/5GHz)	DP1608-A2455DTA0T/LF x2

### 1.2 WiFi Specification (2.4GHz/5GHz)

Based on the transmit power (Tx) and receive sensitivity (Rx) specifications of MT7976DN, we conclude Tx power from chips and summarize Rx specification as the following table.

Radio	2.4GHz	5GHz
Data Rate	574Mbps	1201Mbps
Available Bandwidth	20/40MHz	20/40/80MHz
Adopted FEM	iPA	iPA
Available frequency	2402-2484MHz	5150-5850MHz
Transmit Power @ antenna port	13-21dBm	12-20dBm
Receive Sensitivity	-59~-96dBm	-55~-90dBm

### 1.3 Power Consumption

The max power consumption is around 8W.

PCB Dimensions/Layers.

PCE2311M	Dimension/Layer	50.95 x 30 x 1.0 mm / 4 layers
----------	-----------------	--------------------------------

### 1.4 Support driver

PCE2311M is an integrated module on customer's system board. The selected SDK or driver would be discussed and be negotiated firstly.

According to initial validation from Seano, we successfully brought up this module on MTK7622 platform.

### 1.5 Compliant Regulatory

The planned certification domain would be covered following regulatory.

#### 1.5.1 Tier 1 Compliant Regulatory

Countries/Regions	RF Standards	EMC Standards	Safety Standards
USA	OET Bulleting 65/Part 2.1093 FCC Part 15.247 FCC Part 15.407	FCC Part 15, Subpart B Class B	N/A
EU	EN 300 328 v2.2.2 EN 300 440 EN 301 893 v2.1.1 EN 50385: 2017 EN 301 489-1/-17 v3.1.1	CISPR 32:2012 EN55032:2012 CISPR 24:2010 EN55024:2010 EN55035	N/A

## 2. Warning statements

### FEDERAL COMMUNICATIONS COMMISSION INTERFERENCE STATEMENT

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

-Reorient or relocate the receiving antenna.

- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/ TV technician for help.

**CAUTION:**

Any changes or modifications not expressly approved by the grantee of this device could void the user's authority to operate the equipment.

This module is intended for OEM integrator. The OEM integrator is responsible for the compliance to all the rules that apply to the product into which this certified RF module is integrated. Additional testing and certification may be necessary when multiple modules are used.

**RF Exposure warning**

This equipment must be installed and operated in accordance with provided instructions and the antenna(s) used for this transmitter must be installed to provide a separation distance of at least 20 cm from all persons and must not be co-located or operating in conjunction with any other antenna or transmitter. End-users and installers must be provide with antenna installation instructions and transmitter operating conditions for satisfying RF exposure compliance.

**USERS MANUAL OF THE END PRODUCT**

In the users manual of the end product, the end user has to be informed to keep at least 20 cm separation with the antenna while this end product is installed and operated.

The end user has to be informed that the FCC radio-frequency exposure guidelines for an uncontrolled environment can be satisfied.

The end user has to also be informed that any changes or modifications not expressly approved by the manufacturer could void the user's authority to operate this equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference and (2) this device must accept any interference received, including interferencethat may cause undesired operation.

**LABEL OF THE END PRODUCT**

The final end product must be labeled in a visible area with the following " Contains FCC ID: U2M-PCE2311M ".

This radio transmitter FCC ID: U2M-PCE2311M has been approved by FCC to operate with the antenna types listed below with the maximum permissible gain and required antenna impedance for each antenna type indicated. Antenna types not included in this list, having a gain greater than the maximum gain indicated for that type, are strictly prohibited for use with this device.

**Antenna List**

No.	Manufacturer	Part No.	Antenna Type	Peak Gain
1	AWAN	A8EEE-000012	Dipole	3.44 dBi for 2.4 GHz
		WHITE		5.41 dBi for 5GHz

Note: The antenna connector is SMA Male type.