

105mm

105mm

User Manual

SE-MANL-EGLN-R1-EN-1

INTRODUCTION

This Gigabit Ethernet PCI-Express Card is a high performance 10/100/1000 BASE-T Ethernet LAN controller, is perfectly for home and office use. It provides a low cost solution for connecting to a high speed Local Area Network with a data transfer rate up to 1000Mbps over a group of 4 twisted pair copper wires to a distance of maximum 100 meters away. It is 100 times faster than, and yet 100% fully backward compatible with 10/100BASE-T system, therefore, it can be easily plugged into almost any existing network with CAT-5 cabling.

FEATURES AND SPECIFICATION

- Complies with PCI-Express Revision 1.1
- Supports standard and low profile chassis
- 1-Lane (x1) PCI-Express with transfer rate 2.5Gb/s full duplex channel
- A high performance 1000BASE-T Ethernet controller card
- Backward compatible to 10/100BASE-T networking
- 10/100/1000Mbps data rate auto negotiation operation
- Compatible to existing CAT-5 UTP cabling
- Fully compliant with IEEE 802.3, 802.3u, 802.3ab
- Supports full duplex flow control (IEEE 802.3x)
- Supports IEEE 802.1P Layer 2 Priority Encoding
- Supports IEEE 802.1Q VLAN tagging
- Crossover Detection and Auto Correction operation
- Ideal for home and office use
- Supports Microsoft Windows 98SE, ME, 2000, XP 32/64-bit, Server 2003 32/64-bit, Vista 32/64-bit, Server 2008 32/64-bit, Windows 7 32/64-bit, SCO Unix, Linux, FreeBSD, Novell, DOS and Mac OS X 10.4.x or above

PACKAGE CONTENTS

Please check whether the package contains the following items. If any item is missing or damaged, please contact the retailer as soon as possible:

- Gigabit Ethernet PCI-Express Card x 1
- User manual x 1
- Driver CD x 1

HARDWARE & SOFTWARE INSTALLATION

WARNING

Before installing and activating RAID function, please make sure you have a complete backup of your existing data from your hard drives. Manufacturer is not responsible for data loss due to abuse, misuse, or neglect. Should you have any installation problem, please contact your dealer for assistance.

Before Installation

Before the installation of the controller card, let us make the following assumptions:

1. The end users must have the basic knowledge of installing an internal device and its driver to a PC. If they are not sure about their abilities or have any queries, please call their local dealers immediately, or find somebody who are experienced and qualified for assistance.
2. The computer has been properly installed with the supported operating system.

Installing the Controller Card into the Computer

1. Turn off your computer and all external devices connected to it.
2. Disconnect your computer from the power sources.
3. Open the computer case. Refer to your computer user manual for more details.
4. Find an available PCI-Express x1 slot and remove the slot bracket. Save the bracket screw for later use.
5. Align the controller card horizontally with respect to the slot and insert it into the slot firmly and evenly. Take care not to force it into the slot. Once you have properly positioned the controller card into the slot, fasten it to the computer case with the screw you have just saved.
6. Connect the system to network by inserting the 8-cored CAT-5 cable (not included in the package) into RJ45 connector on the network controller card.
7. Secure the computer case and switch on your computer.

Installing Windows Driver

1. Turn on the computer.
2. Once Windows is running, a new network controller card is detected.
3. If the Windows asks for driver for the network controller card, then insert Driver CD into the optical drive (Assume the optical drive letter is D:).
4. Browse to the following path (Assume the Windows OS used is Windows 7)
D:\Realtek\RTL8111\Windows 7
5. Execute "setup.exe" to install the driver.
6. Follow the on screen instructions until the driver is totally installed.

SE-MANL-EGLN-R1-EN-1

105mm

105mm

Checking the status of the installed driver

1. Right click on the icon of **My Computer** and choose **Properties**
2. Choose **Device Manager**
3. Left click on the "+" sign of the **Network Adapters**
4. The following device should be shown:
Realtek PCIe GBE Family Controller
5. Right click on the device above and choose **Properties**
6. Check the **Device status** in the **General** window. The following should be shown:
This device is working properly

Installing Driver for Other Operating Systems

Please refer to the installation documents in the relevant folder on the Driver CD to install driver. To obtain the latest drivers, please refer to the **Updating Drivers** section below.

Notice

When the device driver is properly installed, there will not be any question and exclamation mark shown against this device. If yes, check the following:

1. The driver for the network controller card is installed straightly according to the procedure listed above:
2. If an older version driver is installed previously?
3. The driver for a similar product is installed?
4. In the worst case, the network controller card is defective. Please contact your local dealer or distributor immediately.

GETTING THE LATEST DRIVER, SOFTWARE & DOCUMENT

1. Please go to <http://www.drivers-download.com>
2. In "Drivers Search" section, enter the Download code (DL code): **DL-0263212** to search for the latest driver, software and document.

Or you can download the latest driver from Realtek website:

1. Please go to <http://www.realtek.com>
2. Select "Downloads"
3. Select "Communications Network ICs"
4. Select "Network Interface Controllers"
5. Select "10/100/1000M Gigabit Ethernet"
6. Select "PCI-Express"
7. Select "Software"
8. The final page shows all the available software for RTL8111x
9. Select and download your desired operating system driver

All contents and specification mentioned in this manual are subject to change without prior notice

All brand names and trade names referenced and mentioned in this manual are property of their respective owners.

FCC Statement:

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.