

***PRODUCT NAME: BLUETOOTH HEADSET***

***TRADE NAME: FOXCONN, MODEL NO.: FBH-302***

## ***Manual***

### **Charging Procedure:**

1. Connect the USB charging cable into the USB port of charger.
2. Plug-in the charger into the AC outlet.
3. Connect the charger to the headset charging port. Then the red LED indicated.
4. 1<sup>st</sup> time charge should be for at least 2 hours. Once the charging completion the red LED turns off.
5. There is an alternative charging way by using attached USB charging cable to connect the computer USB port directly.

### **Turning the Headset On/Off:**

1. To turn the headset on, press MFB 2 seconds until the green LED on. Then release MFB button.
2. To turn the headset off, press MFB 2 seconds while powering on until the red LED on. Then release MFB button.

### **How easy to wear it on:**

1. Insert the earloop into the headset.
2. Wear the open side of headset earloop from the top of ear in place.
3. Turn the headset earloop clockwise or counterclockwise for fitting on left or right ear.
4. Align the microphone with your mouth to get the best reception for the caller.

### **Pairing Procedure:**

1. Turn on the Bluetooth feature on your phone.
2. Keep the headset status at power off
3. Press MFB button for more than 4 seconds until the green LED flashed quickly.
4. Perform your Bluetooth phone to discover the headset.
5. Select the "FBH-302" headset. If prompted for a passkey, enter 0000.
6. When pairing is successful, the indicator on your headset flashes green every five seconds. Your phone will also confirm when pairing is complete.

## Headset Controls and Indicators

Control	Action Key	Visual Indicator	Tone
Power On	ON: Press MFB button for 2 seconds	On: Green LED on 1 second	4 rising tones
Power Off	Off: Press MFB button for 2 seconds	Off: Red LED on 1 second	4 descending tones
Pairing	Press MFB button for more than 4 seconds	Green LED flashes 100ms continuously for 3 minutes	2 rising tones
Voice Dial	Press MFB button less than 1 second	None	1 beep tone
Last Number Redial	Press MFB button twice	None	1 beep tone
Call Answer	Press MFB button less than 1 second	None	2 rising tones
Reject	Press MFB button twice	None	2 descending tones
End a Call	Press MFB button less than 1 second	None	1 beep tone
Audio Transfer	Press MFB button twice	None	1 beep tone
Volume Up	Press Volume Up button less than 1 second for each level	None	1 beep tone
Volume Down	Press Volume Down button less than 1 second for each level	None	1 beep tone
Standby Mode	None	Green LED on 1 second every 5 seconds	
Connected	None	Green LED on 1 second only	1 beep tone
Disconnected	None	Red LED on 1 second only	
Connectable	None	Green LED on 1 second every 2 seconds	

## **FEDERAL COMMUNICATIONS COMMISSION INTERFERENCE STATEMENT**

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

### **CAUTION:**

Any changes or modifications not expressly approved by the grantee of this device could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

RF exposure warning -

The equipment complies with FCC RF exposure limits set forth for an uncontrolled environment.

The equipment must not be co-located or operating in conjunction with any other antenna or transmitter.