



# RF EXPOSURE REPORT

**REPORT NO.:** SA980305H02

**MODEL NO.:** 21-121559

**FCC ID:** UZ721121559

**ACCORDING:** FCC Guidelines for Human Exposure  
IEEE C95.1

**APPLICANT:** Motorola Inc.

**ADDRESS:** One Motorola Plaza Holtsville, NY 11742

**ISSUED BY:** Bureau Veritas Consumer Products Services  
(H.K.) Ltd., Taoyuan Branch

**LAB LOCATION:** No. 81-1, Lu Liao Keng, 9th Ling, Wu Lung  
Tsuen, Chiung Lin Hsiang, Hsin Chu Hsien  
307, Taiwan

# RF Exposure Measurement

## 1. Introduction

In this document, we try to prove the safety of radiation harmfulness to the human body for our product. The limit for Maximum Permissible Exposure (MPE) specified in FCC 1.1310 is followed. The Gain of the antenna used in this product is measured in a Fully Anechoic Chamber (FAC) calibrated for antenna measurement in our lab, and also the maximum total power input to the antenna is measured. Through the Friis transmission formula and the maximum gain of the antenna, we can calculate the distance, away from the product, where the limit of MPE is reached.

Although the Friis transmission formula is a far field assumption, the calculated result of that is an over-prediction for near field power density. We will take that as the worst case to specify the safety range.

## 2. RF Exposure Limit

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environmental impact of human exposure to radio-frequency (RF) radiation as specified in 1.1307(b)

### LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm <sup>2</sup> )	Average Time (minutes)
<b>(A)Limits For Occupational / Control Exposures</b>				
300-1500	...	...	F/300	6
1500-100,000	...	...	5	6
<b>(B)Limits For General Population / Uncontrolled Exposure</b>				
300-1500	...	...	F/1500	30
1500-100,000	...	...	1.0	30

F = Frequency in MHz

### 3. Friis Formula

Friis transmission formula :  $P_d = (P_{out} \cdot G) / (4 \cdot \pi \cdot r^2)$

where

$P_d$  = power density in  $mW/cm^2$

$P_{out}$  = output power to antenna in mW

$G$  = gain of antenna in linear scale

$\pi$  = 3.1416

$R$  = distance between observation point and center of the radiator in cm

$P_d$  is the limit of MPE, 0.601  $mW/cm^2$ . If we know the maximum Gain of the antenna and the total power input to the antenna, through the calculation, we will know the MPE value at distance 20cm.

Ref. : David K. Cheng, *Field and Wave Electromagnetics*, Second Edition,  
Page 640, Eq. (11-133).

### 4. EUT Operating condition

The software provided by Manufacturer enabled the EUT to transmit and receive data at lowest, middle and highest channel individually.

### 5. Classification

This device is Limits for General Population / Uncontrolled Exposure.

This device is classified as **Mobile Device**.

## 6. Test Results

### 6.1 Antenna Gain

The maximum Gain measured in Fully Anechoic Chamber is 1.7dBi or 1.479108 (numeric)

Antenna Type	Connector Type	Gain (dBi)	Cable loss (dB)	Net Gain (dBi)
Dipole Antenna	SMA Female	2	0.3	1.7

### 6.2 Output Power Into Antenna & RF Exposure value at distance 20cm:

For PR-ASK(DRM) – High Power:

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
0	902.75	625.173	0.184	0.601
24	914.75	484.172	0.142	0.601
49	927.25	459.198	0.135	0.601

For PR-ASK(DRM) – Low Power:

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
0	902.75	338.065	0.099	0.601
24	914.75	240.991	0.071	0.601
49	927.25	203.704	0.060	0.601

For DSB-ASK(MRM) – High Power:

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
0	902.75	717.794	0.211	0.601
24	914.75	779.830	0.229	0.601
49	927.25	776.247	0.228	0.601

For DSB-ASK(MRM) – Low Power:

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
0	902.75	14.028	0.004	0.601
24	914.75	9.506	0.003	0.601
49	927.25	9.162	0.003	0.601

For PR-ASK(XRM) – High Power:

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
0	902.75	760.326	0.224	0.601
24	914.75	770.903	0.227	0.601
49	927.25	826.038	0.243	0.601

For PR-ASK(XRM) – Low Power:

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
0	902.75	12.735	0.004	0.601
24	914.75	9.661	0.003	0.601
49	927.25	11.695	0.003	0.601