



BUREAU  
VERITAS

# FCC RF Exposure Test Report



## FCC RF Exposure Test Report

Report No. : W7L-P23050004SA01

Applicant : PAX Technology Limited

Address : Room 2416, 24/F., Sun Hung Kai Centre, 30 Harbour, Hong Kong China

Product : Smart Desktop Terminal

FCC ID : V5PA85004G

Brand : PAX

Model No. : A8500P, A8500N

Standards : FCC Part 2 (Section 2.1091)  
KDB 447498 D01 General RF Exposure Guidance v06

Sample Received Date : May. 5, 2023

Date of Testing : May. 5, 2023 ~ May. 29, 2023

**CERTIFICATION:** The above equipment have been tested by **BV 7LAYERS COMMUNICATIONS TECHNOLOGY (SHENZHEN) CO., LTD.**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's SAR characteristics under the conditions specified in this report. It should not be reproduced except in full, without the written approval of our laboratory. The client should not use it to claim product certification, approval, or endorsement by A2LA or any government agencies.

Prepared By : Jerry Chen  
Jerry Chen / Engineer

Approved By : Luke Lu  
Luke Lu / Manager

This report is governed by, and incorporates by reference, the Conditions of Testing as posted at the date of issuance of this report at <http://www.bureauveritas.com/home/about-us/our-business/cps/about-us/terms-conditions/> and is intended for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. Measurement uncertainty is only provided upon request for accredited tests. Statements of conformity are based on simple acceptance criteria without taking measurement uncertainty into account, unless otherwise requested in writing. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence or if you require measurement uncertainty; provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents.



BUREAU  
VERITAS



## Table of Contents

RELEASE CONTROL RECORD.....	3
1. DESCRIPTION OF EQUIPMENT UNDER TEST .....	4
2. MPE(MAXIMUM PERMISSIBLE EXPOSURE) ASSESSMENT .....	5
2.1 INTRODUCTION.....	7
2.2 RF RADIATION EXPOSURE LIMITS.....	7
2.3 MPE ASSESSMENT METHOD.....	8
2.4 MPE CALCULATION FOR STANDALONE OPERATIONS.....	8
2.5 CONCLUSION OF SIMULTANEOUS TRANSMITTER .....	10
3. INFORMATION ON THE TESTING LABORATORIES.....	11





BUREAU  
VERITAS

# FCC RF Exposure Test Report



## 1. Description of Equipment Under Test

<b>Product:</b>	Smart Desktop Terminal
<b>Brand Name:</b>	PAX
<b>Model Name:</b>	A8500P, A8500N
<b>FCC ID:</b>	V5PA85004G
<b>Tx Frequency Bands (Unit: MHz)</b>	WCDMA Band II : 1852.4 ~ 1907.6 WCDMA Band IV: 1712.4 ~ 1752.6 WCDMA Band V : 826.4 ~ 846.6 LTE Band 2 : 1850.7 MHz ~ 1909.3 MHz LTE Band 4 : 1710.7 MHz ~ 1754.3 MHz LTE Band 5 : 824.7 MHz ~ 848.3 MHz LTE Band 12 : 699.7 MHz ~ 715.3 MHz LTE Band 13 : 779.5 MHz ~ 784.5 MHz LTE Band 17 : 706.5MHz ~ 713.5MHz LTE Band 66 : 1710.7 MHz ~ 1779.3 MHz LTE Band 71 : 665.5 MHz ~ 695.5 MHz WLAN : 2412 ~ 2462, 5180 ~ 5240, 5260 ~ 5320, 5500 ~ 5700, 5745 ~ 5825 Bluetooth : 2402 ~ 2480 NFC : 13.56
<b>Uplink Modulations</b>	WCDMA : BPSK/QPSK LTE : QPSK, 16QAM 802.11b : DSSS 802.11a/g/n/ac : OFDM Bluetooth : GFSK, $\pi/4$ -DQPSK, 8-DPSK NFC : ASK
<b>Antenna Type</b>	WWAN: Fixed Internal antenna WLAN: PIFA Antenna NFC : Loop Antenna
<b>EUT Stage</b>	Production Unit

### Note:

- The above EUT information is declared by manufacturer and for more detailed features description please refers to the manufacturer's specifications or User's Manual.



BUREAU  
VERITAS

# FCC RF Exposure Test Report



2. The difference of A8500N and A8500P is on below:

Object	A8500P	A8500N
Printer	Support	NO support
Adapter 1	Model Name : SW-0396A I/P: 100-240Vac,800mA, O/P: 9.0Vdc, 1000mA	Model Name: SW-0983 I/P: 100-240Vac, 500mA, O/P: 5.0Vdc,2000mA
Adapter 2	Model Name: G024A090100ZZUD I/P: 100-240Vac,800mA, O/P: 9.0Vdc, 1000mA	Model Name: GLH50E2000HW I/P: 100-240Vac, 500mA, O/P: 5.0Vdc,2000mA
LCD Panel 1	Supplier : Hubei Yiou Electronics Co., Ltd Model Name: YH-500BSC046C0-19A00-PTM0 Specifications : 5.0 inch/ 720*RGB*1280 Pixel	
LCD Panel 2	Supplier : Shenzhen Hongzhan Optoelectronics Co., Ltd Model Name: F6050812B-04 Specifications :5.0 inch/ 720*RGB*1280 Pixel	
Automatic operating voltage	Minimum voltage: 8.55V	Minimum voltage: 5.25V
	Normal voltage: 9V	Normal voltage: 5V
	Maximum voltage: 9.9V	Maximum voltage: 4.75V
Note : When the operating voltage changes, It does not affect RF baseband module		



BUREAU  
VERITAS

## FCC RF Exposure Test Report



### List of Accessory:

#### A8500N

ACCESSORIES	BRAND	MANUFACTURER	MODEL	SPECIFICATION
AC Adapter 1	PAX	XIAMEN KELI ELECTRONICS Co.,Ltd.	SW-0983	I/P: 100-240Vac, 0.5A, O/P: 5.0Vdc, 2A
AC Adapter 2	PAX	Shenzhen Sorghum Red Electronic Technology Co., Ltd	GLH50E2000HW	I/P: 100-240Vac, 0.4A, O/P: 5.0Vdc, 2A
USB Cable	N/A	N/A	N/A	Signal Line,1.0meter

#### A8500P

ACCESSORIES	BRAND	MANUFACTURER	MODEL	SPECIFICATION
AC Adapter 1	PAX	XIAMEN KELI ELECTRONICS Co.,Ltd.	SW-0396A	I/P: 100-240Vac, 0.5A, O/P: 9.0Vdc, 1A
AC Adapter 2	PAX	Shenzhen Sorghum Red Electronic Technology Co., Ltd	G024A090100ZZ UD	I/P: 100-240Vac, 0.8A, O/P: 9.0Vdc, 1A



BUREAU  
VERITAS

# FCC RF Exposure Test Report



## 2. MPE(Maximum Permissible Exposure) Assessment

### 2.1 Introduction

According to 47 CFR §2.1091, a mobile device is defined as a transmitting device designed to be used in other than fixed locations and to generally be used in such a way that a separation distance of at least 20 cm is normally maintained between the transmitting antenna and the body of the user or nearby persons. In this context, the term “fixed location” means that the device is physically secured at one location and is not able to be easily moved to another location. Transmitting devices designed to be used by consumers or workers that can be easily re-located, such as wireless devices associated with a personal computer, are considered to be mobile devices if they meet the 20 cm separation requirement. The limits to be used for MPE evaluation are specified in §1.1310. All unlicensed personal communications service (PCS) devices and unlicensed NII devices shall be subject to the limits for general population/uncontrolled exposure.

### 2.2 RF Radiation Exposure Limits

According to 47 CFR §1.1310, the criteria listed in below table shall be used to evaluate the environmental impact of human exposure to RF radiation as specified in §1.1307(b), except in the case of portable devices which shall be evaluated according to the provisions of §2.1093.

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm <sup>2</sup> )	Averaging Time (min)
(A) Limits for Occupational / Controlled Exposures				
0.3 – 3.0	614	1.63	100	6
3.0 – 30	1842/f	4.89/f	900/f <sup>2</sup>	6
30 – 300	61.4	0.163	1.0	6
300 – 1500	-	-	f/300	6
1500 – 100000	-	-	5	6
(B) Limits for General Population / Uncontrolled Exposures				
0.3 – 1.34	614	1.63	100	30
1.34 – 30	824/f	2.19/f	180/f <sup>2</sup>	30
30 – 300	27.5	0.073	0.2	30
300 – 1500	-	-	f/1500	30
1500 – 100000	-	-	1.0	30

Limits for maximum permissible exposure (MPE)

#### Notes:

- f = frequency in MHz
- Occupational/controlled limits apply in situations in which persons are exposed as a consequence of their employment provided those persons are fully aware of the potential for exposure and can exercise control over their exposure. Limits for occupational/controlled exposure also apply in situations when an individual is transient through a location where occupational/controlled limits apply provided they are made aware of the potential for exposure.



BUREAU  
VERITAS

## FCC RF Exposure Test Report



3. General population/uncontrolled exposures apply in situations in which the general public may be exposed, or in which persons that are exposed as a consequence of their employment may not be fully aware of the potential for exposure or cannot exercise control over their exposure.

### **2.3 MPE Assessment Method**

Calculations can be made to predict RF field strength and power density levels around typical RF sources. For example, in the case of a single radiating antenna, a prediction for power density in the far-field of the antenna can be made by use of the general Equations below. This equation is generally accurate in the far-field of an antenna but will over-predict power density in the near field, where they could be used for making a "worst case" or conservative prediction.

$$\text{Power Density (S)} = \frac{PG}{4\pi R^2} = \frac{\text{EIRP}}{4\pi R^2}$$

Where

S = Power Density, unit in mW/cm<sup>2</sup>

P = Power input to the antenna, unit in mW

G = Power gain of the antenna in the direction of interest relative to an isotropic radiator

R = Distance to the center of radiation of the antenna, unit in cm

EIRP = Effective isotropically radiated power

### **2.4 MPE Calculation for Standalone Operations**

The manufacturer expects that the radiated component of this device will not close to the human body during normal usage and the warning statement was also stated in the user instruction. Since the transmitting antenna will be kept at least 20 cm away from the human body, the MPE level is calculated based on this condition and the result is listed in below table.





BUREAU  
VERITAS

# FCC RF Exposure Test Report



## CALCULATION FOR MAXIMUM E.I.R.P

Band	Antenna Gain (dBi)	Maximum Tune up Power (dBm)	Average EIRP (mW)	Power Density (mW/cm <sup>2</sup> )	Limit (mW/cm <sup>2</sup> )	Power Density / Limit	Result (PASS / FAIL)
Bluetooth EDR	0.9	9.5	10.965	0.002	1.000	0.002	Pass
Bluetooth LE 1M	0.9	8.5	8.710	0.002	1.000	0.002	Pass
Bluetooth LE 2M	0.9	8.5	8.710	0.002	1.000	0.002	Pass
2.4GHz WLAN	0.9	21.5	173.780	0.035	1.000	0.035	Pass
5.2GHz WLAN	2.6	15.5	64.565	0.013	1.000	0.013	Pass
5.3GHz WLAN	2.6	15.0	57.544	0.011	1.000	0.011	Pass
5.5GHz WLAN	2.6	15.0	57.544	0.011	1.000	0.011	Pass
5.8GHz WLAN	2.6	16.0	72.444	0.014	1.000	0.014	Pass
WCDMA Band II	0.7	24.5	331.131	0.066	1.000	0.066	Pass
WCDMA Band IV	0.7	24.5	331.131	0.066	1.000	0.066	Pass
WCDMA Band V	1.5	24.5	398.107	0.079	0.551	0.144	Pass
LTE Band 2	0.7	24.0	295.121	0.059	1.000	0.059	Pass
LTE Band 4	0.7	24.0	295.121	0.059	1.000	0.059	Pass
LTE Band 5	1.5	24.0	354.813	0.071	0.550	0.128	Pass
LTE Band 12	1.5	24.0	354.813	0.071	0.466	0.151	Pass
LTE Band 13	1.5	24.0	354.813	0.071	0.520	0.136	Pass
LTE Band 17	1.5	24.0	354.813	0.071	0.471	0.150	Pass
LTE Band 66	0.7	24.0	295.121	0.059	1.000	0.059	Pass
LTE Band 71	1.5	24.0	354.813	0.071	0.444	0.159	Pass

Band	E-field strength (dBuV/m)	E-field strength (V/m)	Average EIRP (mW)	Power Density (mW/cm <sup>2</sup> )	Limit (mW/cm <sup>2</sup> )	Result (PASS / FAIL)
NFC	61.76	0.001225	0.00045	0.00000008955	0.979	Pass

$$EIRP = p_t \times g_t = (E \times d)^2 / 30$$

where

- $p_t$  is the transmitter output power in watts
- $g_t$  is the numeric gain of the transmitting antenna (dimensionless)
- $E$  is the electric field strength in V/m
- $d$  is the measurement distance in meters (m)

$$ERP = EIRP/1.64 = (E \times d)^2 / (30 \times 1.64) = (E \times d)^2 / 49.2$$



BUREAU  
VERITAS

# FCC RF Exposure Test Report



## 2.5 CONCLUSION OF SIMULTANEOUS TRANSMITTER

Both of the WLAN and WWAN can transmit simultaneously, the formula of calculated the MPE is:

$$CPD1/LPD1+CPD2/LPD2+.....etc. < 1$$

CPD = Calculation power density

LPD = Limit of power density

Band	Antenna Gain (dBi)	Maximum Tune up Power (dBm)	Average EIRP (mW)	Power Density (mW/cm <sup>2</sup> )	Power Density / Limit	Σ(Power Density / Limit)	Limit	Result
WWAN	0.7	24.5	331.131	0.066	0.066	0.103	1.000	PASS
WLAN	0.9	21.5	173.780	0.035	0.035			
BT	0.9	9.5	10.965	0.002	0.002			

**Remark:** NFC can't simultaneously transmit with other transmitters.

### Summary:

Since the ERP (effective radiated power) operated at < 1.5 GHz is less than 1.5 watts and > 1.5 GHz is less than 3 watts, the routine environmental evaluation is not required, and the MPE result calculated for this device complies with the MPE limit as specified in 47 CFR §1.1310.



BUREAU  
VERITAS

## FCC RF Exposure Test Report



### **3. Information on the Testing Laboratories**

We, BV 7LAYERS COMMUNICATIONS TECHNOLOGY (SHENZHEN) CO., LTD., were founded in 2015 to provide our best service in EMC, Radio, Telecom and Safety consultation. Our laboratories are accredited and approved according to ISO/IEC 17025.

If you have any comments, please feel free to contact us at the following:

Add: No. B102, Dazu Chuangxin Mansion, North of Beihuan Avenue, North Area, Hi-Tech Industry Park, Nanshan District, Shenzhen, Guangdong, China

Tel: 86-755-8869-6566

Fax: 86-755-8869-6577

**Email:** [customerservice.sw@bureauveritas.com](mailto:customerservice.sw@bureauveritas.com)

**Web Site:** [www.bureauveritas.com](http://www.bureauveritas.com)

The road map of all our labs can be found in our web site also.

---END---