



Test Report No.: SA170629W002



# RF EXPOSURE REPORT

**Product:** Integrated Smart Terminal

**Model Name:** E500

**FCC ID:** V5PE500

**Applicant:** PAX Technology Limited

**Address:** Room 2416, 24/F., Sun Hung Kai Centre, 30 Harbour Road, Wanchai, Hong Kong

**Manufacturer:** PAX Computer Technology (Shenzhen) Co., Ltd.

**Address:** 4/F, No.3 Building, Software Park, Second Central Science-Tech Road, High-Tech industrial Park, Shenzhen, Guangdong, P.R.C.

**Prepared by:** Bureau Veritas Shenzhen Co., Ltd. Dongguan Branch

**Lab Location:** No. 34, Chenwulu Section, Guantai Rd., Houjie Town, Dongguan City, Guangdong 523942, China

**TEL:** +86 769 8593 5656

**FAX:** +86 769 8593 1080

**E-MAIL:** [customerservice.dg@cn.bureauveritas.com](mailto:customerservice.dg@cn.bureauveritas.com)

**Report No.:** SA170629W002

**Received Date:** Jun. 29, 2017

**Test Date:** Jun. 30, 2017 ~ Jul. 10, 2017

**Issued Date:** Jul. 11, 2017

This report should not be used by the client to claim product certification, approval, or endorsement by A2LA or any government agencies.

Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification.

Bureau Veritas Shenzhen Co., Ltd.  
Dongguan Branch

No. 34, Chenwulu Section, Guantai Rd., Houjie  
Town, Dongguan City,  
Guangdong 523942, China

Tel: +86 769 8593 5656  
Fax: +86 769 8593 1080  
Email: [customerservice.dg@cn.bureauveritas.com](mailto:customerservice.dg@cn.bureauveritas.com)



## TABLE OF CONTENTS

<b>RF EXPOSURE REPORT</b> .....	<b>1</b>
<b>RELEASE CONTROL RECORD</b> .....	<b>3</b>
<b>1 CERTIFICATION</b> .....	<b>4</b>
<b>2 GENERAL INFORMATION</b> .....	<b>5</b>
2.1 GENERAL DESCRIPTION OF EUT .....	5
<b>3 RF EXPOSURE</b> .....	<b>6</b>
3.1 LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE) .....	6
3.2 MPE CALCULATION FORMULA .....	6
3.3 CLASSIFICATION .....	6
3.4 CONDUCTED POWER .....	7
3.5 CALCULATION RESULT OF MAXIMUM CONDUCTED POWER.....	9



**BUREAU**  
**VERITAS**

Test Report No.: SA170629W002

## RELEASE CONTROL RECORD

ISSUE NO.	REASON FOR CHANGE	DATE ISSUED
SA170629W002	Original release	Jul. 11, 2017



Test Report No.: SA170629W002

# 1 CERTIFICATION

**PRODUCT:** Integrated Smart Terminal  
**BRAND NAME:** PAX  
**MODEL NAME:** E500  
**APPLICANT:** PAX Technology Limited  
**TESTED:** Jun. 30, 2017 ~ Jul. 10, 2017  
**TEST SAMPLE:** Production Unit  
**STANDARDS:** **FCC Part 2 (Section 2.1091)**  
**FCC OET Bulletin 65, Supplement C (01-01)**  
**KDB 447498 D01 General RF Exposure Guidance v06**  
**IEEE C95.1**

The above equipment has been tested by **Bureau Veritas Shenzhen Co., Ltd. Dongguan Branch** and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

**PREPARED BY :** \_\_\_\_\_ , **DATE:** Jul. 11, 2017  
(Harry Li/ Engineer)

**APPROVED BY :** \_\_\_\_\_ , **DATE:** Jul. 11, 2017  
( Sam Tung / Manager)



## 2 GENERAL INFORMATION

### 2.1 GENERAL DESCRIPTION OF EUT

<b>PRODUCT</b>	Integrated Smart Terminal	
<b>MODEL NAME</b>	E500	
<b>NOMINAL VOLTAGE</b>	24Vdc (adapter or host equipment) 3.7Vdc (Li-ion, battery)	
<b>OPERATING TEMPERATURE RANGE</b>	0 ~ 50°C	
<b>MODULATION TYPE</b>	<b>WLAN</b>	CCK, DQPSK, DBPSK for DSSS 64QAM, 16QAM, QPSK, BPSK for OFDM
	<b>Bluetooth</b>	GFSK, π/4-DQPSK, 8DPSK
	<b>BT_LE</b>	BT-LE(GFSK) for DTS
	<b>RFID</b>	ASK
<b>OPERATING FREQUENCY</b>	<b>WLAN</b>	2412 ~ 2462MHz for 11b/g/n(HT20)
	<b>Bluetooth/BT_LE</b>	2402MHz ~ 2480MHz
	<b>RFID</b>	13.56MHz
<b>ANTENNA GAIN</b>	PIFA Antenna with 1.5dBi gain	
<b>HW VERSION</b>	E500-XXXXX-XXXX-XXX-XX	
<b>SW VERSION</b>	e500_PayDroid_6.0.1_Taurus_V05.1.00_20170627	
<b>I/O PORTS</b>	Refer to user's manual	
<b>CABLE SUPPLIED</b>	N/A	

**NOTE:**

- For a more detailed features description, please refer to the manufacturer's specifications or the user's manual.
- The EUT was powered by the following adapter:

<b>ADAPTER</b>	
<b>BRAND:</b>	HONOR
<b>MODEL:</b>	ADS-65HI-19A-3
<b>INPUT:</b>	AC 100-240V, 1500mA
<b>OUTPUT:</b>	DC 24V, 2700mA
<b>MANUFACTURER:</b>	SHENZHEN HONOR ELECTRONIC CO.,LTD

- For the test results, the EUT had been tested with all conditions. But only the worst case was shown in test report.



### 3 RF EXPOSURE

#### 3.1 LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

FREQUENCY RANGE (MHz)	ELECTRIC FIELD STRENGTH (V/m)	MAGNETIC FIELD STRENGTH (A/m)	POWER DENSITY (mW/cm <sup>2</sup> )	AVERAGE TIME (minutes)
<b>LIMITS FOR GENERAL POPULATION / UNCONTROLLED EXPOSURE</b>				
300-1500	...	...	F/1500	30
1500-100,000	...	...	1.0	30

F = Frequency in MHz

#### 3.2 MPE CALCULATION FORMULA

$$Pd = (Pout * G) / (4 * pi * r^2)$$

where

Pd = power density in mW/cm<sup>2</sup>

Pout = output power to antenna in mW

G = gain of antenna in linear scale

Pi = 3.1416

R = distance between observation point and center of the radiator in cm

#### 3.3 CLASSIFICATION

The antenna of this product, under normal use condition, is at least 20cm away from the body of the user. So, this device is classified as **Mobile device**.



### 3.4 CONDUCTED POWER

#### WIFI 2.4G

##### 802.11b

CHANNEL	CHANNEL FREQUENCY (MHz)	AVERAGE POWER (dBm)	PASS/FAIL
1	2412	13.03	N/A
6	2437	12.73	N/A
11	2462	<b>13.15</b>	N/A

##### 802.11g

CHANNEL	CHANNEL FREQUENCY (MHz)	AVERAGE POWER (dBm)	PASS/FAIL
1	2412	12.50	N/A
6	2437	12.37	N/A
11	2462	12.76	N/A

##### 802.11n (20MHz)

CHANNEL	CHANNEL FREQUENCY (MHz)	AVERAGE POWER (dBm)	PASS/FAIL
1	2412	11.11	N/A
6	2437	10.97	N/A
11	2462	11.14	N/A



Bluetooth

GFSK

CHANNEL	CHANNEL FREQUENCY (MHz)	AVERAGE POWER (dBm)	PASS/FAIL
0	2402	6.79	N/A
39	2441	<b>6.95</b>	N/A
78	2480	6.16	N/A

DQPSK

CHANNEL	CHANNEL FREQUENCY (MHz)	AVERAGE POWER (dBm)	PASS/FAIL
0	2402	4.45	N/A
39	2441	4.49	N/A
78	2480	3.06	N/A

8DPSK

CHANNEL	CHANNEL FREQUENCY (MHz)	AVERAGE POWER (dBm)	PASS/FAIL
0	2402	4.48	N/A
39	2441	4.56	N/A
78	2480	3.09	N/A

BT-LE (GFSK)

CHANNEL	CHANNEL FREQUENCY (MHz)	AVERAGE POWER (dBm)	PASS/FAIL
0	2402	4.92	N/A
19	2440	5.20	N/A
39	2480	4.32	N/A





### 3.5 CALCULATION RESULT OF MAXIMUM CONDUCTED POWER

#### BT & WIFI 2.4G

Band	Frequency (MHz)	Operating Mode	Antenna Gain (dBi)	Tune-up Power (dBm)	E.I.R.P Power (mW)	Power Density (mW/cm <sup>2</sup> )	limit (mW/cm <sup>2</sup> )	PASS / FAIL
Bluetooth	2480	BT_GFSK	1.5	7.0	7.079	0.001	1.00	PASS
WIFI 2.4G	2462	11b	1.5	13.5	31.623	0.006	1.00	PASS