

Operational Description of the equipment

1. Install driver software for windows

1. Insert the Installation Software CD into CD-ROM drive. If the Auto-Run function of CD-ROM is disabled, you can utilize the Windows Explorer to browse CD content and run **Setup.exe** manually.

If the Auto-Run function of CD-ROM is enabled (in Windows, the default setting of this function is usually enabled), then a CD menu will appear automatically.

2. Select the Language you want to installation from the combo box, and then press the “OK” button to continue.

PRODUCT	Wi-Fi and Bluetooth PCI Card
MODEL NO.	Bluew_2310
POWER SUPPLY	3.3V DC form PCI interface
CABLE	N/A
I/O PORT	PCI 32 bits interface
FREQUENCY BAND	Wi-Fi 2412 ~ 2462MHz , Bluetooth 2402 ~ 2480MHz
CARRIER FREQUENCY	Wi-Fi 2412 ~ 2462MHz , Bluetooth 2402 ~ 2480 MHz
NUMBER OF CHANNEL	Wi-Fi 11 , Bluetooth 79
CHANNEL SPACING	Wi-Fi 5MHz , Bluetooth 1MHz
RATED RF OUTPUT POWER	WiFi DSSS 58mW / OFDM 26mW Bluetooth 1mW
I.F. & L.O.	Wi-Fi I.F. 0MHz , L.O. 2412 ~ 2462MHz Bluetooth I.F. 0MHz , L.O. 2402 ~ 2480MHz
MODULATION TYPE	Wi-Fi DSSS,OFDM Bluetooth DQPSK,8DPSK,GFSK
BIT RATE OF TRANSMISSION	Wi-Fi 6,9,12,18,24,36,48,54Mbit/s(802.11g),1,2,5.5,11Mbit/s(802.11b) Bluetooth 1Mbit/s 2Mbit/s 3Mbit/s
ANTENNA TYPE	Reverse SAM Antenna
ANTENNA GAIN	2.0 ± 0.5 dBi