

Exhibit 3 FCC REQUIRED INFORMATION

The following information is presented in the content and format requested by the FCC:

Section 2.1033 (c)(1):

The full name and mailing address of the manufacturer of the device and the applicant for certification

Manufacturer:	Nokia Solutions and Networks US LLC 6000 Connection Drive Irving, TX, 75039 Attention: Steve Mitchell
Applicant:	Nokia Solutions and Networks US LLC 6000 Connection Drive Irving, TX, 75039 Attention: Steve Mitchell Phone: (972)374-3000 email: steve.mitchell@nokia.com

Section 2.1033(c)(2): FCC Identifier: **VBNAAHJ-01**

Section 2.1033(c)(4):Type or types of emission: **10M0F9W and / or 20M0F9W LTE Multicarrier**

This Transceiver System supports the **3GPP 5G LTE** technologies now and will be capable of supporting 5G-NR technologies in the future. The subject of this certification request is for operation using the **3GPP LTE** modulation format in QPSK, 16QAM 64QAM and 256QAM (LTE-TDD) for one to three LTE carriers. The transceiver can be configured for the various transmit configurations by varying the digital information provided from the baseband channel electronics alone without physical, hardware or circuit changes to the transceiver.

Section 2.1033(c)(5): Frequency range, Transmit / Receive : **2590-2690 MHz**

Section 2.1033(c)(6): Range of operating power values or specific operating power levels, and description of any means provided for variation of operating power.

Response:

The Nokia **AirScale MAA 64T64R 128AE B41 120W AAHJ Radio Unit (AAHJ)** FCC ID: **VBNAAHJ-01** has 64 transmit/receive outputs. Each output can produce 1 to 3 RF carriers. Each carrier has a maximum power of 28 dBm for a total of 33 dBm per port. This results in a total output power of 120 Watts for all ports.

RF Power control of the AAHJ transceiver is accomplished via software control of the data stream and the RF power gain. The software controls the RF power gain through the RF transmit path with a Digital Step Attenuator (DSA) to maintain the correct RF power of the AAHJ over frequency and temperature range. The DSA gain control has a resolution of 1 dB per step and an overall range of 10 dB.

Separate circuitry is provided to inhibit the carrier output if a synthesizer in the transmit path loses lock.

Exhibit 3 FCC REQUIRED INFORMATION *continued*

Section 2.1033(c)(7): Maximum power rating as defined in the applicable part (s) of the rules.

Response:

The AAHJ maximum total RF output power is 120 Watts which is the sum of all of its 64T/64R transmit ports.

Section 2.1033 (c)(10): A description of all circuitry and devices for determining and stabilizing frequency.

Response:

The subject of this application is designed to operate in the B41 frequency band. It supports CPRI timing reference signals to regulate internal timing including the RF frequency accuracy. All of the timing reference signals (frequency and phase alignment) and baseband signals are generated in the GPS capable baseband unit and provided to the radio through CPRI interface.

The carrier frequency is determined by the direct up-conversion of digital baseband signals to radio frequencies. Frequency stability of the carrier frequency is achieved with accuracy better than ± 0.05 ppm by phase locking the internal frequency synthesizers to reference timing signals. The frequency accuracy on the system clock for frequency synchronization is maintained by disciplining the master oscillator output with an available external reference source.