

# RF Exposure Evaluation Declaration

Product Name : VDSL2 Security Firewall  
Model No. : Vigor2860, Other models please refer to  
the report attachment 1  
FCC ID. : VGYV2860VN

Applicant : DrayTek Corp.

Address : No.26 Fu Shing Rd., HuKou County,Hsin-Chu  
Industrial Park,Hsin-Chu,Taiwan 303 R.O.C

Date of Receipt : 2013/03/27  
Issued Date : 2013/11/29  
Report No. : 134094R-RF-US-Exp  
Report Version : V1.0



1313

The declaration results relate only to the samples calculated.

The declaration shall not be reproduced except in full without the written approval of Quietek Corporation.

## 1. RF Exposure Evaluation

### 1.1. Limits

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency (RF) radiation as specified in 1.1307(b)

#### LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

| Frequency Range (MHz)                                     | Electric Field Strength (V/m) | Magnetic Field Strength (A/m) | Power Density (mW/cm <sup>2</sup> ) | Average Time (Minutes) |
|---|-------------------------------|-------------------------------|-------------------------------------|------------------------|
| (A) Limits for Occupational/ Control Exposures            |                               |                               |                                     |                        |
| 300-1500  | --                            | --                            | F/300                               | 6                      |
| 1500-100,000  | --                            | --                            | 5                                   | 6                      |
| (B) Limits for General Population/ Uncontrolled Exposures |                               |                               |                                     |                        |
| 300-1500  | --                            | --                            | F/1500                              | 6                      |
| 1500-100,000  | --                            | --                            | 1                                   | 30                     |

F= Frequency in MHz

Friis Formula

Friis transmission formula:  $P_d = (P_{out} * G) / (4 * \pi * r^2)$

Where

$P_d$  = power density in mW/cm<sup>2</sup>

$P_{out}$  = output power to antenna in mW

G = gain of antenna in linear scale

$\pi$  = 3.1416

R = distance between observation point and center of the radiator in cm

$P_d$  is the limit of MPE, 1 mW/cm<sup>2</sup>. If we know the maximum gain of the antenna and the total power input to the antenna, through the calculation, we will know the distance r where the MPE limit is reached.

### 1.2. Test Procedure

Software provided by client enabled the EUT to transmit and receive data at lowest, middle and highest channel individually.

The temperature and related humidity: 18°C and 78% RH.

### 1.3. Test Result of RF Exposure Evaluation

|                |                         |
|----------------|-------------------------|
| Product        | VDSL2 Security Firewall |
| Test Mode      | Transmit                |
| Test Condition | RF Exposure Evaluation  |

#### Antenna Gain

Antenna Gain: The maximum Gain measured in fully anechoic chamber is 1.95dBi or 1.57 in linear scale.

#### Output Power into Antenna & RF Exposure Evaluation Distance:

| IEEE 802.11b  |                         |                              |  |
|---------------|-------------------------|------------------------------|--|
| WLAN Function |                         |                              |  |
| Channel       | Channel Frequency (MHz) | Output Power to Antenna (mW) | Power Density at R = 20 cm (mW/cm <sup>2</sup> ) |
| 1             | 2412                    | 38.9045                      | 0.01215  |
| 6             | 2437                    | 36.1410                      | 0.01129  |
| 11            | 2462                    | 28.7740                      | 0.00899  |

| IEEE 802.11g  |                         |                              |  |
|---------------|-------------------------|------------------------------|--|
| WLAN Function |                         |                              |  |
| Channel       | Channel Frequency (MHz) | Output Power to Antenna (mW) | Power Density at R = 20 cm (mW/cm <sup>2</sup> ) |
| 1             | 2412                    | 55.0808                      | 0.01720  |
| 6             | 2437                    | 51.6416                      | 0.01613  |
| 11            | 2462                    | 44.9780                      | 0.01405  |

The power density Pd (4th column) at a distance of 20 cm calculated from the Friis transmission formula is far below the limit of 1 mW/cm<sup>2</sup>.

|                |                         |
|----------------|-------------------------|
| Product        | VDSL2 Security Firewall |
| Test Mode      | Transmit                |
| Test Condition | RF Exposure Evaluation  |

### Antenna Gain

Antenna Gain: The maximum Gain measured in fully anechoic chamber is 1.95dBi or 1.57 in linear scale.

### Output Power into Antenna & RF Exposure Evaluation Distance:

| IEEE 802.11n (20MHz) (ANT 0+1) |                         |                              |  |
|--------------------------------|-------------------------|------------------------------|--|
| WLAN Function                  |                         |                              |  |
| Channel                        | Channel Frequency (MHz) | Output Power to Antenna (mW) | Power Density at R = 20 cm (mW/cm <sup>2</sup> ) |
| 1                              | 2412                    | 53.2108                      | 0.01662  |
| 6                              | 2437                    | 46.2381                      | 0.01444  |
| 11                             | 2462                    | 40.9261                      | 0.01278  |

| IEEE 802.11n (40MHz) (ANT 0+1) |                         |                              |  |
|--------------------------------|-------------------------|------------------------------|--|
| WLAN Function                  |                         |                              |  |
| Channel                        | Channel Frequency (MHz) | Output Power to Antenna (mW) | Power Density at R = 20 cm (mW/cm <sup>2</sup> ) |
| 3                              | 2422                    | 44.7713                      | 0.01398  |
| 6                              | 2437                    | 45.7088                      | 0.01428  |
| 9                              | 2452                    | 43.4510                      | 0.01357  |

The power density Pd (4th column) at a distance of 20 cm calculated from the Friis transmission formula is far below the limit of 1 mW/cm<sup>2</sup>.

## Attachment 1

### ➤ EUT Detailed Model Number and Detailed Difference

| Mode | Model-name   | VDSL2<br>#1<br>(RJ11) | VDSL2<br>#2<br>(RJ11) | FXS<br>(RJ11) | FXO<br>(RJ11) | WLAN-1   | WLAN-2 | WLAN<br>mode | WAN<br>#1 | RJ45 Port<br>#1~6       | USB<br>2.0 x 2 |
|------|--------------|-----------------------|-----------------------|---------------|---------------|----------|--------|--------------|-----------|-------------------------|----------------|
| 1    | Vigor2860    | V                     |                       |               |               |          |        |              | RJ45      | LAN#1~6(RJ45)           | V              |
| 2    | Vigor2860n   | V                     |                       |               |               | V (2.4G) |        | 1            | RJ45      | LAN#1~6(RJ45)           | V              |
| 3    | Vigor2860V   | V                     |                       | V             | V             |          |        |              | RJ45      | LAN#1~6(RJ45)           | V              |
| 4    | Vigor2860Vn  | V                     |                       | V             | V             | V (2.4G) |        | 1            | RJ45      | LAN#1~6(RJ45)           | V              |
| 5    | Vigor2862    | V                     | V(dual)               |               |               |          |        |              | RJ45      | LAN#1~6(RJ45)           | V              |
| 6    | Vigor2862n   | V                     | V(dual)               |               |               | V (2.4G) |        | 1            | RJ45      | LAN#1~6(RJ45)           | V              |
| 7    | Vigor2862V   | V                     | V(dual)               | V             | V             |          |        |              | RJ45      | LAN#1~6(RJ45)           | V              |
| 8    | Vigor2862Vn  | V                     | V(dual)               | V             | V             | V (2.4G) |        | 1            | RJ45      | LAN#1~6(RJ45)           | V              |
| 9    | Vigor2863    | V                     | V (bond)              |               |               |          |        |              | RJ45      | LAN#1~6(RJ45)           | V              |
| 10   | Vigor2863n   | V                     | V (bond)              |               |               | V (2.4G) |        | 1            | RJ45      | LAN#1~6(RJ45)           | V              |
| 11   | Vigor2863V   | V                     | V (bond)              | V             | V             |          |        |              | RJ45      | LAN#1~6(RJ45)           | V              |
| 12   | Vigor2863Vn  | V                     | V (bond)              | V             | V             | V (2.4G) |        | 1            | RJ45      | LAN#1~6(RJ45)           | V              |
| 13   | Vigor2925    |                       |                       |               |               |          |        |              | RJ45      | WAN#2/LAN#1~5<br>(RJ45) | V              |
| 14   | Vigor2925n   |                       |                       |               |               | V (2.4G) |        | 1            | RJ45      | WAN#2/LAN#1~5<br>(RJ45) | V              |
| 15   | Vigor2925V   |                       |                       | V             | V             |          |        |              | RJ45      | WAN#2/LAN#1~5<br>(RJ45) | V              |
| 16   | Vigor2925Vn  |                       |                       | V             | V             | V (2.4G) |        | 1            | RJ45      | WAN#2/LAN#1~5<br>(RJ45) | V              |
| 17   | Vigor2925F   |                       |                       |               |               |          |        |              | SFP       | WAN#2/LAN#1~5<br>(RJ45) | V              |
| 18   | Vigor2925Fn  |                       |                       |               |               | V (2.4G) |        | 1            | SFP       | WAN#2/LAN#1~5<br>(RJ45) | V              |
| 19   | Vigor2925FV  |                       |                       | V             | V             |          |        |              | SFP       | WAN#2/LAN#1~5<br>(RJ45) | V              |
| 20   | Vigor2925FVn |                       |                       | V             | V             | V (2.4G) |        | 1            | SFP       | WAN#2/LAN#1~5<br>(RJ45) | V              |
| 21   | Vigor2860F   | V                     |                       |               |               |          |        |              | SFP       | LAN#1~6(RJ45)           | V              |
| 22   | Vigor2860Fn  | V                     |                       |               |               | V (2.4G) |        | 1            | SFP       | LAN#1~6(RJ45)           | V              |
| 23   | Vigor2860FV  | V                     |                       | V             | V             |          |        |              | SFP       | LAN#1~6(RJ45)           | V              |

| Mode | Model-name      | VDSL2<br>#1<br>(RJ11) | VDSL2<br>#2<br>(RJ11) | FXS<br>(RJ11) | FXO<br>(RJ11) | WLAN-1   | WLAN-2 | WLAN<br>mode | WAN<br>#1 | RJ45 Port<br>#1~6       | USB<br>2.0 x 2 |
|------|-----------------|-----------------------|-----------------------|---------------|---------------|----------|--------|--------------|-----------|-------------------------|----------------|
| 24   | Vigor2860FVn    | V                     |                       | V             | V             | V (2.4G) |        | 1            | SFP       | LAN#1~6(RJ45)           | V              |
| 25   | Vigor1PPBX2860  | V                     |                       | V             | V             |          |        |              | RJ45      | LAN#1~6(RJ45)           | V              |
| 26   | Vigor1PPBX2860n | V                     |                       | V             | V             | V (2.4G) |        | 1            | RJ45      | LAN#1~6(RJ45)           | V              |
| 27   | Vigor3220       |                       |                       |               |               |          |        |              | RJ45      | LAN#2/WAN#1~5<br>(RJ45) | V              |
| 28   | Vigor3220n      |                       |                       |               |               | V (2.4G) |        | 1            | RJ45      | LAN#2/WAN#1~5<br>(RJ45) | V              |
| 29   | Vigor3220V      |                       |                       | V             | V             |          |        |              | RJ45      | LAN#2/WAN#1~5<br>(RJ45) | V              |
| 30   | Vigor3220Vn     |                       |                       | V             | V             | V (2.4G) |        | 1            | RJ45      | LAN#2/WAN#1~5<br>(RJ45) | V              |
| 31   | Vigor3220F      |                       |                       |               |               |          |        |              | SFP       | LAN#2/WAN#1~5<br>(RJ45) | V              |
| 32   | Vigor3220Fn     |                       |                       |               |               | V (2.4G) |        | 1            | SFP       | LAN#2/WAN#1~5<br>(RJ45) | V              |
| 33   | Vigor3220FV     |                       |                       | V             | V             |          |        |              | SFP       | LAN#2/WAN#1~5<br>(RJ45) | V              |
| 34   | Vigor3220FVn    |                       |                       | V             | V             | V (2.4G) |        | 1            | SFP       | LAN#2/WAN#1~5<br>(RJ45) | V              |