

Operational Description of the equipment

Getting Started

1. Charging Battery

The Headset comes with a rechargeable battery included. The battery is not fully charged when it is new. For first time use, it takes 2 hours to fully charge the battery. Afterwards, it will take about 1.5 hours to fully charge the battery.

Plug the adapter into an AC outlet. The red indicator on the headset will turn on.

When the battery is full, the red indicator will turn off.

2. Check the Headset buttons

- S1 Button: Power on/off, Answer calls, End Call, Pairing, Voice Dial, Transfer Audio
- S2 Button: Volume Up, Reject Call, Last Number Redial
- S3 Button: Volume Down, Accept Waiting Call

3. Turning the Headset On or Off

- To turn the Headset on

Press and hold the S1 button for 3 seconds, then the blue indicator of the Headset flashes. The Headset is now turned on. (*Note: When it is on low battery, the red indicator will flash.*)

- To turn the Headset off

Press and hold the S1 button for 3 seconds, then the Red indicator will flash, and then the Headset will turn off

PRODUCT	Bluetooth Mono Headset
MODEL NO.	VH-1000
POWER SUPPLY	DC 3.7 V, 0.02A
FREQUENCY BAND	2400MHz ~2483.5MHz
CARRIER FREQUENCY	CH0:2402MHz~CH78:2480MHz
NUMBER OF CHANNEL	79
CHANNEL SPACING	1 MHz
RATED RF OUTPUT POWER	0dBm
MODULATION TYPE	GFSK, II/4DQPSK, 8DPSK
DUTY CYCLE	50%
MODE OF OPERATION	duplex
BIT RATE OF TRANSMISSION	2.1 Mbps
ANTENNA TYPE	Ceramic Chip ANT
ANTENNA GAIN	-2 dBi
OPERATING TEMPERATURE	-10~55°C
CHANNEL BANDWIDTH	1MHz