



Radio Test Report

*FCC Part 22
(824.2 MHz to 848.8 MHz)*

and

*FCC Part 24
(1850.2 MHz to 1909.8 MHz)*

Model: HC25

COMPANY: Juniper Systems, Inc.
1132 West 1700 North
Logan, UT 84321

TEST SITE(S): Elliott Laboratories
41039 Boyce Road.
Fremont, CA. 94538-2435

REPORT DATE: August 31, 2010

FINAL TEST DATES: July 15, 2010

AUTHORIZED SIGNATORY:

A handwritten signature in blue ink that reads "Mark Briggs".

Mark Briggs
Staff Engineer
Elliott Laboratories



Testing Cert #2016.01

Elliott Laboratories is accredited by the A2LA, certificate number 2016-01, to perform the test(s) listed in this report, except where noted otherwise. This report shall not be reproduced, except in its entirety, without the written approval of Elliott Laboratories

REVISION HISTORY

Rev#	Date	Comments	Modified By
-	08-31-2010	First release	

TABLE OF CONTENTS

REVISION HISTORY 2

TABLE OF CONTENTS 2

SCOPE..... 3

OBJECTIVE 3

STATEMENT OF COMPLIANCE..... 4

DEVIATIONS FROM THE STANDARDS 4

TEST RESULTS..... 4

 FCC PART 22 AND RSS-132 (HANDSET OR OTHER UE) 4

 FCC PART 24 (HANDSET OR OTHER UE) AND RSS-133 5

 MEASUREMENT UNCERTAINTIES..... 5

EQUIPMENT UNDER TEST (EUT) DETAILS..... 6

 GENERAL..... 6

 ANTENNA SYSTEM 6

 ENCLOSURE..... 6

 MODIFICATIONS 6

 SUPPORT EQUIPMENT 6

 EUT INTERFACE PORTS 6

 EUT OPERATION 6

TESTING 7

 GENERAL INFORMATION 7

RADIATED EMISSIONS MEASUREMENTS..... 7

 INSTRUMENTATION 8

 FILTERS/ATTENUATORS 8

 ANTENNAS..... 9

 ANTENNA MAST AND EQUIPMENT TURNTABLE..... 9

SAMPLE CALCULATIONS 9

 SAMPLE CALCULATIONS - CONDUCTED SPURIOUS EMISSIONS 9

 SAMPLE CALCULATIONS –RADIATED FIELD STRENGTH 9

 SAMPLE CALCULATIONS –RADIATED POWER 11

APPENDIX A TEST EQUIPMENT CALIBRATION DATA 1

APPENDIX B TEST DATA 2

APPENDIX C TEST CONFIGURATION PHOTOGRAPHS..... 3

SCOPE

Tests have been performed on the Juniper Systems, Inc. model HC25, pursuant to the relevant requirements of the following standard(s) in order to obtain device certification against the regulatory requirements of the Federal Communications Commission and Industry Canada.

- Code of Federal Regulations (CFR) Title 47 Part 2
- CFR 47 Part 22
- CFR 47 Part 24

Conducted and radiated emissions data has been collected, reduced, and analyzed within this report in accordance with measurement guidelines set forth in the following reference standards and as outlined in Elliott Laboratories test procedures:

ANSI C63.4:2003
ANSI TIA-603-C August 17, 2004

The intentional radiator above has been tested in a simulated typical installation to demonstrate compliance with the relevant Industry Canada performance and procedural standards.

Every practical effort was made to perform an impartial test using appropriate test equipment of known calibration. All pertinent factors have been applied to reach the determination of compliance.

The test results recorded herein are based on a single type test of the Juniper Systems, Inc. model HC25 and therefore apply only to the tested sample. The sample was selected and prepared by Kent Campbell of Juniper Systems, Inc..

OBJECTIVE

The primary objective of the manufacturer is compliance with the regulations outlined in the previous section.

Prior to marketing in the USA, the device requires certification. Prior to marketing in Canada, Class I transmitters, receivers and transceivers require certification.

Certification is a procedure where the manufacturer submits test data and technical information to a certification body and receives a certificate or grant of equipment authorization upon successful completion of the certification body's review of the submitted documents. Once the equipment authorization has been obtained, the label indicating compliance must be attached to all identical units, which are subsequently manufactured.

Maintenance of compliance is the responsibility of the manufacturer. Any modification of the product which may result in increased emissions should be checked to ensure compliance has been maintained (i.e., printed circuit board layout changes, different line filter, different power supply, harnessing or I/O cable changes, etc.).

STATEMENT OF COMPLIANCE

The tested sample of Juniper Systems, Inc. model HC25 complied with the requirements of the standards and frequency bands declared in the scope of this test report.

Maintenance of compliance is the responsibility of the manufacturer. Any modifications to the product should be assessed to determine their potential impact on the compliance status of the device with respect to the standards detailed in this test report.

DEVIATIONS FROM THE STANDARDS

No deviations were made from the published requirements listed in the scope of this report.

TEST RESULTS**FCC Part 22 and RSS-132 (Handset or other UE)**

FCC	Canada	Description	Measured	Limit	Result
Transmitter Modulation, output power and other characteristics					
§2.1033 (c) (5)	RSS 132	824.2 – 848.8 MHz 824.4 – 848.6 MHz	Unchanged from original filing.		
§2.1033 (c) (6) §2.1033 (c) (7) §2.1046 §22.913(a)	RSS-132 4.4	RF power output at the antenna terminals (Peak output power)			
§2.1033 (c) (6) §2.1033 (c) (7) §2.1046 § 22.913(a)	RSS-132 4.4	ERP	0.741 Watts erp	7 Watts erp	Pass
§2.1033 (c) (4) §2.1047 § 22.917(b)	RSS 132 4.5.1.1	Emission types	Unchanged from original filing.		
§2.1049		Emission mask			
		Occupied Bandwidth			
Transmitter spurious emissions					
§2.1051 §2.1057 §22.917	RSS 132 4.5	At the antenna terminals	Unchanged from original filing.		
§2.1053 §2.1057 §22.917	RSS 132 4.5	Field strength			
Receiver spurious emissions					
-	RSS GEN 7.2.3	At the antenna terminals	Unchanged from original filing.		
15.109	-				
15.109	RSS GEN 7.2.3 Table 1	Field strength			
Other details					
§2.1055 §22.355	RSS-132 4.3	Frequency stability	Unchanged from original filing.		
§2.1093	RS 102	RF Exposure	Refer to separate SAR Test report		
§2.1033 (c) (8)	RSP 100 7.2 (a)	Final radio frequency amplifying circuit's dc voltages and currents over the power range	Unchanged from original filing.		

FCC Part 24 (Handset or other UE) and RSS-133

FCC	Canada	Description	Measured	Limit	Result
Transmitter Modulation, output power and other characteristics					
§2.1033 (c) (5)	RSS-133	1850.2 – 1909.8 MHz 1852.4 – 1907.6 MHz	Unchanged from original filing.		
§2.1033 (c) (6) §2.1033 (c) (7) §2.1046 § 24.232(c)	RSS-133 6.4	RF power output at the antenna terminals			
§2.1033 (c) (6) §2.1033 (c) (7) §2.1046 § 24.232(c)	RSS-133 6.4	EIRP			
§2.1033 (c) (4) §2.1047 §24.238 (b)	RSS-133 6.5	Emission types Emission mask	Unchanged from original filing.		
§2.1049 §24.238 (b)		Occupied Bandwidth			
Transmitter spurious emissions					
§2.1051 §2.1057 §24.238	RSS-133 6.5	At the antenna terminals	Unchanged from original filing.		
§2.1053 §2.1057 §24.238	RSS-133 6.5	Field strength			
Other details					
§2.1055 §24.235		Frequency stability	Unchanged from original filing.		
§2.1093	RS 102	RF Exposure	Refer to separate SAR Test report		
§2.1033 (c) (8)	RSP 100 7.2 (a)	Final radio frequency amplifying circuit's dc voltages and currents for normal operation over the power range	Unchanged from original filing.		

MEASUREMENT UNCERTAINTIES

ISO Guide 17025 requires that an estimate of the measurement uncertainties associated with the emissions test results be included in the report. The measurement uncertainties given below are based on a 95% confidence level (based on a coverage factor (k=2) and were calculated in accordance with NAMAS document NIS 81 and M3003.

Measurement Type	Measurement Unit	Frequency Range	Expanded Uncertainty
Radiated emission (substitution method)	dBm	25 to 40,000 MHz	± 2.5 dB

EQUIPMENT UNDER TEST (EUT) DETAILS**GENERAL**

The Juniper Systems, Inc. model HC25 is a quad band GSM module. Testing covered by the scope of this test report was performed to evaluate the module in a specific host system, the Juniper Systems' MESA hand-held PDT. As the module has been approved under the FCC's modular approval system, and as no changes other than the use in the specific host system configuration detailed in the application documents associated with this report, testing was limited to an evaluation of the radiated power from the device when installed into the host system.

The sample was received on July 12, 2010 and tested on July 15, 2010. The EUT consisted of the following component(s):

Company	Model	Description	Serial Number	FCC ID
Juniper Systems	HC25	GSM module	None	VSF22572

ANTENNA SYSTEM

The antenna system for the HC25 module is integrated into the host system.

ENCLOSURE

The host system enclosure is constructed of a magnesium alloy case-front and molded plastic case-back. It measures approximately 13 cm wide by 22 cm deep by 5 cm high.

MODIFICATIONS

No modifications were made to the EUT during the time the product was at Elliott.

SUPPORT EQUIPMENT

Company	Model	Description
Juniper Systems	MESA	Hand-held PDT
Agilent	E5515C /2 /3 /E1993A3 /H03 /V48	8960 Wireless Communications Test Set

EUT INTERFACE PORTS

Port	Connected To	Description	Cable(s)	
			Shielded or Unshielded	Length(m)
Handheld DC Power In	AC/DC Adapter	Multiconductor	Unshielded (w/molded Ferrite)	1.5m
AC/DC Adapter AC In	AC Mains	-	-	-

EUT OPERATION

During testing the module was installed into the host system and exercised using an Agilent E5515C to transmit at full (maximum) power on a single time slot.

TESTING**GENERAL INFORMATION**

Antenna port measurements were taken at the Elliott Laboratories test site located at 41039 Boyce Road, Fremont, CA 94538-2435.

Radiated spurious emissions measurements were taken at the Elliott Laboratories Anechoic Chambers and/or Open Area Test Site(s) listed below. The sites conform to the requirements of ANSI C63.4: 2003 *American National Standard for Methods of Measurement of Radio-Noise Emissions from Low-Voltage Electrical and Electronic Equipment in the Range of 9 kHz to 40 GHz* and CISPR 16-1-4:2007 - *Specification for radio disturbance and immunity measuring apparatus and methods Part 1-4: Radio disturbance and immunity measuring apparatus Ancillary equipment Radiated disturbances*. They are on file with the FCC and industry Canada.

Site	Registration Numbers		Location
	FCC	Canada	
Chamber 5	211948	IC 2845B-5	41039 Boyce Road Fremont, CA 94538-2435

In the case of Open Area Test Sites, ambient levels are at least 6 dB below the specification limits with the exception of predictable local TV, radio, and mobile communications traffic.

Considerable engineering effort has been expended to ensure that the facilities conform to all pertinent requirements.

RADIATED EMISSIONS MEASUREMENTS

Receiver radiated spurious emissions measurements are made in accordance with ANSI C63.4:2003 by measuring the field strength of the emissions from the device at a specific test distance and comparing them to a field strength limit. Where the field strength limit is specified at a longer distance than the measurement distance the measurement is extrapolated to the limit distance.

Transmitter radiated spurious emissions are initially measured as a field strength. The eirp or erp limit as specified in the relevant rule part(s) is converted to a field strength at the test distance and the emissions from the EUT are then compared to that limit. Emissions within 20dB of this limit are the subjected to a substitution measurement.

All radiated emissions measurements are performed in two phases. A preliminary scan of emissions is conducted in either an anechoic chamber or on an OATS during which all significant EUT frequencies are identified with the system in a nominal configuration. At least two scans are performed across the complete frequency range of interest and at each operating frequency identified in the reference standard. One or more of these is with the antenna polarized vertically while the one or more of these is with the antenna polarized horizontally. Initial scans are made using a peak detector (RBW=VBW) and using scan rates to ensure that the EUT transmits before the sweep moves out of each resolution bandwidth (for transmit mode).

During the preliminary scans, the EUT is rotated through 360°, the antenna height is varied and cable positions are varied to determine the highest emission relative to the limit. For transmitter spurious emissions, where the limit is expressed as an effective radiated power, the eirp or erp is converted to a field strength limit.

Final measurements are made on an OATS or in a semi-anechoic chamber at the significant frequencies observed during the preliminary scan(s) using the same process of rotating the EUT and raising/lowering the measurement antenna to find the highest level of the emission. The field strength is recorded and, for receiver spurious emissions, compared to the field strength limit. For the final measurement the appropriate detectors (average, peak, normal, sample, quasi-peak) are used. For receiver measurements below 1GHz the detector is a Quasi-Peak detector, above 1GHz a peak detector is used and the peak value (RB=VB=1MHz) and average value (RB=1MHz, VB=10Hz) are recorded.

For transmitter spurious emissions, the radiated power of all emissions within 20dB of the calculated field strength limit are determined using a substitution measurement. The substitution measurement is made by replacing the EUT with an antenna of known gain (typically a dipole antenna or a double-ridged horn antenna), connected to a signal source. The output power of the signal generator is adjusted until the maximum field strength from the substitution antenna is similar to the field strength recorded from the EUT. The erp of the EUT is then calculated.

INSTRUMENTATION

An EMI receiver as specified in CISPR 16-1-1 is used for radiated emissions measurements. The receivers used can measure over the frequency range of 9 kHz up to 7000 MHz. These receivers allow both ease of measurement and high accuracy to be achieved. The receivers have Peak, Average, and CISPR (Quasi-peak) detectors built into their design so no external adapters are necessary.

For measurements above the frequency range of the receivers and for all conducted measurements a spectrum analyzer is utilized because it provides visibility of the entire spectrum along with the precision and versatility required to support engineering analysis.

Measurement bandwidths for the test instruments are set in accordance with the requirements of the standards referenced in this document.

Software control is used to correct the measurements for transducer factors (e.g. antenna) and the insertion loss of cables, attenuators and other series elements to obtain the final measurement value. This provides faster, more accurate readings by performing the conversions described under Sample Calculations within the Test Procedures section of this report. Results are exported in a graphic and/or tabular format, as appropriate.

FILTERS/ATTENUATORS

External filters and precision attenuators are often connected between the EUT antenna port or receiving antenna and the test receiver. This eliminates saturation effects and non-linear operation due to high amplitude transient events.

ANTENNAS

A combination of biconical, log periodic or bi-log antennas are used to cover the range from 30 MHz to 1000 MHz. Broadband antennas or tuned dipole antennas are used over the entire 25 to 1000 MHz frequency range as the reference antenna for substitution measurements.

Above 1000 MHz, a dual-ridge guide horn antenna or octave horn antenna are used as reference and measurement antennas.

The antenna calibration factors are included in site factors that are programmed into the test receivers and instrument control software when measuring the radiated field strength.

ANTENNA MAST AND EQUIPMENT TURNTABLE

The antennas used to measure the radiated electric field strength are mounted on a non-conductive antenna mast equipped with a motor-drive to vary the antenna height.

Table mounted devices are placed on a non-conductive table at a height of 80 centimeters above the floor. Floor mounted equipment is placed on the ground plane if the device is normally used on a conductive floor or separated from the ground plane by insulating material from 3 to 12 mm if the device is normally used on a non-conductive floor. The EUT is positioned on a motorized turntable to allow it to be rotated during testing to determine the angle with the highest level of emissions.

SAMPLE CALCULATIONS

SAMPLE CALCULATIONS - CONDUCTED SPURIOUS EMISSIONS

Measurements are compared directly to the conducted emissions specification limit (decibel form). The calculation is as follows:

$$R_f - S = M$$

where:

$$\begin{aligned} R_f &= \text{Measured value in dBm} \\ S &= \text{Specification Limit in dBm} \\ M &= \text{Margin to Specification in +/- dB} \end{aligned}$$

SAMPLE CALCULATIONS -RADIATED FIELD STRENGTH

Measurements of radiated field strength are compared directly to the specification limit (decibel form). The receiver and/or control software corrects for cable loss, preamplifier gain, and antenna factor. The calculations are in the reverse direction of the actual signal flow, thus cable loss is added and the amplifier gain is subtracted. The Antenna Factor converts the voltage at the antenna coaxial connector to the field strength at the antenna elements.

A distance factor is used when measurements are made at a test distance that is different to the specified limit distance by using the following formula:

$$F_d = 20 * \text{LOG}_{10} (D_m/D_s)$$

where:

$$F_d = \text{Distance Factor in dB}$$

$$D_m = \text{Measurement Distance in meters}$$

$$D_s = \text{Specification Distance in meters}$$

For electric field measurements below 30MHz the extrapolation factor is either determined by making measurements at multiple distances or a theoretical value is calculated using the formula:

$$F_d = 40 * \text{LOG}_{10} (D_m/D_s)$$

The margin of a given emission peak relative to the limit is calculated as follows:

$$R_c = R_r + F_d$$

and

$$M = R_c - L_s$$

where:

$$R_r = \text{Receiver Reading in dBuV/m}$$

$$F_d = \text{Distance Factor in dB}$$

$$R_c = \text{Corrected Reading in dBuV/m}$$

$$L_s = \text{Specification Limit in dBuV/m}$$

$$M = \text{Margin in dB Relative to Spec}$$

SAMPLE CALCULATIONS –RADIATED POWER

The erp/eirp limits for transmitter spurious measurements are converted to a field strength in free space using the following formula:

$$E = \frac{\sqrt{30 P G}}{d}$$

where:

- E = Field Strength in V/m
- P = Power in Watts
- G = Gain of isotropic antenna (numeric gain) = 1
- D = measurement distance in meters

The field strength limit is then converted to decibel form (dBuV/m) and the margin of a given emission peak relative to the limit is calculated (refer to *SAMPLE CALCULATIONS –RADIATED FIELD STRENGTH*).

When substitution measurements are required (all signals with less than 20dB of margin relative to the calculated field strength limit) the eirp of the spurious emission is calculated using:

$$P_{EUT} = P_S - (E_S - E_{EUT})$$

and

$$P_S = G + P_{in}$$

where:

- P_S = effective isotropic radiated power of the substitution antenna (dBm)
- P_{in} = power input to the substitution antenna (dBm)
- G = gain of the substitution antenna (dBi)
- E_S = field strength the substitution antenna (dBm) at eirp P_S
- E_{EUT} = field strength measured from the EUT

Where necessary the effective isotropic radiated power is converted to effective radiated power by subtracting the gain of a dipole (2.2dBi) from the eirp value.

Appendix A Test Equipment Calibration Data**Radiated Emissions, 30 - 2,000 MHz, 15-Jul-10**

<u>Manufacturer</u>	<u>Description</u>	<u>Model</u>	<u>Asset #</u>	<u>Cal Due</u>
EMCO	Antenna, Horn, 1-18 GHz (SA40-Blu)	3115	1386	9/2/2010
Sunol Sciences	Biconilog, 30-3000 MHz	JB3	1657	5/28/2012
Rohde & Schwarz	EMI Test Receiver, 20 Hz-7 GHz	ESIB7	1756	3/16/2011

Appendix B Test Data

T79928 4 Pages



EMC Test Data

Client:	Juniper Systems	Job Number:	J79764
Model:	W2SW0001 and HC25 in Mesa	T-Log Number:	T79928
		Account Manager:	Christine Krebill
Contact:	Kent Campbell	Project Engineer:	Mark Briggs
Emissions Standard(s):	FCC 15.247 / RSS 210	Class:	-
Immunity Standard(s):	-	Environment:	-

EMC Test Data

For The

Juniper Systems

Model

W2SW0001 and HC25 in Mesa

Date of Last Test: 7/15/2010

Client:	Juniper Systems	Job Number:	J79764
Model:	W2SW0001 and HC25 in Mesa	T-Log Number:	T79928
		Account Manager:	Christine Krebill
Contact:	Kent Campbell		
Standard:	FCC 15.247 / RSS 210	Class:	N/A

FCC Parts 22 and 24 Radiated Power Measurements (ERP, EIRP)

Test Specific Details

Objective: The objective of this test session is to perform final qualification testing of the EUT with respect to the specification listed above.

General Test Configuration

Radiated measurements are made with the EUT located on a non-conductive table, 3m from the measurement antenna.

Ambient Conditions:

Temperature: 20-25 °C
 Rel. Humidity: 30-40 %

Summary of Results

Run #	Test Performed	Limit	Pass / Fail	Result / Margin
1	850MHz Band - erp	22.913 (a)	Pass	28.7dBm (0.741W)
1	1900MHz Band - eirp	24.232(c)	Pass	29.3dBm (0.851W)

Modifications Made During Testing

No modifications were made to the EUT during testing

Deviations From The Standard

No deviations were made from the requirements of the standard.



Radio Test Data

Client:	Juniper Systems	Job Number:	J79764
Model:	W2SW0001 and HC25 in Mesa	T-Log Number:	T79928
Contact:	Kent Campbell	Account Manager:	Christine Krebill
Standard:	FCC 15.247 / RSS 210	Class:	N/A

Run #1: Output Power, Radiated, QPHC25 module.

Date: 7/15/2010 Engineer: Mehran Birgani Location: Chamber #3

Frequency MHz	Level dBμV/m	Pol V/H	FCC 22/24		Detector Pk/QP/Avg	Azimuth degrees	Height meters	Comments	
			Limit	Margin				EUT orientation	Channel
823.888	122.8	V	-	-	PK	162	1.0	Flat	128
824.068	128.2	H	-	-	PK	110	1.0	Flat	128
824.048	124.0	V	-	-	PK	155	1.7	Side	128
825.130	126.6	H	-	-	PK	122	1.0	Side	128
823.186	125.9	V	-	-	PK	304	1.0	Upright	128
824.048	121.7	H	-	-	PK	273	2.0	Upright	128
835.730	121.7	V	-	-	PK	307	1.0	Flat	186
835.754	129.0	H	-	-	PK	121	1.0	Flat	186
848.858	123.0	V	-	-	PK	303	1.0	Flat	251
848.686	130.5	H	-	-	PK	123	1.0	Flat	251
1849.970	125.1	V	-	-	PK	283	1.0	Flat	512
1850.130	121.2	H	-	-	PK	146	1.4	Flat	512
1850.110	121.5	V	-	-	PK	68	1.0	Side	512
1850.520	122.3	H	-	-	PK	151	1.3	Side	512
1850.050	124.3	V	-	-	PK	296	1.3	Upright	512
1850.210	124.8	H	-	-	PK	49	1.0	Upright	512
1880.080	125.3	V	-	-	PK	292	1.0	Flat	661
1880.030	122.0	H	-	-	PK	142	1.7	Flat	661
1909.660	125.4	V	-	-	PK	292	1.00	Falt	810
1909.720	120.8	H	-	-	PK	145	1.69	Falt	810

Note 1: Measurements made at 3m with RB=3MHz, VB=3MHz, peak detector.

Client:	Juniper Systems	Job Number:	J79764
Model:	W2SW0001 and HC25 in Mesa	T-Log Number:	T79928
Contact:	Kent Campbell	Account Manager:	Christine Krebill
Standard:	FCC 15.247 / RSS 210	Class:	N/A

Substitution measurements

Horizontal

Frequency MHz	Substitution measurements			Site Factor ⁴	EUT measurements			eirp W	erp W
	Pin ¹	Gain ²	FS ³		FS ⁵	eirp (dBm)	erp (dBm)		
824.068	-4.5	6.2	100.8	99.1	128.2	29.1	26.9		0.490
835.754	-5.7	6.3	99.4	98.8	129.0	30.2	28.0		0.631
848.686	-5.7	6.4	100.3	99.6	130.5	30.9	28.7		0.741
1849.970	-4.0	8.3	101.4	97.1	125.1	28.0	25.8	0.631	
1880.030	-8.0	8.2	96.2	96.0	125.3	29.3	27.1	0.851	
1909.660	-10.0	8.1	94.8	96.7	125.4	28.7	26.5	0.741	

- Note 1: Pin is the input power (dBm) to the substitution antenna
- Note 2: Gain is the gain (dBi) for the substitution antenna.
- Note 3: FS is the field strength (dBuV/m) measured from the substitution antenna.
- Note 4: Site Factor - this is the site factor to convert from a field strength in dBuV/m to an eirp in dBm.
- Note 5: EUT field strength as measured during initial run.

Appendix C Test Configuration Photographs

Test configuration photographs will be provided as a separate document.