

EXHIBIT 13. MPE CALCULATIONS

The following MPE calculations are based on a 1.8 centimeter inverted-F printed circuit board trace antenna, with a measured ERP of 114.0 dBμV/m, at 3 meters, and conducted RF power of +19.8 dBm as presented to the antenna. The calculated gain of this antenna, based on the ERP measurements is -1.03 dBi.

Prediction of MPE limit at a given distance

Equation from page 18 of OET Bulletin 65, Edition 97-01

$$S = \frac{PG}{4\pi R^2}$$

where: S = power density
P = power input to the antenna
G = power gain of the antenna in the direction of interest relative to an isotropic radiator
R = distance to the center of radiation of the antenna

Maximum peak output power at antenna input terminal:	20.66 (dBm)
Maximum peak output power at antenna input terminal:	116.413 (mW)
Antenna gain(typical):	-1.03 (dBi)
Maximum antenna gain:	0.789 (numeric)
Prediction distance:	20 (cm)
Prediction frequency:	2400 (MHz)
MPE limit for uncontrolled exposure at prediction frequency:	1 (mW/cm ²)
Power density at prediction frequency:	0.018270 (mW/cm ²)
Maximum allowable antenna gain:	16.4 (dBi)
Margin of Compliance at 20 cm =	17.4 dB

Prepared For: CEL	Model #: ZFSM-201-F-ES	LS Research, LLC
EUT: FreeStar Pro	Serial #:ES0401	Template: 15.247 DTS TX (V2 9-06-06)
Report #: 309123		Page 55 of 65