

1. Product Description

Avantalk Sunday Pro is a sleek designed Text-To-Speech Bluetooth Speakerphone. It does not only announces instructions and status in 5 languages (EN, IT, FR, GM, SP) but also supports phonebook download and caller name announcement. So the user knows who calls them without moving their eyes from the road. The advanced DSP (Digital Signal Processing) technology and echo cancellation / noise suppression function also enable crystal clear conversation. On top of these, the leading edge solar charging function allows you to have a lengthy conversation without worrying about the battery. This is an ideal partner for driving – real Hands Free, Eyes Free and Charge Free!

2. Product Overview



- | | | |
|----------------------|--------------------------------|----------------|
| 1. Mute Button | 4. Microphone | 7. Volume Down |
| 2. Volume Up | 5. Multi-function Button (MFB) | 8. Speaker |
| 3. Windscreen Holder | 6. Micro USB Charging Socket | |

- 2 -

3. Charging

Avantalk Sunday Pro uses a popular Micro USB charging socket. Coming with USB charging cable, USB car charger, you can recharge by Solar power, by Car via car charger, or by PC via USB charging cable.

Using Car Charger / USB charging cable

- 1) First time, please charge the device for 3.5 hours to make sure the speakerphone is fully charged and the battery reach its full capacity (by car charger, or by PC via USB charging cable)
- 2) Afterwards, each charge cycle may take up to 3 hours.
- 3) LED will indicate red in charging and off when charging is complete.
- 4) If you have not use the item for a few months, LED might not turn red when first charging. It might take 15-35 minutes before the LED turn red.

Using Solar Power

- 1) Direct the solar panel on the back side of the speakerphone towards sun.
- 2) If the speakerphone receives sufficient sunlight for 2 hours, you can talk for

duration of up 1 hour. Using solar power charge, the operation time (talk time and the standby time) will be extended continuously without any additional charge required by the car charger.

- 3) Under strong sunshine, the unit could be under slow charging without obvious LED indicator because the solar charging power is relatively low and the LED cover housing is dark.

4. Pairing / Connect

- 1) It is important to pair the speakerphone with your Bluetooth device for the first time use.
- 2) Pairing procedure:
 - A. Ensure the speakerphone is off
 - B. Press and hold the MFB button for 5 seconds until LED blink orange and unit announces 'pairing mode, pls...'
 - C. Go to Bluetooth of your mobile phone, searching a new device.
 - D. Once found "Avantalk Sunday Pro", follow the steps and enter pin code 0000 to pair;
 - E. Connect the speakerphone to the device.
 - F. Speakerphone is ready for use until announces 'phone is ready for use'.
- 3) Once paired and connected, the speakerphone will be automatically

- 4 -

connected to the device whenever you turn the speakerphone on again, provided the device is in the range.

We found most of the online technical support questions are caused by improper pairing between the speakerphone and the Bluetooth device. Please follow the instruction step-by-step.

5. Basic Operations

5.1 Speakerphone on / off

Turn on the speakerphone – Press and hold the "MFB" button for 3 seconds, LED indicates Orange ("Power On" is announced)

Turn off the speakerphone – Press and hold the "MFB" button for 3 seconds, LED indicate Red ("Power Off" is announced).

Please Note: To save power, the speakerphone will automatically turn off if it is not connected to any device for more than 10 minutes.

5.2 Answer a call – press the MFB briefly to pick up the call.

5.3 Reject a call – press and hold the MFB for 3 seconds.

- 5 -

5.4 Re-dialing – press the MFB button twice for last number redial.

5.5 Ending a call – press the MFB briefly once.

5.6 Transferring calls –

- (1) Speakerphone to mobile phone: press the "MUTE" button twice.
- (2) Mobile phone to speakerphone: press MFB button once.

5.7 Mute / Un-mute –

- (1) Mute: press and hold the "Mute" button for 3 seconds, the LED indicate Red.
- (2) Un-mute: press and hold the "MUTE" button for 3 seconds again, red LED goes off.

5.8 Privacy Mode–

In the middle of a conversation, press the "MUTE" button once and the speakerphone volume are automatically decreased to minimal level.

5.9 Voice Dialing

Please check if your mobile phone supports voice dialing function. If your phone does support this function, please follow your mobile phone manual

- 6 -

instructions for set up. Then press the MFB briefly, say the name of the person you wish to call.

6. Advanced Operations – Text-to- Speech

6.1. Turning ON/OFF the Text-to-Speech Function

To toggle the TTS function on/off, simply hold the "V+" for 6 seconds in standby mode ("Voice Prompt On" or "Voice Prompt Off" is announced to denote its current status)

6.2. Select Language

The speakerphone is available in 5 language options. During the standby mode, press the "V+" button for 3 seconds until the Orange LED flashes 3 times, and it announces "Select Language". Repeat this process to select the desired language in the following order of English, French, Italian, German, Spanish.

6.3. Transferring Mobile phone's Phonebook to Speakerphone Phonebook transfer

- In standby mode, press and hold "MUTE" for 3 seconds. It would announces "Loading phonebook, please wait" and the red LED will be steady on when receiving the phonebook.

- 7 -

- During phonebook transfer process, it announces "please wait" in every 30 seconds.
- Phonebook transfer done – It announces "contact saved" & "numbers of phonebook data received from mobile phone phonebook and SIM card", and the LED will resume standby mode.
- The speakerphone will not transferring the phonebook again when connect in the second time.
- For updates of phonebook, you have to re-download the phonebook again
- The phonebook data saved in the speakerphone will be erased automatically when it is paired with another mobile phone.
- Removing Phonebook Entries – During standby mode, hold on both "V+" and "V-" for 3 seconds ("Phonebook deleted" is announced)

NOTE: Please check whether your mobile phone support this function.

7. Product Specification

- * Bluetooth V2.1
- * Operating Frequency Band: 2.4GHz ~ 2.48GHz unlicensed ISM band
- * Output Power: Class 2 Power Output, up to 10 meters
- * Support Profiles: HSP, HFP 1.5 Profiles
- * Integrates TTS
- * TTS Support Language: English, French, Italian, German, Spanish
- * Integrated phonebook: Stores up to 1000 contacts

- 8 -

- * Support Multiple paired Device: Up to 8 Bluetooth Phone can be paired
- * Integrated with echo cancellation
- * Built in speaker and microphone
- * Standby Time: Up to 450 hours
- * Talk time: 11-13 hours
- * Battery Charging Time: Using charger about 3 hours
Using solar power about 18 hours
- * Charger Voltage: DC5.0V 400mA
- * Battery Type: 550mA (Rechargeable Lithium Battery)

The talk and standby times may vary when used with different mobile phones or other compatible Bluetooth devices, usage settings, usage styles and environments.

8. Safety Information

- To avoid any damage or malfunction of the device do not drop device from high places.
- Keep device away from humidity, water and any other liquid. If the device is exposed to water, moisture and other liquid, do not operate it to avoid any electrical shock, explosion and damage to the device or yourself.
- Do not place or keep this device near any heat source, such as, direct sun light, radiators, stoves or other apparatus which produces heat. It may cause

- 9 -

- explosion, degrade the performance and/or reduce battery life.
- Do not modify, repair or disassemble device at discretion (Especially battery: It may cause an explosion). Doing this will void the warranty.
- Do not place heavy objects on the device.
- Use only supplied and approved charger.
- Replacement or service must be done by qualified service center or manufacturer.
- Unplug this device when unused for long periods of time or during lightning storms.

CAUTIONS: ELECTRIC SHOCK HAZARD

The battery used in this device may present a risk of fire or chemical burn if mistreated.

9. Declaration of Conformity

9.1. FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential

- 10 -

installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

NOTE: The manufacturer is not responsible for ANY interference, for example RADIO or TV interference, caused by unauthorized modifications to this equipment. Such modifications could void the user's authority to operate the equipment.

- 11 -

9.2. EU

This product is CE certified according to the provision of the R&TTE Directive (99/5/EC). Declares that this product is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC.

9.3. Trademark Statement

The *Bluetooth* word mark and logos are owned by the Bluetooth SIG, Inc. Avantalk is a trademark owned by Avantronics limited.

10. Warranty

The condition of this warranty and our responsibilities under this warranty are as follows:

Warranty is non-transferable and is limited to the original purchaser only.

- You must be able to prove the date of original purchase of the unit with a dated receipt.
- The warranty is not applicable if the product has been subject to physical abuse, improper installation, modification or repair by unauthorized third party.
- The responsibility of supplier's products shall be limited to the repair or

- 12 -

replacement of the product at its sole discretion.

- Specifically exempt from any warranty are limited-life consumable components subject to normal wear and tear, such as, batteries and other accessories.
- Supplier will not take any responsibility if the failure of the unit has resulted from accident, abuse, misuse, or any unauthorized repair, modification or disassemble.
- Modification and repair of the unit should be done by authorized and qualified service center or returned to the manufacturer.
- This warranty gives you specific legal rights, and you may also have other rights which vary under local laws.

11. Manufacturer Information

Company: Avantronics Limited
Address: Unit 1903, Shenhua Commercial Building, No. 2018 Jiabin Rd, Shenzhen, China

Product Name: Bluetooth Solar Charging Speakerphone
Model No. : Avantalk SundayPro (BTCK-18t)

- 13 -

Avantalk
Designed for Freedom

Bluetooth Solar Charging Speakerphone

Text-To-Speech



User Guide

SundayPro

Technical Support & Product Tutorial

More information about this product and other Avantalk Bluetooth Products, including the video user guides, product tutorials and online technical support, please refer to www.avantalk.com 'Product Tutorial' Page and 'Download' Page.

Due to the nature of the products, there might be some software changes without notice. Please always refer to the Avantalk website for the latest information.

Z-PKMN-BTCK-18T-0000