

RF EXPOSURE EVALUATION

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency(RF) Radiation as specified in §1.1307(b)

FCC ID: WQ8-IA900WA2021

EUT Specification

EUT	Wheel Alignment & ADAS Calibration
Frequency band (Operating)	<input checked="" type="checkbox"/> WLAN: 2.412GHz ~ 2.462GHz <input checked="" type="checkbox"/> WLAN: 5.18GHz ~ 5.24GHz <input checked="" type="checkbox"/> WLAN: 5.745GHz ~ 5.825GHz <input checked="" type="checkbox"/> Others: Bluetooth: 2402-2480MHz
Device category	<input type="checkbox"/> Portable (<20cm separation) <input checked="" type="checkbox"/> Mobile (>20cm separation) <input type="checkbox"/> Others ____
Exposure classification	<input type="checkbox"/> Occupational/Controlled exposure (S = 5mW/cm ²) <input checked="" type="checkbox"/> General Population/Uncontrolled exposure (S=1mW/cm ²)
Antenna diversity	<input type="checkbox"/> Single antenna <input checked="" type="checkbox"/> Multiple antennas <input type="checkbox"/> Tx diversity <input type="checkbox"/> Rx diversity <input type="checkbox"/> Tx/Rx diversity
Antenna gain (Max)	BDR+EDR: 0.5 dBi Module 1 WiFi 2.4G ANT1/ANT2: 2.4 dBi Module 2 WiFi 2.4G ANT1/ANT2: 2.5 dBi Module 1 WiFi 5.2G ANT1/ANT2: 2 dBi Module 2 WiFi 5.2G ANT1/ANT2: 2 dBi Module 1 WiFi 5.8G ANT1/ANT2: 2 dBi Module 2 WiFi 5.8G ANT1/ANT2: 2 dBi
Evaluation applied	<input checked="" type="checkbox"/> MPE Evaluation <input type="checkbox"/> SAR Evaluation

Limits for Maximum Permissible Exposure(MPE)

Frequency Range(MHz)	Electric Field Strength(V/m)	Magnetic Field Strength(A/m)	Power Density(mW/cm ²)	Average Time
(A) Limits for Occupational/Control Exposures				
300-1500	--	--	F/300	6
1500-100000	--	--	5	6
(B) Limits for General Population/Uncontrol Exposures				
300-1500	--	--	F/1500	6
1500-100000	--	--	1	30

Friis transmission formula: $P_d = (P_{out} * G) / (4 * \pi * R^2)$

Where

P_d = Power density in mW/cm²

P_{out} =output power to antenna in Mw

G= gain of antenna in linear scale

π =3.1416

R= distance between observation point and center of the radiator in cm

P_d the limit of MPE, 1mW/cm². If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

Max Measurement Result

Operating Mode	Measured Power	Tune up tolerance	Max. Tune up Power	Antenna Gain	Power density at 20cm	Power density Limits (mW/cm ²)
	(dBm)	(dBm)	(dBm)	(dBi)	(mW/ cm ²)	
BDR+EDR	3.04	3.04 ±1	4.04	0.5	0.0006	1
Module 1 WiFi 2.4G ANT1	17.52	17.52 ±1	18.52	2.4	0.0246	1
Module 1 WiFi 2.4G ANT2	17.44	17.44 ±1	18.44	2.4	0.0242	1
Module 2 WiFi 2.4G ANT1	17.58	17.58 ±1	18.58	2.5	0.0255	1
Module 2 WiFi 2.4G ANT2	17.33	17.33 ±1	18.33	2.5	0.0241	1
Module 1 WiFi 5.2G ANT1	15.10	15.10 ±1	16.10	2	0.0129	1
Module 1 WiFi 5.2G ANT2	14.64	14.64 ±1	15.64	2	0.0116	1

Module 2 WiFi 5.2G ANT1	12.30	12.30 ±1	13.30	2	0.0067	1
Module 2 WiFi 5.2G ANT2	12.41	12.41 ±1	13.41	2	0.0069	1
Module 1 WiFi 5.8G ANT1	12.92	12.92 ±1	13.92	2	0.0078	1
Module 1 WiFi 5.8G ANT2	13.88	13.88 ±1	14.88	2	0.0097	1
Module 2 WiFi 5.8G ANT1	13.65	13.65 ±1	14.65	2	0.0092	1
Module 2 WiFi 5.8G ANT2	13.73	13.73 ±1	14.73	2	0.0094	1

Result: No Standalone SAR test is required.

The Module 1 WiFi 2.4G ANT1 and Module 1 WiFi 2.4G ANT2 can transmit simultaneously:

$$\sum_i \frac{S_i}{S_{Limit,i}}$$

$$= S_{Module 1 WiFi 2.4G ANT1} / S_{limit-2.4} + S_{Module 1 WiFi 2.4G ANT2} / S_{limit-2.4}$$

$$= 0.0246/1 + 0.0242/1$$

$$= 0.0488$$

$$< 1.0$$

The Module 2 WiFi 2.4G ANT1 and Module 1 WiFi 2.4G ANT2 can transmit simultaneously:

$$\sum_i \frac{S_i}{S_{Limit,i}}$$

$$= S_{Module 2 WiFi 2.4G ANT1} / S_{limit-2.4} + S_{Module 2 WiFi 2.4G ANT2} / S_{limit-2.4}$$

$$= 0.0255/1 + 0.0241/1$$

$$= 0.0496$$

$$< 1.0$$

The Module 1 WiFi 5.2G ANT1 and Module 1 WiFi 5.2G ANT2 can transmit simultaneously:

$$\sum_i \frac{S_i}{S_{Limit,i}}$$

$$= S_{Module 1 WiFi 5.2G ANT1} / S_{limit-5.2} + S_{Module 1 WiFi 5.2G ANT2} / S_{limit-5.2}$$

$$= 0.0129/1 + 0.0116/1$$

$$= 0.0245$$

$$< 1.0$$

The Module 2 WiFi 5.2G ANT1 and Module 1 WiFi 5.2G ANT2 can transmit simultaneously:

$$\sum_i \frac{S_i}{S_{Limit,i}}$$

$$\begin{aligned} &= S_{Module\ 2\ WiFi\ 5.2G\ ANT1}/S_{limit-5.2} + S_{Module\ 2\ WiFi\ 5.2G\ ANT2}/S_{limit-5.2} \\ &= 0.0067/1 + 0.0069/1 \\ &= 0.0136 \\ &< 1.0 \end{aligned}$$

The Module 1 WiFi 5.8G ANT1 and Module 1 WiFi 5.8G ANT2 can transmit simultaneously:

$$\sum_i \frac{S_i}{S_{Limit,i}}$$

$$\begin{aligned} &= S_{Module\ 1\ WiFi\ 5.8G\ ANT1}/S_{limit-5.8} + S_{Module\ 1\ WiFi\ 5.8G\ ANT2}/S_{limit-5.8} \\ &= 0.0078/1 + 0.0097/1 \\ &= 0.0175 \\ &< 1.0 \end{aligned}$$

The Module 2 WiFi 5.8G ANT1 and Module 1 WiFi 5.8G ANT2 can transmit simultaneously:

$$\sum_i \frac{S_i}{S_{Limit,i}}$$

$$\begin{aligned} &= S_{Module\ 2\ WiFi\ 5.8G\ ANT1}/S_{limit-5.8} + S_{Module\ 2\ WiFi\ 5.8G\ ANT2}/S_{limit-5.8} \\ &= 0.0092/1 + 0.0094/1 \\ &= 0.0186 \\ &< 1.0 \end{aligned}$$

Note: The module 1 and module 2 can't transmit simultaneously