



# FCC RF Test Report

**APPLICANT** : Sonim Technologies, Inc.  
**EQUIPMENT** : Smart phone  
**BRAND NAME** : Sonim  
**MODEL NAME** : XP9900 (P14001)  
**FCC ID** : WYPP14010  
**STANDARD** : 47 CFR Part 2, 96  
**CLASSIFICATION** : Citizens Band End User Devices (CBE)  
**EQUIPMENT TYPE** : End User Equipment  
**TEST DATE(S)** : Aug. 24, 2023 ~ Oct. 18, 2023

We, Sporton International Inc. (Kunshan), would like to declare that the tested sample has been evaluated in accordance with the procedures given in ANSI C63.26 and shown compliance with the applicable technical standards.

The test results in this report apply exclusively to the tested model / sample. Without written approval of Sporton International Inc. (Kunshan), the test report shall not be reproduced except in full.

Jason Jia

Approved by: Jason Jia



**Sporton International Inc. (Kunshan)**

**No. 1098, Pengxi North Road, Kunshan Economic Development Zone Jiangsu Province 215300  
People's Republic of China**



# Table of Contents

History of this test report..... 3

Summary of Test Result..... 4

**1 General Description ..... 5**

    1.1 Applicant..... 5

    1.2 Manufacturer ..... 5

    1.3 Feature of Equipment Under Test..... 5

    1.4 Maximum EIRP Power and Emission Designator ..... 6

    1.5 Testing Site..... 6

    1.6 Test Software ..... 6

    1.7 Applied Standards ..... 7

**2 Test Configuration of Equipment Under Test ..... 8**

    2.1 Test Mode..... 8

    2.2 Connection Diagram of Test System ..... 9

    2.3 Support Unit used in test configuration ..... 9

    2.4 Measurement Results Explanation Example ..... 9

    2.5 Frequency List of Low/Middle/High Channels..... 10

**3 Conducted Test Items..... 11**

    3.1 Measuring Instruments..... 11

    3.2 Conducted Output Power ..... 12

    3.3 EIRP ..... 13

    3.4 Occupied Bandwidth ..... 14

    3.5 Conducted Band Edge ..... 15

    3.6 Conducted Spurious Emission ..... 16

    3.7 Frequency Stability..... 17

**4 Radiated Test Items ..... 18**

    4.1 Measuring Instruments..... 18

    4.2 Test Setup ..... 18

    4.3 Test Result of Radiated Test..... 19

    4.4 Radiated Spurious Emission ..... 20

**5 List of Measuring Equipment..... 21**

**6 Measurement Uncertainty ..... 22**

**Appendix A. Test Results of Conducted Test**

**Appendix B. Test Results of Radiated Test**

**Appendix C. Test Setup Photographs**





### Summary of Test Result

Report Clause	Ref Std. Clause	Test Items	Result (PASS/FAIL)	Remark
3.2	§2.1046	Conducted Output Power	Reporting only	-
-	§96.41	Peak-to-Average Ratio	Not Applicable	Not applicable for End User Devices
3.3	§96.41	Maximum E.I.R.P	Pass	-
		Maximum Power Spectral Density	Not Applicable	Not applicable for End User Devices
3.4	§2.1049 §96.41	Occupied Bandwidth	Reporting only	-
3.5	§2.1051 §96.41	Conducted Band Edge Measurement Adjacent Channel Leakage Ratio	Pass	-
3.6	§2.1051 §96.41	Conducted Spurious Emission	Pass	
3.7	§2.1055	Frequency Stability for Temperature & Voltage	Pass	-
4.4	§2.1051 §96.41	Radiated Spurious Emission	Pass	Under limit 7.75 dB at 14424.00 MHz

Conformity Assessment Condition:
1. The test results (PASS/FAIL) with all measurement uncertainty excluded are presented against the regulation limits or in accordance with the requirements stipulated by the applicant/manufacturer who shall bear all the risks of non-compliance that may potentially occur if measurement uncertainty is taken into account.
2. The measurement uncertainty please refer to each test result in the section "Measurement Uncertainty"
Disclaimer:
The product specifications of the EUT presented in the test report that may affect the test assessments are declared by the manufacturer who shall take full responsibility for the authenticity.



# 1 General Description

## 1.1 Applicant

Sonim Technologies, Inc.  
4445 Eastgate Mall, Suite 200, San Diego, CA 92121, USA

## 1.2 Manufacturer

Sonim Technologies, Inc.  
4445 Eastgate Mall, Suite 200, San Diego, CA 92121, USA

## 1.3 Feature of Equipment Under Test

Product Feature	
Equipment	Smart phone
Brand Name	Sonim
Model Name	XP9900 (P14001)
FCC ID	WYPP14010
Tx Frequency	5G NR n48: 3550 MHz ~ 3700 MHz
Rx Frequency	5G NR n48: 3550 MHz ~ 3700 MHz
SCS	30kHz
Bandwidth	10MHz / 20MHz / 40MHz (50MHz / 60MHz / 80MHz / 90MHz / 100MHz Downlink only)
Antenna Gain	<Ant. 5>: -3.8 dBi
Type of Modulation	DFT-s-OFDM: PI/2 BPSK / QPSK / 16QAM / 64QAM / 256QAM CP-OFDM: QPSK / 16QAM / 64QAM / 256QAM
IMEI Code	Conducted : 016188000785233 Radiation : 016188000788997
HW Version	V1.0
SW Version	10.0.0-01-12.0.0-10.60.10
EUT Stage	Identical Prototype

**Remark:**

1. The above EUT's information was declared by manufacturer. Please refer to the specifications or user's manual for more detailed description.
2. 5G NR n48 supports SA and NSA mode. The whole testing has assessed SA mode for n48 by referring to the higher conducted power for conducted test items.
3. The EN-DC combination declared by the manufacturer is as follows: DC\_13A\_n48A.



### 1.4 Maximum EIRP Power and Emission Designator

5G NR n48		PI/2 BPSK		QPSK		16QAM/64QAM/256QAM	
BW (MHz)	Frequency Range (MHz)	Maximum EIRP(W)	Emission Designator (99%OBW)	Maximum EIRP(W)	Emission Designator (99%OBW)	Maximum EIRP(W)	Emission Designator (99%OBW)
10	3555.00~3694.98	0.0953	-	0.0951	8M56G7D	0.0953	8M59W7D
20	3560.01~3690.00	0.0920	-	0.0927	18M2G7D	0.0759	18M2W7D
40	3570.00~3679.98	0.0975	-	0.0964	37M8G7D	0.0778	37M9W7D

### 1.5 Testing Site

Sporton International Inc. (Kunshan) is accredited to ISO/IEC 17025:2017 by American Association for Laboratory Accreditation with Certificate Number 5145.02.

<b>Test Firm</b>	Sporton International Inc. (Kunshan)		
<b>Test Site Location</b>	No. 1098, Pengxi North Road, Kunshan Economic Development Zone Jiangsu Province 215300 People's Republic of China TEL : +86-512-57900158		
<b>Test Site No.</b>	<b>Sporton Site No.</b>	<b>FCC Designation No.</b>	<b>FCC Test Firm Registration No.</b>
	03CH03-KS TH01-KS	CN1257	314309

### 1.6 Test Software

Item	Site	Manufacture	Name	Version
1.	TH01-KS	Tonscend	JS1120-3 test system China_210602	3.3.10
2.	03CH03-KS	AUDIX	E3	210616



## 1.7 Applied Standards

According to the specifications of the manufacturer, the EUT must comply with the requirements of the following standards:

- ♦ ANSI C63.26-2015
- ♦ 47 CFR Part 2, 96
- ♦ FCC KDB 971168 D01 Power Meas. License Digital Systems v03r01
- ♦ FCC KDB 940660 D01 Part 96 CBRS v03
- ♦ FCC KDB 412172 D01 Determining ERP and EIRP v01r01

**Remark:** All test items were verified and recorded according to the standards and without any deviation during the test.



## 2 Test Configuration of Equipment Under Test

### 2.1 Test Mode


Antenna port conducted and radiated test items listed below are performed according to KDB 971168 D01 Power Meas. License Digital Systems v03r01 with maximum output power.

For radiated measurement, pre-scanned in three orthogonal panels, X, Y, Z. The worst cases (X plane) were recorded in this report.

Test Items	Band	Bandwidth (MHz)						Modulation					RB #		Test Channel			
		5	10	15	20	30	40	PI/2 BPSK	QPSK	16QAM	64QAM	256 QAM	1	Full	L	M	H	
Max. Output Power	n48	-	v	-	v	-	v	v	v	v	v	v	v	v	v	v	v	v
26dB and 99% Bandwidth	n48	-	v	-	v	-	v		v	v	v	v		v			v	
Adjacent Channel Leakage Ratio	n48	-	v	-	v	-	v	v	v	v	v	v	v	v	v	v	v	v
Conducted Band Edge	n48	-	v	-	v	-	v	v	v					v	v	v		v
Conducted Spurious Emission	n48	-	v	-	v	-	v	v	v					v			v	v
E.R.P / E.I.R.P	n48	-	v	-	v	-	v	v	v	v	v	v	v	v	v	v	v	v
Frequency Stability	n48	-		-	v	-			v						v			v
Radiated Spurious Emission	n48	Worst Case													v	v	v	
Remark	<ol style="list-style-type: none"> <li>The mark "v" means that this configuration is chosen for testing</li> <li>The mark "-" means that this bandwidth is not supported.</li> <li>The device is investigated from 30MHz to 10 times of fundamental signal for radiated spurious emission test under different RB size/offset and modulations in exploratory test. Subsequently, only the worst case emissions are reported.</li> <li>All test items are based on engineering evaluation.</li> <li>Frequency Stability : Normal Voltage = 3.9V; Low Voltage =3.6V; High Voltage =4.45V.</li> </ol>																	



## 2.2 Connection Diagram of Test System



## 2.3 Support Unit used in test configuration

Item	Equipment	Trade Name	Model No.	FCC ID	Data Cable	Power Cord
1.	Power Supply	GWINSTEK	PSS-2002	N/A	N/A	Unshielded, 1.8 m
2.	LTE Base Station	Anritsu	MT8821C	N/A	N/A	Unshielded, 1.8 m
3.	NR Base Station	Anritsu	MT8000A	N/A	N/A	Unshielded, 1.8 m

## 2.4 Measurement Results Explanation Example

### For all conducted test items:

The offset level is set in the spectrum analyzer to compensate the RF cable loss and attenuator factor between EUT conducted output port and spectrum analyzer. With the offset compensation, the spectrum analyzer reading level is exactly the EUT RF output level.

The spectrum analyzer offset is derived from RF cable loss and attenuator factor.

*Offset = RF cable loss + attenuator factor.*

Following shows an offset computation example with cable loss 6.5 dB and 20dB attenuator.

Example :

$$\begin{aligned} \text{Offset(dB)} &= \text{RF cable loss(dB)} + \text{attenuator factor(dB)} \\ &= 6.5 + 20 = 26.5 \text{ (dB)} \end{aligned}$$



## 2.5 Frequency List of Low/Middle/High Channels

5G NR n48 Channel and Frequency List				
BW [MHz]	Channel/Frequency(MHz)	Lowest	Middle	Highest
40	Channel	638000	641666	645332
	Frequency	3570	3624.99	3679.98
20	Channel	637334	641666	646000
	Frequency	3560.01	3624.99	3690
10	Channel	637000	641666	646332
	Frequency	3555	3624.99	3694.98


### 3 Conducted Test Items

#### 3.1 Measuring Instruments


See list of measuring instruments of this test report.

##### 3.1.1 Test Setup


##### 3.1.2 Conducted Output Power / ACLR



##### 3.1.3 Occupied Bandwidth, Conducted Band-Edge and Conducted Spurious Emission



##### 3.1.4 Frequency Stability



##### 3.1.5 Test Result of Conducted Test

Please refer to Appendix A.



## **3.2 Conducted Output Power**

### **3.2.1 Description of the Conducted Output Power Measurement**

A system simulator was used to establish communication with the EUT. Its parameters were set to force the EUT transmitting at maximum output power. The measured power in the radio frequency on the transmitter output terminals shall be reported.

### **3.2.2 Test Procedures**

1. The transmitter output port was connected to the system simulator.
2. Set EUT at maximum power through the system simulator.
3. Select lowest, middle, and highest channels for each band and different modulation.
4. Measure and record the power level from the system simulator.

### 3.3 EIRP

#### 3.3.1 Description of the EIRP Measurement

EIRP limits for CBRS equipment as below table:

Device		Maximum EIRP (dBm/10 MHz)	Maximum PSD (dBm/MHz)
Applied	End User Device	23	n/a
<input type="checkbox"/>	Category A CBSD	30	20
<input type="checkbox"/>	Category B CBSD	47	37

**Remark:**

1. The worst case EIRP shown in this section is found with NR operating only using 1RB. As such, the EIRP/10MHz and full channel EIRP values will be identical since 1RB is fully contained within all available channel bandwidths (i.e. 10, 20, 40MHz)

#### 3.3.2 Test Procedures for EIRP

1. Establishing a communications link with the call box (Base station) to measure the Maximum conducted power, the parameters were set to force the EUT transmitting at maximum output power level. Use the average power measurement function to measure total channel power of each channel bandwidth (per ANSI C63.26-2015 Section 5.2.1)
2. Determining ERP and/or EIRP from conducted RF output power measurements (Per ANSI C63.26-2015 Section 5.2.5.5)
 

$EIRP = P_T + G_T - L_C$ ,  $ERP = EIRP - 2.15$ , where  
 $P_T$  = transmitter output power in dBm  
 $G_T$  = gain of the transmitting antenna in dBi  
 $L_C$  = signal attenuation in the connecting cable between the transmitter and antenna in dB



### 3.4 Occupied Bandwidth

#### 3.4.1 Description of Occupied Bandwidth Measurement

The occupied bandwidth is the width of a frequency band such that, below the lower and above the upper frequency limits, the mean powers emitted are each equal to a specified percentage 0.5% of the total mean transmitted power.

The 26 dB emission bandwidth is defined as the frequency range between two points, one above and one below the carrier frequency, at which the spectral density of the emission is attenuated 26 dB below the maximum in-band spectral density of the modulated signal. Spectral density (power per unit bandwidth) is to be measured with a detector of resolution bandwidth equal to approximately 1.0% of the emission bandwidth.

#### 3.4.2 Test Procedures

The testing follows ANSI C63.26-2015 Section 5.4.3 (26dB) and Section 5.4.4 (99OB)

1. The EUT was connected to spectrum analyzer and system simulator via a power divider.
2. The spectrum analyzer center frequency is set to the nominal EUT channel center frequency. The span range for the spectrum analyzer shall be between two and five times the anticipated OBW.
3. The nominal resolution bandwidth (RBW) shall be in the range of 1 to 5 % of the anticipated OBW, and the VBW shall be at least 3 times the RBW.
4. Set the detection mode to peak, and the trace mode to max hold.
5. Determine the reference value: Set the EUT to transmit a modulated signal. Allow the trace to stabilize. Set the spectrum analyzer marker to the highest level of the displayed trace.  
(this is the reference value)
6. Determine the “-26 dB down amplitude” as equal to (Reference Value – X).
7. Place two markers, one at the lowest and the other at the highest frequency of the envelope of the spectral display such that each marker is at or slightly below the “-X dB down amplitude” determined in step 6. If a marker is below this “-X dB down amplitude” value it shall be placed as close as possible to this value. The OBW is the positive frequency difference between the two markers.
8. Use the 99 % power bandwidth function of the spectrum analyzer and report the measured bandwidth.

## 3.5 Conducted Band Edge

### 3.5.1 Description of Conducted Band Edge Measurement

Part 96.41 (e) (1) (i)

For CBSD the emission limits outside the fundamental are as follows:

Within 0 MHz to 10 MHz above and below the assigned channel  $\leq -13$  dBm/MHz

Greater than 10 MHz above and below the assigned channel  $\leq -25$  dBm/MHz

Part 96.41 (e) (1) (ii)

For End User Devices the emission limits outside the fundamental are as follows:

Within 0 MHz to B MHz above and below the assigned channel  $\leq -13$  dBm/MHz

Greater than B MHz above and below the assigned channel  $\leq -25$  dBm/MHz

where B is the bandwidth in megahertz of the assigned channel or multiple contiguous channels of the End User Device.

Notwithstanding the emission limits in this paragraph, the Adjacent Channel Leakage Ratio for End User Devices shall be at least 30 dB.

Part 96.41 (e) (2)

For CBSDs and End User Devices, the conducted power of emissions below 3540 MHz or above 3710 MHz shall not exceed  $-25$  dBm/MHz, and the conducted power of emissions below 3530 MHz or above 3720 MHz shall not exceed  $-40$ dBm/MHz

### 3.5.2 Test Procedures

The testing follows FCC KDB 971168 D01 v03r01 Section 6.1.

1. The EUT was connected to spectrum analyzer and system simulator via a power divider.
2. The band edges of low and high channels for the highest RF powers were measured.
3. Set RBW  $\geq 1\%$  EBW in the 1MHz band immediately outside and adjacent to the band edge.
4. Beyond the 1 MHz band from the band edge, RBW=1MHz was used
5. Offset has included the duty factor for LTE Band 48. Duty factor =  $10 \log (1/x)$ , where x is the measured duty cycle.
6. Set spectrum analyzer with RMS detector.
7. The RF fundamental frequency should be excluded against the limit line in the operating frequency band.



## 3.6 Conducted Spurious Emission

### 3.6.1 Description of Conducted Spurious Emission Measurement

96.41 (e)(2)

The conducted power of any emissions below 3530 MHz or above 3720 MHz shall not exceed -40dBm/MHz.

### 3.6.2 Test Procedures

The testing follows FCC KDB 971168 D01 v03r01 Section 6.1.

1. The EUT was connected to spectrum analyzer and system simulator via a power divider.
2. The RF output of EUT was connected to the spectrum analyzer by RF cable and attenuator. The path loss was compensated to the results for each measurement.
3. The middle channel for the highest RF power within the transmitting frequency was measured.
4. The conducted spurious emission for the whole frequency range was taken.
5. Make the measurement with the spectrum analyzer's RBW = 1MHz, VBW = 3MHz.
6. Set spectrum analyzer with RMS detector.
7. Taking the record of maximum spurious emission.
8. The RF fundamental frequency should be excluded against the limit line in the operating frequency band.
9. The limit line is -40dBm/MHz.



## 3.7 Frequency Stability

### 3.7.1 Description of Frequency Stability Measurement

The frequency stability shall be measured by variation of ambient temperature and variation of primary supply voltage to ensure that the fundamental emission stays within the authorized frequency block. The frequency stability of the transmitter shall be maintained within  $\pm 0.00025\%$  ( $\pm 2.5\text{ppm}$ ) of the center frequency

### 3.7.2 Test Procedures for Temperature Variation

The testing follows FCC KDB 971168 D01 v03r01 Section 9.0.

1. The EUT was set up in the thermal chamber and connected with the system simulator.
2. With power OFF, the temperature was decreased to  $-30^{\circ}\text{C}$  and the EUT was stabilized before testing. Power was applied and the maximum change in frequency was recorded within one minute.
3. With power OFF, the temperature was raised in  $10^{\circ}\text{C}$  step up to  $50^{\circ}\text{C}$ . The EUT was stabilized at each step for at least half an hour. Power was applied and the maximum frequency change was recorded within one minute.

### 3.7.3 Test Procedures for Voltage Variation

The testing follows FCC KDB 971168 D01 v03r01 Section 9.0.

1. The EUT was placed in a temperature chamber at  $25\pm 5^{\circ}\text{C}$  and connected with the system simulator.
2. The power supply voltage to the EUT was varied from 85% to 115% of the nominal value measured at the input to the EUT.
3. The variation in frequency was measured for the worst case.


## 4 Radiated Test Items

### 4.1 Measuring Instruments


See list of measuring instruments of this test report.

### 4.2 Test Setup


#### 4.2.1 For radiated test below 30MHz



#### 4.2.2 For radiated test from 30MHz to 1GHz



### 4.2.3 For radiated test above 1GHz



### 4.3 Test Result of Radiated Test

The low frequency, which started from 9 kHz to 30MHz, was pre-scanned and the result which was 20dB lower than the limit line was not reported.

Please refer to Appendix B.



## 4.4 Radiated Spurious Emission

### 4.4.1 Description of Radiated Spurious Emission Measurement

The radiated spurious emission was measured by substitution method according to ANSI C63.26. The power of any emission outside of the authorized operating frequency ranges must be attenuated below the transmitter power (P) by a factor of at least -40dBm / MHz.

The spectrum is scanned from 30 MHz up to a frequency including its 10th harmonic.

### 4.4.2 Test Procedures

1. The EUT was placed on a turntable with 0.8 meter height for frequency below 1GHz and 1.5 meter height for frequency above 1GHz respectively above ground.
2. The EUT was set 3 meters from the receiving antenna mounted on the antenna tower.
3. The table was rotated 360 degrees to determine the position of the highest spurious emission.
4. The height of the receiving antenna is varied between 1m to 4m to search the maximum spurious emission for both horizontal and vertical polarizations.
5. During the measurement, the system simulator parameters were set to force the EUT transmitting at maximum output power.
6. Make the measurement with the spectrum analyzer's RBW = 1MHz, VBW = 3MHz, taking the record of maximum spurious emission.
7. A horn antenna was substituted in place of the EUT and was driven by a signal generator. Tune the output power of signal generator to the same emission level with EUT maximum spurious emission.  
$$\text{EIRP (dBm)} = \text{S.G. Power} - \text{Tx Cable Loss} + \text{Tx Antenna Gain}$$
$$\text{ERP (dBm)} = \text{EIRP} - 2.15$$
8. The RF fundamental frequency should be excluded against the limit line in the operating frequency band.  
The limit line is -40dBm/MHz



## 5 List of Measuring Equipment

Instrument	Manufacturer	Model No.	Serial No.	Characteristics	Calibration Date	Test Date	Due Date	Remark
Spectrum Analyzer	R&S	FSV40	101040	10Hz~40GHz	Oct. 12, 2022	Aug. 24, 2023~ Oct. 18, 2023	Oct. 11, 2023	Conducted (TH01-KS)
Power divider	STI	STI08-0055	-	0.5~40GHz	NCR	Aug. 24, 2023~ Oct. 18, 2023	NCR	Conducted (TH01-KS)
Temperature & humidity chamber	Hongzhan	LP-150U	H2014011440	-40~+150°C 20%~95%RH	Jul. 06, 2023	Aug. 24, 2023~ Oct. 18, 2023	Jul. 05, 2024	Conducted (TH01-KS)
EMI Test Receiver	Keysight	N9038A	MY56400004	3Hz~8.5GHz;Max 30dBm	Oct. 13, 2022	Aug. 30, 2023	Oct. 12, 2023	Radiation (03CH03-KS)
EXA Spectrum Analyzer	Keysight	N9010A	MY55150244	10Hz~44GHz	May 15, 2023	Aug. 30, 2023	May 14, 2024	Radiation (03CH03-KS)
Loop Antenna	R&S	HFH2-Z2	100321	9kHz~30MHz	Oct. 16, 2022	Aug. 30, 2023	Oct. 15, 2023	Radiation (03CH03-KS)
Bilog Antenna	TeseQ	CBL6112D	23182	30MHz-1GHz	Dec. 23, 2022	Aug. 30, 2023	Dec. 22, 2023	Radiation (03CH03-KS)
Double Ridge Horn Antenna	ETS-Lindgren	3117	75957	1GHz~18GHz	Nov. 15, 2022	Aug. 30, 2023	Nov. 14, 2023	Radiation (03CH03-KS)
SHF-EHF Horn	com-power	AH-840	101116	18GHz~40GHz	Oct. 17, 2022	Aug. 30, 2023	Oct. 16, 2023	Radiation (03CH03-KS)
Amplifier	SONOMA	310N	413740	30MHz ~1000MHz	Jan. 05, 2023	Aug. 30, 2023	Jan. 04, 2024	Radiation (03CH03-KS)
Amplifier	EM	EM18G40G A	060851	18~40GHz	Jan. 05, 2023	Aug. 30, 2023	Jan. 04, 2024	Radiation (03CH03-KS)
high gain Amplifier	MITEQ	AMF-7D-00 101800-30-1 0P	2082394	1Ghz-18Ghz	Jan. 05, 2023	Aug. 30, 2023	Jan. 04, 2024	Radiation (03CH03-KS)
Amplifier	Keysight	83017A	MY53270319	1GHz~26.5GHz	Oct. 12, 2022	Aug. 30, 2023	Oct. 11, 2023	Radiation (03CH03-KS)
AC Power Source	Chroma	61601	F104090004	N/A	NCR	Aug. 30, 2023	NCR	Radiation (03CH03-KS)
Turn Table	ChamPro	EM 1000-T	060762-T	0~360 degree	NCR	Aug. 30, 2023	NCR	Radiation (03CH03-KS)
Antenna Mast	ChamPro	EM 1000-A	060762-A	1 m~4 m	NCR	Aug. 30, 2023	NCR	Radiation (03CH03-KS)

NCR: No Calibration Required



## 6 Measurement Uncertainty

### Uncertainty of Conducted Measurement

Test Item	Uncertainty
Conducted Power	±0.46 dB
Conducted Emissions	±2.26 dB
Occupied Channel Bandwidth	±0.1 %

### Uncertainty of Radiated Emission Measurement (30 MHz ~ 1000 MHz)

Measuring Uncertainty for a Level of Confidence of 95% (U = 2Uc(y))	3.76dB
---	--------

### Uncertainty of Radiated Emission Measurement (1 GHz ~ 18 GHz)

Measuring Uncertainty for a Level of Confidence of 95% (U = 2Uc(y))	3.65dB
---	--------

### Uncertainty of Radiated Emission Measurement (18 GHz ~ 40 GHz)

Measuring Uncertainty for a Level of Confidence of 95% (U = 2Uc(y))	3.57dB
---	--------

----- THE END -----



## Appendix A. Test Results of Conducted Test

Test Engineer :	Smile Wang	Temperature :	22~23°C
		Relative Humidity :	40~42%

# FR1 N48

## Transmitter Conducted Output Power And EIRP, (G<sub>T</sub> - L<sub>C</sub>)=-3.8dB

NR Band	SCS	Band Width	Arfcn	Freq (MHz)	Modulation	RB	Conducted Power (dBm)	EIRP (dBm)	EIRP (W)
48	30	10	637000	3555	DFT-s-OFDM PI/2 BPSK	1@1	23.39	19.59	0.0910
48	30	10	637000	3555	DFT-s-OFDM QPSK	1@1	23.38	19.58	0.0908
48	30	10	637000	3555	DFT-s-OFDM 16 QAM	1@1	22.54	18.74	0.0748
48	30	10	641666	3624.99	DFT-s-OFDM PI/2 BPSK	1@1	23.5	19.7	0.0933
48	30	10	641666	3624.99	DFT-s-OFDM QPSK	1@1	23.58	19.78	0.0951
48	30	10	641666	3624.99	DFT-s-OFDM 16 QAM	1@1	23.59	19.79	0.0953
48	30	10	646332	3694.98	DFT-s-OFDM PI/2 BPSK	1@1	23.59	19.79	0.0953
48	30	10	646332	3694.98	DFT-s-OFDM QPSK	1@1	23.55	19.75	0.0944
48	30	10	646332	3694.98	DFT-s-OFDM 16 QAM	1@1	22.77	18.97	0.0789
48	30	20	637334	3560.01	DFT-s-OFDM PI/2 BPSK	1@1	23.27	19.47	0.0885
48	30	20	637334	3560.01	DFT-s-OFDM QPSK	1@1	23.38	19.58	0.0908
48	30	20	637334	3560.01	DFT-s-OFDM 16 QAM	1@1	22.45	18.65	0.0733
48	30	20	641666	3624.99	DFT-s-OFDM PI/2 BPSK	1@1	23.42	19.62	0.0916
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	1@1	22.51	18.71	0.0743
48	30	20	641666	3624.99	DFT-s-OFDM 16 QAM	1@1	22.54	18.74	0.0748
48	30	20	646000	3690	DFT-s-OFDM PI/2 BPSK	1@1	23.44	19.64	0.0920
48	30	20	646000	3690	DFT-s-OFDM QPSK	1@1	23.47	19.67	0.0927
48	30	20	646000	3690	DFT-s-OFDM 16 QAM	1@1	22.6	18.8	0.0759
48	30	40	638000	3570	DFT-s-OFDM PI/2 BPSK	50@25	23.49	19.69	0.0931
48	30	40	638000	3570	DFT-s-OFDM PI/2 BPSK	1@1	23.48	19.68	0.0929
48	30	40	638000	3570	DFT-s-OFDM PI/2 BPSK	1@104	23.51	19.71	0.0935
48	30	40	638000	3570	DFT-s-OFDM QPSK	50@25	23.45	19.65	0.0923
48	30	40	638000	3570	DFT-s-OFDM QPSK	1@1	23.52	19.72	0.0938
48	30	40	638000	3570	DFT-s-OFDM QPSK	1@104	23.49	19.69	0.0931
48	30	40	638000	3570	DFT-s-OFDM 16 QAM	50@25	22.49	18.69	0.0740
48	30	40	638000	3570	DFT-s-OFDM 16 QAM	1@1	22.53	18.73	0.0746
48	30	40	638000	3570	DFT-s-OFDM 16 QAM	1@104	22.63	18.83	0.0764
48	30	40	638000	3570	DFT-s-OFDM 64 QAM	50@25	20.95	17.15	0.0519
48	30	40	638000	3570	DFT-s-OFDM 64 QAM	1@1	20.89	17.09	0.0512
48	30	40	638000	3570	DFT-s-OFDM 64 QAM	1@104	20.96	17.16	0.0520
48	30	40	638000	3570	DFT-s-OFDM 256 QAM	50@25	18.88	15.08	0.0322
48	30	40	638000	3570	DFT-s-OFDM 256 QAM	1@1	18.82	15.02	0.0318
48	30	40	638000	3570	DFT-s-OFDM 256 QAM	1@104	18.87	15.07	0.0321
48	30	40	638000	3570	CP-OFDM QPSK	53@26	21.95	18.15	0.0653
48	30	40	638000	3570	CP-OFDM QPSK	1@1	21.95	18.15	0.0653
48	30	40	638000	3570	CP-OFDM QPSK	1@104	21.98	18.18	0.0658
48	30	40	641666	3624.99	DFT-s-OFDM PI/2 BPSK	50@25	23.61	19.81	0.0957
48	30	40	641666	3624.99	DFT-s-OFDM PI/2 BPSK	1@1	23.61	19.81	0.0957
48	30	40	641666	3624.99	DFT-s-OFDM PI/2 BPSK	1@104	23.62	19.82	0.0959
48	30	40	641666	3624.99	DFT-s-OFDM QPSK	50@25	23.56	19.76	0.0946



48	30	40	641666	3624.99	DFT-s-OFDM QPSK	1@1	23.63	19.83	0.0962
48	30	40	641666	3624.99	DFT-s-OFDM QPSK	1@104	23.62	19.82	0.0959
48	30	40	641666	3624.99	DFT-s-OFDM 16 QAM	50@25	22.59	18.79	0.0757
48	30	40	641666	3624.99	DFT-s-OFDM 16 QAM	1@1	22.71	18.91	0.0778
48	30	40	641666	3624.99	DFT-s-OFDM 16 QAM	1@104	22.68	18.88	0.0773
48	30	40	641666	3624.99	DFT-s-OFDM 64 QAM	50@25	21.07	17.27	0.0533
48	30	40	641666	3624.99	DFT-s-OFDM 64 QAM	1@1	20.98	17.18	0.0522
48	30	40	641666	3624.99	DFT-s-OFDM 64 QAM	1@104	20.99	17.19	0.0524
48	30	40	641666	3624.99	DFT-s-OFDM 256 QAM	50@25	18.98	15.18	0.0330
48	30	40	641666	3624.99	DFT-s-OFDM 256 QAM	1@1	18.94	15.14	0.0327
48	30	40	641666	3624.99	DFT-s-OFDM 256 QAM	1@104	18.93	15.13	0.0326
48	30	40	641666	3624.99	CP-OFDM QPSK	53@26	22.04	18.24	0.0667
48	30	40	641666	3624.99	CP-OFDM QPSK	1@1	22.1	18.3	0.0676
48	30	40	641666	3624.99	CP-OFDM QPSK	1@104	22.13	18.33	0.0681
48	30	40	645332	3679.98	DFT-s-OFDM PI/2 BPSK	50@25	23.55	19.75	0.0944
48	30	40	645332	3679.98	DFT-s-OFDM PI/2 BPSK	1@1	23.69	19.89	0.0975
48	30	40	645332	3679.98	DFT-s-OFDM PI/2 BPSK	1@104	23.59	19.79	0.0953
48	30	40	645332	3679.98	DFT-s-OFDM QPSK	50@25	23.59	19.79	0.0953
48	30	40	645332	3679.98	DFT-s-OFDM QPSK	1@1	23.64	19.84	0.0964
48	30	40	645332	3679.98	DFT-s-OFDM QPSK	1@104	23.62	19.82	0.0959
48	30	40	645332	3679.98	DFT-s-OFDM 16 QAM	50@25	22.57	18.77	0.0753
48	30	40	645332	3679.98	DFT-s-OFDM 16 QAM	1@1	22.7	18.9	0.0776
48	30	40	645332	3679.98	DFT-s-OFDM 16 QAM	1@104	22.7	18.9	0.0776
48	30	40	645332	3679.98	DFT-s-OFDM 64 QAM	50@25	21.1	17.3	0.0537
48	30	40	645332	3679.98	DFT-s-OFDM 64 QAM	1@1	20.99	17.19	0.0524
48	30	40	645332	3679.98	DFT-s-OFDM 64 QAM	1@104	21.01	17.21	0.0526
48	30	40	645332	3679.98	DFT-s-OFDM 256 QAM	50@25	19.04	15.24	0.0334
48	30	40	645332	3679.98	DFT-s-OFDM 256 QAM	1@1	19.03	15.23	0.0333
48	30	40	645332	3679.98	DFT-s-OFDM 256 QAM	1@104	19.02	15.22	0.0333
48	30	40	645332	3679.98	CP-OFDM QPSK	53@26	22.07	18.27	0.0671
48	30	40	645332	3679.98	CP-OFDM QPSK	1@1	22.04	18.24	0.0667
48	30	40	645332	3679.98	CP-OFDM QPSK	1@104	22.07	18.27	0.0671


## Frequency Stability

NR Band	SCS (kHz)	Bandwidth (MHz)	Arfcn	Freq (MHz)	Modulation	RB	Deviation (ppm)	Verdict	Environment
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	50@0	0.0027	PASS	NV
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	50@0	0.0014	PASS	LV
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	50@0	0.0012	PASS	HV
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	50@0	0.0005	PASS	-30°C
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	50@0	0.0014	PASS	-20°C
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	50@0	0.0018	PASS	-10°C
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	50@0	0.0010	PASS	0°C
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	50@0	0.0015	PASS	10°C
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	50@0	0.0022	PASS	20°C
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	50@0	0.0026	PASS	30°C
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	50@0	0.0007	PASS	40°C
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	50@0	0.0029	PASS	50°C


## Occupied Bandwidth

NR Band	SCS (kHz)	Bandwidth (MHz)	Arfcn	Freq (MHz)	Modulation	RB	OBW (MHz)	26dB BW (MHz)
48	30	10	641666	3624.99	CP-OFDM QPSK	24@0	8.5551	9.46
48	30	10	641666	3624.99	CP-OFDM 16 QAM	24@0	8.5606	9.358
48	30	10	641666	3624.99	CP-OFDM 64 QAM	24@0	8.585	9.228
48	30	10	641666	3624.99	CP-OFDM 256 QAM	24@0	8.5703	9.175
48	30	20	641666	3624.99	CP-OFDM QPSK	51@0	18.183	19.12
48	30	20	641666	3624.99	CP-OFDM 16 QAM	51@0	18.226	19.33
48	30	20	641666	3624.99	CP-OFDM 64 QAM	51@0	18.197	19.09
48	30	20	641666	3624.99	CP-OFDM 256 QAM	51@0	18.202	19.13
48	30	40	641666	3624.99	CP-OFDM QPSK	106@0	37.829	39.15
48	30	40	641666	3624.99	CP-OFDM 16 QAM	106@0	37.794	39.29
48	30	40	641666	3624.99	CP-OFDM 64 QAM	106@0	37.9	39.27
48	30	40	641666	3624.99	CP-OFDM 256 QAM	106@0	37.769	39.32


### N48(10M)\_CP- OFDM\_QPSK\_Outer\_Full\_Mid\_CH




### N48(10M)\_CP-OFDM\_16 QAM\_Outer\_Full\_Mid\_CH




### N48(10M)\_CP-OFDM\_64 QAM\_Outer\_Full\_Mid\_CH




### N48(10M)\_CP-OFDM\_256 QAM\_Outer\_Full\_Mid\_CH




### N48(20M)\_CP- OFDM\_QPSK\_Outer\_Full\_Mid\_CH




### N48(20M)\_CP-OFDM\_16 QAM\_Outer\_Full\_Mid\_CH




### N48(20M)\_CP-OFDM\_64 QAM\_Outer\_Full\_Mid\_CH




### N48(20M)\_CP-OFDM\_256 QAM\_Outer\_Full\_Mid\_CH




### N48(40M)\_CP- OFDM\_QPSK\_Outer\_Full\_Mid\_CH




### N48(40M)\_CP-OFDM\_16 QAM\_Outer\_Full\_Mid\_CH



### N48(40M)\_CP-OFDM\_64 QAM\_Outer\_Full\_Mid\_CH



### N48(40M)\_CP-OFDM\_256 QAM\_Outer\_Full\_Mid\_CH



## Adjacent Channel Leakage Ratio


NR Band	SCS (kHz)	Bandwidth (MHz)	Arfcn	Freq (MHz)	Modulation	RB	Lower Margin	Upper Margin	Result	Verdict
48	30	10	637000	3555.0	DFT-s-OFDM PI/2 BPSK	24@0	-14.12	-13.91	see graph	PASS
48	30	10	637000	3555.0	DFT-s-OFDM PI/2 BPSK	1@0	-11.22	-28.8	see graph	PASS
48	30	10	637000	3555.0	DFT-s-OFDM PI/2 BPSK	1@23	-29.23	-12.74	see graph	PASS
48	30	10	637000	3555.0	DFT-s-OFDM QPSK	24@0	-11.66	-11.73	see graph	PASS
48	30	10	637000	3555.0	DFT-s-OFDM QPSK	1@0	-11.44	-28.47	see graph	PASS
48	30	10	637000	3555.0	DFT-s-OFDM QPSK	1@23	-28.53	-12.81	see graph	PASS
48	30	10	641666	3624.99	DFT-s-OFDM PI/2 BPSK	24@0	-16.63	-16.87	see graph	PASS
48	30	10	641666	3624.99	DFT-s-OFDM PI/2 BPSK	1@0	-10.25	-24.32	see graph	PASS
48	30	10	641666	3624.99	DFT-s-OFDM PI/2 BPSK	1@23	-27.64	-13.24	see graph	PASS
48	30	10	641666	3624.99	DFT-s-OFDM QPSK	24@0	-14.25	-14.72	see graph	PASS
48	30	10	641666	3624.99	DFT-s-OFDM QPSK	1@0	-9.25	-23.77	see graph	PASS
48	30	10	641666	3624.99	DFT-s-OFDM QPSK	1@23	-24.93	-12.69	see graph	PASS
48	30	10	646332	3694.98	DFT-s-OFDM PI/2 BPSK	24@0	-18.59	-19.37	see graph	PASS
48	30	10	646332	3694.98	DFT-s-OFDM PI/2 BPSK	1@0	-10.47	-25.99	see graph	PASS
48	30	10	646332	3694.98	DFT-s-OFDM PI/2 BPSK	1@23	-25.7	-12.29	see graph	PASS
48	30	10	646332	3694.98	DFT-s-OFDM QPSK	24@0	-16.59	-17.28	see graph	PASS
48	30	10	646332	3694.98	DFT-s-OFDM QPSK	1@0	-11.12	-25.55	see graph	PASS
48	30	10	646332	3694.98	DFT-s-OFDM QPSK	1@23	-25.38	-12.71	see graph	PASS
48	30	20	637334	3560.01	DFT-s-OFDM PI/2 BPSK	50@0	-14.84	-13.65	see graph	PASS
48	30	20	637334	3560.01	DFT-s-OFDM PI/2 BPSK	1@0	-14.83	-26.42	see graph	PASS
48	30	20	637334	3560.01	DFT-s-OFDM PI/2 BPSK	1@50	-24.64	-14.88	see graph	PASS
48	30	20	637334	3560.01	DFT-s-OFDM QPSK	50@0	-11.99	-11.13	see graph	PASS
48	30	20	637334	3560.01	DFT-s-OFDM QPSK	1@0	-13.1	-26.32	see graph	PASS

48	30	20	637334	3560.01	DFT-s-OFDM QPSK	1@50	-25.47	-12.69	see graph	PASS
48	30	20	641666	3624.99	DFT-s-OFDM PI/2 BPSK	50@0	-17.03	-16.78	see graph	PASS
48	30	20	641666	3624.99	DFT-s-OFDM PI/2 BPSK	1@0	-13.43	-23.58	see graph	PASS
48	30	20	641666	3624.99	DFT-s-OFDM PI/2 BPSK	1@50	-24.05	-13.4	see graph	PASS
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	50@0	-14.77	-14.51	see graph	PASS
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	1@0	-12.26	-22.85	see graph	PASS
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	1@50	-23.01	-11.35	see graph	PASS
48	30	20	646000	3690.0	DFT-s-OFDM PI/2 BPSK	50@0	-18.85	-19.22	see graph	PASS
48	30	20	646000	3690.0	DFT-s-OFDM PI/2 BPSK	1@0	-11.64	-22.49	see graph	PASS
48	30	20	646000	3690.0	DFT-s-OFDM PI/2 BPSK	1@50	-23.64	-15.21	see graph	PASS
48	30	20	646000	3690.0	DFT-s-OFDM QPSK	50@0	-15.77	-16.62	see graph	PASS
48	30	20	646000	3690.0	DFT-s-OFDM QPSK	1@0	-12.43	-23.79	see graph	PASS
48	30	20	646000	3690.0	DFT-s-OFDM QPSK	1@50	-20.5	-11.48	see graph	PASS
48	30	40	638000	3570.0	DFT-s-OFDM PI/2 BPSK	100@0	-15.2	-13.24	see graph	PASS
48	30	40	638000	3570.0	DFT-s-OFDM PI/2 BPSK	1@0	-15.84	-20.33	see graph	PASS
48	30	40	638000	3570.0	DFT-s-OFDM PI/2 BPSK	1@105	-21.49	-16.59	see graph	PASS
48	30	40	638000	3570.0	DFT-s-OFDM QPSK	100@0	-12.96	-11.68	see graph	PASS
48	30	40	638000	3570.0	DFT-s-OFDM QPSK	1@0	-14.09	-20.0	see graph	PASS
48	30	40	638000	3570.0	DFT-s-OFDM QPSK	1@105	-20.17	-14.22	see graph	PASS
48	30	40	641666	3624.99	DFT-s-OFDM PI/2 BPSK	100@0	-17.13	-15.67	see graph	PASS
48	30	40	641666	3624.99	DFT-s-OFDM PI/2 BPSK	1@0	-16.88	-20.99	see graph	PASS
48	30	40	641666	3624.99	DFT-s-OFDM PI/2 BPSK	1@105	-19.62	-16.1	see graph	PASS
48	30	40	641666	3624.99	DFT-s-OFDM QPSK	100@0	-15.2	-14.32	see graph	PASS
48	30	40	641666	3624.99	DFT-s-OFDM QPSK	1@0	-14.84	-19.67	see graph	PASS


48	30	40	641666	3624.99	DFT-s-OFDM QPSK	1@105	-21.55	-13.88	see graph	PASS
48	30	40	645332	3679.98	DFT-s-OFDM PI/2 BPSK	100@0	-17.96	-18.11	see graph	PASS
48	30	40	645332	3679.98	DFT-s-OFDM PI/2 BPSK	1@0	-15.2	-20.0	see graph	PASS
48	30	40	645332	3679.98	DFT-s-OFDM PI/2 BPSK	1@105	-21.36	-15.86	see graph	PASS
48	30	40	645332	3679.98	DFT-s-OFDM QPSK	100@0	-16.91	-17.09	see graph	PASS
48	30	40	645332	3679.98	DFT-s-OFDM QPSK	1@0	-14.53	-20.0	see graph	PASS
48	30	40	645332	3679.98	DFT-s-OFDM QPSK	1@105	-20.27	-14.77	see graph	PASS




N48(10M)\_DFT-s-OFDM\_PI\_2-BPSK\_Outer\_Full\_Low\_CH




N48(10M)\_DFT-s-OFDM\_PI\_2-BPSK\_Edge\_1RB\_Left\_Low\_CH




N48(10M)\_DFT-s-OFDM\_PI\_2-BPSK\_Edge\_1RB\_Right\_Low\_CH




N48(10M)\_DFT-s-OFDM\_QPSK\_Outer\_Full\_Low\_CH




N48(10M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_Low\_CH




N48(10M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Right\_Low\_CH




N48(10M)\_DFT-s-OFDM\_PI\_2-BPSK\_Outer\_Full\_Mid\_CH




N48(10M)\_DFT-s-OFDM\_PI\_2-BPSK\_Edge\_1RB\_Left\_Mid\_CH




N48(10M)\_DFT-s-OFDM\_PI\_2-BPSK\_Edge\_1RB\_Right\_Mid\_CH




N48(10M)\_DFT-s-OFDM\_QPSK\_Outer\_Full\_Mid\_CH




N48(10M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_Mid\_CH




N48(10M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Right\_Mid\_CH




N48(10M)\_DFT-s-OFDM\_PI\_2-BPSK\_Outer\_Full\_High\_CH




N48(10M)\_DFT-s-OFDM\_PI\_2-BPSK\_Edge\_1RB\_Left\_High\_CH




N48(10M)\_DFT-s-OFDM\_PI\_2-BPSK\_Edge\_1RB\_Right\_High\_CH




N48(10M)\_DFT-s-OFDM\_QPSK\_Outer\_Full\_High\_CH




N48(10M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_High\_CH




N48(10M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Right\_High\_CH




N48(20M)\_DFT-s-OFDM\_PI\_2-BPSK\_Outer\_Full\_Low\_CH




N48(20M)\_DFT-s-OFDM\_PI\_2-BPSK\_Edge\_1RB\_Left\_Low\_CH




N48(20M)\_DFT-s-OFDM\_PI\_2-BPSK\_Edge\_1RB\_Right\_Low\_CH




N48(20M)\_DFT-s-OFDM\_QPSK\_Outer\_Full\_Low\_CH




N48(20M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_Low\_CH




N48(20M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Right\_Low\_CH




N48(20M)\_DFT-s-OFDM\_PI\_2-BPSK\_Outer\_Full\_Mid\_CH




N48(20M)\_DFT-s-OFDM\_PI\_2-BPSK\_Edge\_1RB\_Left\_Mid\_CH




N48(20M)\_DFT-s-OFDM\_PI\_2-BPSK\_Edge\_1RB\_Right\_Mid\_CH




N48(20M)\_DFT-s-OFDM\_QPSK\_Outer\_Full\_Mid\_CH



N48(20M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_Mid\_CH




N48(20M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Right\_Mid\_CH




N48(20M)\_DFT-s-OFDM\_PI\_2-BPSK\_Outer\_Full\_High\_CH




N48(20M)\_DFT-s-OFDM\_PI\_2-BPSK\_Edge\_1RB\_Left\_High\_CH




N48(20M)\_DFT-s-OFDM\_PI\_2-BPSK\_Edge\_1RB\_Right\_High\_CH




N48(20M)\_DFT-s-OFDM\_QPSK\_Outer\_Full\_High\_CH




N48(20M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_High\_CH




N48(20M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Right\_High\_CH




N48(40M)\_DFT-s-OFDM\_PI\_2-BPSK\_Outer\_Full\_Low\_CH




N48(40M)\_DFT-s-OFDM\_PI\_2-BPSK\_Edge\_1RB\_Left\_Low\_CH




N48(40M)\_DFT-s-OFDM\_PI\_2-BPSK\_Edge\_1RB\_Right\_Low\_CH




N48(40M)\_DFT-s-OFDM\_QPSK\_Outer\_Full\_Low\_CH




N48(40M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_Low\_CH




N48(40M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Right\_Low\_CH




N48(40M)\_DFT-s-OFDM\_PI\_2-BPSK\_Outer\_Full\_Mid\_CH




N48(40M)\_DFT-s-OFDM\_PI\_2-BPSK\_Edge\_1RB\_Left\_Mid\_CH




N48(40M)\_DFT-s-OFDM\_PI\_2-BPSK\_Edge\_1RB\_Right\_Mid\_CH




N48(40M)\_DFT-s-OFDM\_QPSK\_Outer\_Full\_Mid\_CH



N48(40M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_Mid\_CH



N48(40M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Right\_Mid\_CH








## Conducted Spurious Emissions

NR Band	SCS (kHz)	Bandwidth (MHz)	Arfcn	Freq (MHz)	Modulation	RB	Result	Verdict
48	30	10	637000	3555.0	DFT-s-OFDM BPSK	1@0	see graph	---
48	30	10	637000	3555.0	DFT-s-OFDM BPSK	1@0	see graph	PASS
48	30	10	637000	3555.0	DFT-s-OFDM BPSK	1@0	see graph	PASS
48	30	10	637000	3555.0	DFT-s-OFDM QPSK	1@0	see graph	---
48	30	10	637000	3555.0	DFT-s-OFDM QPSK	1@0	see graph	PASS
48	30	10	637000	3555.0	DFT-s-OFDM QPSK	1@0	see graph	PASS
48	30	10	641666	3624.99	DFT-s-OFDM BPSK	1@0	see graph	---
48	30	10	641666	3624.99	DFT-s-OFDM BPSK	1@0	see graph	PASS
48	30	10	641666	3624.99	DFT-s-OFDM BPSK	1@0	see graph	PASS
48	30	10	641666	3624.99	DFT-s-OFDM QPSK	1@0	see graph	---
48	30	10	641666	3624.99	DFT-s-OFDM QPSK	1@0	see graph	PASS
48	30	10	641666	3624.99	DFT-s-OFDM QPSK	1@0	see graph	PASS
48	30	10	646332	3694.98	DFT-s-OFDM BPSK	1@0	see graph	---
48	30	10	646332	3694.98	DFT-s-OFDM BPSK	1@0	see graph	PASS
48	30	10	646332	3694.98	DFT-s-OFDM BPSK	1@0	see graph	PASS
48	30	10	646332	3694.98	DFT-s-OFDM QPSK	1@0	see graph	---
48	30	10	646332	3694.98	DFT-s-OFDM QPSK	1@0	see graph	PASS
48	30	10	646332	3694.98	DFT-s-OFDM QPSK	1@0	see graph	PASS
48	30	20	637334	3560.01	DFT-s-OFDM BPSK	1@0	see graph	---
48	30	20	637334	3560.01	DFT-s-OFDM BPSK	1@0	see graph	PASS
48	30	20	637334	3560.01	DFT-s-OFDM BPSK	1@0	see graph	PASS
48	30	20	637334	3560.01	DFT-s-OFDM QPSK	1@0	see graph	---
48	30	20	637334	3560.01	DFT-s-OFDM QPSK	1@0	see graph	PASS


48	30	20	637334	3560.01	DFT-s-OFDM QPSK	1@0	see graph	PASS
48	30	20	641666	3624.99	DFT-s-OFDM BPSK	1@0	see graph	---
48	30	20	641666	3624.99	DFT-s-OFDM BPSK	1@0	see graph	PASS
48	30	20	641666	3624.99	DFT-s-OFDM BPSK	1@0	see graph	PASS
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	1@0	see graph	---
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	1@0	see graph	PASS
48	30	20	641666	3624.99	DFT-s-OFDM QPSK	1@0	see graph	PASS
48	30	20	646000	3690.0	DFT-s-OFDM BPSK	1@0	see graph	---
48	30	20	646000	3690.0	DFT-s-OFDM BPSK	1@0	see graph	PASS
48	30	20	646000	3690.0	DFT-s-OFDM BPSK	1@0	see graph	PASS
48	30	20	646000	3690.0	DFT-s-OFDM QPSK	1@0	see graph	---
48	30	20	646000	3690.0	DFT-s-OFDM QPSK	1@0	see graph	PASS
48	30	20	646000	3690.0	DFT-s-OFDM QPSK	1@0	see graph	PASS
48	30	40	638000	3570.0	DFT-s-OFDM BPSK	1@0	see graph	---
48	30	40	638000	3570.0	DFT-s-OFDM BPSK	1@0	see graph	PASS
48	30	40	638000	3570.0	DFT-s-OFDM BPSK	1@0	see graph	PASS
48	30	40	638000	3570.0	DFT-s-OFDM QPSK	1@0	see graph	---
48	30	40	638000	3570.0	DFT-s-OFDM QPSK	1@0	see graph	PASS
48	30	40	638000	3570.0	DFT-s-OFDM QPSK	1@0	see graph	PASS
48	30	40	641666	3624.99	DFT-s-OFDM BPSK	1@0	see graph	---
48	30	40	641666	3624.99	DFT-s-OFDM BPSK	1@0	see graph	PASS
48	30	40	641666	3624.99	DFT-s-OFDM BPSK	1@0	see graph	PASS
48	30	40	641666	3624.99	DFT-s-OFDM QPSK	1@0	see graph	---
48	30	40	641666	3624.99	DFT-s-OFDM QPSK	1@0	see graph	PASS

48	30	40	641666	3624.99	DFT-s-OFDM QPSK	1@0	see graph	<b>PASS</b>
48	30	40	645332	3679.98	DFT-s-OFDM BPSK	1@0	see graph	---
48	30	40	645332	3679.98	DFT-s-OFDM BPSK	1@0	see graph	<b>PASS</b>
48	30	40	645332	3679.98	DFT-s-OFDM BPSK	1@0	see graph	<b>PASS</b>
48	30	40	645332	3679.98	DFT-s-OFDM QPSK	1@0	see graph	---
48	30	40	645332	3679.98	DFT-s-OFDM QPSK	1@0	see graph	<b>PASS</b>
48	30	40	645332	3679.98	DFT-s-OFDM QPSK	1@0	see graph	<b>PASS</b>


N48(10M)\_DFT-s-OFDM\_BPSK\_Edge\_1RB\_Left\_Low\_CH




N48(10M)\_DFT-s-OFDM\_BPSK\_Edge\_1RB\_Left\_Low\_CH




N48(10M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_Low\_CH




N48(10M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_Low\_CH




N48(10M)\_DFT-s-OFDM\_BPSK\_Edge\_1RB\_Left\_Mid\_CH




N48(10M)\_DFT-s-OFDM\_BPSK\_Edge\_1RB\_Left\_Mid\_CH




N48(10M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_Mid\_CH




N48(10M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_Mid\_CH




N48(10M)\_DFT-s-OFDM\_BPSK\_Edge\_1RB\_Left\_High\_CH




N48(10M)\_DFT-s-OFDM\_BPSK\_Edge\_1RB\_Left\_High\_CH




N48(10M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_High\_CH




N48(10M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_High\_CH




N48(20M)\_DFT-s-OFDM\_BPSK\_Edge\_1RB\_Left\_Low\_CH




N48(20M)\_DFT-s-OFDM\_BPSK\_Edge\_1RB\_Left\_Low\_CH




N48(20M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_Low\_CH




N48(20M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_Low\_CH




N48(20M)\_DFT-s-OFDM\_BPSK\_Edge\_1RB\_Left\_Mid\_CH




N48(20M)\_DFT-s-OFDM\_BPSK\_Edge\_1RB\_Left\_Mid\_CH




N48(20M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_Mid\_CH




N48(20M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_Mid\_CH




N48(20M)\_DFT-s-OFDM\_BPSK\_Edge\_1RB\_Left\_High\_CH



N48(20M)\_DFT-s-OFDM\_BPSK\_Edge\_1RB\_Left\_High\_CH



N48(20M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_High\_CH



N48(20M)\_DFT-s-OFDM\_QPSK\_Edge\_1RB\_Left\_High\_CH

