



RF Exposure Info / MPE Sample Calculation

Model: ION-U EU H 19P2

FCC-ID: XS5-UEUH19P2

The ION-U is an optical fiber based DAS system that efficiently takes the outputs of multiple Base Transceiver Stations (BTS) sectors and converts those RF signals to optical to send them over fiber optic cables to remote units to provide coverage in indoor and outdoor locations. The system supports both low power and high power remotes units and SISO and MIMO operation.

The ION-U H 19P2 is a high-power multi-operator 1900 MHz band Extension Unit (EU). It works in conjunction with a Master Unit in the ION-U optical distribution system and is connected to the main Remote Unit via an extension cable bridge.

The Extension Unit adds an additional band (1900 MHz) to the main Remote Unit using the same fiber allowing multiple operators to transport signals to the DAS. The additional service or frequency band provided by the Extension Unit is achieved without any impact on the installed network.

The compact mechanical design is specifically architected to be mounted inside poles or next to the main Remote Unit with a minimal visual impact. A shroud is available to mount the RU and EU in a single protected structure.

The specific device generally will be professionally installed.

Hereby the gain of the finally installed antenna(s), cable attenuation and antenna height will be defined site specific at the time of licensing with the appropriate FCC Bureau(s).

The maximum permissible exposure limit is defined in **47 CFR 1.1310 (B)**.

S = power density limit [W/m]

P = power [W]

R = distance [m]

$$S_n = \frac{P_n G_n}{4\pi R_n^2} \Rightarrow R_n = \sqrt{\frac{P_n G_n}{4\pi S_n}} \text{ (to calculate the distance at one frequency)}$$

If we have more bands, than we have to calculated as a percentage:

The additional of the terms have to be lower than 1.

$$\frac{S_{cal1}}{S_1} + \frac{S_{cal2}}{S_2} + \frac{S_{cal3}}{S_3} + \dots + \frac{S_{caln}}{S_n} < 1$$

$$\frac{\frac{P_1 G_1}{4\pi R_1^2}}{S_1} + \frac{\frac{P_2 G_2}{4\pi R_2^2}}{S_2} + \frac{\frac{P_3 G_3}{4\pi R_3^2}}{S_3} + \dots + \frac{\frac{P_n G_n}{4\pi R_n^2}}{S_n} < 1$$

We are looking for a distance of ensures that the formula is satisfied.

$$R_1 = R_2 = R_3 = \dots = R_n$$

$$\frac{P_1 G_1}{4\pi R^2 S_1} + \frac{P_2 G_2}{4\pi R^2 S_2} + \frac{P_3 G_3}{4\pi R^2 S_3} + \dots + \frac{P_n G_n}{4\pi R^2 S_n} < 1$$

$$\frac{P_1 G_1}{4\pi S_1} + \frac{P_2 G_2}{4\pi S_2} + \frac{P_3 G_3}{4\pi S_3} + \dots + \frac{P_n G_n}{4\pi S_n} < R^2$$

$$\sqrt{\frac{P_1 G_1}{4\pi S_1} + \frac{P_2 G_2}{4\pi S_2} + \frac{P_3 G_3}{4\pi S_3} + \dots + \frac{P_n G_n}{4\pi S_n}} < R$$

$$\text{With } R_n = \sqrt{\frac{P_n G_n}{4\pi S_n}} \Rightarrow R_n^2 = \frac{P_n G_n}{4\pi S_n}$$

$$\sqrt{R_1^2 + R_2^2 + R_3^2 + \dots + R_n^2} < R$$

What you have to do for calculate the minimum distance were the power density limit is met:

1) If you have **one path**, you have to put you special values in the following formula.

$$R_n = \sqrt{\frac{P_n G_n}{4\pi S_n}} \quad (\text{Distance for one carrier})$$

Limits for General Population / Uncontrolled Exposures

Frequency Range (MHz)

Power Density (mW/cm²)

300 – 1500

S = f/1500

1550 – 100,000

S = 1

2) If you have **more than one path**, you must add the individual terms quadratic.

$$R_n = \sqrt{\frac{P_n G_n}{4\pi S_n}} \quad (\text{Distance for individual carrier})$$

$$\sqrt{R_1^2 + R_2^2 + R_3^2 + \dots + R_n^2} < R \quad (\text{See previous page})$$

For example:

The EUT operates in one frequency band: 1930 MHz – 1990 MHz.

The max measured conducted output power is 47.8 dBm.

Calculation with maximum possible antenna gain and without cable loss:

| Frequency [MHz] | Max Power out [dBm] | Max. possible Antenna gain, without cable loss [dBi] | Max. Distance [m] |
|-----------------|---------------------|--|-------------------|
| 1930 | 47.8 | 14.35 | 3.613 |

For more accurate calculation, the cable loss and actual antenna gain have to be included in the finally system.

The antenna(s) used with device must be fixed-mounted on permanent structures with a distance to any human body to comply with the RF Exposure limit.