

7206-EBOM

No.	P/A	CODE	Description	UNIT	NUM	REF.
001	P	H-0502-000JB0-B00	Resistance,0 ohm,±5%,1/16W,0402	PCS	20	R403,R411,R414,R503-R504,R521,R706,R800-R801,R810,R1201,R120 2,R1205-R1206,R1213,R1214,R1215,R1331 ,R1332,R1
002	P	H-0502-036FE0-D00	Resistance,0.36 ohm,±1%,1/4W,0805	PCS	1	R300
003	P	H-0502-100JB0-B00	Resistance,10 ohm,±5%,1/16W,0402	PCS	2	R310,R1114
004	P	H-0502-330JB0-B00	Resistance,33 ohm,±5%,1/16W,0402	PCS	11	R202-R203,R903-R904,R1002-R1004,R1009,R1012-R1014
005	P	H-0502-101JB0-B00	Resistance,100 ohm,±5%,1/16W,0402	PCS	2	R600,R604
006	P	H-0502-511JB0-B00	Resistance,510 ohm,±5%,1/16W,0402	PCS	2	R605-R606
007	P	H-0502-102JB0-B00	Resistance,1K ohm,±5%,1/16W,0402	PCS	10	R231,R405-R408,R601,R615,R941,R942,R1000
008	P	H-0502-152JB0-B00	Resistance,1.5K ohm,±5%,1/16W,0402	PCS	3	R208,R608-R609
009	P	H-0502-202JB0-B00	Resistance,2K ohm,±5%,1/16W,0402	PCS	3	R614,R802-R803
010	P	H-0502-512JB0-B00	Resistance,5.1K ohm,±5%,1/16W,0402	PCS	2	R1245,R1203
011	P	H-0502-622FB0-B00	Resistance,6.2K ohm,±1%,1/16W,0402	PCS	1	R201
012	P	H-0502-103JB0-B00	Resistance,10K ohm,±5%,1/16W,0402	PCS	4	R206,R505,R523,R525
013	P	H-0502-153JB0-B00	Resistance,15K ohm,±5%,1/16W,0402	PCS	1	R401
014	P	H-0502-203JB0-B00	Resistance,20K ohm,±5%,1/16W,0402	PCS	2	R621,R622
015	P	H-0502-473JB0-B00	Resistance,47K ohm,±5%,1/16W,0402	PCS	3	R623,R1115-R1116
016	P	H-0502-753JB0-B00	Resistance,75K ohm,±5%,1/16W,0402	PCS	1	R624
017	P	H-0502-104JB0-B00	Resistance,100K ohm,±5%,1/16W,0402	PCS	1	R1133
018	P	H-0502-154JB0-B00	Resistance,150K ohm,±5%,1/16W,0402	PCS	1	R213
019	P	H-0504-502050-B00	ESD,Varistor,0402,AVLCS502050,AMOTECH	PCS	12	VR600-VR605,VR701,VR702,VR902-VR904,VR1000
020	A	H-0504-100555-400	ESD,Varistor,0402,SDV1005E5R5C400NPTF,Sunlord	PCS	12	VR600-VR605,VR701,VR702,VR902-VR904,VR1000
021	A	H-0504-050550-000	ESD,Varistor,ICV50505500FR,0402,ICT	PCS	12	VR600-VR605,VR701,VR702,VR902-VR904,VR1000
022	P	H-0504-AVRCS5-050	ESD,Varistor(25pF+100 ohm),AVRCS5050Q50,AMOTECH	PCS	5	RCN701-RCN705
023	A	H-0504-210542-501	ESD,Varistor(25pF+100 ohm),ICVE21054E250R101FR,ICT	PCS	5	RCN701-RCN705
024	P	H-0602-15FC8A-B00	CAP,1.5pF,±0.25pF,50V,COG,0402	PCS	4	C414-C417
025	P	H-0602-22FC8A-B00	CAP,2.2pF,±0.25pF,50V,COG,0402	PCS	4	C404-C405,C432-C433
026	P	H-0602-27J8A-B00	CAP,2.7pF,±0.25pF,50V,COG,0402	PCS	1	C442
027	P	H-0602-33FC8A-B00	CAP,3.3pF,±0.25pF,50V,COG,0402	PCS	4	C425-C426,C428-C429
028	P	H-0602-39FB8A-B00	CAP,3.9pF,±0.1pF,50V,COG,0402	PCS	1	C440
029	P	H-0602-47FD8A-B00	CAP,4.7pF,±0.5pF,50V,COG,0402	PCS	1	C418
030	P	H-0602-100J8A-B00	CAP,10pF,±5%,50V,COG,0402	PCS	3	C401,C1204-C1205
031	P	H-0602-220J8A-B00	CAP,22pF,±5%,50V,COG,0402	PCS	3	C203-C204,C456
032	P	H-0602-270J8A-B00	CAP,27pF,±5%,50V,COG,0402	PCS	4	C431,C912,C1100,C1103
033	P	H-0602-330J8A-B00	CAP,33pF,±5%,50V,COG,0402	PCS	3	C410-C411,C441
034	P	H-0602-470J8A-B00	CAP,47pF,±5%,50V,COG,0402	PCS	4	C312,C435,C619,C622
035	P	H-0602-560J8A-B00	CAP,56pF,±5%,50V,COG,0402	PCS	1	C455
036	P	H-0602-101J8A-B00	CAP,100pF,±5%,50V,COG,0402	PCS	10	C406-C407,C409,C413,C601,C605,C607,C609,C1207,C1243
037	P	H-0602-471K8A-B00	CAP,470pF,±10%,50V,X7R,0402	PCS	1	C209
038	P	H-0602-681K8D-B00	CAP,680pF,±10%,50V,COG,0402	PCS	2	C402-C403
039	P	H-0602-102K8D-B00	CAP,1nF,±10%,50V,X7R,0402	PCS	2	C202,C1225
040	P	H-0602-103K4D-B00	CAP,10nF,±10%,16V,X7R,0402	PCS	3	C201,C300,C436
041	P	H-0602-223K3D-B00	CAP,22nF,±10%,16V,X7R,0402	PCS	6	C602-C604,C606,C661,C662
042	P	H-0602-104K3C-B00	CAP,100nF,±10%,10V,X5R,0402	PCS	19	C200,C330,C400,C501,C502,C503,C600,C663,C700,C701,C702,C800-C801,C905,C1222,C1223,C1245,C1248-C1249
043	P	H-0602-105K3C-C00	CAP,1uF,±10%,10V,X5R,0603	PCS	1	C205
044	P	H-0602-105K2C-B00	CAP,1uF,±10%,6.3V,X5R,0402	PCS	12	C206-C208,C301-C302,C420-C423,C1134,R 526 ,R1212
045	P	H-0602-225K2C-C00	CAP,2.2uF,±10%,6.3V,X5R,0603	PCS	8	C304-C305,C307-C310,C628,C664
046	P	H-0602-475K2C-C00	CAP,4.7uF,±10%,6.3V,X5R,0603	PCS	3	C210,C1221,C1224
047	P	H-0602-106M2C-D00	CAP,10uF,±20%,6.3V,X5R,0805	PCS	4	C311,C623-C625
048	P	H-0602-106M2C-D01	CAP,10uF,±10%,6.3V,X5R,0805,0.85mmH	PCS	3	C211,C303,C437
049	P	H-0701-24FSB1-001	IND,2.4nH,±0.3nH,0402,SDCL1005C2N1STDF,SUNLORD	PCS	1	L404
050	A	H-0701-24FSB1-000	IND,2.4nH,±0.3nH,0402,LQG15HS2N4S02D,MURATA	PCS	1	L404
051	P	H-0701-39FSB1-001	IND,3.9nH,±0.3nH,0402,SDCL1005C3N9STDF,Sunlord	PCS	1	L1201
052	A	H-0701-39FSB1-000	IND,3.9nH,±0.3nH,0402,LQG15HS3N9S02,Murata	PCS	1	L1201
053	P	H-0701-62FSB1-001	IND,6.2nH,±0.3nH,0402,SDCL1005C6N2STDF,SUNLORD	PCS	3	L405-L407
054	A	H-0701-62FSB1-000	IND,6.2nH,±0.3nH,0402,LQG15HS6N2J02D,MURATA	PCS	3	L405-L407
055	P	H-0701-100JB1-001	IND,10nH,±5%,0402,SDCL1005C10NJTDF,Sunlord	PCS	1	L400
056	A	H-0701-100JB0-000	IND,10nH,±5%,0402,HK100510NJ-T,Taiyo-yuden	PCS	1	L400
057	A	H-0701-100JB1-000	IND,10nH,±5%,0402,LQG15HS10NJ02D,Murata	PCS	1	L400
058	P	H-0701-150JB1-001	IND,15nH,±5%,0402,SDCL1005C15NJTDF,Sunlord	PCS	1	L403
059	A	H-0701-150JB1-000	IND,15nH,±5%,0402,LQG15HS15NJ02D,Murata	PCS	1	L403
060	A	H-0701-150JB0-000	IND,15nH,±5%,0402,HK100515NJ-T,Taiyo-yuden	PCS	1	L403
061	P	H-0701-180JB0-000	IND,18nH,±5%,0402,HK100518NJ-T,Taiyo-yuden	PCS	1	L402
062	A	H-0701-180JB1-000	IND,18nH,±5%,0402,LQG15HS18NJ02D,Murata	PCS	1	L402
063	A	H-0701-180JB1-001	IND,18nH,±5%,0402,SDCL1005C18NJTDF,Sunlord	PCS	1	L402
064	P	H-0701-121JB1-001	IND,120nH,±5%,0402,SDCL1005CR12JTDF,SUNLORD	PCS	1	L913
065	A	H-0701-121JB1-002	IND,120nH,±5%,0402,HK1005R12J,TAIYO-YUDEN	PCS	1	L913
066	A	H-0701-121JB1-010	IND,120nH,±5%,0402,LQG15HSR12J02,MURATA	PCS	1	L913
067	P	H-0801-100575-000	0402 Bead(75 ohm),600mA,SZ1005G750TF,SUNLORD	PCS	6	B600-B605
068	A	H-0801-157505-000	0402 Bead(75 ohm),300mA,BLM15B7505SN1D,MURATA	PCS	6	B600-B605
069	P	H-0801-100510-201	0402 Bead(1000 ohm),250mA,HZ1005K102TFB01,SUNLORD	PCS	3	B901-B903
070	A	H-0801-151025-000	0402 Bead(1000 ohm),250mA,BLM15H15H102SN1,MURATA	PCS	3	B901-B903
071	P	H-1401-TPCF8B-010	FET,TPCF8B01,TOSHIBA	PCS	1	Q301
072	A	H-1401-02005B-000	MOSFET WITH SCHOTTKY,WPM2005B-8/TR,DFN3x2-8L,WILL	PCS	1	Q301
073	P	H-1401-SI1305-DLT	P-FET,0.28ohm,-0.86A,0.29W,SI1305DL-T1-E3,SC-70-3,WISHAY	PCS	1	Q1101
074	A	H-1401-001480-000	P-FET(-20V,-1.4A),WPM1480-3/TR,WILL	PCS	1	Q1101
075	A	H-1401-004101-100	P-FET(-20V,-1.37A),SIS4101PT1G,SOT-323,SIG	PCS	1	Q1101
076	P	H-1501-HB336G-000	0603 LED(BLUE),BL-HB336G-TRB,BRIGHT	PCS	7	D1008,D1011-D1013,D1015-D1017
077	A	H-1501-C193TB-KT5	LED(BLUE),L1TST-C193TBKT-5A,LITE-ON	PCS	7	D1008,D1011-D1013,D1015-D1017
079	A	H-1501-0603B0-005	0603 LED(BLUE),HT-193NB5,HARVATEK	PCS	7	D1008,D1011-D1013,D1015-D1017
080	P	H-1100-631301-000	SBD,SIG631E30T1G,SOD-523,SIG	PCS	3	D1001-D1002,D1100
081	A	H-1100-521S30-000	SBD,RB521S-30TE61,ROHM	PCS	3	D1001-D1002,D1100
082	A	H-1100-DSF521-000	SBD,DSF521,TOSHIBA	PCS	3	D1001-D1002,D1100
083	P	H-1401-SSM3K7-002	N-Channel FET,SSM3K7002F,TOSHIBA	PCS	2	Q901,Q1102
084	A	T-1203-2N7002-000	MOSFET(N-Channel),60V(D-S),SOT-23,2N7002E	PCS	2	Q901,Q1102
085	A	H-1401-037002-BF0	MOSFET,SSM3K7002BF,TOSHIBA	PCS	2	Q901,Q1102
086	A	H-1401-SN8113-000	MOSFET(N-CANNEL),SOT-23,SN8113LT1G,SIG	PCS	2	Q901,Q1102
087	P	H-1100-ESD525-000	TVS,(5V,80pF),ESD525.0T1G,SOD523,ONSEMI	PCS	1	TVS301
088	A	T-1100-000057-000	TVS(7V,65pF),ESD527.0T1G,SOD23,ONSEMI	PCS	1	TVS301
089	P	Z-1401-SC6600-H30	SC6600L3(SC6600H3)	PCS	1	U100
090	A	Z-1401-SC6600-L20	SC6600L2	PCS	1	U100
091	P	H-1800-141960-550	SAW(PCS),SF14-1960M5UB50/A1,KYOCERA	PCS	1	U400
092	A	H-1800-001960-000	SAW(PCS),EFCH1960TDA1,PANASONIC	PCS	1	U400
093	P	H-1800-140881-550	SAW(850),SF14-0881M5UB50/A1,KYOCERA	PCS	1	U401
094	A	H-1800-881MTD-A10	SAW(850),EFCH881MTDA1,PANASONIC	PCS	1	U401
095	P	H-1401-RF7168-000	Switch+PA,dual-band(EGSM),RF7168,RFMD	PCS	1	U402
096	P	Z-1401-OQS518-000		PCS	1	U404
097	P	H-1800-900180-010	DUAL SAW(EGSM/DCS),SAWEN942MCN0F0,MURATA	PCS	1	U405
098	A	H-1800-009418-100	DUAL SAW(DCS/EGSM),EFCH9418TDL1,PANASONIC	PCS	1	U405
099	A	H-1800-001894-005	DUAL SAW(DCS/EGSM),SFR942PY002,WISOL	PCS	1	U405
100	P	H-1401-SN4990-A00	Audio PA,SN4990AIF09E,SI-EN	PCS	1	U601

101	P	H-1401-587200-000	BT IC,6x6mm,40Pin QFN,RDA5872,RDA	PCS	1	U1201
102	P	H-1401-005802-E00	FM IC,4x4mm,RDA5802E,RDA	PCS	1	U1203
103	A	H-1401-001080-000	FM/AM IC,BK1080QB,QFN24,BEKEN	PCS	1	U1203
104	P	H-2107-300362-000	BAT CONNECTOR,3.0pitch,8.4x3.5x6.2mmH,PAN30-03626-1500.LCN	PCS	1	J301
105	A	H-2107-300362-001	BAT CONNECTOR,3.0pitch,8.4x3.5x6.2mmH,WKBAV006-D31P	PCS	1	J301
106	P	H-2103-01215T-P03	MINI USB,12PIN,2.0mmH,MICFS-01215-TP03(UAF05-12204-1501).LCN	PCS	1	J902
107	A	H-2103-051220-001	MINI USB,0.5PITCH,12PIN,2.0mmH,WKUBI008-001	PCS	1	J902
108	A	H-2103-BK5000-000	MINI USB,12PIN,2.0mmH,TDUB01-BK5000	PCS	1	J902
109	P	H-2112-110819-000	T-FLASH CONNECTOR,1.9mmH,CAH11-08193-SF01(CAH11-08193-SF03).LCN	PCS	1	TF1100
110	A	H-2112-110819-001	T-FLASH CONNECTOR,1.93mmH,WKTFH010-S01	PCS	1	TF1100
111	P	H-2105-00615T-P31	SIM CONNECTOR,1.80mmH,SIMMS-00615-TP31(CAF99-06183-1503).LCN	PCS	2	J1100-J1101
112	A	H-2105-6K5000-000	SIMCONNECTOR,1.80mmH,TDSM01-6K5000	PCS	2	J1100-J1101
113	P	H-2200-32K768-002	32.768KHz Crystal,12.5pF,±20ppm,Q13MC1462000200(Q13MC1461000200).EPSON	PCS	1	X200
114	A	H-2200-32K768-001	32.768KHz Crystal,12.5pF,±20ppm,SSP-T7-F.SII	PCS	1	X200
115	A	H-2200-32K768-000	32.768KHz Crystal,12.5pF,±20ppm,MS3V-T1R,MICRO	PCS	1	X200
116	P	H-2200-426245-000	26MHz Crystal(3225),±10ppm,8.0pI,TN4-26245,EPSON	PCS	1	X400
117	A	H-2200-26M000-002	Crystal,26MHz,CX3225SB26000C4ZF06-KYOCERA	PCS	1	X400
118	P	H-2302-720602-000	PCB mainboard,7206-MB-V0.2	PCS	1	
119	P	H-5305-720200-000	RF shielding,20.2x16.25x1.5mm,7202	PCS	1	
120	P	T-5309-712000-000	TV shielding,15.6x21.1x1.6mm,7120	PCS	1	
121	P	H-5313-609000-000	BT shielding,12.75x10.66x1.5mmH	PCS	1	
122	P	H-5303-720200-000	BB shielding,25.75x19.1x1.5mmH,7202	PCS	1	
123	P	H-1401-6040T3-000	MCP PSRAM FLASH(64Mb+32Mb),M36W0T6050T3ZAQ,NUMONYX	PCS	1	U501