



TEST REPORT

Report Reference No. : **TRE1710001001** R/C.....: 39153

FCC ID : **YAMMD78XGV3**

Applicant's name : **Hytera Communications Corporation Limited**

Address : Hytera Tower, Hi-Tech Industrial Park North, 9108# Beihuan Road, Nanshan District, Shenzhen, China

Manufacturer : Hytera Communications Corporation Limited

Address : Hytera Tower, Hi-Tech Industrial Park North, 9108# Beihuan Road, Nanshan District, Shenzhen, China

Test item description : **DIGITAL MOBILE RADIO**

Trade Mark : Hytera

Model/Type reference : MD782G V(3)

Listed Model(s) : -

Standard : **FCC Part 90/FCC Part 2**

Date of receipt of test sample : Oct. 10, 2017

Date of testing : Oct. 11, 2017 – Nov. 01, 2017

Date of issue : Nov. 02, 2017

Result : **PASS**

Compiled by
(position+printed name+signature) . : File administrators Shayne Zhu 

Supervised by
(position+printed name+signature) . : Project Engineer Cary Luo 

Approved by
(position+printed name+signature) . : RF Manager Hans Hu 

Testing Laboratory Name : **Shenzhen Huatongwei International Inspection Co., Ltd.**

Address : 1/F, Bldg 3, Hongfa Hi-tech Industrial Park, Genyu Road, Tianliao, Gongming, Shenzhen, China

Shenzhen Huatongwei International Inspection Co., Ltd. All rights reserved.

This publication may be reproduced in whole or in part for non-commercial purposes as long as the Shenzhen Huatongwei International Inspection Co., Ltd. is acknowledged as copyright owner and source of the material. Shenzhen Huatongwei International Inspection Co., Ltd. takes no responsibility for and will not assume liability for damages resulting from the reader's interpretation of the reproduced material due to its placement and context.

*The test report merely corresponds to the test sample.
It is not permitted to copy extracts of these test result without the written permission of the test laboratory.*

Contents

| | | |
|-----------|---|-----------|
| 1. | <u>TEST STANDARDS AND REPORT VERSION</u> | 3 |
| 1.1. | Test Standards | 3 |
| 1.2. | Report version | 3 |
| 2. | <u>TEST DESCRIPTION</u> | 4 |
| 3. | <u>SUMMARY</u> | 5 |
| 3.1. | Client Information | 5 |
| 3.2. | Product Description | 5 |
| 3.3. | Test frequency list | 6 |
| 3.4. | EUT operation mode | 7 |
| 3.5. | EUT configuration | 7 |
| 4. | <u>TEST ENVIRONMENT</u> | 8 |
| 4.1. | Address of the test laboratory | 8 |
| 4.2. | Test Facility | 8 |
| 4.3. | Environmental conditions | 9 |
| 4.4. | Statement of the measurement uncertainty | 9 |
| 4.5. | Equipments Used during the Test | 10 |
| 5. | <u>TEST CONDITIONS AND RESULTS</u> | 12 |
| 5.1. | Maximum Transmitter Power | 12 |
| 5.2. | Occupied Bandwidth | 14 |
| 5.3. | Emission Mask | 18 |
| 5.4. | Modulation Limit | 21 |
| 5.5. | Audio Frequency Response | 23 |
| 5.6. | Frequency Stability Test | 25 |
| 5.7. | Transmitter Frequency Behaviour | 28 |
| 5.8. | Spurious Emission on Antenna Port | 30 |
| 5.9. | Transmitter Radiated Spurious Emission | 33 |
| 5.10. | Conducted Emissions | 51 |
| 5.11. | Radiated Emission | 52 |
| 6. | <u>TEST SETUP PHOTOS OF THE EUT</u> | 55 |
| 7. | <u>EXTERNAL AND INTERNAL PHOTOS OF THE EUT</u> | 57 |

1. TEST STANDARDS AND REPORT VERSION

1.1. Test Standards

The tests were performed according to following standards:

[FCC Rules Part 90](#) Private land mobile radio services.

[TIA/EIA 603 D: June 2010](#) Land Mobile FM or PM Communications Equipment Measurement and Performance Standards.

[FCC Part 15 Subpart B](#) Unintentional Radiators

[FCC Part 2](#) Frequency allocations and radio treaty matters, general rules and regulations.

[KDB579009 D03 v01](#): Applications Part 90 Refarming Bands.

[KDB971168 D01 v02r02](#): MEASUREMENT GUIDANCE FOR CERTIFICATION OF LICENSED DIGITAL TRANSMITTERS

1.2. Report version

| Version No. | Date of issue | Description |
|-------------|---------------|-------------|
| 00 | Nov. 02, 2017 | Original |
| | | |
| | | |
| | | |
| | | |

2. Test Description

| Transmitter Requirement | | | |
|--|---|-------------------------------------|-------------------------------------|
| Test item | Standards requirement | Result | |
| | | Pass | N/A |
| Maximum Transmitter Power | FCC Part 90.205, FCC Part 2.1046 | <input checked="" type="checkbox"/> | |
| Modulation Characteristic | FCC Part 90.207, FCC Part 2.1047 | <input checked="" type="checkbox"/> | |
| Occupied Bandwidth | FCC Part 90.209, FCC Part 90.210, FCC Part 2.1049 | <input checked="" type="checkbox"/> | |
| Emission Mask | FCC Part 90.209, FCC Part 90.210, FCC Part 2.1049 | <input checked="" type="checkbox"/> | |
| Frequency Stability | FCC Part 90.213, FCC Part 2.1055 | <input checked="" type="checkbox"/> | |
| Transmitter Frequency Behavior | FCC Part 90.214 | | <input checked="" type="checkbox"/> |
| Transmitter Radiated Spurious Emission | FCC Part 90.210, FCC Part 2.1053 | <input checked="" type="checkbox"/> | |
| Spurious Emission On Antenna Port | FCC Part 90.210, FCC Part 2.1051 | <input checked="" type="checkbox"/> | |
| Receiver Requirement | | | |
| Test item | Standards requirement | Result | |
| | | Pass | N/A |
| Conducted Emission | FCC Part 15.107 | | <input checked="" type="checkbox"/> |
| Radiated Emission | FCC Part 15.109 | <input checked="" type="checkbox"/> | |

3. SUMMARY

3.1. Client Information

| | |
|---------------|---|
| Applicant: | Hytera Communications Corporation Limited |
| Address: | Hytera Tower, Hi-Tech Industrial Park North,9108# Beihuan Road, Nanshan District, Shenzhen, China |
| Manufacturer: | Hytera Communications Corporation Limited |
| Address: | Hytera Tower, Hi-Tech Industrial Park North,9108# Beihuan Road, Nanshan District, Shenzhen, China |

3.2. Product Description

| | | |
|----------------------------|--|---|
| Name of EUT: | DIGITAL MOBILE RADIO | |
| Trade mark: | Hytera | |
| Model/Type reference: | MD782G V(3) | |
| Listed model(s): | - | |
| Power supply: | DC 13.6V | |
| Battery information: | - | |
| Charger information: | - | |
| Adapter information: | - | |
| | | |
| Operation Frequency Range: | From 210MHz to 270MHz | |
| Rated Output Power: | High Power: 25W (43.98dBm); Low Power: 5W (36.99dBm) | |
| Modulation Type: | Analog Voice: | FM |
| | Digital Voice/Digital Data: | 4FSK |
| Digital Type: | DMR | |
| Channel Separation: | Analog Voice: | <input checked="" type="checkbox"/> 12.5kHz |
| | Digital Voice /Digital Data: | <input checked="" type="checkbox"/> 12.5kHz <input type="checkbox"/> 6.25kHz |
| Emission Designator: | Analog Voice: | <input checked="" type="checkbox"/> 12.5kHz Channel Separation: 9K99F3E |
| | Digital Voice& Data: | <input checked="" type="checkbox"/> 12.5kHz Channel Separation: 7K79FXW <input type="checkbox"/> 6.25kHz Channel Separation: --- |
| | Digital Data: | <input checked="" type="checkbox"/> 12.5kHz Channel Separation: 7K79FXD <input type="checkbox"/> 6.25kHz Channel Separation: --- |
| Support data rate: | 9.6kbps | |
| Antenna Type: | External | |
| Maximum Transmitter Power: | Digital | 26.30W for 12.5kHz Channel Separation |
| | Analog | 24.89W for 12.5kHz Channel Separation |

Note:

- 1)The product has the same digital working characters when operating in both two digitized voice/data mode. So only one set of test results for digital modulation modes are provided in this test report.
- 2)This equipment is capable of supporting a minimum data rate of 4800 bits per second per 6.25 kHz of channel bandwidth. DMR interphone's bandwidth is 12.5 kHz, and it has a double time slot, one is the speech time slot, one is the data time slot, just language sequence is satisfied with 4800 bps/6.25 kHz BW.

3.3. Test frequency list

| Mode | Modulation | Channel Separation (kHz) | Operation Frequency Range (MHz) | Test Channel | Test Frequency (MHz) |
|---------|------------|--------------------------|---------------------------------|------------------|----------------------|
| Analog | FM | 12.5 | 210~216 | CH _{L1} | 210.0125 |
| | | | | CH _{H1} | 215.9875 |
| Digital | 4FSK | 12.5 | | CH _{L1} | 210.0125 |
| | | | | CH _{H1} | 215.9875 |
| Analog | FM | 12.5 | 216~220 | CH _{L2} | 216.0125 |
| | | | | CH _{H2} | 219.9875 |
| Digital | 4FSK | 12.5 | | CH _{L2} | 216.0125 |
| | | | | CH _{H2} | 219.9875 |
| Analog | FM | 12.5 | 220~222 | CH _{L3} | 220.0125 |
| | | | | CH _{H3} | 221.9875 |
| Digital | 4FSK | 12.5 | | CH _{L3} | 220.0125 |
| | | | | CH _{H3} | 221.9875 |
| Analog | FM | 12.5 | 222~270 | CH _{L4} | 222.0125 |
| | | | | CH _{H4} | 269.9875 |
| Digital | 4FSK | 12.5 | | CH _{L4} | 222.0125 |
| | | | | CH _{H4} | 269.9875 |

Note:

In section KDB 634817 D01 Sections II(f)1) and 2):

- (1) Test only on the allowed frequencies.
- (2) Test at least one frequency in each band for each rule part applied under and ensure the device is capable of operating on the frequency under each rule part. This requirement may result in testing on multiple frequencies. Testing on one frequency may be acceptable if multiple listed bands for a rule part with a continuous frequency range are split to remove a conflict with other rules and the technical requirements in the split bands are the same. Additional requirements for RF exposure may apply.

3.4. EUT operation mode

| Test mode | Transmitting | Receiving | Power level | | Digital | Analog |
|-----------|--------------|-----------|-------------|-----|---------|---------|
| | | | High | Low | 12.5kHz | 12.5kHz |
| TX1 | √ | | √ | | √ | |
| TX2 | √ | | | √ | √ | |
| TX3 | √ | | √ | | | √ |
| TX4 | √ | | | √ | | √ |
| RX1 | | √ | | | √ | |
| RX2 | | √ | | | | √ |
| RX3 | | √ | | | | |

√: is operation mode.

3.5. EUT configuration

The following peripheral devices and interface cables were connected during the measurement:

- - supplied by the manufacturer
- - supplied by the lab

| | | | |
|---|-------------|----------------|--------------|
| ● | Power Cable | Length (m) : | / |
| | | Shield : | Unshielded |
| | | Detachable : | Undetachable |
| ○ | Multimeter | Manufacturer : | / |
| | | Model No. : | / |

4. TEST ENVIRONMENT

4.1. Address of the test laboratory

Laboratory: Shenzhen Huatongwei International Inspection Co., Ltd.

Address: 1/F, Bldg 3, Hongfa Hi-tech Industrial Park, Genyu Road, Tianliao, Gongming, Shenzhen, China

Phone: 86-755-26748019 Fax: 86-755-26748089

4.2. Test Facility

The test facility is recognized, certified, or accredited by the following organizations:

CNAS-Lab Code: L1225

Shenzhen Huatongwei International Inspection Co., Ltd. has been assessed and proved to be in compliance with CNAS-CL01 Accreditation Criteria for Testing and Calibration Laboratories (identical to ISO/IEC17025: 2005 General Requirements) for the Competence of Testing and Calibration Laboratories.

A2LA-Lab Cert. No.: 3902.01

Shenzhen Huatongwei International Inspection Co., Ltd. EMC Laboratory has been accredited by A2LA for technical competence in the field of electrical testing, and proved to be in compliance with ISO/IEC 17025: 2005 General Requirements for the Competence of Testing and Calibration Laboratories and any additional program requirements in the identified field of testing.

FCC-Registration No.: 762235

Shenzhen Huatongwei International Inspection Co., Ltd. EMC Laboratory has been registered and fully described in a report filed with the FCC (Federal Communications Commission). The acceptance letter from the FCC is maintained in our files. Registration 762235.

IC-Registration No.: 5377B-1

Two 3m Alternate Test Site of Shenzhen Huatongwei International Inspection Co., Ltd. has been registered by Certification and Engineering Bureau of Industry Canada for the performance of radiated measurements with Registration No. 5377B-1.

ACA

Shenzhen Huatongwei International Inspection Co., Ltd. EMC Laboratory can also perform testing for the Australian C-Tick mark as a result of our A2LA accreditation.

4.3. Environmental conditions

| Normal Conditon | |
|--------------------|---------------|
| Relative humidity: | 20 % to 75 %. |
| Air Pressure: | 950~1050mba |
| Voltage: | DC 13.6V |

4.4. Statement of the measurement uncertainty

The data and results referenced in this document are true and accurate. The reader is cautioned that there may be errors within the calibration limits of the equipment and facilities. The measurement uncertainty was calculated for all measurements listed in this test report acc. to CISPR 16 - 4 „Specification for radio disturbance and immunity measuring apparatus and methods – Part 4: Uncertainty in EMC Measurements“ and is documented in the Shenzhen Huatongwei International Inspection Co., Ltd quality system acc. to DIN EN ISO/IEC 17025. Furthermore, component and process variability of devices similar to that tested may result in additional deviation. The manufacturer has the sole responsibility of continued compliance of the device.

Hereafter the best measurement capability for Shenzhen Huatongwei laboratory is reported:

| Test Items | Measurement Uncertainty | Notes |
|---|-------------------------|-------|
| Frequency stability | 25 Hz | (1) |
| Transmitter power conducted | 0.57 dB | (1) |
| Transmitter power Radiated | 2.20 dB | (1) |
| Conducted spurious emission 9KHz-40 GHz | 1.60 dB | (1) |
| Conducted Emission 9KHz-30MHz | 3.39 dB | (1) |
| Radiated Emission 30~1000MHz | 4.65 dB | (1) |
| Radiated Emission 1~18GHz | 5.16 dB | (1) |
| Radiated Emission 18-40GHz | 5.54 dB | (1) |
| Occupied Bandwidth | 35 Hz | (1) |
| FM deviation | 25 Hz | (1) |
| Audio level | 0.62 dB | (1) |
| Low Pass Filter Response | 0.76 dB | (1) |
| Modulation Limiting | 0.42 % | (1) |
| Transient Frequency Behavior | 6.8 % | (1) |

(1) This uncertainty represents an expanded uncertainty expressed at approximately the 95% confidence level using a coverage factor of k=1.96.

4.5. Equipments Used during the Test

| Conducted Emission | | | | |
|---------------------------|---------------|-------------|---------------|------------|
| Name of Equipment | Manufacturer | Model | Serial Number | Last Cal. |
| Artificial Mains | Rohde&Schwarz | ESH2-Z5 | 100028 | 2016/11/13 |
| EMI Test Receiver | Rohde&Schwarz | ESCS 30 | 100038 | 2016/11/13 |
| Pulse Limiter | Rohde&Schwarz | ESHSZ2 | 100044 | 2016/11/13 |
| EMI Test Software | Rohde&Schwarz | ES-K1 V1.71 | N/A | N/A |
| RF COMMUNICATION TEST SET | HP | 8920A | 3813A10206 | 2016/11/13 |
| Artificial Mains | Rohde&Schwarz | ESH3-Z6 | 100210 | 2016/11/13 |
| Artificial Mains | Rohde&Schwarz | ESH3-Z6 | 100211 | 2016/11/13 |
| Test cable | ENVIROFLEX | 3651 | 1101902 | 2016/11/13 |

| Modulation Characteristic | | | | |
|---------------------------|---------------------|-------|---------------|------------|
| Name of Equipment | Manufacturer | Model | Serial Number | Last Cal. |
| RF COMMUNICATION TEST SET | HP | 8920A | 3813A10206 | 2016/11/13 |
| RF Cable | Chengdu E-Microwave | ---- | ---- | 2016/11/13 |

| Frequency Stability | | | | |
|---------------------------|---------------------|---------|---------------|------------|
| Name of Equipment | Manufacturer | Model | Serial Number | Last Cal. |
| RF COMMUNICATION TEST SET | HP | 8920A | 3813A10206 | 2016/11/13 |
| Signal Generator | Rohde&Schwarz | SMT03 | 100059 | 2016/11/13 |
| Climate Chamber | ESPEC | EL-10KA | 05107008 | 2016/11/13 |
| RF Cable | Chengdu E-Microwave | ---- | ---- | 2016/11/13 |

| Transmitter Radiated Spurious Emission | | | | |
|--|-------------------|-------------|---------------|------------|
| Name of Equipment | Manufacturer | Model | Serial Number | Last Cal. |
| Ultra-Broadband Antenna | Rohde&Schwarz | HL562 | 100015 | 2016/11/13 |
| EMI Test Receiver | Rohde&Schwarz | ESI 26 | 100009 | 2016/11/13 |
| RF Test Panel | Rohde&Schwarz | TS / RSP | 335015/ 0017 | N/A |
| HORN ANTENNA | Rohde&Schwarz | HF906 | 100039 | 2016/11/13 |
| Turntable | ETS | 2088 | 2149 | N/A |
| Antenna Mast | ETS | 2075 | 2346 | N/A |
| EMI Test Software | Rohde&Schwarz | ES-K1 V1.71 | N/A | N/A |
| RF COMMUNICATION TEST SET | HP | 8920A | 3813A10206 | 2016/11/13 |
| Ultra-Broadband Antenna | ShwarzBeck | VULB9163 | 538 | 2016/11/13 |
| Ultra-Broadband Antenna | ShwarzBeck | VULB9163 | 539 | 2016/11/13 |
| HORN ANTENNA | ShwarzBeck | 9120D | 1012 | 2016/11/13 |
| HORN ANTENNA | ShwarzBeck | 9120D | 1011 | 2016/11/13 |
| TURNTABLE | MATURO | TT2.0 | ---- | N/A |
| ANTENNA MAST | MATURO | TAM-4.0-P | ---- | N/A |
| Test cable | Siva Cables Italy | RG 58A/U | W14.02 | 2016/11/13 |

| Maximum Transmitter Power & Spurious Emission On Antenna Port & Occupied Bandwidth & Emission Mask | | | | |
|--|---------------------|---------------------|---------------|------------|
| Name of Equipment | Manufacturer | Model | Serial Number | Last Cal. |
| Receiver | Rohde&Schwarz | ESI 26 | 100009 | 2016/11/13 |
| Attenuator | R&S | ESH3-22 | 100449 | 2016/11/13 |
| RF COMMUNICATION TEST SET | HP | 8920A | 3813A10206 | 2016/11/13 |
| Digital Radio Test Set | AEROFLEX | 3920 | 299001967 | 2016/11/13 |
| High-Pass Filter | Anritsu | MP526B | 6220875256 | 2016/11/13 |
| High-Pass Filter | Anritsu | MP526D | 6220878392 | 2016/11/13 |
| Spectrum Analyzer | Aglient | E4407B | MY44210775 | 2016/11/13 |
| Spectrum Analyzer | Rohde&Schwarz | FSP40 | 1164.4391.40 | 2016/11/13 |
| SPECTRUM ANALYZER | Agilent | E4407B | MY44210775 | 2016/11/13 |
| Attenuator | Chengdu E-Microwave | EMCAXX-10RNZ-3 | ---- | 2016/11/13 |
| RF Cable | Chengdu E-Microwave | ---- | ---- | 2016/11/13 |
| Combiner | Chengdu E-Microwave | EMPD-T-2-180-10-600 | ---- | 2016/11/13 |

| Transient Frequency Behavior | | | | |
|------------------------------|---------------------|----------|---------------|------------|
| Name of Equipment | Manufacturer | Model | Serial Number | Last Cal. |
| Signal Generator | Rohde&Schwarz | SMT03 | 100059 | 2016/11/13 |
| Storage Oscilloscope | Tektronix | TDS3054B | B033027 | 2016/11/13 |
| RF COMMUNICATION TEST SET | HP | 8920A | 3813A10206 | 2016/11/13 |
| RF Cable | Chengdu E-Microwave | ---- | ---- | 2016/11/13 |

The calibration interval was one year.

5. TEST CONDITIONS AND RESULTS

5.1. Maximum Transmitter Power

Applicants for licenses must request and use no more power than the actual power necessary for satisfactory operation.


LIMIT

FCC Part 90.205, FCC Part 2.1046

Maximum ERP is dependent upon the station's antenna HAAT and required service area.

The output power shall not exceed by more than 20 percent either the output power shown in the Radio Equipment List for transmitters included in this list or when not so listed, the manufacturer's rated output power for the particular transmitter specifically listed on the authorization.

TEST CONFIGURATION



TEST PROCEDURE

Measurements shall be made to establish the radio frequency power delivered by the transmitter the standard output termination. The power output shall be monitored and recorded and no adjustment shall be made to the transmitter after the test has begun, except as noted bellow:

If the power output is adjustable, measurements shall be made for the highest and lowest power levels.

Connect the equipment as illustrated.

TEST MODE:

Please reference to the section 3.4

TEST RESULTS

Passed **Not Applicable**

Please refer to the below test data:

| Operation Mode | Test Channel | Measured power (dBm) | Measured power (W) | Limit (W) | Result |
|----------------|------------------|----------------------|--------------------|-----------|--------|
| TX1 | CH _{L1} | 43.90 | 24.55 | 20~30 | Pass |
| | CH _{H1} | 43.90 | 24.55 | | |
| | CH _{L2} | 43.90 | 24.55 | | |
| | CH _{H2} | 43.90 | 24.55 | | |
| | CH _{L3} | 43.90 | 24.55 | | |
| | CH _{H3} | 43.90 | 24.55 | | |
| | CH _{L4} | 43.90 | 24.55 | | |
| | CH _{H4} | 44.20 | 26.30 | | |
| TX2 | CH _L | 37.30 | 5.37 | 4~6 | Pass |
| | CH _{M1} | 37.30 | 5.37 | | |
| | CH _{M2} | 37.30 | 5.37 | | |
| | CH _{M3} | 37.20 | 5.25 | | |
| | CH _{M4} | 37.20 | 5.25 | | |
| | CH _{M5} | 37.20 | 5.25 | | |
| | CH _{M6} | 37.20 | 5.25 | | |
| | CH _H | 37.10 | 5.13 | | |
| TX3 | CH _{L1} | 43.75 | 23.71 | 20~30 | Pass |
| | CH _{H1} | 43.75 | 23.71 | | |
| | CH _{L2} | 43.76 | 23.77 | | |
| | CH _{H2} | 43.77 | 23.82 | | |
| | CH _{L3} | 43.77 | 23.82 | | |
| | CH _{H3} | 43.77 | 23.82 | | |
| | CH _{L4} | 43.78 | 23.88 | | |
| | CH _{H4} | 43.96 | 24.89 | | |
| TX4 | CH _{L1} | 36.84 | 4.83 | 4~6 | Pass |
| | CH _{H1} | 36.82 | 4.81 | | |
| | CH _{L2} | 36.83 | 4.82 | | |
| | CH _{H2} | 36.76 | 4.74 | | |
| | CH _{L3} | 36.77 | 4.75 | | |
| | CH _{H3} | 36.76 | 4.74 | | |
| | CH _{L4} | 36.76 | 4.74 | | |
| | CH _{H4} | 36.86 | 4.85 | | |

5.2. Occupied Bandwidth


The occupied bandwidth, that is the frequency bandwidth such that, below its lower and above its upper frequency limits.

LIMIT

FCC Part 90.209, FCC Part 90.210, FCC Part 2.1049

| Frequency band (MHz) | Channel spacing (kHz) | Authorized bandwidth (kHz) |
|----------------------|-----------------------|----------------------------|
| Below 252 | | |
| 25-50 | 20 | 20 |
| 72-76 | 20 | 20 |
| 150-174 | 17.5 | 1 320/11.25/6 |
| 216-2205 | 6.25 | 20/11.25/6 |
| 220-222 | 5 | 4 |
| 406-5122 | 16.25 | 1 320/11.25/6 |
| 806-809/851-854 | 12.5 | 20 |
| 809-824/854-869 | 25 | 20 |
| 896-901/935-940 | 12.5 | 13.6 |
| 902-9284 | | |
| 929-930 | 25 | 20 |
| 1427-14325 | 12.5 | 12.5 |
| 32450-2483.52 | | |
| Above 25002 | | |

TEST CONFIGURATION



TEST PROCEDURE

- 1 The EUT was modulated by 2.5kHz sine wave audio signal; the level of the audio signal employed is 16dB greater than that necessary to produce 50% of rated system deviation. Rated system deviation is 2.5 kHz for 12.5kHz channel spacing).
- 2 Spectrum set as follow:
Centre frequency = fundamental frequency, span=50kHz for 12.5kHz channel spacing,
RBW=100Hz, VBW=300Hz, Sweep = auto,
Detector function = peak, Trace = max hold
- 3 Set 99% Occupied Bandwidth and 26dB Occupied Bandwidth
- 4 Measure and record the results in the test report.

TEST MODE:

Please reference to the section 3.4


TEST RESULTS


Passed Not Applicable

Note: have pre-tested TX1 to TX4 mode, record the worst case mode TX1 and TX3 on the report.

| Operation Mode | Test Channel | Occupied Bandwidth (kHz) | | Limit(kHz) | Result |
|----------------|------------------|--------------------------|--------|------------|--------|
| | | 99% | 26dB | | |
| TX1 | CH _{L1} | 7.59 | 9.613 | ≤11.25 | Pass |
| | CH _{H1} | 7.74 | 9.740 | | |
| | CH _{L2} | 7.59 | 9.533 | | |
| | CH _{H2} | 7.69 | 9.540 | | |
| | CH _{L3} | 7.59 | 9.597 | | |
| | CH _{H3} | 7.74 | 10.121 | | |
| | CH _{L4} | 7.54 | 9.944 | | |
| | CH _{H4} | 7.79 | 10.343 | | |
| TX3 | CH _{L1} | 9.99 | 10.180 | ≤11.25 | Pass |
| | CH _{H1} | 9.99 | 10.166 | | |
| | CH _{L2} | 9.99 | 10.171 | | |
| | CH _{H2} | 9.99 | 10.198 | | |
| | CH _{L3} | 9.99 | 10.223 | | |
| | CH _{H3} | 9.94 | 10.123 | | |
| | CH _{L4} | 9.99 | 10.187 | | |
| | CH _{H4} | 9.99 | 10.178 | | |

Test plot as follows:





5.3. Emission Mask

Transmitters used in the radio services governed by this part must comply with the emission masks outlined in this section.

LIMIT


FCC Part 90.209, FCC Part 90.210, FCC Part 2.1049

| Frequency band (MHz) | Mask for equipment with audio low pass filter | Mask for equipment without audio low pass filter |
|----------------------|---|--|
| Below 251 | A or B | A or C |
| 25-50 | B | C |
| 72-76 | B | C |
| 150-1742 | B, D, or E | C, D or E |
| 150 paging only | B | C |
| 220-222 | F | F |
| 421-5122.5 | B, D, or E | C, D, or E |
| 450 paging only | B | G |
| 806-809/851-854 | B | H |
| 809-824/854-8693.5 | B | G |
| 896-901/935-940 | I | J |
| 902-928 | K | K |
| 929-930 | B | G |
| 4940-4990 MHz | L or M | L or M |
| 5850-59254 | | |
| All other bands | B | C |

(f) Emission Mask F. For transmitters operating in the 220-222 MHz frequency band, any emission must be attenuated below the power (P) of the highest emission contained within the authorized bandwidth as follows:

- (1) On any frequency from the center of the authorized bandwidth f_0 to the edge of the authorized bandwidth f_e : Zero dB.
- (2) On any frequency removed from the center of the authorized bandwidth by a displacement frequency (f_d in kHz) of more than 2 kHz up to and including 3.75 kHz: $30 + 20(f_d - 2)$ dB or $55 + 10 \log(P)$, or 65 dB, whichever is the lesser attenuation.
- (3) On any frequency beyond 3.75 kHz removed from the center of the authorized bandwidth f_0 : At least $55 + 10 \log(P)$ dB.

TEST CONFIGURATION



TEST PROCEDURE

- 1 Connect the equipment as illustrated.
- 2 Spectrum set as follow:
Centre frequency = fundamental frequency, span=120kHz for 12.5kHz channel spacing, RBW=100Hz, VBW=1000Hz, Sweep = auto, Detector function = peak, Trace = max hold
- 3 Key the transmitter, and set the level of the unmodulated carrier to a full scale reference line. This is the 0dB reference for the measurement.
- 4 Modulate the transmitter with a 2500 Hz sine wave at an input level 16 dB greater than that necessary to produce 50% of rated system deviation (Rated system deviation is 2.5 kHz for 12.5kHz channel spacing). The input level shall be established at the frequency of maximum response of the audio modulating circuit. Transmitters employing digital modulation techniques that bypass the limiter and the audio low-pass filter shall be modulated as specified by the manufacturer
- 5 Measure and record the results in the test report.


TEST MODE:


Please reference to the section 3.4

TEST RESULTS

Passed Not Applicable

Note: have pre-tested TX1 to TX4 mode, record the worst case mode TX1 and TX3 on the report.





5.4. Modulation Limit


Modulation limiting is the transmitter circuit's ability to limit the transmitter from producing deviations in excess of a rated system deviation.

LIMIT

FCC Part 2.1047(b)

2.5kHz for 12.5 kHz Channel Spacing System

TEST CONFIGURATION



TEST PROCEDURE

- 1) Connect the equipment as illustrated.
- 2) Adjust the transmitter per the manufacturer's procedure for full rated system deviation.
- 3) Set the test receiver to measure peak positive deviation. Set the audio bandwidth for ≤ 0.25 Hz to $\geq 15,000$ Hz. Turn the de-emphasis function off.
- 4) Apply a 1000 Hz modulating signal to the transmitter from the audio frequency generator, and adjust the level to obtain 60% of full rated system deviation, this level is as a reference (0dB) and vary the input level from -20 to $+20$ dB.
- 5) Measure both the instantaneous and steady-state deviation at and after the time of increasing the audio input level
- 6) Repeat step 4-5 with input frequency changing to 300Hz, 1004Hz, 1500Hz and 2500Hz in sequence.

TEST MODE:

Please reference to the section 3.4


TEST RESULTS

Passed Not Applicable

Note: have pre-tested TX3 to TX4 mode, record the worst case mode TX3 on the report.

| TX3: CH _{H2} | | | | | | |
|-----------------------|--------------------------------|--------|--------|---------|-------------|--------|
| Modulation Level (dB) | Peak frequency deviation (kHz) | | | | Limit (kHz) | Result |
| | 300Hz | 1004Hz | 1500Hz | 2500 Hz | | |
| -20 | 0.06 | 0.11 | 0.12 | 0.17 | 2.5 | Pass |
| -15 | 0.07 | 0.14 | 0.180 | 0.27 | | |
| -10 | 0.09 | 0.21 | 0.29 | 0.45 | | |
| -5 | 0.12 | 0.33 | 0.49 | 2.2 | | |
| 0 | 0.48 | 1.51 | 2.21 | 2.31 | | |
| 5 | 0.49 | 1.61 | 2.36 | 2.31 | | |
| 10 | 0.47 | 1.6 | 2.34 | 2.32 | | |
| 15 | 0.48 | 1.61 | 2.37 | 2.31 | | |
| 20 | 0.51 | 1.74 | 2.35 | 2.32 | | |

Test plot as follows:




5.5. Audio Frequency Response

The audio frequency response is the degree of closeness to which the frequency deviation of the transmitter follows a prescribed characteristic.


LIMIT

2.1047(a): Voice modulated communication equipment. A curve or equivalent data showing the frequency response of the audio modulating circuit over a range of 100 to 5000 Hz shall be submitted. For equipment required to have an audio low-pass filter, a curve showing the frequency response of the filter or of all circuitry installed between the modulation limiter and the modulated stage shall be submitted.



An additional 6 dB per octave attenuation is allowed from 2500 Hz to 3000 Hz in equipment operating in the 25 MHz to 869 MHz range.

TEST CONFIGURATION



TEST PROCEDURE

- 1) Configure the EUT as shown in figure .
- 2) Adjust the audio input for 20% of rated system deviation at 1kHz using this level as a reference.
- 3) Vary the Audio frequency from 300Hz to 3 kHz and record the frequency deviation.
- 4) Audio Frequency Response = $20\log_{10} (V_{FREQ}/V_{REF})$.

TEST MODE:

Please reference to the section 3.4


TEST RESULTS

Passed Not Applicable

Note: have pre-tested TX3 to TX4 mode, record the worst case mode TX3 on the report.

| TX3: CH _{H2} | | | |
|-----------------------|-------------------------------|----------------|-------------------------------|
| Frequency (Hz) | Audio Frequency Response (dB) | Frequency (Hz) | Audio Frequency Response (dB) |
| 100 | -19.37 | 2100 | 6.03 |
| 200 | -19.04 | 2200 | 6.53 |
| 300 | -9.93 | 2300 | 6.69 |
| 400 | -7.52 | 2400 | 6.87 |
| 500 | -5.26 | 2500 | 7.39 |
| 600 | -4.17 | 2600 | 7.67 |
| 700 | -3.19 | 2700 | 7.76 |
| 800 | -2.18 | 2800 | 7.86 |
| 900 | -1.02 | 2900 | 8.10 |
| 1000 | 0.00 | 3000 | 8.01 |
| 1200 | 1.03 | 3500 | -19.09 |
| 1400 | 2.61 | 4000 | -19.62 |
| 1600 | 3.42 | 4500 | -19.83 |
| 1800 | 4.80 | 5000 | -19.64 |
| 2000 | 5.40 | | |

Test plot as follows:



5.6. Frequency Stability Test

The carrier frequency stability is the ability of the transmitter to maintain an assigned carrier frequency.

LIMIT

FCC Part 90.213, FCC Part 2.1055

| Frequency range (MHz) | Fixed and base stations | Mobile stations | |
|-----------------------|-------------------------|---------------------------|------------------------------|
| | | Over 2 watts output power | 2 watts or less output power |
| Below 25 | 12 3100 | 100 | 200 |
| 25-50 | 20 | 20 | 50 |
| 72-76 | 5 | | 50 |
| 150-174 | 5 115 | 65 | 4 650 |
| 216-220 | 1.0 | | 1.0 |
| 220-222.12 | 0.1 | 1.5 | 1.5 |
| 421-512 | 7 11 142.5 | 85 | 85 |
| 806-809 | 141.0 | 1.5 | 1.5 |
| 809-824 | 141.5 | 2.5 | 2.5 |
| 851-854 | 1.0 | 1.5 | 1.5 |
| 854-869 | 1.5 | 2.5 | 2.5 |
| 896-901 | 140.1 | 1.5 | 1.5 |
| 902-928 | 2.5 | 2.5 | 2.5 |
| 902-928.13 | 2.5 | 2.5 | 2.5 |
| 929-930 | 1.5 | | |
| 935-940 | 0.1 | 1.5 | 1.5 |
| 1427-1435 | 9300 | 300 | 300 |
| Above 2450.10 | | | |

⁵In the 150-174 MHz band, fixed and base stations with a 12.5 kHz channel bandwidth must have a frequency stability of 2.5 ppm. Fixed and base stations with a 6.25 kHz channel bandwidth must have a frequency stability of 1.0 ppm.


⁷In the 421-512 MHz band, fixed and base stations with a 12.5 kHz channel bandwidth must have a frequency stability of 1.5 ppm. Fixed and base stations with a 6.25 kHz channel bandwidth must have a frequency stability of 0.5 ppm.

¹¹Paging transmitters operating on paging-only frequencies must operate with frequency stability of 5 ppm in the 150-174 MHz band and 2.5 ppm in the 421-512 MHz band.

¹⁴Control stations may operate with the frequency tolerance specified for associated mobile frequencies.

¹²Mobile units may utilize synchronizing signals from associated base stations to achieve the specified carrier stability.

TEST CONFIGURATION



TEST PROCEDURE

1. According to FCC Part 2 Section 2.1055 (a)(1), the frequency stability shall be measured with variation of ambient temperature from -30°C to +50°C.
2. According to FCC Part 2 Section 2.1055 (d) (2), for battery powered equipment, the frequency stability shall be measured with reducing primary supply voltage to the battery operating end point, which is specified by the manufacture.
3. Vary primary supply voltage from 3.6V to 4.2V.
4. The EUT was set in the climate chamber and connected to an external DC power supply. The RF output was directly connected to Spectrum Analyzer, The coupling loss of the additional cables was recorded and taken in account for all the measurements. After temperature stabilization (approx. 20 min for each stage), the frequency for the lower, the middle and the highest frequency range was recorded. For Frequency stability Vs. Voltage the EUT was connected to a DC power supply and the voltage was adjusted in the required ranges. The result was recorded.

TEST MODE:

Please reference to the section 3.4

TEST RESULTS **Passed** **Not Applicable**

Note: have pre-tested TX1 to TX4 mode, record the worst case mode TX1 and TX3 on the report.

| TX1 | | | | | | | | | | | |
|-----------------|----------|-----------------------|------------------|------------------|------------------|------------------|------------------|------------------|------------------|-------------|--------|
| Test conditions | | Frequency error (ppm) | | | | | | | | Limit (ppm) | Result |
| Voltage(V) | Temp(°C) | CH _{L1} | CH _{H1} | CH _{L2} | CH _{H2} | CH _{L3} | CH _{H3} | CH _{L4} | CH _{H4} | | |
| 13.6 | -30 | -0.08 | -0.08 | -0.07 | -0.09 | -0.07 | -0.06 | -0.09 | -0.08 | Note | Pass |
| | -20 | -0.09 | -0.08 | -0.10 | -0.10 | -0.09 | -0.09 | -0.08 | -0.07 | | |
| | -10 | -0.10 | -0.07 | -0.07 | -0.10 | -0.08 | -0.08 | -0.08 | -0.09 | | |
| | 0 | -0.09 | -0.10 | -0.08 | -0.09 | -0.08 | -0.07 | -0.07 | -0.07 | | |
| | 10 | -0.10 | -0.10 | -0.10 | -0.10 | -0.08 | -0.06 | -0.07 | -0.09 | | |
| | 20 | -0.10 | -0.07 | -0.10 | -0.10 | -0.09 | -0.07 | -0.09 | -0.07 | | |
| | 30 | -0.09 | -0.10 | -0.08 | -0.08 | -0.07 | -0.06 | -0.06 | -0.09 | | |
| | 40 | -0.09 | -0.09 | -0.08 | -0.09 | -0.07 | -0.08 | -0.07 | -0.07 | | |
| | 50 | -0.08 | -0.07 | -0.08 | -0.10 | -0.08 | -0.07 | -0.07 | -0.08 | | |
| 11.56 | 20 | -0.09 | -0.10 | -0.07 | -0.08 | -0.08 | -0.08 | -0.08 | -0.07 | | |
| 15.64 | 20 | -0.07 | -0.08 | -0.09 | -0.08 | -0.09 | -0.07 | -0.08 | -0.09 | | |

Note: ± 1 ppm for 210~220MHz, ± 0.1 ppm for 220~270MHz.

| TX3 | | | | | | | | | | | |
|-----------------|----------|-----------------------|------------------|------------------|------------------|------------------|------------------|------------------|------------------|-------------|--------|
| Test conditions | | Frequency error (ppm) | | | | | | | | Limit (ppm) | Result |
| Voltage(V) | Temp(°C) | CH _{L1} | CH _{H1} | CH _{L2} | CH _{H2} | CH _{L3} | CH _{H3} | CH _{L4} | CH _{H4} | | |
| 13.6 | -30 | 0.27 | 0.26 | 0.27 | 0.24 | 0.08 | 0.06 | 0.07 | 0.07 | Note | Pass |
| | -20 | 0.25 | 0.27 | 0.27 | 0.27 | 0.08 | 0.07 | 0.07 | 0.06 | | |
| | -10 | 0.24 | 0.23 | 0.25 | 0.23 | 0.09 | 0.09 | 0.06 | 0.07 | | |
| | 0 | 0.27 | 0.23 | 0.23 | 0.24 | 0.08 | 0.08 | 0.08 | 0.08 | | |
| | 10 | 0.26 | 0.24 | 0.24 | 0.27 | 0.07 | 0.08 | 0.09 | 0.09 | | |
| | 20 | 0.27 | 0.27 | 0.26 | 0.26 | 0.09 | 0.09 | 0.09 | 0.08 | | |
| | 30 | 0.26 | 0.24 | 0.26 | 0.25 | 0.07 | 0.09 | 0.07 | 0.06 | | |
| | 40 | 0.26 | 0.25 | 0.25 | 0.24 | 0.08 | 0.08 | 0.08 | 0.08 | | |
| | 50 | 0.26 | 0.25 | 0.27 | 0.24 | 0.09 | 0.07 | 0.08 | 0.07 | | |
| 11.56 | 20 | 0.25 | 0.25 | 0.27 | 0.26 | 0.09 | 0.09 | 0.06 | 0.09 | | |
| 15.64 | 20 | 0.26 | 0.23 | 0.27 | 0.23 | 0.06 | 0.07 | 0.08 | 0.09 | | |

Note: ± 1 ppm for 210~220MHz, ± 0.1 ppm for 220~270MHz.

5.7. Transmitter Frequency Behaviour

LIMIT

FCC part 90.214


Transmitters designed to operate in the 150-174 MHz and 421-512 MHz frequency bands must maintain transient frequencies within the maximum frequency difference limits during the time intervals indicated:

| Time intervals ^{1 2} | Maximum frequency difference ³ | All equipment | |
|---|---|----------------|----------------|
| | | 150 to 174 MHz | 421 to 512 MHz |
| Transient Frequency Behavior for Equipment Designed to Operate on 25 kHz Channels | | | |
| t ₁ ⁴ | ±25.0 kHz | 5.0 ms | 10.0 ms |
| t ₂ | ±12.5 kHz | 20.0 ms | 25.0 ms |
| t ₃ ⁴ | ±25.0 kHz | 5.0 ms | 10.0 ms |
| Transient Frequency Behavior for Equipment Designed to Operate on 12.5 kHz Channels | | | |
| t ₁ ⁴ | ±12.5 kHz | 5.0 ms | 10.0 ms |
| t ₂ | ±6.25 kHz | 20.0 ms | 25.0 ms |
| t ₃ ⁴ | ±12.5 kHz | 5.0 ms | 10.0 ms |
| Transient Frequency Behavior for Equipment Designed to Operate on 6.25 kHz Channels | | | |
| t ₁ ⁴ | ±6.25 kHz | 5.0 ms | 10.0 ms |
| t ₂ | ±3.125 kHz | 20.0 ms | 25.0 ms |
| t ₃ ⁴ | ±6.25 kHz | 5.0 ms | 10.0 ms |

Note:

- On is the instant when a 1 kHz test signal is completely suppressed, including any capture time due to phasing.
 - t₁ is the time period immediately following ton.
 - t₂ is the time period immediately following t₁.
 - t₃ is the time period from the instant when the transmitter is turned off until toff.
 - t_{off} is the instant when the 1 kHz test signal starts to rise.
- During the time from the end of t₂ to the beginning of t₃, the frequency difference must not exceed the limits specified in § 90.213.
- Difference between the actual transmitter frequency and the assigned transmitter frequency.
- If the transmitter carrier output power rating is 6 watts or less, the frequency difference during this time period may exceed the maximum frequency difference for this time period.

TEST CONFIGURATION



TEST PROCEDURE

According to TIA/EIA-603 2.2.19 requirement, as for the product different from PTT, we use test steps as follows:

1. Connect DUT into Test discriminator and Storage Oscilloscope and keep DUT stats ON;
2. Input 1kHz signal into DUT;
3. Set the modulation domain analyzer to trigger on the rising edge of the waveform in order to capture a single-shot turn-on of the transmitter signals;
4. Keep DUT in OFF state and Key the PTT;
5. Observe the stored oscilloscope of modulation domain analyzer. The signal trace shall be maintained within the allowable limits during the periods t_1 and t_2 , and shall also remain within limits following t_2 ;
6. Adjust the modulation domain analyzer to trigger on the falling edge of the transmitter waveform in order to capture a single-shot turn-off transmitter of the transmitter signal.
7. Keep the digital portable radio in ON state and unkey the PTT;
8. Observe the stored oscilloscope of modulation domain analyzer, The signal trace shall be maintained within the allowable limits during the period t_3 .
9. Set the signal generator to the assigned transmitter frequency and modulate it with a 1 kHz tone at ± 12.5 kHz deviation and set its output level to -100dBm.
10. Turn on the transmitter.
11. Supply sufficient attenuation via the RF attenuator to provide an input level to the stored oscilloscope
12. that is 40 dB below the maximum allowed input power when the transmitter is operating at its rated power level. Note this power level on the stored oscilloscope as P_0 .
13. Turn off the transmitter.
14. Adjust the RF level of the signal generator to provide RF power equal to P_0 . This signal generator RF level shall be maintained throughout the rest of the measurement.
15. Remove the attenuation, so the input power to the stored oscilloscope is increased by 30 dB when the transmitter is turned on.
16. Adjust the vertical amplitude control of the stored oscilloscope to display the 1000 Hz at ± 4 divisions vertically centered on the display. Set trigger mode of the Spectrum Analyzer to "Video", and tune the "trigger level" on suitable level. Then set the "trigger offset" to -10ms for turn on and -15ms for turn off.
17. Turn on the transmitter and the transient wave will be captured on the screen of Spectrum Analyzer. Observe the stored display. The instant when the 1 kHz test signal is completely suppressed is considered to be t_{on} . The trace should be maintained within the allowed divisions during the period t_1 and t_2 .
18. Then turn off the transmitter, and another transient wave will be captured on the screen of Spectrum
19. Analyzer. The trace should be maintained within the allowed divisions during the period t_3 .

TEST MODE:

Please reference to the section 3.4

TEST RESULTS

Passed Not Applicable

Note:

The operating frequency range of this device is 210MHz~270MHz.

5.8. Spurious Emission on Antenna Port

Conducted spurious emissions are emissions at the antenna terminals on a frequency or frequencies that are outside a band sufficient to ensure transmission of information of required quality for the class of communication desired

LIMIT

FCC Part 90.210 (f)(3), FCC Part 2.1051 :

On any frequency beyond 3.75 kHz removed from the center of the authorized bandwidth fd: At least $55 + 10 \log(P)$ dB. At least $55 + 10 \log(P)$ dB

Note: In general, the worse case attenuation requirement shown above was applied.


Calculation: Limit (dBm) = EL - 55 - 10 log₁₀ (TP)

EL is the emission level of the Output Power expressed in dBm,

In this application, the EL is P (dBm)

Limit (dBm) = P (dBm) - 55 - 10 log (Pwatts) = -25dBm

TEST CONFIGURATION



TEST PROCEDURE

1. The RF output of the EUT was connected to a spectrum analyzer through appropriate attenuation.
2. The resolution bandwidth of the spectrum analyzer was set to 100 kHz. Sufficient scans were taken to show any out of band emission up to 10th. Harmonic for the lower and the highest frequency range.
3. Set RBW 100 kHz, VBW 300 kHz in the frequency band 30MHz to 1GHz, while set RBW=1MHz. VBW=3MHz from the 1GHz to 10th Harmonic.
4. The audio input was set the unmodulated carrier, the resulting picture is print out for each channel separation.


TEST MODE:


Please reference to the section 3.4

TEST RESULTS

Passed **Not Applicable**

1. The measurement frequency range from 30 MHz to 3 GHz.
2. We tested TX1 to TX3 recorded worst case TX1 and TX3.





5.9. Transmitter Radiated Spurious Emission

Radiated spurious emissions are emissions from the equipment when transmitting into a nonradiating load on a frequency or frequencies that are outside an occupied band sufficient to ensure transmission of information of required quality for the class of communications desired.

LIMIT

FCC Part 90.210 (f)(3), FCC Part 2.1051 :

On any frequency beyond 3.75 kHz removed from the center of the authorized bandwidth f_d : At least $55 + 10 \log (P)$ dB. At least $55 + 10 \log (P)$ dB

Note: In general, the worse case attenuation requirement shown above was applied.

Calculation: Limit (dBm) = EL-55-10log₁₀ (TP)


EL is the emission level of the Output Power expressed in dBm,

In this application, the EL is P (dBm)


Limit (dBm) = P (dBm)-55-10 log (Pwatts) = -25dBm


TEST CONFIGURATION

Below 1GHz:



Above 1GHz:





TEST PROCEDURE

1. Standard Transmitter Load with a $50\ \Omega$ input impedance and an output impedance matched to the test equipment.
2. EUT was placed on a 0.8 meter high non-conductive stand at a 3 meter test distance from the receive antenna. A receiving antenna was placed on the antenna mast 3 meters from the EUT for emission measurements. The height of receiving antenna is 1.0 m. Detected emissions were maximized at each frequency by rotating the EUT through 360° and adjusting the receiving antenna polarization. The radiated emission measurements of all transmit frequencies in six channels were measured with peak detector.
3. A log-periodic antenna or double-ridged waveguide horn antenna shall be substituted in place of the EUT. The log-periodic antenna will be driven by a signal generator and the level will be adjusted till the same power value on the spectrum analyzer or receiver. The level of the spurious emissions can be calculated through the level of the signal generator, cable loss, the gain of the substitution antenna and the reading of the spectrum analyzer or receiver.
4. The EUT is then put into continuously transmitting mode at its maximum power level during the test. Set Test Receiver or Spectrum RBW=1MHz, VBW=3MHz for above 1GHz and RBW=100kHz, VBW=300kHz for 30MHz to 1GHz, And the maximum value of the receiver should be recorded as (Pr).
5. The EUT shall be replaced by a substitution antenna. In the chamber, an substitution antenna for the frequency band of interest is placed at the reference point of the chamber. An RF Signal source for the frequency band of interest is connected to the substitution antenna with a cable that has been constructed to not interfere with the radiation pattern of the antenna. A power (PMea) is applied to the input of the substitution antenna, and adjust the level of the signal generator output until the value of the receiver reach the previously recorded (Pr). The power of signal source (PMea) is recorded. The test should be performed by rotating the test item and adjusting the receiving antenna polarization.
6. A amplifier should be connected to the Signal Source output port. And the cable should be connect between the Amplifier and the Substitution Antenna. The cable loss (Pcl), the Substitution Antenna Gain (Ga) and the Amplifier Gain (PAg) should be recorded after test.
The measurement results are obtained as described below:
Power(EIRP)=PMea- PAg - Pcl - Ga
We used SMF100A microwave signal generator which signal level can up to 33dBm,so we not used power Amplifier for substitution test; The measurement results are amend as described below:
Power(EIRP)=PMea- Pcl - Ga
7. This value is EIRP since the measurement is calibrated using an antenna of known gain (2.15 dBi) and known input power.
8. ERP can be calculated from EIRP by subtracting the gain of the dipole, ERP = EIRP-2.15dBi.

TEST MODE:

Please reference to the section 3.4

TEST RESULTS


Passed **Not Applicable**

Note:

1. In general, the worse case attenuation requirement shown above was applied.
2. The measurement frequency range from 30 MHz to 3 GHz.
3. We tested TX1 to TX3 recorded worst case TX1 and TX3.

TX1


Test Frequency: CH_{L1} Polarity: Horizontal



Trace: (Discrete)

| Mark | Frequency mhz | Reading dBm | Antenna dB | Cable dB | Preamp dB | Level dBm | Limit dBm | Over limit | Remark |
|------|------------------|----------------|---------------|-------------|--------------|--------------|--------------|---------------|--------|
| 1 | 100.57 | -80.85 | 26.00 | 1.14 | 29.10 | -82.81 | -25.00 | -57.81 | Peak |
| 2 | 630.49 | -37.82 | 31.78 | 3.03 | 28.90 | -31.91 | -25.00 | -6.91 | Peak |
| 3 | 1211.98 | -69.99 | 39.15 | 4.68 | 36.56 | -62.72 | -25.00 | -37.72 | Peak |
| 4 | 1586.32 | -70.65 | 40.25 | 5.53 | 36.70 | -61.57 | -25.00 | -36.57 | Peak |
| 5 | 1987.01 | -70.46 | 41.03 | 6.25 | 37.29 | -60.47 | -25.00 | -35.47 | Peak |
| 6 | 2405.58 | -71.67 | 42.14 | 6.77 | 37.90 | -60.66 | -25.00 | -35.66 | Peak |

Test Frequency: CH_{L1} Polarity: Vertical




Trace: (Discrete)

| Mark | Frequency mhz | Reading dBm | Antenna dB | Cable dB | Preamp dB | Level dBm | Limit dBm | Over limit | Remark |
|------|------------------|----------------|---------------|-------------|--------------|--------------|--------------|---------------|--------|
| 1 | 97.78 | -80.28 | 25.76 | 1.14 | 29.09 | -82.47 | -25.00 | -57.47 | Peak |
| 2 | 630.49 | -34.58 | 31.78 | 3.03 | 28.90 | -28.67 | -25.00 | -3.67 | Peak |
| 3 | 1418.16 | -69.60 | 39.82 | 5.05 | 36.48 | -61.21 | -25.00 | -36.21 | Peak |
| 4 | 1490.03 | -69.91 | 40.01 | 5.26 | 36.58 | -61.22 | -25.00 | -36.22 | Peak |
| 5 | 1819.83 | -69.54 | 40.73 | 5.99 | 37.16 | -59.98 | -25.00 | -34.98 | Peak |
| 6 | 2249.65 | -70.89 | 41.75 | 6.52 | 37.48 | -60.10 | -25.00 | -35.10 | Peak |

TX1


Test Frequency: CH_{H1} Polarity: Horizontal



Trace: (Discrete)

| Mark | Frequency mhz | Reading dBm | Antenna dB | Cable dB | Preamp dB | Level dBm | Limit dBm | Over limit | Remark |
|------|------------------|----------------|---------------|-------------|--------------|--------------|--------------|---------------|--------|
| 1 | 100.57 | -80.43 | 26.00 | 1.14 | 29.10 | -82.39 | -25.00 | -57.39 | Peak |
| 2 | 648.48 | -43.66 | 31.84 | 3.10 | 28.79 | -37.51 | -25.00 | -12.51 | Peak |
| 3 | 1354.21 | -70.42 | 39.62 | 4.92 | 36.49 | -62.37 | -25.00 | -37.37 | Peak |
| 4 | 1619.78 | -70.37 | 40.32 | 5.61 | 36.76 | -61.20 | -25.00 | -36.20 | Peak |
| 5 | 2198.35 | -71.77 | 41.59 | 6.44 | 37.34 | -61.08 | -25.00 | -36.08 | Peak |
| 6 | 2486.19 | -71.63 | 42.33 | 6.83 | 37.87 | -60.34 | -25.00 | -35.34 | Peak |

Test Frequency: CH_{H1} Polarity: Vertical




Trace: (Discrete)

| Mark | Frequency mhz | Reading dBm | Antenna dB | Cable dB | Preamp dB | Level dBm | Limit dBm | Over limit | Remark |
|------|------------------|----------------|---------------|-------------|--------------|--------------|--------------|---------------|--------|
| 1 | 98.82 | -79.73 | 25.92 | 1.14 | 29.09 | -81.76 | -25.00 | -56.76 | Peak |
| 2 | 648.48 | -38.46 | 31.84 | 3.10 | 28.79 | -32.31 | -25.00 | -7.31 | Peak |
| 3 | 1340.89 | -70.29 | 39.57 | 4.90 | 36.49 | -62.31 | -25.00 | -37.31 | Peak |
| 4 | 1387.34 | -70.55 | 39.71 | 4.98 | 36.47 | -62.33 | -25.00 | -37.33 | Peak |
| 5 | 1870.51 | -70.89 | 40.82 | 6.07 | 37.20 | -61.20 | -25.00 | -36.20 | Peak |
| 6 | 2494.39 | -71.30 | 42.37 | 6.84 | 37.87 | -59.96 | -25.00 | -34.96 | Peak |

TX1


Test Frequency: CH_{L2} Polarity: Horizontal



Trace: (Discrete)

| Mark | Frequency mhz | Reading dBm | Antenna dB | Cable dB | Preamp dB | Level dBm | Limit dBm | Over limit | Remark |
|------|------------------|----------------|---------------|-------------|--------------|--------------|--------------|---------------|--------|
| 1 | 98.13 | -81.25 | 25.84 | 1.14 | 29.09 | -83.36 | -25.00 | -58.36 | Peak |
| 2 | 648.48 | -40.86 | 31.84 | 3.10 | 28.79 | -34.71 | -25.00 | -9.71 | Peak |
| 3 | 1523.13 | -70.59 | 40.11 | 5.35 | 36.62 | -61.75 | -25.00 | -36.75 | Peak |
| 4 | 1737.77 | -70.06 | 40.57 | 5.84 | 37.01 | -60.66 | -25.00 | -35.66 | Peak |
| 5 | 2115.42 | -71.82 | 41.40 | 6.37 | 37.32 | -61.37 | -25.00 | -36.37 | Peak |
| 6 | 2486.19 | -71.63 | 42.33 | 6.83 | 37.87 | -60.34 | -25.00 | -35.34 | Peak |

Test Frequency: CH_{L2} Polarity: Vertical




Trace: (Discrete)

| Mark | Frequency mhz | Reading dBm | Antenna dB | Cable dB | Preamp dB | Level dBm | Limit dBm | Over limit | Remark |
|------|------------------|----------------|---------------|-------------|--------------|--------------|--------------|---------------|--------|
| 1 | 99.87 | -80.61 | 26.08 | 1.14 | 29.10 | -82.49 | -25.00 | -57.49 | Peak |
| 2 | 648.48 | -34.72 | 31.84 | 3.10 | 28.79 | -28.57 | -25.00 | -3.57 | Peak |
| 3 | 1543.35 | -69.74 | 40.15 | 5.41 | 36.65 | -60.83 | -25.00 | -35.83 | Peak |
| 4 | 1819.83 | -69.54 | 40.73 | 5.99 | 37.16 | -59.98 | -25.00 | -34.98 | Peak |
| 5 | 2129.41 | -71.19 | 41.44 | 6.38 | 37.33 | -60.70 | -25.00 | -35.70 | Peak |
| 6 | 2486.19 | -71.63 | 42.33 | 6.83 | 37.87 | -60.34 | -25.00 | -35.34 | Peak |

TX1


Test Frequency: CH_{H2} Polarity: Horizontal



Trace: (Discrete)

| Mark | Frequency mhz | Reading dBm | Antenna dB | Cable dB | Preamp dB | Level dBm | Limit dBm | Over limit | Remark |
|------|------------------|----------------|---------------|-------------|--------------|--------------|--------------|---------------|--------|
| 1 | 99.52 | -80.58 | 26.00 | 1.14 | 29.10 | -82.54 | -25.00 | -57.54 | Peak |
| 2 | 659.98 | -36.22 | 31.89 | 3.12 | 28.73 | -29.94 | -25.00 | -4.94 | Peak |
| 3 | 1150.99 | -69.48 | 38.93 | 4.55 | 36.59 | -62.59 | -25.00 | -37.59 | Peak |
| 4 | 1284.65 | -70.28 | 39.40 | 4.80 | 36.52 | -62.60 | -25.00 | -37.60 | Peak |
| 5 | 1568.99 | -70.60 | 40.20 | 5.48 | 36.68 | -61.60 | -25.00 | -36.60 | Peak |
| 6 | 1987.01 | -70.46 | 41.03 | 6.25 | 37.29 | -60.47 | -25.00 | -35.47 | Peak |

Test Frequency: CH_{H2} Polarity: Vertical



Trace: (Discrete)

| Mark | Frequency mhz | Reading dBm | Antenna dB | Cable dB | Preamp dB | Level dBm | Limit dBm | Over limit | Remark |
|------|------------------|----------------|---------------|-------------|--------------|--------------|--------------|---------------|--------|
| 1 | 98.47 | -80.09 | 25.84 | 1.14 | 29.09 | -82.20 | -25.00 | -57.20 | Peak |
| 2 | 659.98 | -44.09 | 31.89 | 3.12 | 28.73 | -37.81 | -25.00 | -12.81 | Peak |
| 3 | 1286.06 | -69.63 | 39.40 | 4.81 | 36.52 | -61.94 | -25.00 | -36.94 | Peak |
| 4 | 1444.89 | -69.96 | 39.90 | 5.13 | 36.52 | -61.45 | -25.00 | -36.45 | Peak |
| 5 | 1737.77 | -70.06 | 40.57 | 5.84 | 37.01 | -60.66 | -25.00 | -35.66 | Peak |
| 6 | 2051.34 | -70.65 | 41.21 | 6.31 | 37.31 | -60.44 | -25.00 | -35.44 | Peak |