

### \* RF Exposure

# 1. Regulation

According to §15.247(i), systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy levels in excess of the Commission's guidelines. See § 1.1307(b)(1) of this Chapter.

Limits for Maximum Permissive Exposure: RF exposure is calculated.

Emilio for maximum reministre Exposure. Re exposure is calculated.							
Eraguanay Danga	Electric Field	Magnetic Field	Power Density	Averaging Time			
Frequency Range	Strength [V/m]	Strength [A/m]	$[mW/cm^2]$	[minute]			
Limits for General Population / Uncontrolled Exposure							
0.3 ~ 1.34	614	1.63	*(100)	30			
1.34 ~ 30	824/f	2.19/f	$*(180/f^2)$	30			
30 ~ 300	27.5	0.073	0.2	30			
300 ~ 1 500	/	/	f/1 500	30			
1 500 ~ 15 000	/	/	1.0	30			

f=frequency in ML, \*= plane-wave equivalent power density

#### MPE (Maximum Permissive Exposure) Prediction

Predication of MPE limit at a given distance: Equation from page 18 of OET Bulletin 65, Edition 97-01

$$S = PG/4\pi R^2 \quad \left( \Rightarrow R = \sqrt{PG/4\pi S} \right)$$

 $S = power density [mW/cm^2]$ 

P = Power input to antenna [mW]

G = Power gain of the antenna in the direction of interest relative to an isotropic radiator

R = distance to the center of radiation of the antenna [cm]



# 2. RF Exposure Compliance Issue

The information should be included in the user's manual:

This appliance and its antenna must not be co-located or operation in conjunction with any other antenna or transmitter. A minimum separation distance of 20 cm must be maintained between the antenna and the person for this appliance to satisfy the RF exposure requirements.

# 3. Calculation Result of RF Exposure

Channel	Target power	Tune up tolerance	Max tune up power	Max tune up power	Ant Gain	Ant Gain	Power Density at 20 cm	Limit
	[dB]	[dB]	[dB]	[mW]	[dB <b>m</b> ]	[mW]	[mW/cm²]	[mW/cm²]
Lowest	3.00	±2	5.00	3.16	-1.35	0.73	0.000 46	1.000 00

# 4. Target power and tolerance, Max tuneup power

Channel	Target power	Tolerance	Max tuneup power
Lowest	3.00	±2	5.00
Middle	3.00	±2	5.00
Highest	3.00	±2	5.00