

75MM

75MM

110MM



Bluetooth Headset P01

Technical Specifications

- Bluetooth® Specification V3.0
- RF frequency range: 2.402-2.480GHZ, 2.4G ISM band
- Radio performance: Receive Sensitivity of -92dBm
- Supports Bluetooth headset and handsfree profiles
- 4 button design: easy-to-operate On/Off slide switch, MFB, VOL+, VOL-
- LED indicator status: blue, red
- Rechargeable Li-polymer battery
- Micro 5 pin charging port
- Nominal charging time: max 2 hours
- Talk time: up to 6 hours
- Standby time: up to 200 hours
- Operating temperature: -10°C~50°C
- Storage temperature: -20°C~60°C

Features

- Cancels out unwanted background noise, leaving your conversation crystal clear.
- Provides 6 hours of continuous wireless hands-free talk.
- Provides 200 hours of standby time.
- Easily pair/disconnect to your mobile device using the ON/OFF switch.
- Provides in-ear ergonomic fit with extra ear gels and ear hooks that can be worn on either ear.
- Control your volume from the headset.
- Rechargeable battery charges by USB cable to either wall outlet (using AC Charger adapter) or your computer's USB port (USB 2.0).

FCC Warning:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:


- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference,
- and (2) this device must accept any interference received, including interference that may cause undesired operation.

Functions



Basic use:

1. To make a call, use your phone in the normal way when the headset is connected to your phone.
2. To answer a call, press and release the Call Button or press the answer key on your mobile phone.
3. To end a call, press and release the Call Button or press the answer key on your mobile phone.
4. To redial the last number, press and hold the volume up button for 3 seconds.

Note: Not all phones support this feature.

5. To reject an incoming call, press and hold the Call Button for 3 seconds until you hear a short beep.
6. To adjust the volume, press volume up or volume down to increase or decrease the volume level.
7. To mute the microphone (place the call on hold), press and hold the volume down button for 3 seconds. You will hear a beep.
8. To unmute the microphone (take the call off hold), press and hold the volume down button for 3 seconds. You will hear a beep.

Charging the headset:

1. Connect the charging pin of the USB cable to the charging socket of the headset.
2. Connect the other end of the USB cable to either the AC Charger (and plug into a wall A/C outlet) or the computer's USB port.

The red LED indicator light turns on while the headset is charging.

The red LED indicator light shuts off when the headset is fully charged (approximately 2-3 hours).

Note: When the battery is running low, the red LED indicator light starts to flash along with a warning beep.

Note: Unplug the charger from the wall outlet and the device when not in use. Do not leave a fully charged battery connected to a charger, since overcharging may shorten its lifetime.

Switching the headset on/off:

1. To switch on, set the Power Switch to the ON position (green). The indicator light will flash blue.
2. To switch off, set the Power Switch to the OFF position (red). The indicator light will flash red before the headset shuts off.

Pairing for the first time:

1. Ensure the Bluetooth headset is within 3 feet of your mobile phone or Bluetooth enabled device.
2. Set the Power Switch to the ON position.
3. When the indicator light flashes red and blue alternately, you can connect the headset to your Bluetooth enabled device.

Note: If the first time pairing was unsuccessful or for future pairing, manually pair the headset to your Bluetooth enabled device.

Manually pairing the headset:

1. Ensure the Bluetooth headset is within 3 feet of your mobile phone or Bluetooth enabled device.
2. Set the Power Switch to the ON position.
3. Press and hold the Call Button until the indicator light flashes red and blue alternately. The blinking red and blue lights indicate that the headset is in pairing mode.
4. Set your mobile phone to search for Bluetooth devices. When your mobile phone finds the headset, confirm by selecting PBT100 from the list.
5. Enter the passcode "0000" when prompted by the phone. Select "Pair" to complete the pairing process.

Note: To enter pairing mode at any time, you must press and HOLD the Call button down for approximately 8 seconds.

Note: If the Bluetooth version of your Bluetooth mobile phone is V2.1, you will not need to enter a passcode during above pairing process.

Note: If the pairing is successful, the headset's indicator light turns to standby mode and flashes once every three seconds.

For additional information or questions about this product call us toll free at 888-666-6332 or email us at info@premier.com